

ETSI TS 102 361-1 v2.3.1 (2013-07)



Electromagnetic compatibility and Radio spectrum Matters (ERM); Digital Mobile Radio (DMR) Systems; Part 1: DMR Air Interface (AI) protocol

| Reference |
|---------------------|
| RTS/ERM-TGDMR-313-1 |
| Keywords |
| digital, PMR |

ETSI

650 Route des Lucioles
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - NAF 742 C
Association à but non lucratif enregistrée à la
Sous-Préfecture de Grasse (06) N° 7803/88

Important notice

Individual copies of the present document can be downloaded from:
<http://www.etsi.org>

The present document may be made available in more than one electronic version or in print. In any case of existing or perceived difference in contents between such versions, the reference version is the Portable Document Format (PDF). In case of dispute, the reference shall be the printing on ETSI printers of the PDF version kept on a specific network drive within ETSI Secretariat.

Users of the present document should be aware that the document may be subject to revision or change of status.

Information on the current status of this and other ETSI documents is available at

<http://portal.etsi.org/tb/status/status.asp>

If you find errors in the present document, please send your comment to one of the following services:

http://portal.etsi.org/chaircor/ETSI_support.asp

Copyright Notification

No part may be reproduced except as authorized by written permission.
The copyright and the foregoing restriction extend to reproduction in all media.

© European Telecommunications Standards Institute 2013.
All rights reserved.

DECT™, PLUGTESTS™, UMTS™ and the ETSI logo are Trade Marks of ETSI registered for the benefit of its Members.
3GPP™ and **LTE™** are Trade Marks of ETSI registered for the benefit of its Members and
of the 3GPP Organizational Partners.

GSM® and the GSM logo are Trade Marks registered and owned by the GSM Association.

Contents

| | |
|---|----|
| Intellectual Property Rights | 8 |
| Foreword..... | 8 |
| 1 Scope | 9 |
| 2 References | 9 |
| 2.1 Normative references | 9 |
| 2.2 Informative references..... | 10 |
| 3 Definitions, symbols and abbreviations | 10 |
| 3.1 Definitions | 10 |
| 3.2 Symbols..... | 13 |
| 3.3 Abbreviations | 13 |
| 4 Overview | 15 |
| 4.1 Protocol architecture..... | 16 |
| 4.1.1 Air Interface Physical Layer (layer 1)..... | 17 |
| 4.1.2 Air Interface Data Link Layer (layer 2) | 17 |
| 4.1.3 Air Interface Call Control Layer (CCL) (layer 3)..... | 17 |
| 4.2 DMR TDMA structure | 18 |
| 4.2.1 Overview of burst and channel structure | 18 |
| 4.2.2 Burst and frame structure..... | 19 |
| 4.3 Frame synchronization | 20 |
| 4.4 Timing references..... | 22 |
| 4.4.1 Repeater mode BS established timing relationship..... | 22 |
| 4.4.2 Repeater mode MS established timing relationship..... | 22 |
| 4.4.3 Direct mode timing relationship | 22 |
| 4.4.4 TDMA direct mode timing relationship..... | 22 |
| 4.5 Common Announcement Channel (CACH)..... | 23 |
| 4.6 Basic channel types | 24 |
| 4.6.1 Traffic channel with CACH..... | 24 |
| 4.6.2 Traffic channel with guard time..... | 24 |
| 4.6.3 Bi-directional channel..... | 25 |
| 5 Layer 2 protocol description..... | 25 |
| 5.1 Layer 2 timing | 25 |
| 5.1.1 Channel timing relationship..... | 25 |
| 5.1.1.1 Aligned channel timing | 26 |
| 5.1.1.2 Offset channel timing..... | 26 |
| 5.1.2 Voice timing | 26 |
| 5.1.2.1 Voice superframe | 26 |
| 5.1.2.2 Voice initiation..... | 27 |
| 5.1.2.3 Voice termination..... | 28 |
| 5.1.3 Data timing | 28 |
| 5.1.3.1 Single slot data timing..... | 28 |
| 5.1.3.2 Dual slot data timing | 29 |
| 5.1.4 Traffic timing..... | 29 |
| 5.1.4.1 BS timing | 29 |
| 5.1.4.2 Single frequency BS timing | 30 |
| 5.1.4.3 Direct mode timing | 31 |
| 5.1.4.4 Time Division Duplex (TDD) timing..... | 31 |
| 5.1.4.5 Continuous transmission mode | 31 |
| 5.1.4.6 TDMA direct mode timing..... | 32 |
| 5.1.5 Reverse Channel (RC) timing..... | 32 |
| 5.1.5.1 Embedded outbound Reverse Channel (RC)..... | 33 |
| 5.1.5.2 Dedicated outbound Reverse Channel (RC) | 33 |
| 5.1.5.3 Standalone inbound Reverse Channel (RC) | 34 |
| 5.1.5.4 Direct mode Reverse Channel (RC)..... | 34 |

| | | |
|-----------|---|----|
| 5.2 | Channel access | 35 |
| 5.2.1 | Basic channel access rules | 36 |
| 5.2.1.1 | Types of channel activity | 36 |
| 5.2.1.2 | Channel status | 37 |
| 5.2.1.3 | Timing master | 37 |
| 5.2.1.4 | Hang time messages and timers | 38 |
| 5.2.1.5 | Slot 1 and 2 dependency | 38 |
| 5.2.1.6 | Transmit admit criteria | 38 |
| 5.2.1.7 | Transmission re-tries | 39 |
| 5.2.2 | Channel access procedure | 39 |
| 5.2.2.1 | Direct mode Channel Access | 39 |
| 5.2.2.1.1 | MS Out_of_Sync Channel Access | 40 |
| 5.2.2.1.2 | MS Out_of_Sync_Channel_Monitored Channel Access | 42 |
| 5.2.2.1.3 | MS In_Sync_Unknown_System Channel Access | 43 |
| 5.2.2.1.4 | MS Not_in_Call Channel Access | 44 |
| 5.2.2.1.5 | MS Others_Call Channel Access | 44 |
| 5.2.2.1.6 | MS My_Call Channel Access | 44 |
| 5.2.2.2 | Repeater mode channel access | 44 |
| 5.2.2.2.1 | MS Out_of_Sync Channel Access | 44 |
| 5.2.2.2.2 | MS Out_of_Sync_Channel_Monitored Channel Access | 46 |
| 5.2.2.2.3 | MS In_Sync_Unknown_System channel access | 47 |
| 5.2.2.2.4 | MS TX_Wakeup_Message | 48 |
| 5.2.2.2.5 | MS Not_In_Call channel access | 49 |
| 5.2.2.2.6 | MS Others_Call channel access | 50 |
| 5.2.2.2.7 | MS My_Call channel access | 50 |
| 5.2.2.2.8 | MS In_Session channel access | 50 |
| 5.2.2.3 | Non-time critical CSBK ACK/NACK channel access | 50 |
| 5.2.2.4 | TDMA direct mode channel access | 51 |
| 5.2.2.4.1 | MS Out_of_Sync channel access | 51 |
| 5.2.2.4.2 | MS Out_of_Sync_Channel_Monitored channel access | 54 |
| 5.2.2.4.3 | MS In_Sync_Unknown_System channel access | 55 |
| 5.2.2.4.4 | MS Not_in_Call channel access | 56 |
| 5.2.2.4.5 | MS Others_Call channel access | 56 |
| 5.2.2.4.6 | MS My_Call channel access | 56 |
| 5.2.2.4.7 | Immediate response channel access | 56 |
| 6 | Layer 2 burst format | 56 |
| 6.1 | Vocoder socket | 57 |
| 6.2 | Data and control | 58 |
| 6.3 | Common Announcement Channel burst | 59 |
| 6.4 | Reverse Channel | 60 |
| 6.4.1 | Standalone inbound Reverse Channel burst | 60 |
| 6.4.2 | Outbound reverse channel (RC) burst | 61 |
| 7 | DMR signalling | 61 |
| 7.1 | Link Control message structure | 61 |
| 7.1.1 | Voice LC header | 62 |
| 7.1.2 | Terminator with LC | 63 |
| 7.1.3 | Embedded signalling | 64 |
| 7.1.3.1 | Outbound channel | 64 |
| 7.1.3.2 | Inbound channel | 65 |
| 7.1.4 | Short Link Control in CACH | 65 |
| 7.2 | Control Signalling BlocK (CSBK) message structure | 66 |
| 7.2.1 | Control Signalling Block (CSBK) | 66 |
| 7.3 | Idle message | 67 |
| 7.4 | Multi Block Control (MBC) message structure | 68 |
| 7.4.1 | Multi Block Control (MBC) | 69 |
| 8 | DMR Packet Data Protocol (PDP) | 71 |
| 8.1 | Internet Protocol | 71 |
| 8.2 | Datagram fragmentation and re-assembly | 72 |
| 8.2.1 | Header block structure | 73 |
| 8.2.1.1 | Unconfirmed data Header | 74 |

| | | |
|---------|---|-----|
| 8.2.1.2 | Confirmed data header | 75 |
| 8.2.1.3 | Response data header | 75 |
| 8.2.1.4 | Proprietary data header | 75 |
| 8.2.1.5 | Status/precoded short data header | 76 |
| 8.2.1.6 | Raw short data header | 77 |
| 8.2.1.7 | Defined short data header | 77 |
| 8.2.1.8 | Unified Data Transport (UDT) data header | 78 |
| 8.2.2 | Data block structure | 78 |
| 8.2.2.1 | Unconfirmed data block structure | 78 |
| 8.2.2.2 | Confirmed data block structure | 81 |
| 8.2.2.3 | Response packet format | 84 |
| 8.2.2.4 | Hang time for response packet | 85 |
| 8.2.2.5 | Unified Data Transport (UDT) last data block structure | 86 |
| 9 | Layer 2 PDU description | 87 |
| 9.1 | PDUs for voice bursts, general data bursts and the CACH | 87 |
| 9.1.1 | Synchronization (SYNC) PDU | 87 |
| 9.1.2 | Embedded signalling (EMB) PDU | 88 |
| 9.1.3 | Slot Type (SLOT) PDU | 88 |
| 9.1.4 | TACT PDU | 89 |
| 9.1.5 | Reverse Channel (RC) PDU | 89 |
| 9.1.6 | Full Link Control (FULL LC) PDU | 89 |
| 9.1.7 | Short Link Control (SHORT LC) PDU | 89 |
| 9.1.8 | Control Signalling Block (CSBK) PDU | 90 |
| 9.1.9 | Pseudo Random Fill Bit (PR FILL) PDU | 90 |
| 9.2 | Data related PDU description | 90 |
| 9.2.1 | Confirmed packet Header (C_HEAD) PDU | 90 |
| 9.2.2 | Rate ¾ coded packet Data (R_3_4_DATA) PDU | 91 |
| 9.2.3 | Rate ¾ coded Last Data block (R_3_4_LDATA) PDU | 91 |
| 9.2.4 | Confirmed Response packet Header (C_RHEAD) PDU | 92 |
| 9.2.5 | Confirmed Response packet Data (C_RDATA) PDU | 92 |
| 9.2.6 | Unconfirmed data packet Header (U_HEAD) PDU | 92 |
| 9.2.7 | Rate ½ coded packet Data (R_1_2_DATA) PDU | 93 |
| 9.2.8 | Rate ½ coded Last Data block (R_1_2_LDATA) PDU | 93 |
| 9.2.9 | Proprietary Header (P_HEAD) PDU | 94 |
| 9.2.10 | Status/Precoded short data packet Header (SP_HEAD) PDU | 94 |
| 9.2.11 | Raw short data packet Header (R_HEAD) PDU | 94 |
| 9.2.12 | Defined Data short data packet Header (DD_HEAD) PDU | 95 |
| 9.2.13 | Unified Data Transport Header (UDT_HEAD) PDU | 95 |
| 9.2.14 | Unified Data Transport Last Data block (UDT_LDATA) PDU | 95 |
| 9.2.15 | Rate 1 coded packet Data (R_1_DATA) PDU | 96 |
| 9.2.16 | Rate 1 coded Last Data block (R_1_LDATA) PDU | 96 |
| 9.3 | Layer 2 information element coding | 97 |
| 9.3.1 | Colour Code (CC) | 97 |
| 9.3.2 | Privacy Indicator (PI) | 97 |
| 9.3.3 | LC Start/Stop (LCSS) | 97 |
| 9.3.4 | EMB parity | 97 |
| 9.3.5 | Feature set ID (FID) | 98 |
| 9.3.6 | Data Type | 98 |
| 9.3.7 | Slot Type parity | 98 |
| 9.3.8 | Access Type (AT) | 99 |
| 9.3.9 | TDMA Channel (TC) | 99 |
| 9.3.10 | Protect Flag (PF) | 99 |
| 9.3.11 | Full Link Control Opcode (FLCO) | 99 |
| 9.3.12 | Short Link Control Opcode (SLCO) | 99 |
| 9.3.13 | TACT parity | 100 |
| 9.3.14 | RC parity | 100 |
| 9.3.15 | Group or Individual (G/I) | 100 |
| 9.3.16 | Response Requested (A) | 100 |
| 9.3.17 | Data Packet Format (DPF) | 100 |
| 9.3.17A | Header Compression (HC) | 101 |
| 9.3.18 | SAP identifier (SAP) | 101 |

| | | |
|-----------------------------|---|------------|
| 9.3.19 | Logical Link ID (LLID)..... | 101 |
| 9.3.20 | Full message flag (F) | 101 |
| 9.3.21 | Blocks to Follow (BF) | 102 |
| 9.3.22 | Pad Octet Count (POC)..... | 102 |
| 9.3.23 | Re-Synchronize Flag (S)..... | 102 |
| 9.3.24 | Send sequence number (N(S)) | 103 |
| 9.3.25 | Fragment Sequence Number (FSN)..... | 103 |
| 9.3.26 | Data Block Serial Number (DBSN)..... | 104 |
| 9.3.27 | Data block CRC (CRC-9) | 104 |
| 9.3.28 | Class (Class) | 104 |
| 9.3.29 | Type (Type) | 104 |
| 9.3.30 | Status (Status) | 104 |
| 9.3.31 | Last Block (LB) | 105 |
| 9.3.32 | Control Signalling Block Opcde (CSBKO)..... | 105 |
| 9.3.33 | Appended Blocks (AB)..... | 105 |
| 9.3.34 | Source Port (SP) | 105 |
| 9.3.35 | Destination Port (DP)..... | 105 |
| 9.3.36 | Status/Precoded (S_P)..... | 106 |
| 9.3.37 | Selective Automatic Repeat reQuest (SARQ) | 106 |
| 9.3.38 | Defined Data format (DD) | 106 |
| 9.3.39 | Unified Data Transport Format (UDT Format) | 107 |
| 9.3.40 | UDT Appended Blocks (UAB)..... | 107 |
| 9.3.41 | Supplementary Flag (SF) | 107 |
| 9.3.42 | Pad Nibble | 107 |
| 10 | Physical Layer | 108 |
| 10.1 | General parameters..... | 108 |
| 10.1.1 | Frequency range..... | 108 |
| 10.1.2 | RF carrier bandwidth | 108 |
| 10.1.3 | Transmit frequency error | 108 |
| 10.1.4 | Time base clock drift error | 108 |
| 10.2 | Modulation | 109 |
| 10.2.1 | Symbols | 109 |
| 10.2.2 | 4FSK generation | 109 |
| 10.2.2.1 | Deviation index | 109 |
| 10.2.2.2 | Square root raised cosine filter | 109 |
| 10.2.2.3 | 4FSK Modulator | 110 |
| 10.2.3 | Burst timing | 110 |
| 10.2.3.1 | Normal burst | 111 |
| 10.2.3.1.1 | Power ramp time | 111 |
| 10.2.3.1.2 | Symbol timing | 112 |
| 10.2.3.1.3 | Propagation delay and transmission time | 112 |
| 10.2.3.2 | Reverse channel (RC) burst..... | 113 |
| 10.2.3.2.1 | Power ramp time..... | 113 |
| 10.2.3.2.2 | Symbol timing | 114 |
| 10.2.3.2.3 | Propagation delay | 115 |
| 10.2.3.3 | Synthesizer Lock-Time constraints | 115 |
| 10.2.3.4 | Transient frequency constraints during symbol transmission time | 115 |
| Annex A (normative): | Numbering and addressing | 116 |
| Annex B (normative): | FEC and CRC codes..... | 117 |
| B.1 | Block Product Turbo Codes | 118 |
| B.1.1 | BPTC (196,96) | 118 |
| B.2 | Variable length BPTC | 121 |
| B.2.1 | Variable length BPTC for embedded signalling..... | 121 |
| B.2.2 | Variable length BPTC for Reverse Channel..... | 123 |
| B.2.3 | Variable length BPTC for CACH signalling | 124 |
| B.2.4 | Rate ¾ Trellis code..... | 126 |
| B.2.5 | Rate 1 coded data | 130 |

| | | |
|-------------------------------|--|------------|
| B.3 | Generator matrices and polynomials | 132 |
| B.3.1 | Golay (20,8) | 132 |
| B.3.2 | Quadratic residue (16,7,6) | 132 |
| B.3.3 | Hamming (17,12,3) | 133 |
| B.3.4 | Hamming (13,9,3), Hamming (15,11,3), and Hamming (16,11,4) | 133 |
| B.3.5 | Hamming (7,4,3) | 134 |
| B.3.6 | Reed-Solomon (12,9) | 134 |
| B.3.7 | 8-bit CRC calculation | 136 |
| B.3.8 | CRC-CCITT calculation | 137 |
| B.3.9 | 32-bit CRC calculation | 137 |
| B.3.10 | CRC-9 calculation | 139 |
| B.3.11 | 5-bit Checksum (CS) calculation | 140 |
| B.3.12 | Data Type CRC Mask | 140 |
| B.4 | Interleaving | 141 |
| B.4.1 | CACH interleaving | 141 |
| Annex C (informative): | Example timing diagrams | 143 |
| C.1 | Direct mode timing | 143 |
| C.2 | Reverse Channel timing | 143 |
| Annex D (normative): | Idle and Null message bit definition | 144 |
| D.1 | Null embedded message bit definitions | 144 |
| D.2 | Idle message bit definitions | 145 |
| Annex E (normative): | Transmit bit order | 147 |
| Annex F (normative): | Timers and constants in DMR | 160 |
| F.1 | Layer 2 timers | 160 |
| F.2 | Layer 2 constants | 161 |
| Annex G (informative): | High level states overview | 162 |
| G.1 | High Level MS states and SDL description | 162 |
| G.1.1 | MS Level 1 SDL | 162 |
| G.1.2 | MS Level 2 SDL | 165 |
| G.2 | High level BS states and SDL descriptions | 167 |
| G.2.1 | BS Both Slots SDL | 167 |
| G.2.2 | BS Single Slot SDL | 168 |
| Annex H (normative): | Feature interoperability | 170 |
| H.1 | Feature set ID (FID) | 170 |
| H.2 | Application for Manufacturer's Feature set ID | 170 |
| Annex I (informative): | ETSI MFID application form | 171 |
| Annex J (informative): | Change requests | 172 |
| History | 174 | |

Intellectual Property Rights

IPRs essential or potentially essential to the present document may have been declared to ETSI. The information pertaining to these essential IPRs, if any, is publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: *"Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards"*, which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (<http://ipr.etsi.org>).

Pursuant to the ETSI IPR Policy, no investigation, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

Foreword

This Technical Specification (TS) has been produced by ETSI Technical Committee Electromagnetic compatibility and Radio spectrum Matters (ERM).

The present document is part 1 of a multi-part deliverable covering the Technical Requirements for Digital Mobile Radio (DMR), as identified below:

Part 1: "DMR Air Interface (AI) protocol";

Part 2: "DMR voice and generic services and facilities"

Part 3: "DMR data protocol";

Part 4: "DMR trunking protocol".

iteh STANDARD PREVIEW
(standards.iteh.ai)
Full standard:
<https://standards.iteh.ai/catalog/standards/sist/5916776d-bae4-4240-89ed-d3b93806d595/etsi-ts-102-361-1-v2.3.1>
2013-07

1 Scope

The present document contains technical requirements for Digital Mobile Radio (DMR) operating in the existing licensed land mobile service frequency bands, as identified in CEPT/ERC/T/R 25-08 [i.3].

The present document describes the Air Interface of a scalable Digital Mobile Radio system which covers three tiers of possible products:

- Tier I: DMR equipment having an integral antenna and working in direct mode (communication without infrastructure) under a general authorization with no individual rights operation.
- Tier II: DMR systems operating under individual licences working in direct mode or using a Base Station (BS) for repeating.
- Tier III: DMR trunking systems under individual licences operating with a controller function that automatically regulates the communications.

NOTE 1: Tier II and Tier III products encompass both simulcast and non-simulcast systems.

NOTE 2: The three tiers of possible products will work only independently and not interoperable.

(For more information please see the System reference documents TR 102 335-1 [i.1] and TR 102 335-2 [i.2].)

The present document specifies the Air Interface, complying with either EN 300 113-1 [1] and EN 300 113-2 [2] or EN 300 390-1 [3] and EN 300 390-2 [4], that has been specifically developed with the intention of being suitable for all identified product tiers. A polite spectrum access protocol for sharing the physical channel has also been specified. Specifically, in this case for use in the existing land mobile service bands with the intention of causing minimum change to the spectrum planning and regulations. Thus the DMR protocol is intended to be applicable to the land mobile frequency bands, physical channel offset, duplex spacing, range assumptions and all other spectrum parameters without need for any change.

2 References

References are either specific (identified by date of publication and/or edition number or version number) or non-specific. For specific references, only the cited version applies. For non-specific references, the latest version of the reference document (including any amendments) applies.

Referenced documents which are not found to be publicly available in the expected location might be found at <http://docbox.etsi.org/Reference>.

NOTE: While any hyperlinks included in this clause were valid at the time of publication, ETSI cannot guarantee their long term validity.

2.1 Normative references

The following referenced documents are necessary for the application of the present document.

- [1] ETSI EN 300 113-1: "Electromagnetic compatibility and Radio spectrum Matters (ERM); Land mobile service; Radio equipment intended for the transmission of data (and/or speech) using constant or non-constant envelope modulation and having an antenna connector; Part 1: Technical characteristics and methods of measurement".
- [2] ETSI EN 300 113-2: "Electromagnetic compatibility and Radio spectrum Matters (ERM); Land mobile service; Radio equipment intended for the transmission of data (and/or speech) using constant or non-constant envelope modulation and having an antenna connector; Part 2: Harmonized EN covering the essential requirements of article 3.2 of the R&TTE Directive".
- [3] ETSI EN 300 390-1: "ElectroMagnetic Compatibility and Radio Spectrum Matters (ERM); Land Mobile Service; Radio equipment intended for the transmission of data (and speech) and using an integral antenna; Part 1: Technical characteristics and test conditions".

- [4] ETSI EN 300 390-2: "Electromagnetic compatibility and Radio spectrum Matters (ERM); Land Mobile Service; Radio equipment intended for the transmission of data (and speech) and using an integral antenna; Part 2: Harmonized EN covering essential requirements under article 3.2 of the R&TTE Directive".
- [5] ETSI TS 102 361-2: "Electromagnetic compatibility and Radio spectrum Matters (ERM); Digital Mobile Radio (DMR) Systems; Part 2: DMR voice and generic services and facilities".
- [6] IETF RFC 791: "Internet Protocol; DARPA Internet Program; Protocol Specification".
- [7] Void.
- [8] IEC 61162-1: "Maritime navigation and radiocommunication equipment and systems - Digital interfaces - Part 1: Single talker and multiple listeners".
- [9] ISO/IEC 646: "Information technology -- ISO 7-bit coded character set for information interchange".
- [10] ISO/IEC 8859: "Information technology -- 8-bit single-byte coded graphic character sets".
- [11] ETSI TS 102 361-4: "Electromagnetic compatibility and Radio spectrum Matters (ERM); Digital Mobile Radio (DMR) Systems; Part 4: DMR trunking protocol".
- [12] ETSI TS 102 361-3: "Electromagnetic compatibility and Radio spectrum Matters (ERM); Digital Mobile Radio (DMR) Systems; Part 3: DMR data protocol".

2.2 Informative references

The following referenced documents are not necessary for the application of the present document but they assist the user with regard to a particular subject area.

- [i.1] ETSI TR 102 335-1: "Electromagnetic compatibility and Radio spectrum Matters (ERM); System reference document for harmonized use of Digital Mobile Radio (DMR); Part 1: Tier 1 DMR#, expected to be for general authorization with no individual rights operation".
- [i.2] ETSI TR 102 335-2: "Electromagnetic compatibility and Radio spectrum Matters (ERM); System reference document for harmonized use of Digital Mobile Radio (DMR); Part 2: Systems operating under individual licences in the existing land mobile service spectrum bands".
- [i.3] CEPT/ERC/T/R 25-08: "Planning criteria and co-ordination of frequencies in the Land Mobile Service in the range 29,7 - 921 MHz".

3 Definitions, symbols and abbreviations

3.1 Definitions

For the purposes of the present document, the following terms and definitions apply:

1:1-mode: 1 traffic channel mode

NOTE: 1:1-mode supports one "MS to fixed end" duplex call or one simplex call with an optional inbound RC using a two frequency BS.

2:1-mode: 2 traffic channel mode

NOTE: 2:1-mode supports two independent calls which may be either "MS to fixed end" duplex calls, simplex calls using a two frequency BS or simplex calls between MS units on a single frequency.

backward: logical channel from target to source in direct mode

Base Station (BS): fixed end equipment that is used to obtain DMR services

bearer service: telecommunication service providing the capability for information transfer between access points

burst: elementary amount of bits within the physical channel

NOTE 1: Three different bursts exist with different number of bits. The Traffic burst contains 264 bits, the CACH burst contains 24 bits and the RC burst contains 96 bits.

NOTE 2: The burst may include a guard time at the beginning and end of the burst used for power ramp-up and ramp-down.

NOTE 3: For detailed burst definition see clause 4.2.1.

call: complete sequence of related transactions between MSs

NOTE: Transactions may be one or more bursts containing specific call related information.

channel slot timing: time slot 1 and time slot 2 timing boundaries established by a TDMA direct mode leader

Control plane (C-plane): part of the DMR protocol stack dedicated to control and data services

conventional: non-trunked communication

NOTE: This is a communication technique where any radio unit (MS) may communicate with one or more other radio units (MSs) without using a trunking protocol, and may be either in direct mode or using any additional equipment (e.g. BS).

Digital Mobile Radio (DMR): physical grouping that contains all of the mobile and/or fixed end equipment that is used to obtain DMR services

direct mode: mode of operation where MSs may communicate outside the control of a network

NOTE 1: This is communication technique where any radio unit (MS) may communicate with one or more other radio units (MSs) without the need for any additional equipment (e.g. BS).

NOTE 2: Supports one transmission per 12,5 kHz frequency; 12,5 kHz equivalent (12,5e) spectral efficiency.

duplex: mode of operation by which information can be transferred in both directions and where the two directions are independent

NOTE: Duplex is also known as full duplex.

forward: logical channel from source to target in direct mode

frame: two contiguous time slots labelled 1 and 2

NOTE: A frame has a length of 60 ms.

Golay code: type of error correcting code named Golay

Hamming code: type of error correcting code named Hamming

inbound: MS to BS transmission

logical channel: distinct data path between logical endpoints

NOTE: The logical channels are labelled 1 and 2. The logical channel may consist of sub-channels, e.g. SYNC, embedded signalling, etc.

Mobile Station (MS): physical grouping that contains all of the mobile equipment that is used to obtain DMR mobile services

outbound: BS to MS transmission

payload: bits in the information field

physical channel: RF carrier that is modulated with information bits of the bursts

NOTE: The RF carrier may be a single frequency or a duplex pair of frequencies. The physical channel of a DMR subsystem is required to support the logical channels.

polite protocol: "Listen Before Transmit" (LBT) protocol

NOTE: This is a medium access protocol that implements a LBT function in order to ensure that the channel is free before transmitting.

privacy: secret transformation

NOTE: Any transformation of transmitted information that is derived from a shared secret between the sender and receiver.

Protocol Data Unit (PDU): unit of information consisting of protocol control information (signalling) and possibly user data exchanged between peer protocol layer entities

Radio Frequency channel: radio frequency carrier (RF carrier)

NOTE: This is a specified portion of the RF spectrum. In DMR, the RF carrier separation is 12,5 kHz. The physical channel may be a single frequency or a duplex spaced pair of frequencies.

Received Signal Strength Indication (RSSI): root mean squared (rms) value of the signal received at the receiver antenna

Reed-Solomon code: type of error correcting code named Reed-Solomon

repeater mode: mode of operation where MSs may communicate through a BS

NOTE: This is a communication technique where any radio unit (MS) may communicate with one or more other radio units (MSs) with the need for an intermediate BS.

Reverse Channel (RC): signalling burst from target to source

signalling: exchange of information specifically concerned with the establishment and control of connections, and with management, in a telecommunication network

simplex: mode of working by which information can be transferred in both directions but not at the same time

superframe: 6 continuous traffic bursts on a logical channel labelled "A" to "F"

NOTE: A superframe has a length of 360 ms and is used for voice traffic only.

TDMA direct mode: direct mode operation that supports two transmissions per 12,5 kHz frequency

NOTE: Supports 6,25 kHz equivalent (6,25e) spectral efficiency.

time slot (or slot): elementary timing of the physical channel

NOTE: A timeslot has a length of 30 ms and will be numbered "1" or "2".

transmission: transfer period of bursts containing information or signalling

NOTE: The transmission may be continuous, i.e. multiple bursts transmission without ramp-up, ramp-down, or discontinuous, i.e. single burst transmission with ramp-up and ramp-down period.

Trellis code: type of error correcting code for modulation named Trellis

trunking: network controlled communication

NOTE: This is a communication technique where any radio unit (MS) may communicate with one or more other radio units (MSs) using a trunking protocol and all MSs will be under control of a network.

User plane (U-plane): part of the DMR protocol stack dedicated to user voice services

vocoder socket: 216 bits vocoder payload

3.2 Symbols

For the purposes of the present document, the following symbols apply:

| | |
|--------|---|
| dBm | absolute power level relative to 1 mW, expressed in dB |
| dBp | Power relative to the average power transmitted over a burst in decibel |
| Dabit | 2 bits grouped together to represent a 4-level symbol |
| Eb | Energy per bit |
| Nibble | 4 bits grouped together |
| No | Noise per Hz |
| Octet | 8 bits grouped together, also called a byte |
| Tribit | 3 bits grouped together into a symbol for a trellis code |

3.3 Abbreviations

For the purposes of the present document, the following abbreviations apply:

| | |
|------|-----------------------------------|
| 4FSK | Four-level Frequency Shift Keying |
| AB | Appended Blocks |
| ACK | (positive) ACKnowledgement |
| AI | Air Interface |
| ARP | Address Resolution Protocol |
| ARQ | Automatic Retransmission reQuest |
| AT | Access Type |
| BCD | Binary Code Decimal |
| BER | Bit Error Rate |
| BF | Blocks to Follow |
| BOR | Begining Of Receive |
| BPTC | Block Product Turbo Code |
| BS | Base Station |

NOTE: A reference designating a fixed end device.

| | |
|-----------|--|
| CACH | Common Announcement Channel |
| CC | Colour Code |
| CCL | Call Control Layer |
| C-plane | Control plane |
| CR | CRC bits |
| CRC | Cyclic Redundancy Checksum for data error detection |
| CS | CheckSum |
| CSBK | Control Signalling BlocK |
| CSBKO | CSBK Opcode |
| D_Sync | general Data burst Sync |
| DBSN | Data Block Serial Number |
| DD | Defined Data format |
| DLL | Data Link Layer |
| DMR | Digital Mobile Radio |
| DP | Destination Port |
| DPF | Data Packet Format |
| DT | Data Type field for General Data Bursts |
| EMB | EMBedded signalling field |
| Enc_Dabit | output Dabit from trellis Encoder |
| EOR | End Of Receive |
| ERC | European Radiocommunication Committee |
| ERM | Electromagnetic compatibility and Radio spectrum Matters |
| FEC | Forward Error Correction |
| FID | Feature set ID |
| FLCO | Full Link Control Opcode |
| FM | Frequency Modulation |
| FMF | Full Message Flag |
| FSM | Finite State Machine |