
**Radiofrequency identification
of animals —**

**Part 4:
Evaluation of performance of RFID
transceivers conforming with ISO 11784
and ISO 11785**

iTeh STANDARD PREVIEW

(standards.iteh.ai)

Identification des animaux par radiofréquence —

*Partie 4: Évaluation de la performance des émetteurs-récepteurs RFID
conformes à l'ISO 11784 et à l'ISO 11785*

ISO 24631-4:2009

<https://standards.iteh.ai/catalog/standards/sist/8403e30d-ce62-4845-80c5-2d0bf7c9c06a/iso-24631-4-2009>



PDF disclaimer

This PDF file may contain embedded typefaces. In accordance with Adobe's licensing policy, this file may be printed or viewed but shall not be edited unless the typefaces which are embedded are licensed to and installed on the computer performing the editing. In downloading this file, parties accept therein the responsibility of not infringing Adobe's licensing policy. The ISO Central Secretariat accepts no liability in this area.

Adobe is a trademark of Adobe Systems Incorporated.

Details of the software products used to create this PDF file can be found in the General Info relative to the file; the PDF-creation parameters were optimized for printing. Every care has been taken to ensure that the file is suitable for use by ISO member bodies. In the unlikely event that a problem relating to it is found, please inform the Central Secretariat at the address given below.

iTeh STANDARD PREVIEW
(standards.iteh.ai)

ISO 24631-4:2009

<https://standards.iteh.ai/catalog/standards/sist/8403e30d-ce62-4845-80c5-2d0bf7c9c06a/iso-24631-4-2009>



COPYRIGHT PROTECTED DOCUMENT

© ISO 2009

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either ISO at the address below or ISO's member body in the country of the requester.

ISO copyright office
Case postale 56 • CH-1211 Geneva 20
Tel. + 41 22 749 01 11
Fax + 41 22 749 09 47
E-mail copyright@iso.org
Web www.iso.org

Published in Switzerland

Contents

Page

Foreword.....	iv
Introduction	v
1 Scope	1
2 Conformance	1
3 Normative references	1
4 Terms and definitions.....	1
5 Abbreviated terms	3
6 Application	3
7 Test procedures	4
7.1 Test apparatus	4
7.2 Test conditions	4
7.3 Measurement of reading distance diagram.....	5
7.4 Measurement of transceiver response time	7
Annex A (normative) Test application form.....	9
Annex B (normative) Transponder emulation circuit (TEC) design specifications.....	10
Annex C (informative) Example of distance diagram	14
Bibliography	15

<https://standards.iteh.ai/catalog/standards/sist/8403e30d-ce62-4845-80c5-2d0bf7c9c06a/iso-24631-4-2009>

Foreword

ISO (the International Organization for Standardization) is a worldwide federation of national standards bodies (ISO member bodies). The work of preparing International Standards is normally carried out through ISO technical committees. Each member body interested in a subject for which a technical committee has been established has the right to be represented on that committee. International organizations, governmental and non-governmental, in liaison with ISO, also take part in the work. ISO collaborates closely with the International Electrotechnical Commission (IEC) on all matters of electrotechnical standardization.

International Standards are drafted in accordance with the rules given in the ISO/IEC Directives, Part 2.

The main task of technical committees is to prepare International Standards. Draft International Standards adopted by the technical committees are circulated to the member bodies for voting. Publication as an International Standard requires approval by at least 75 % of the member bodies casting a vote.

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. ISO shall not be held responsible for identifying any or all such patent rights.

ISO 24631-4 was prepared by Technical Committee ISO/TC 23, *Tractors and machinery for agriculture and forestry*, Subcommittee SC 19, *Agricultural electronics*.

ISO 24631 consists of the following parts, under the general title *Radiofrequency identification of animals*:

- Part 1: Evaluation of conformance of RFID transponders with ISO 11784 and ISO 11785 (including granting and use of a manufacturer code)
- Part 2: Evaluation of conformance of RFID transceivers with ISO 11784 and ISO 11785
- Part 3: Evaluation of performance of RFID transponders conforming with ISO 11784 and ISO 11785
- Part 4: Evaluation of performance of RFID transceivers conforming with ISO 11784 and ISO 11785

Introduction

ISO has appointed ICAR (International Committee for Animal Recording) as the registration authority (RA) competent to register manufacturer codes used in the radiofrequency identification (RFID) of animals in accordance with ISO 11784 and ISO 11785.

ISO 24631 defines means, based upon ICAR test procedures [1], for evaluating and verifying both the conformance and performance of RFID devices in respect of ISO 11784 and ISO 11785. Only those results emanating from RA-approved test centres are recognized.

This part of ISO 24631 deals with the performance of RFID transceivers. Measurements are made using transponder emulation circuits, ensuring that the transceiver testing is always performed against the same, known stimuli.

iTeh STANDARD PREVIEW (standards.iteh.ai)

ISO 24631-4:2009

<https://standards.iteh.ai/catalog/standards/sist/8403e30d-ce62-4845-80c5-2d0bf7c9c06a/iso-24631-4-2009>

iTeh STANDARD PREVIEW **(standards.iteh.ai)**

ISO 24631-4:2009

<https://standards.iteh.ai/catalog/standards/sist/8403e30d-ce62-4845-80c5-2d0bf7c9c06a/iso-24631-4-2009>

Radiofrequency identification of animals —

Part 4: Evaluation of performance of RFID transceivers conforming with ISO 11784 and ISO 11785

1 Scope

This part of ISO 24631 provides the means of evaluating the performance of ISO 11784- and ISO 11785-conformant RFID (radiofrequency identification) transceivers used in the individual identification of animals.

The test procedures specified in this part of ISO 24631 are recognized by the FECAVA (Federation of European Companion Animals Veterinary Association) and WSAVA (World Small Animal Veterinarian Association) and as such can be applied also to companion animals.

2 Conformance

Test centres approved by the registration authority (RA) shall perform transceiver testing using the procedures specified in Clause 7 and shall report the test results to the RA. These tests are in accordance with the technical requirements of ISO 11784 and ISO 11785. The manufacturer shall apply for transceiver testing by completing and submitting to the RA the application form provided in Annex A. Only transceivers that have been issued an approval reference number by the RA (see ISO 24631-2) may be tested. A transceiver test report shall be accorded to a manufacturer whose product has been tested as per Clause 7.

3 Normative references

The following referenced documents are indispensable for the application of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

ISO 3166-1, *Codes for the representation of names of countries and their subdivisions — Part 1: Country codes*

ISO 11784:1996, *Radio frequency identification of animals — Code structure*

ISO 11785:1996, *Radio frequency identification of animals — Technical concept*

ISO 24631-1:2009, *Radiofrequency identification of animals — Part 1: Evaluation of conformance of RFID transponders with ISO 11784 and ISO 11785 (including granting and use of a manufacturer code)*

4 Terms and definitions

For the purposes of this document, the following terms and definitions apply.

4.1

approval reference number

number issued to the manufacturer of an approved transceiver by the registration authority

EXAMPLE ISO 24631-2 2009-02-001

NOTE It comprises the reference of the International Standard for which approval is made, the year of issue (4 digits), the type of device tested ("02" for transceivers according to this part of ISO 24631) and the running number (3 digits) referencing the transceivers tested successfully during that year.

4.2

country code

three-digit numeric code representing a country in accordance with ISO 3166-1

4.3

ISO 11784 and ISO 11785 transceiver

transceiver that reads at least both FDX-B and HDX transponders as defined in ISO 11784 and ISO 11785

4.4

ISO 11784 and ISO 11785 transponder

radiofrequency identification (RFID) device that transmits its transponder code according to ISO 11784 and ISO 11785 when activated by a transceiver

4.5

manufacturer

company that submits an application for testing transceivers for conformance with ISO 11784 and ISO 11785

4.6

manufacturer code

MFC

three-digit number granted by the RA to a manufacturer under the conditions set forth in ISO 24631-1:2009, Annex E, whose range and placement within the code structure are in accordance with ISO 11784

NOTE Only one manufacturer code is granted to the same manufacturer.

4.7

RA-approved test centre

accredited test centre meeting the criteria of the registration authority

NOTE Accreditation: third-party attestation related to a conformity assessment body conveying formal demonstration of its competence to carry out specific conformity assessment tasks (see Reference [3]).

4.8

RA-approved transponder

transponder approved by the registration authority

4.9

reference transponder

transponder used to test a transceiver, selected from the different RA-approved transponder types

4.10

registration authority

RA

entity that approves test laboratories and issues and registers manufacturer and product codes

4.11

transceiver

device used to communicate with the transponder

4.12**transponder**

radiofrequency identification (RFID) device that transmits its stored information when activated by a transceiver and that may be able to store new information

NOTE See ISO 24631-1 for definitions of the main types.

4.13**transponder code**

code programmed in the transponder, as defined in ISO 11784:1996, Table 1, and in ISO 11785

4.14**transponder emulation circuit**

circuit used to substitute for a transponder, built from well-defined components and an arbitrary waveform generator (AWG)

4.15**transceiver under test****TUT**

mobile transceiver that has passed conformance testing in accordance with ISO 24631-2

5 Abbreviated terms

AWG advanced waveform generator

FDX-B full duplex communication protocol (conforming to ISO 11785, excluding protocols mentioned in ISO 11785:1996, Annex A)

FSK frequency shift keying

HDX half duplex communication protocol

MFC manufacturer code

NP0 negative positive zero

NRZ non-return to zero

RA registration authority

RF radiofrequency

RFID radiofrequency identification

TEC transponder emulation circuit

TUT transceiver under test

6 Application

6.1 The application submitted to the RA for testing the performance of a transceiver shall consist of a covering letter and the application form presented in Annex A. The RA shall confirm receipt of the application to the manufacturer within two weeks. By signing the application form, the manufacturer agrees to fulfil the provisions of this part of ISO 24631.

6.2 The test centre shall be approved by the RA.

6.3 The RA maintains a list of approved test centres, from which the manufacturer may choose the centre that will test his transceiver product.

6.4 A performance test application alone shall only be accepted for a transceiver type and model already issued an approval reference number by the RA. If a transceiver product does not have an approval reference number, the test shall only be performed in combination with transceiver conformance testing in accordance with ISO 24631-2.

6.5 The manufacturer shall send a transceiver and all necessary accessories to the RA-approved test centre. It is permitted to request the RA-approved test centre to use a transceiver already used for conformance testing. The manufacturer shall ensure that the equipment is able to display or store the transponder codes during testing.

6.6 The RA-approved test centre shall verify the transceivers using the test procedures specified in Clause 7.

6.7 The RA-approved test centre shall prepare a confidential report of the results and shall send two copies (and an electronic version) of the report to the chairman of the RA.

6.8 The RA chairman shall inform the manufacturer of the test results in a letter together with a copy of the report.

6.9 The tested transceivers shall be kept by the RA-approved test centre, under the ownership of the RA.

6.10 The RA shall make publicly available the main results of the test, including a photograph of the approved transceiver. A manufacturer shall have the right to refuse that the results be made publicly available or to request their withdrawal from public availability. In the first case, the manufacturer shall send a request to the RA not to publish, within two weeks of having received the test report. In the second, the manufacturer shall send a request to the RA and the RA shall remove the results from public availability within four weeks of receipt of this request.

6.11 The RA shall do everything within its power to protect the integrity of this procedure with regard to ISO 11784 and ISO 11785.

7 Test procedures

7.1 Test apparatus

7.1.1 Transponder emulation circuit (TEC), designed in accordance with Annex B.

The TEC shall be used in the place of an FDX-B or HDX transponder in order to guarantee comparability of results between the different tests and ensure that results will be reproducible in every laboratory, whenever needed. Built from standard components, it also serves to avoid deviations that can occur due to progress in technology or the spread in production of commercially available transponders.

7.2 Test conditions

The test conditions shall be as follows.

Ambient temperature:	minimum 15 °C and maximum 30 °C
Ambient humidity:	minimum 40 % rH and maximum 80 % rH
Ambient noise floor and ambient peak noise:	< 30 dBµV/m (bandwidth 2,7 kHz) 50 Hz to 1 MHz during measurements

Special attention shall be given to spurious emissions, which can be emitted, for example, by insufficiently shielded computer monitors. The electromagnetic test conditions of the measurements shall be checked by carrying out the measurements both with and without a transponder in the field.

7.3 Measurement of reading distance diagram

7.3.1 Purpose

The purpose of this test is to determine the reading test distance as a function of the transponder coil position relative to the transceiver antenna, and also called *antenna pattern*. It is applied to the paths:

- transceiver to transponder (downlink), which is the activation field strength parameter;
- transponder to transceiver (uplink), which is the sensitivity parameter.

7.3.2 Transponder orientation

The *optimum* orientation for the different antenna types is as follows.

a) TUT with loop antenna

- 1) Air-coil transponder, as used with the TEC: the transponder shall be orientated parallel to the antenna plane.
- 2) Ferrite-coil transponder: it shall be orientated perpendicular to the antenna plane.

b) TUT with ferrite antenna

- 1) Air-coil transponder, as used with the TEC: the antenna plane shall be orientated perpendicular to the axis of the ferrite antenna of the TUT.
- 2) Ferrite-coil transponder: measurements shall be performed in the optimum orientation, in which the transponder is orientated in parallel with the antenna axis of the TUT's ferrite coil, as well as in a *minimum* orientation, in which the transponder is oriented perpendicular to the optimum orientation.

7.3.3 Test geometry

The measurements shall be performed in a test plane. Within that plane, the origin or reference point is well defined in respect to the housing of the transceiver antenna.

- a) Transceiver loop antenna: the test plane shall be perpendicular to the antenna.
- b) Ferrite antenna: the axis of the ferrite shall lie within the test plane.

Polar coordinates shall be applied for the position of the air-coil of the TEC. The measurements shall be taken in 10° steps, as shown in Figure 1.

The TEC coil shall be aligned, as appropriate, in accordance with 7.3.2.

For a symmetric antenna design, only 10 measurements are required to define the complete three-dimensional reading range of the transceiver.

However, if the transceiver antenna has been designed so as not to emit a symmetric field around its axis, or if it has a non-symmetric sensitivity characteristic, 20 measurements shall be performed in two orthogonal test planes, such as X-Y and X-Z. See Figures 1 and 2.