



**GEO-Mobile Radio Interface Specifications (Release 3);
Third Generation Satellite Packet Radio Service;
Part 5: Radio interface physical layer specifications;
Sub-part 2: Multiplexing and Multiple Access;
Stage 2 Service Description;
GMR-1 3G 45.002**

https://standards.etsi.org/standards/etsi-ts/101-376-5-2/v3.4.1/2015-10/etsi-ts-101-376-5-2-v3.4.1-2015-10.pdf
7d71-4a75-9899-eef31216eef1a97e92d2-

ReferenceRTS/SES-00374-5-2

Keywords

3G, GMPRS, GMR, GPRS, GSM, GSO,
interface, MES, mobile, MSS, MUX, radio,
satellite, S-PCN, TDMA

ETSI

650 Route des Lucioles
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - NAF 742 C
Association à but non lucratif enregistrée à la
Sous-Préfecture de Grasse (06) N° 7803/88

Important notice

The present document can be downloaded from:
<http://www.etsi.org/standards-search>

The present document may be made available in electronic versions and/or in print. The content of any electronic and/or print versions of the present document shall not be modified without the prior written authorization of ETSI. In case of any existing or perceived difference in contents between such versions and/or in print, the only prevailing document is the print of the Portable Document Format (PDF) version kept on a specific network drive within ETSI Secretariat.

Users of the present document should be aware that the document may be subject to revision or change of status.
Information on the current status of this and other ETSI documents is available at
<http://portal.etsi.org/tb/status/status.asp>

If you find errors in the present document, please send your comment to one of the following services:
<https://portal.etsi.org/People/CommitteeSupportStaff.aspx>

Copyright Notification

No part may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm except as authorized by written permission of ETSI.

The content of the PDF version shall not be modified without the written authorization of ETSI.
The copyright and the foregoing restriction extend to reproduction in all media.

© European Telecommunications Standards Institute 2015.
All rights reserved.

DECT™, PLUGTESTS™, UMTS™ and the ETSI logo are Trade Marks of ETSI registered for the benefit of its Members.
3GPP™ and **LTE™** are Trade Marks of ETSI registered for the benefit of its Members and
of the 3GPP Organizational Partners.
GSM® and the GSM logo are Trade Marks registered and owned by the GSM Association.

Contents

Intellectual Property Rights	7
Foreword.....	7
Modal verbs terminology.....	8
Introduction	8
1 Scope	10
2 References	10
2.1 Normative references	10
2.2 Informative references.....	11
3 Definitions and abbreviations.....	11
3.1 Definitions.....	11
3.2 Abbreviations	11
4 General	11
5 Logical channels.....	11
5.1 General	11
5.2 Traffic channels.....	11
5.2.1 General.....	11
5.2.2 Speech traffic channels	12
5.2.3 Data traffic channels	12
5.2.4 Summary of traffic channel characteristics.....	12
5.2.5 Packet Data Traffic CHannels (PDTCH) (A/Gb mode only)	12
5.2.5a Packet Data Traffic Channels (PDTCH3) (Iu mode only).....	13
5.2.6 Packet Mode Dedicated Channels (Iu mode only)	14
5.3 Control channels.....	15
5.3.1 General.....	15
5.3.2 Broadcast channels	15
5.3.2.1 Frequency Correction CHannel (FCCH)	15
5.3.2.2 GPS Broadcast control CHannel (GBCH)	15
5.3.2.3 Broadcast Control CHannel (BCCH)	15
5.3.3 Common Control Channel (CCCH).....	15
5.3.4 Dedicated control channels	15
5.3.5 Cell Broadcast CHannel (CBCH)	15
5.3.6 Packet Common Control CHannels (PCCCH)	15
5.3.7 Packet dedicated control channels	16
6 The physical resource	16
6.1 General	16
6.2 Radio frequency channels.....	16
6.2.1 Spot beam allocation.....	16
6.2.2 Downlink and uplink	16
6.3 Timeslots and TDMA frames.....	16
6.3.1 General.....	16
6.3.2 Timeslot number	16
6.3.3 TDMA frame number	16
7 Bursts.....	16
7.1 General	16
7.2 Timing	17
7.2.1 Half-symbol period	17
7.2.2 Useful duration	17
7.2.3 Guard period	17
7.3 Multiple unique word patterns in bursts	18
7.4 Types of bursts	18
7.4.0 General.....	18
7.4.1 BACH burst	18

7.4.1.0	General	18
7.4.1.1	BACH3 burst.....	18
7.4.2	BCCH burst	18
7.4.3	CICH burst.....	18
7.4.4	DC2 burst.....	18
7.4.5	DC6 burst.....	18
7.4.6	DKAB bursts	19
7.4.6.0	General.....	19
7.4.6.1	KAB3 burst	19
7.4.7	FCCH burst.....	20
7.4.7.0	General.....	20
7.4.7.1	FCCH3 burst	20
7.4.8	NT3 burst.....	20
7.4.8.0	General	20
7.4.8.1	NT3 burst for encoded speech.	20
7.4.8.2	NT3 burst for FACCH	20
7.4.9	NT6 burst.....	20
7.4.10	NT9 burst.....	20
7.4.11	RACH burst	21
7.4.11.0	General	21
7.4.11.1	RACH3 burst.....	21
7.4.12	SDCCH burst.....	21
7.4.13	Packet Normal Bursts (PNB).....	21
7.4.13.0	General	21
7.4.13.1	Burst header	25
7.4.13.1.0	General	25
7.4.13.1.1	Guard bits	25
7.4.13.1.2	Unique Word (UW).....	25
7.4.13.1.3	PUBLIC Information (PUI) field.....	26
7.4.13.1.4	Transition symbols	26
7.4.13.2	Encoded PRivate Information (PRI)	26
7.4.13.3	Formats of packet normal burst.....	27
7.4.13.3.0	General	27
7.4.13.3.1	Void.....	27
7.4.13.3.2	PNB(4,3).....	27
7.4.13.3.3	PNB(5,3).....	27
7.4.13.3.4	PNB(1,6).....	28
7.4.13.3.5	PNB(2,6).....	28
7.4.13.3.6	LDPC coded PNB2(5,12)/Downlink	29
7.4.13.3.7	LDPC coded PNB2(5,12)/Uplink	30
7.4.13.3.8	LDPC coded PNB2(5,3)/Downlink	30
7.4.13.3.9	LDPC coded PNB2(5,3)/Uplink	31
7.4.13.3.10	PNB3(5,12)/Uplink	32
7.4.13.3.11	PNB3(5,12)/Downlink.....	32
7.4.13.3.12	PNB3(5,3)/Uplink	33
7.4.13.3.13	PNB3(5,3)/Downlink.....	34
7.4.13.3.14	PNB3(10,3) Downlink.....	35
7.4.13.3.15	PNB3(1,3) Burst	36
7.4.13.3.16	PNB3(1,6) burst.....	37
7.4.13.3.17	PNB3(1,8) burst.....	38
7.4.13.3.18	PNB3(2,6).....	39
7.4.14	Packet Access Burst (PAB)	40
7.4.15	Packet Keep-Alive Burst (PKAB)	40
7.4.16	DC12 burst.....	42
8	Logical-physical channel mapping.....	43
8.1	General	43
8.1.0	Abstract.....	43
8.1.1	Frequency-domain description.....	43
8.1.2	Time-domain description	43
8.1.2.1	Physical channels	43
8.1.2.2	Logical channels	43

8.2	Physical Channel (PC) types and names	43
8.3	Logical channel parameters.....	43
8.4	Permitted channel configurations	44
8.5	Logical channel frame sequencing concepts	44
8.5.0	General.....	44
8.5.1	Simple frame sequence	44
8.5.1.0	General	44
8.5.1.1	Simple frame sequence subchannels	44
8.5.2	Simple paired-frame sequence	44
8.5.2.0	General	44
8.5.2.1	Simple paired-frame sequence subchannels.....	44
8.5.3	Configured paired-frame sequence (A/Gb mode only).....	44
8.5.3.0	General	44
8.5.3.1	CBCH configuration	44
8.5.3a	CBCH configuration (Iu mode only)	44
8.5.4	Statistically multiplexed paired-frame sequence (A/Gb mode only).....	45
8.5.4.0	General	45
8.5.4.1	Pool size.....	45
8.5.4.2	Statistically multiplexed paired-frame sequence subchannels	45
8.5.4.3	Example using SDCCH.....	45
8.5.5	System information cycle sequencing.....	45
8.5.5.0	General	45
8.5.5.1	Physical-Channel-Relative Timeslot Number (PCRTN)	45
8.5.5.2	System-Information-Relative Frame Number (SIRFN)	45
8.5.5.3	Graphical representation of system information cycle timeslots.....	45
8.6	Mapping of logical channels to BCCH/CCCH.....	45
8.6.0	General.....	45
8.6.1	Fixed reserved-slot logical channels.....	45
8.6.1.0	General	45
8.6.1.1	FCCH	45
8.6.1.1a	FCCH3	45
8.6.1.2	CICH	46
8.6.1.3	BCCH.....	46
8.6.2	Optional reserved-slot logical channels.....	46
8.6.2.0	General	46
8.6.2.1	PCH.....	47
8.6.2.2	BACH	48
8.6.3	Unreserved-slot logical channels	48
8.6.4	Mapping of CBCH (Iu mode)	48
8.7	Mapping of logical channels to normal CCCH	48
8.7a	Mapping of logical channels to SI extended/AGCH/CCCH (Iu mode only)	49
8.8	Mapping in time of packet logical channels onto physical channels.....	50
8.8.1	General.....	50
8.8.2	Mapping of the uplink channels.....	50
8.8.2.1	Mapping of uplink packet traffic channel (PDTCH/U) and PACCH/U	50
8.8.2.2	Mapping of the packet timing advance control channel (PTCCH/U) (A/Gb mode only)	51
8.8.2.3	Mapping of the uplink PCCCH, i.e. PRACH (A/Gb mode only)	51
8.8.2.3a	Mapping of the uplink PCCCH, i.e. PRACH3 (Iu mode only)	51
8.8.3	Mapping of the downlink channels	52
8.8.3.1	Mapping of the (PDTCH/D) and PACCH/D	52
8.8.3.2	Mapping of the PTCCH/D (A/Gb mode only).....	52
8.8.3.3	Mapping of the PBCCH	52
8.8.3.4	Mapping of the PCCCH	52
8.8.4	Mapping of PBCCH data.....	52
8.8.5	Permitted combination of packet data channels.....	52
8.9	Multislot configurations	53
8.9.0	General.....	53
8.9.1	Multislot configurations for circuit switched connections.....	53
8.9.2	Multislot configurations for packet switched connections.....	53
9	Operation of channels.....	53
9.0	General	53

9.1	PC6d and PC12u pairing	53
9.1a	PC12d and PC12u pairing	53
9.2	Bidirectional channel timeslot assignments.....	54
9.3	GBCH.....	54
9.3a	GBCH3.....	54
9.4	DKABs.....	54
9.5	FCCH and CICH	54
9.6	TACCH/2	54
9.7	MES monitoring of paging and alerting groups	54
9.7.0	General.....	54
9.7.1	Determination of assigned CCCH	54
9.7.2	Determination of assigned paging group	54
9.7.3	Determination of alerting group.....	55
9.7.4	Determination of PCCCH_GROUP and PAGING_GROUP for MES in GPRS attached mode	55
9.8	MES selection of PC12U	55
9.9	SDCCH vs. CBCH	55
9.10	MES monitors paired CCCH for AGCH	55
9.11	Additional air interface constraints.....	55
10	BCCH parameters	55
10.0	General	55
10.1	Types of BCCH parameters.....	55
10.2	Information used to obtain synchronization	55
10.3	Channel meta-information.....	55
10.4	Beam-configurable multichannel information.....	56
10.5	Information specific to one instance of a channel	56
Annex A (normative): Multislot capability.....		57
A.1	MES classes for multislot capability.....	57
A.2	Constraints imposed by the service selected	58
A.3	Network requirements for supporting MES multislot classes	58
Annex B (informative): Asymmetrical pairing of PDCH/D(2,m) with PDCH/U(1,m).....		59
Annex C (normative): GMR-1 3G Terminal Types		60
Annex D (informative): Bibliography		77
History		78

Intellectual Property Rights

IPRs essential or potentially essential to the present document may have been declared to ETSI. The information pertaining to these essential IPRs, if any, is publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: "Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards", which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (<http://ipr.etsi.org>).

Pursuant to the ETSI IPR Policy, no investigation, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

Foreword

This Technical Specification (TS) has been produced by ETSI Technical Committee Satellite Earth Stations and Systems (SES).

The contents of the present document are subject to continuing work within TC-SES and may change following formal TC-SES approval. Should TC-SES modify the contents of the present document it will then be republished by ETSI with an identifying change of release date and an increase in version number as follows:

Version 3.m.n

where:

- the third digit (n) is incremented when editorial only changes have been incorporated in the specification;
- the second digit (m) is incremented for all other types of changes, i.e. technical enhancements, corrections, updates, etc.

The present document is part 5, sub-part 2 of a multi-part deliverable covering the GEO-Mobile Radio Interface Specifications (Release 3); Third Generation Satellite Packet Radio Service, as identified below:

Part 1: "General specifications";

Part 2: "Service specifications";

Part 3: "Network specifications";

Part 4: "Radio interface protocol specifications";

Part 5: "Radio interface physical layer specifications":

Sub-part 1: "Physical Layer on the Radio Path: General Description";

Sub-part 2: "Multiplexing and Multiple Access; Stage 2 Service Description";

Sub-part 3: "Channel Coding";

Sub-part 4: "Modulation";

Sub-part 5: "Radio Transmission and Reception";

Sub-part 6: "Radio Subsystem Link Control";

Sub-part 7: "Radio Subsystem Synchronization";

Part 6: "Speech coding specifications";

Part 7: "Terminal adaptor specifications".

Modal verbs terminology

In the present document "**shall**", "**shall not**", "**should**", "**should not**", "**may**", "**need not**", "**will**", "**will not**", "**can**" and "**cannot**" are to be interpreted as described in clause 3.2 of the [ETSI Drafting Rules](#) (Verbal forms for the expression of provisions).

"must" and **"must not"** are **NOT** allowed in ETSI deliverables except when used in direct citation.

Introduction

GMR stands for GEO (Geostationary Earth Orbit) Mobile Radio interface, which is used for Mobile Satellite Services (MSS) utilizing geostationary satellite(s). GMR is derived from the terrestrial digital cellular standard GSM and supports access to GSM core networks.

The present document is part of the GMR Release 3 specifications. Release 3 specifications are identified in the title and can also be identified by the version number:

- Release 1 specifications have a GMR 1 prefix in the title and a version number starting with "1" (V1.x.x).
- Release 2 specifications have a GMPRS 1 prefix in the title and a version number starting with "2" (V2.x.x).
- Release 3 specifications have a GMR-1 3G prefix in the title and a version number starting with "3" (V3.x.x).

The GMR release 1 specifications introduce the GEO Mobile Radio interface specifications for circuit mode Mobile Satellite Services (MSS) utilizing geostationary satellite(s). GMR release 1 is derived from the terrestrial digital cellular standard GSM (phase 2) and it supports access to GSM core networks.

The GMR release 2 specifications add packet mode services to GMR release 1. The GMR release 2 specifications introduce the GEO Mobile Packet Radio Service (GMPRS). GMPRS is derived from the terrestrial digital cellular standard GPRS (included in GSM Phase 2+) and it supports access to GSM/GPRS core networks.

The GMR release 3 specifications evolve packet mode services of GMR release 2 to 3rd generation UMTS compatible services. The GMR release 3 specifications introduce the GEO-Mobile Radio Third Generation (GMR-1 3G) service. Where applicable, GMR-1 3G is derived from the terrestrial digital cellular standard 3GPP and it supports access to 3GPP core networks.

Due to the differences between terrestrial and satellite channels, some modifications to the GSM or 3GPP standard are necessary. Some GSM and 3GPP specifications are directly applicable, whereas others are applicable with modifications. Similarly, some GSM and 3GPP specifications do not apply, while some GMR specifications have no corresponding GSM or 3GPP specification.

Since GMR is derived from GSM and 3GPP, the organization of the GMR specifications closely follows that of GSM or 3GPP as appropriate. The GMR numbers have been designed to correspond to the GSM and 3GPP numbering system. All GMR specifications are allocated a unique GMR number. This GMR number has a different prefix for Release 2 and Release 3 specifications as follows:

- Release 1: GMR n xx.zyy.
- Release 2: GMPRS n xx.zyy.
- Release 3: GMR-1 3G xx.zyy.

where:

- xx.0yy (z = 0) is used for GMR specifications that have a corresponding GSM or 3GPP specification. In this case, the numbers xx and yy correspond to the GSM or 3GPP numbering scheme.
- xx.2yy (z = 2) is used for GMR specifications that do not correspond to a GSM or 3GPP specification. In this case, only the number xx corresponds to the GSM or 3GPP numbering scheme and the number yy is allocated by GMR.
- n denotes the first (n = 1) or second (n = 2) family of GMR specifications.

A GMR system is defined by the combination of a family of GMR specifications and GSM and 3GPP specifications as follows:

- If a GMR specification exists it takes precedence over the corresponding GSM or 3GPP specification (if any). This precedence rule applies to any references in the corresponding GSM or 3GPP specifications.

NOTE: Any references to GSM or 3GPP specifications within the GMR specifications are not subject to this precedence rule. For example, a GMR specification may contain specific references to the corresponding GSM or 3GPP specification.

- If a GMR specification does not exist, the corresponding GSM or 3GPP specification may or may not apply. The applicability of the GSM or 3GPP specifications is defined in ETSI TS 101 376-1-2 [2].

The clause numbering and the table numbering and figure numbering in the present document are aligned to the corresponding numbering of ETSI TS 101 376-5-2 (Release 1) [10] as far as possible. In several places, this means that the table numbering and figure numbering is non-continuous in the present document in order to maintain this alignment, the following rules apply:

- A table that uses the same table number replaces the corresponding table in ETSI TS 101 376-5-2 (Release 1) [10].
- A table that uses a different table number is a new additional table.

iteh STANDARD PREVIEW
(standards.iteh.ai)
Full standard:
<https://standards.iteh.ai/catalog/standards/sist/a97e92d2-7d71-4a75-9859-ce7120d6316b/etsi-ts-101-376-5-2-v3.4.1-2015-10>

1 Scope

The present document defines the structure of the physical channels for the radio subsystem in the GMR-1 3G Mobile Satellite System. It describes the GMR-1 3G concept of logical channels and the timing concepts of TDMA frames, timeslots, and bursts. It defines the relationship between logical and physical channels, and defines the logical channels in terms of size, structure and timing relationships.

2 References

2.1 Normative references

References are either specific (identified by date of publication and/or edition number or version number) or non-specific. For specific references, only the cited version applies. For non-specific references, the latest version of the reference document (including any amendments) applies.

Referenced documents which are not found to be publicly available in the expected location might be found at <http://docbox.etsi.org/Reference>.

NOTE: While any hyperlinks included in this clause were valid at the time of publication, ETSI cannot guarantee their long term validity.

The following referenced documents are necessary for the application of the present document.

In the case of a reference to a 3GPP document (including a GSM document), a non-specific reference implicitly refers to the latest release and the latest version of that document up to and including Release 7.

In the case of a reference to a GMR-1 3G document, a non-specific reference implicitly refers to the latest version of that document in the same Release as the present document.

- [1] ETSI TS 101 376-1-1: "GEO-Mobile Radio Interface Specifications (Release 2) General Packet Radio Service; Part 1: General specifications; Sub-part 1: Abbreviations and acronyms; GMPRS-1 01.004".

NOTE: This is a reference to a GMR-1 Release 2 specification. See the introduction for more details.

- [2] ETSI TS 101 376-1-2: "GEO-Mobile Radio Interface Specifications (Release 3); Third Generation Satellite Packet Radio Service; Part 1: General specifications; Sub-part 2: Introduction to the GMR-1 family; GMR-1 3G 41.201".

- [3] ETSI TS 101 376-4-8: "GEO-Mobile Radio Interface Specifications (Release 3); Third Generation Satellite Packet Radio Service; Part 4: Radio interface protocol specifications; Sub-part 8: Mobile Radio Interface Layer 3 Specifications; GMR-1 3G 44.008".

- [4] ETSI TS 101 376-5-3: "GEO-Mobile Radio Interface Specifications (Release 3); Third Generation Satellite Packet Radio Service; Part 5: Radio interface physical layer specifications; Sub-part 3: Channel Coding; GMR-1 3G 45.003".

- [5] ETSI TS 101 376-5-4: "GEO-Mobile Radio Interface Specifications (Release 3); Third Generation Satellite Packet Radio Service; Part 5: Radio interface physical layer specifications; Sub-part 4: Modulation; GMR-1 3G 45.004".

- [6] ETSI TS 101 376-5-5: "GEO-Mobile Radio Interface Specifications (Release 3); Third Generation Satellite Packet Radio Service; Part 5: Radio interface physical layer specifications; Sub-part 5: Radio Transmission and Reception; GMR-1 3G 45.005".

- [7] ETSI TS 101 376-5-7: "GEO-Mobile Radio Interface Specifications (Release 3); Third Generation Satellite Packet Radio Service; Part 5: Radio interface physical layer specifications; Sub-part 7: Radio Subsystem Synchronization; GMR-1 3G 45.010".

- [8] ETSI TS 101 376-3-22: "GEO-Mobile Radio Interface Specifications (Release 3); Third Generation Satellite Packet Radio Service; Part 3: Network specifications; Sub-part 22: Overall description of the GMPRS radio interface; Stage 2; GMR-1 3G 43.064".

- [9] ETSI TS 101 376-4-12: "GEO-Mobile Radio Interface Specifications (Release 3); Third Generation Satellite Packet Radio Service; Part 4: Radio interface protocol specifications; Sub-part 12: Mobile Earth Station (MES) - Base Station System (BSS) interface; Radio Link Control/Medium Access Control (RLC/MAC) protocol; GMR-1 3G 44.060".
- [10] ETSI TS 101 376-5-2: "GEO-Mobile Radio Interface Specifications; Part 5: Radio interface physical layer specifications; Sub-part 2: Multiplexing and Multiple Access; Stage 2 Service Description; Sub-part 2: Multiplexing and Multiple Access; Stage 2 Service Description; GMR-1 05.002".

NOTE: This is a reference to a GMR-1 Release 1 specification. See the introduction for more details.

2.2 Informative references

References are either specific (identified by date of publication and/or edition number or version number) or non-specific. For specific references, only the cited version applies. For non-specific references, the latest version of the reference document (including any amendments) applies.

NOTE: While any hyperlinks included in this clause were valid at the time of publication, ETSI cannot guarantee their long term validity.

The following referenced documents are not necessary for the application of the present document but they assist the user with regard to a particular subject area.

Not applicable.

3 Definitions and abbreviations

3.1 Definitions

For the purposes of the present document, the terms and definitions given in GMR-1 3G 41.201 [2] apply.

3.2 Abbreviations

For the purposes of the present document, the abbreviations given in GMPRS-1 01.004 [1] apply.

4 General

Same as clause 4 in ETSI TS 101 376-5-2 [10].

5 Logical channels

5.1 General

Same as clause 5.1 in ETSI TS 101 376-5-2 [10].

5.2 Traffic channels

5.2.1 General

TCHs are intended to carry either encoded speech or user data. Three general types of traffic channels are defined:

- 1) TCH3: This channel carries data at a gross rate of 5,20 kbps.
- 2) TCH6: This channel carries data at a gross rate of 10,75 kbps.
- 3) TCH9: This channel carries data at a gross rate of 16,45 kbps.

The data gross rate is defined as the number of encoded bits in NT3, NT6 and NT9 burst, respectively, excluding the number of power control bits, divided by 40 ms frame time.

All traffic channels are bidirectional.

The types of traffic channels capable of speech and user data are identified in the following clauses.

5.2.2 Speech traffic channels

Same as clause 5.2.2 in ETSI TS 101 376-5-2 [10].

5.2.3 Data traffic channels

Same as clause 5.2.3 in ETSI TS 101 376-5-2 [10].

5.2.4 Summary of traffic channel characteristics

Table 5.1 summarizes the characteristics of traffic channels, where the gross transmission rate is the channel transmission bit rate (2 times channel transmission symbol rate) multiplied by the duty cycle of the channel.

Table 5.1: Summary of traffic channel characteristics

Channel type	User information capability	Gross transmission rate
TCH3	Encoded speech	5,85 kbps (= 46,8 / 8)
TCH6	User data: 4,8 kbps Fax: 2 kbps, 4 kbps or 4,8 kbps	11,70 kbps (= 46,8 / 8 x 2)
TCH9	User data: 9,6 kbps Fax: 2 kbps, 4 kbps, 4,8 kbps, or 9,6 kbps	17,55 kbps (= 46,8 / 8 x 3)

5.2.5 Packet Data Traffic Channels (PDTCH) (A/Gb mode only)

The following Packet Data Traffic Channels (PDTCH) apply to A/Gb mode.

A PDTCH corresponds to the resource allocated to a single MES on one physical channel for user data transmission. Different logical channels may be dynamically multiplexed on to the same PDTCH. The PDTCH uses $\pi/2$ -BPSK, $\pi/4$ -QPSK, 16 APSK, or 32 APSK modulation. All packet data traffic channels are unidirectional, either uplink (PDTCH/U), for a mobile-originated packet transfer or downlink (PDTCH/D) for a mobile-terminated packet transfer. PDTCH and PDTCH2 traffic data channels may be multiplexed on the same physical carrier.

PDTCHs are used to carry packet data traffic. Different PDTCHs are defined by the suffix (m,n) where m indicates the bandwidth of the physical channel in which the PDTCH is mapped, $m \times 31,25$ kHz, and n defines the number of timeslots allocated to this physical channel. Table 5.2 summarizes different types of packet traffic data channels, PDTCH (m, 3), (m = 4 and 5), where the burst duration is 5 ms, PDTCH (m, 6), (m = 1, 2), where the burst duration is 10 ms, and PDTCH (m, 12), (m = 5), where the burst duration is 20 ms.

Table 5.2: Packet Traffic Data Channels (Peak Transmission Rates)

Channels	Direction (U: Uplink, D: Downlink)	Transmission symbol rate (ksp/s)	Channel Coding	Modulation	Peak payload transmission rate (without CRC) (kbps)	Peak payload transmission rate (with CRC) (kbps)
PDTCH(4,3)	U/D	93,6	Conv.	$\pi/4$ -QPSK	113,6	116,8
PDTCH(5,3)	U/D	117,0	Conv.	$\pi/4$ -QPSK	145,6	148,8
PDTCH(1,6)	U	23,4	Conv.	$\pi/4$ -QPSK	27,2	28,8
PDTCH(2,6)	D	46,8	Conv.	$\pi/4$ -QPSK	62,4	64,0
PDTCH2(5,12)	D	117,0	LDPC	$\pi/4$ -QPSK	199,2	199,6
PDTCH2(5,12)	D	117,0	LDPC	16-APSK	354,8	355,2
PDTCH2(5,12)	D	117,0	LDPC	32-APSK	443,6	444,0
PDTCH2(5,12)	U	117,0	LDPC	$\pi/4$ -QPSK	199,2	199,6
PDTCH2(5,12)	U	117,0	LDPC	16-APSK	399,2	399,6
PDTCH2(5,3)	U/D	117,0	LDPC	$\pi/4$ -QPSK	169,6	171,2
PDTCH2(5,3)	U/D	117,0	LDPC	16-APSK	342,4	344,0
PDTCH2(5,3)	U/D	117,0	LDPC	32-APSK	380,8	382,4

The payload is the Private Information (PRI) delivered to the physical layer by the link layer. The PRI includes the MAC header and the other higher layer overhead. The peak payload transmission rate (without CRC) is defined as the maximum attainable PRI data rate with continuous transmission, i.e. using all 24 timeslots in a frame. The above peak-rates are achieved with rate 3/4 coding for PDTCH(4,3) and PDTCH(5,3) and are achieved with rate 4/5 for PDTCH(1,6) and PDTCH(2,6). The peak rates of LDPC coded PDTCH2(5,12) and LDPC coded PDTCH2(5,3) are achieved for different modulation schemes with the following coding rate combinations:

- Downlink: 32 APSK Rate 4/5, 16 APSK Rate 4/5, $\pi/4$ -QPSK Rate 9/10.
- Uplink: 16 APSK Rate 9/10, $\pi/4$ -QPSK Rate 9/10.

NOTE: All the above coding rates are approximate rates. Refer to ETSI TS 101 376-5-3 [4] for the exact coding rates.

5.2.5a Packet Data Traffic Channels (PDTCH3) (Iu mode only)

The following Packet Data Traffic Channels3 (PDTCH3) apply to Iu mode.

A PDTCH3 corresponds to the resource allocated to a single MES on one physical channel for user data transmission. Different logical channels may be dynamically multiplexed on to the same PDTCH3. The PDTCH3 uses $\pi/2$ -BPSK, $\pi/4$ -QPSK, 16 APSK, or 32 APSK modulation. All packet data traffic channels are unidirectional, either uplink (PDTCH3/U), for a mobile-originated packet transfer or downlink (PDTCH3/D) for a mobile-terminated packet transfer. PDTCH3 may not be multiplexed with PDTCH and PDTCH2 on the same physical carrier.