

ETSI TS 125 104 V12.7.0 (2016-01)



Universal Mobile Telecommunications System (UMTS); Base Station (BS) radio transmission and reception (FDD) (3GPP TS 25.104 version 12.7.0 Release 12)

Standard Preview
Full standard available at: <https://standards.iteh.ai/catalog/standards/sist/ee00917e-b0df-42b8-8869-4201dfede482/etsi-ts-125-104-v12.7.0-2016-01>



Reference

RTS/TSGR-0425104vc70

Keywords

UMTS**ETSI**

650 Route des Lucioles
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - NAF 742 C
Association à but non lucratif enregistrée à la
Sous-Préfecture de Grasse (06) N° 7803/88

Important notice

The present document can be downloaded from:

<http://www.etsi.org/standards-search>

The present document may be made available in electronic versions and/or in print. The content of any electronic and/or print versions of the present document shall not be modified without the prior written authorization of ETSI. In case of any existing or perceived difference in contents between such versions and/or in print, the only prevailing document is the print of the Portable Document Format (PDF) version kept on a specific network drive within ETSI Secretariat.

Users of the present document should be aware that the document may be subject to revision or change of status.

Information on the current status of this and other ETSI documents is available at

<http://portal.etsi.org/tb/status/status.asp>

If you find errors in the present document, please send your comment to one of the following services:

<https://portal.etsi.org/People/CommiteeSupportStaff.aspx>

Copyright Notification

No part may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm except as authorized by written permission of ETSI.

The content of the PDF version shall not be modified without the written authorization of ETSI.

The copyright and the foregoing restriction extend to reproduction in all media.

© European Telecommunications Standards Institute 2016.

All rights reserved.

DECT™, **PLUGTESTS™**, **UMTS™** and the ETSI logo are Trade Marks of ETSI registered for the benefit of its Members.
3GPP™ and **LTE™** are Trade Marks of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners.
GSM® and the GSM logo are Trade Marks registered and owned by the GSM Association.

Intellectual Property Rights

IPRs essential or potentially essential to the present document may have been declared to ETSI. The information pertaining to these essential IPRs, if any, is publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: *"Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards"*, which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (<https://ipr.etsi.org>).

Pursuant to the ETSI IPR Policy, no investigation, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

Foreword

This Technical Specification (TS) has been produced by ETSI 3rd Generation Partnership Project (3GPP).

The present document may refer to technical specifications or reports using their 3GPP identities, UMTS identities or GSM identities. These should be interpreted as being references to the corresponding ETSI deliverables.

The cross reference between GSM, UMTS, 3GPP and ETSI identities can be found under <http://webapp.etsi.org/key/queryform.asp>.

Modal verbs terminology

In the present document "**shall**", "**shall not**", "**should**", "**should not**", "**may**", "**need not**", "**will**", "**will not**", "**can**" and "**cannot**" are to be interpreted as described in clause 3.2 of the [ETSI Drafting Rules](#) (Verbal forms for the expression of provisions).

"**must**" and "**must not**" are **NOT** allowed in ETSI deliverables except when used in direct citation.

Contents

Intellectual Property Rights	2
Foreword.....	2
Modal verbs terminology.....	2
Foreword.....	7
1 Scope	8
2 References	8
3 Definitions and abbreviations.....	8
3.1 Definitions	8
3.2 Abbreviations	10
3.3 Symbols.....	11
4 General	12
4.1 Relationship between Minimum Requirements and Test Requirements	12
4.2 Base station classes	12
4.3 Regional requirements.....	13
4.4 Environmental requirements for the BS equipment	14
4.5 Applicability of requirements.....	14
4.6 Requirements for contiguous and non-contiguous spectrum.....	14
4.7 Requirements for BS capable of multi-band operation	15
5 Frequency bands and channel arrangement.....	15
5.1 General	15
5.2 Frequency bands.....	16
5.3 Tx-Rx frequency separation.....	18
5.4 Channel arrangement.....	18
5.4.1 Channel spacing.....	18
5.4.2 Channel raster	19
5.4.3 Channel number	19
6 Transmitter characteristics	20
6.1 General	20
6.2 Base station output power	21
6.2.1 Base station maximum output power.....	21
6.2.1.1 Minimum requirement	21
6.3 Frequency error	22
6.3.1 Minimum requirement	22
6.4 Output power dynamics.....	22
6.4.1 Inner loop power control in the downlink.....	22
6.4.1.1 Power control steps	22
6.4.1.1.1 Minimum requirement.....	22
6.4.2 Power control dynamic range	23
6.4.2.1 Minimum requirements	23
6.4.3 Total power dynamic range	23
6.4.3.1 Minimum requirement	23
6.4.4 Primary CPICH power.....	23
6.4.4.1 Minimum requirement	23
6.4.4A Secondary CPICH power.....	23
6.4.4A.1 Minimum Requirement for MIMO mode.....	24
6.4.4A.2 Minimum Requirement for MIMO mode with four transmit antennas	24
6.4.4B Demodulation CPICH power for MIMO mode with four transmit antennas.....	24
6.4.4B.1 Minimum Requirement.....	24
6.4.5 IPDL time mask	24
6.4.5.1 Minimum Requirement	24
6.4.6 Home base station output power for adjacent channel protection.....	25

6.4.6.1	Minimum requirement	26
6.5	(void)	26
6.6	Output RF spectrum emissions	26
6.6.1	Occupied bandwidth	26
6.6.1.1	Minimum requirement	26
6.6.2	Out of band emission	26
6.6.2.1	Spectrum emission mask	26
6.6.2.2	Adjacent Channel Leakage power Ratio (ACLR)	32
6.6.2.2.1	Minimum requirement	33
6.6.2.2.2	Cumulative ACLR requirement in non-contiguous spectrum	33
6.6.3	Spurious emissions	34
6.6.3.1	Mandatory Requirements	35
6.6.3.1.1	Spurious emissions (Category A)	35
6.6.3.1.2	Spurious emissions (Category B)	35
6.6.3.2	Protection of the BS receiver of own or different BS	37
6.6.3.2.1	Minimum Requirement	37
6.6.3.3	Co-existence with other systems in the same geographical area	39
6.6.3.3.1	Minimum Requirements	40
6.6.3.4	Co-existence with co-located and co-sited base stations	43
6.6.3.4.1	Minimum Requirements	44
6.6.3.5	Co-existence with PHS	49
6.6.3.5.1	Minimum Requirement	49
6.6.3.6	Co-existence with services in adjacent frequency bands	49
6.6.3.6.1	Minimum requirement	49
6.6.3.7	Void	50
6.6.3.7.1	Void	50
6.6.3.7.2	Void	50
6.6.3.8	Protection of Public Safety Operations	50
6.6.3.8.1	Minimum Requirement	50
6.6.3.9	Co-existence with Home BS operating in other bands	50
6.6.3.9.1	Minimum Requirements	51
6.7	Transmitter intermodulation	52
6.7.1	Minimum requirement	52
6.8	Transmit modulation	52
6.8.1	Transmit pulse shape filter	53
6.8.2	Error Vector Magnitude	53
6.8.2.1	Minimum requirement	53
6.8.3	Peak code Domain error	53
6.8.3.1	Minimum requirement	53
6.8.4	Time alignment error	53
6.8.4.1	Minimum Requirements	54
6.8.5	Relative Code Domain Error for 64QAM modulation	54
6.8.5.1	Minimum requirement	54
7	Receiver characteristics	54
7.1	General	54
7.2	Reference sensitivity level	55
7.2.1	Minimum requirement	55
7.2.2	Maximum Frequency Deviation for Receiver Performance	55
7.3	Dynamic range	55
7.3.1	Minimum requirement	55
7.4	Adjacent Channel Selectivity (ACS)	56
7.4.1	Minimum requirement	56
7.4.2	Minimum requirement - Co-location with UTRA-TDD	56
7.5	Blocking characteristics	56
7.5.1	Minimum requirement	56
7.5.2	Minimum Requirement - Co-location with GSM, DCS, PCS, CDMA, UTRA and/or E-UTRA, UTRA TDD and/or E-UTRA TDD	65
7.5.3	Void	71
7.6	Intermodulation characteristics	71
7.6.1	Minimum requirement	71
7.7	Spurious emissions	73

7.7.1	Minimum requirement	74
8	Performance requirement	74
8.1	General	74
8.2	Demodulation in static propagation conditions	75
8.2.1	Demodulation of DCH.....	75
8.2.1.1	Minimum requirement	75
8.3	Demodulation of DCH in multipath fading conditions	76
8.3.1	Multipath fading Case 1.....	76
8.3.1.1	Minimum requirement	76
8.3.2	Multipath fading Case 2.....	76
8.3.2.1	Minimum requirement	76
8.3.3	Multipath fading Case 3.....	77
8.3.3.1	Minimum requirement	77
8.3.4	Multipath fading Case 4.....	77
8.3.4.1	Minimum requirement	78
8.4	Demodulation of DCH in moving propagation conditions.....	78
8.4.1	Minimum requirement	78
8.5	Demodulation of DCH in birth/death propagation conditions.....	78
8.5.1	Minimum requirement	79
8.5A	Demodulation of DCH in high speed train conditions	79
8.5A.1	General.....	79
8.5A.2	Minimum requirement	79
8.6	(void).....	79
8.7	Performance requirement for RACH.....	79
8.7.1	Performance requirement for RACH preamble detection.....	79
8.7.2	Demodulation of RACH message.....	80
8.7.2.1	Minimum requirements for Static Propagation Condition.....	80
8.7.2.2	Minimum requirements for Multipath Fading Case 3.....	81
8.7.2.3	Minimum requirements for high speed train conditions	81
8.8	(void).....	82
8.9	(void).....	82
8.10	Performance of ACK/NACK detection for HS-DPCCH.....	82
8.10.1	ACK false alarm	82
8.10.2	ACK mis-detection	82
8.10A	Performance of ACK/NACK detection for 4C-HSDPA HS-DPCCH.....	82
8.10A.1	Performance requirements	83
8.10A.1.1	ACK false alarm.....	83
8.10A.1.2	ACK mis-detection.....	83
8.10A.2	Applicability of requirements	84
8.10B	Performance of ACK/NACK detection for 8C-HSDPA HS-DPCCH.....	84
8.11	Demodulation of E-DPDCH in multipath fading condition	85
8.11A	Demodulation of E-DPDCH and S-E-DPDCH in multipath fading condition for UL MIMO.....	85
8.12	Performance of signaling detection for E-DPCCH in multipath fading condition	86
Annex A (normative): Measurement channels.....		88
A.1	Summary of UL reference measurement channels.....	88
A.2	UL reference measurement channel for 12.2 kbps.....	89
A.3	UL reference measurement channel for 64 kbps.....	90
A.4	UL reference measurement channel for 144 kbps.....	91
A.5	UL reference measurement channel for 384 kbps.....	92
A.6	(void).....	92
A.7	Reference measurement channels for UL RACH	93
A.8	Reference measurement channel for HS-DPCCH.....	93
A.8A	Reference measurement channel for HS-DPCCH for 4C-HSDPA	94
A.9	Summary of E-DPDCH Fixed reference channels.....	95

A.10	E-DPDCH Fixed reference channel 1 (FRC1)	95
A.11	E-DPDCH Fixed reference channel 2 (FRC2)	96
A.12	E-DPDCH Fixed reference channel 3 (FRC3)	97
A.13	E-DPDCH Fixed reference channel 4 (FRC4)	98
A.14	E-DPDCH Fixed reference channel 5 (FRC5)	99
A.15	E-DPDCH Fixed reference channel 6 (FRC6)	100
A.16	E-DPDCH Fixed reference channel 7 (FRC7)	100
A.17	E-DPDCH Fixed reference channel 8 (FRC8)	101
A.18	E-DPDCH Fixed reference channel 9 (FRC9)	102
A.19	E-DPDCH Fixed reference channel 10 (FRC10)	103
Annex B (normative):	Propagation conditions	105
B.1	Static propagation condition	105
B.2	Multi-path fading propagation conditions	105
B.3	Moving propagation conditions	105
B.4	Birth-Death propagation conditions	106
B.4A	High speed train conditions	107
B.5	Multipath fading propagation conditions for E-DPDCH and E-DPCCH	109
Annex C (normative):	Characteristics of the W-CDMA interference signal	110
Annex D (normative):	Regional requirement for protection of DTT	111
Annex E (informative):	Change History	112
History		116

Foreword

This Technical Specification has been produced by the 3GPP.

The contents of the present document are subject to continuing work within the TSG and may change following formal TSG approval. Should the TSG modify the contents of this TS, it will be re-released by the TSG with an identifying change of release date and an increase in version number as follows:

Version 3.y.z

where:

- x the first digit:
 - 1 presented to TSG for information;
 - 2 presented to TSG for approval;
 - 3 Indicates TSG approved document under change control.
- y the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- z the third digit is incremented when editorial only changes have been incorporated in the specification.

iTeh STANDARD PREVIEW
(standards.iteh.ai)
Full standard:
<https://standards.iteh.ai/catalog/standards/sist/6c0917e-b0df-42b8-8869-4201dfede482/etsi-ts-125-104-v12-7-0-2016-01>

1 Scope

This document establishes the Base Station minimum RF characteristics of the FDD mode of UTRA.

2 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- References are either specific (identified by date of publication, edition number, version number, etc.) or non-specific.
- For a specific reference, subsequent revisions do not apply.
- For a non-specific reference, the latest version applies. In the case of a reference to a 3GPP document (including a GSM document), a non-specific reference implicitly refers to the latest version of that document *in the same Release as the present document*.

- [1] ITU-R Recommendation SM.329, "Unwanted emissions in the spurious domain".
- [2] (void)
- [3] ETSI ETR 273-1-2: "Electromagnetic compatibility and Radio spectrum Matters (ERM); Improvement of radiated methods of measurement (using test sites) and evaluation of the corresponding measurement uncertainties; Part 1: Uncertainties in the measurement of mobile radio equipment characteristics; Sub-part 2: Examples and annexes".
- [4] 3GPP TR 25.942 "RF System Scenarios"
- [5] 3GPP TS 45.004: "Digital cellular telecommunications system (Phase 2+); Modulation".
- [6] 3GPP TS 25.213: "Spreading and modulation (FDD)".
- [7] ITU-R recommendation SM.328: "Spectra and bandwidth of emissions".
- [8] 3GPP TS 36.104: "Evolved Universal Terrestrial Radio Access (E-UTRA); Base Station (BS) radio transmission and reception".
- [9] ECC/DEC/(09)03 "Harmonised conditions for MFCN in the band 790-862 MHz", 30 Oct. 2009
- [10] 3GPP TS 37.104: "E-UTRA, UTRA and GSM/EDGE; Multi-Standard Radio (MSR) Base Station (BS) radio transmission and reception".
- [11] 3GPP TS 25.331: "Radio Resource Control. Protocol Specification".
- [12] 3GPP TS 25.214: "Physical layer procedures (FDD)".
- [13] CEPT ECC Decision (13)03, 'The harmonised use of the frequency band 1452-1492 MHz for Mobile/Fixed Communications Networks Supplemental Downlink (MFCN SDL)'.

3 Definitions and abbreviations

3.1 Definitions

For the purposes of the present document, the following definitions apply:

Output power: mean power of one carrier of the base station, delivered to a load with resistance equal to the nominal load impedance of the transmitter.

Rated output power: mean power level per carrier that the manufacturer has declared to be available at the antenna connector.

Maximum output Power: mean power level per carrier of the base station measured at the antenna connector in a specified reference condition.

Mean power: power (transmitted or received) in a bandwidth of at least $(1 + \alpha)$ times the chip rate of the radio access mode.

NOTE 1: $\alpha = 0,22$ is the roll-off factor of the WCDMA signal. The roll-off factor α is defined in section 6.8

NOTE 2: The period of measurement shall be at least one timeslot unless otherwise stated.

MIMO mode: downlink MIMO configuration with two transmit antennas

MIMO mode with four transmit antennas: downlink MIMO configuration with four transmit antennas.

Power control dynamic range: difference between the maximum and the minimum transmit output power of a code channel for a specified reference condition.

RRC filtered mean power: mean power as measured through a root raised cosine filter with roll-off factor α and a bandwidth equal to the chip rate of the radio access mode.

NOTE 1: The RRC filtered mean power of a perfectly modulated W-CDMA signal is 0.246 dB lower than the mean power of the same signal.

NOTE 2: The roll-off factor α is defined in section 6.8.1.

Code domain power: part of the mean power which correlates with a particular (OVSF) code channel.

NOTE: The sum of all powers in the code domain equals the mean power in a bandwidth of $(1 + \alpha)$ times the chip rate of the radio access mode.

Total power dynamic range: difference between the maximum and the minimum total transmit output power for a specified reference condition.

Secondary serving HS-DSCH cell(s): set of cells where the UE is configured to simultaneously monitor an HS-SCCH set and receive the HS-DSCH if it is scheduled in that cell.

NOTE: There can be up to 7 secondary serving HS-DSCH cells in addition to the serving HS-DSCH cell.

Channel bandwidth: RF bandwidth supporting a single UTRA RF carrier.

NOTE: The channel bandwidth is measured in MHz and is used as a reference for transmitter and receiver RF requirements.

Channel edge: lowest or highest frequency of the UTRA carrier, separated by the channel bandwidth.

Base Station RF Bandwidth: bandwidth in which a base station transmits and/or receives single or multiple carriers simultaneously within each supported operating band.

NOTE: In single carrier operation the channel bandwidth is equal to Base Station RF Bandwidth

Base Station RF Bandwidth edge: frequency of one of the edges of the Base Station RF Bandwidth.

Contiguous spectrum: spectrum consisting of a contiguous block of spectrum with no sub-block gap(s).

Highest carrier: carrier with the highest carrier centre frequency transmitted/received in the specified operating band(s).

Non-contiguous spectrum: spectrum consisting of two or more sub-blocks separated by sub-block gap(s).

Radio Bandwidth: frequency difference between the upper edge of the highest used carrier and the lower edge of the lowest used carrier.

Sub-block: one contiguous allocated block of spectrum for use by the same base station.

NOTE: There may be multiple instances of sub-blocks within an Base Station RF Bandwidth.

Sub-block bandwidth: RF bandwidth of one sub-block.

Sub-block gap: frequency gap between two consecutive sub-blocks within an Base Station RF Bandwidth, where the RF requirements in the gap are based on co-existence for un-coordinated operation.

Lower sub-block edge: frequency at the lower edge of one sub-block.

NOTE: It is used as a frequency reference point for both transmitter and receiver requirements.

Lowest carrier: carrier with the lowest carrier centre frequency transmitted/received in the specified operating band(s).

Upper sub-block edge: frequency at the higher edge of one sub-block.

NOTE: It is used as a frequency reference point for both transmitter and receiver requirements.

Inter-band gap: The frequency gap between two supported consecutive operating bands.

Inter RF Bandwidth gap: frequency gap between two consecutive Base Station RF Bandwidths that respectively correspond to two supported operating bands.

Multi-band base station: base station characterized by the ability of its transmitter and/or receiver to process two or more carriers in common active RF components simultaneously, where at least one carrier is configured at a different non-overlapping operating band than the other carrier(s).

Multi-band transmitter: transmitter characterized by the ability to process two or more carriers in common active RF components simultaneously, where at least one carrier is configured at a different non-overlapping operating band than the other carrier(s).

Multi-band receiver: receiver characterized by the ability to process two or more carriers in common active RF components simultaneously, where at least one carrier is configured at a different non-overlapping operating band than the other carrier(s).

Rated total output power: the total power level that the manufacturer has declared to be available at the antenna connector.

3.2 Abbreviations

For the purposes of the present document, the following abbreviations apply:

4C-HSDPA	Four-Carrier HSDPA. HSDPA operation configured on 3 or 4 DL carriers
8C-HSDPA	Eight-Carrier HSDPA. HSDPA operation configured for 5 to 8 DL carriers
16QAM	16 Quadrature Amplitude Modulation
ACIR	Adjacent Channel Interference Ratio
ACLRL	Adjacent Channel Leakage power Ratio
ACS	Adjacent Channel Selectivity
BS	Base Station
BER	Bit Error Ratio
BLER	Block Error Ratio
CACLR	Cumulative ACLR
CPICH	Common Pilot Channel
CW	Continuous Wave (unmodulated signal)
DB-DC-HSDPA	Dual Band Dual Cell HSDPA
DC-HSDPA	Dual Cell HSDPA
DC-HSUPA	Dual Cell HSUPA
DL	Down Link (forward link)
DTT	Digital Terrestrial Television
EIRP	Effective Isotropic Radiated Power
FDD	Frequency Division Duplexing
GSM	Global System for Mobile Communications
HSDPA	High Speed Downlink Packet Access
HSUPA	High Speed Uplink Packet Access
IE	Information Element
LA	Local Area

MIMO	Multiple Input Multiple Output
MR	Medium Range
NC-4C-HSDPA	Non-contiguous Four-Carrier HSDPA. HSDPA operation for two non-adjacent blocks within a single band configured on 2, 3 or 4 DL carriers.
P-CPICH	Primary CPICH
PHS	Personal Handyphone System
PPM	Parts Per Million
RAT	Radio Access Technology
RF	Radio Frequency
QPSK	Quadrature Phase Shift Keying
RSSI	Received Signal Strength Indicator
S-CPICH	Secondary CPICH
SIR	Signal to Interference ratio
TAE	Time Alignment Error
TDD	Time Division Duplexing
TPC	Transmit Power Control
UARFCN	UTRA Absolute Radio Frequency Channel Number
UE	User Equipment
UL	Up Link (reverse link)
WCDMA	Wideband Code Division Multiple Access
WA	Wide Area

3.3 Symbols

For the purposes of the present document, the following symbols apply:

α	Roll-off factor
E_b	Average energy per information bit
E_c	Total energy per PN chip
f	Frequency Δf Frequency offset of the measurement filter -3dB point, as defined in section 6.6.2.1
Δf_{\max}	The largest value of Δf used for defining the requirement
f_{offset}	Frequency offset of the measurement filter centre frequency, as defined in section 6.6.2.1
$F_{\text{DL_low}}$	The lowest frequency of the downlink operating band
$F_{\text{DL_high}}$	The highest frequency of the downlink operating band
$F_{\text{DL_Offset}}$	The offset parameter used to calculate the UARFCN for downlink
$F_{\text{UL_low}}$	The lowest frequency of the uplink operating band
$F_{\text{UL_high}}$	The highest frequency of the uplink operating band
$F_{\text{UL_Offset}}$	The offset parameter used to calculate the UARFCN for uplink
F_{uw}	Frequency offset of unwanted signal
$P_{\text{EM},N}$	Declared emission level for channel N
$P_{\text{EM},B32,\text{ind}}$	Declared emission level in Band 32, ind=a, b, c, d, e
P_{out}	Output power
$P_{\text{rated},c}$	Rated output power (per carrier)
$P_{\text{max},c}$	Maximum output power (per carrier)
Rx	Receiver
Tx	Transmitter
W_{gap}	Sub-block gap or Inter RF Bandwidth gap size

4 General

4.1 Relationship between Minimum Requirements and Test Requirements

The Minimum Requirements given in this specification make no allowance for measurement uncertainty. The test specification 25.141 section 4 defines Test Tolerances. These Test Tolerances are individually calculated for each test. The Test Tolerances are used to relax the Minimum Requirements in this specification to create Test Requirements.

The measurement results returned by the Test System are compared - without any modification - against the Test Requirements as defined by the shared risk principle.

The Shared Risk principle is defined in ITU-R M.1545.

4.2 Base station classes

The requirements in this specification apply to Wide Area Base Stations, Medium Range Base Stations, Local Area Base Stations and Home Base Stations unless otherwise stated.

Wide Area Base Stations are characterised by requirements derived from Macro Cell scenarios with a BS to UE minimum coupling loss equal to 70 dB. The Wide Area Base Station class has the same requirements as the base station for General Purpose application in Release 99, 4 and 5.

Medium Range Base Stations are characterised by requirements derived from Micro Cell scenarios with a BS to UE minimum coupling loss equal to 53 dB.

Local Area Base Stations are characterised by requirements derived from Pico Cell scenarios with a BS to UE minimum coupling loss equal to 45 dB.

Home Base Stations are characterised by requirements derived from Femto Cell scenarios.