

ETSI TS 145 008 V13.0.0 (2016-01)



TECHNICAL SPECIFICATION

**Digital cellular telecommunications system (Phase 2+) (GSM);
Radio subsystem link control
(3GPP TS 45.008 version 13.0.0 Release 13)**

*iTeh STANDARDS PREVIEW
(standards.it-euhq.eu)
Full standards list: <https://standards.it-euhq.eu/standards/380faa61-b9a2-43d7-a7a4-38a614b03a51/3gpp-ts-45-008-v13-0-0-2016-01>*



Reference

RTS/TSGG-0145008vd00

Keywords

LTE**ETSI**

650 Route des Lucioles
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - NAF 742 C
Association à but non lucratif enregistrée à la
Sous-Préfecture de Grasse (06) N° 7803/88

Important notice

The present document can be downloaded from:

<http://www.etsi.org/standards-search>

The present document may be made available in electronic versions and/or in print. The content of any electronic and/or print versions of the present document shall not be modified without the prior written authorization of ETSI. In case of any existing or perceived difference in contents between such versions and/or in print, the only prevailing document is the print of the Portable Document Format (PDF) version kept on a specific network drive within ETSI Secretariat.

Users of the present document should be aware that the document may be subject to revision or change of status.

Information on the current status of this and other ETSI documents is available at

<http://portal.etsi.org/tb/status/status.asp>

If you find errors in the present document, please send your comment to one of the following services:

<https://portal.etsi.org/People/CommitteeSupportStaff.aspx>

Copyright Notification

No part may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm except as authorized by written permission of ETSI.

The content of the PDF version shall not be modified without the written authorization of ETSI.

The copyright and the foregoing restriction extend to reproduction in all media.

© European Telecommunications Standards Institute 2016.

All rights reserved.

DECT™, **PLUGTESTS™**, **UMTS™** and the ETSI logo are Trade Marks of ETSI registered for the benefit of its Members.
3GPP™ and **LTE™** are Trade Marks of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners.
GSM® and the GSM logo are Trade Marks registered and owned by the GSM Association.

Intellectual Property Rights

IPRs essential or potentially essential to the present document may have been declared to ETSI. The information pertaining to these essential IPRs, if any, is publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: *"Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards"*, which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (<https://ipr.etsi.org/>).

Pursuant to the ETSI IPR Policy, no investigation, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

Foreword

This Technical Specification (TS) has been produced by ETSI 3rd Generation Partnership Project (3GPP).

The present document may refer to technical specifications or reports using their 3GPP identities, UMTS identities or GSM identities. These should be interpreted as being references to the corresponding ETSI deliverables.

The cross reference between GSM, UMTS, 3GPP and ETSI identities can be found under <http://webapp.etsi.org/key/queryform.asp>.

Modal verbs terminology

In the present document "**shall**", "**shall not**", "**should**", "**should not**", "**may**", "**need not**", "**will**", "**will not**", "**can**" and "**cannot**" are to be interpreted as described in clause 3.2 of the [ETSI Drafting Rules](#) (Verbal forms for the expression of provisions).

"**must**" and "**must not**" are **NOT** allowed in ETSI deliverables except when used in direct citation.

Contents

Intellectual Property Rights	2
Foreword.....	2
Modal verbs terminology.....	2
Foreword.....	8
1 Scope	9
1.1 References	9
1.2 Abbreviations	11
1.3 Definitions.....	11
1.4 Restrictions.....	11
2 General	11
3 Handover	13
3.1 Overall process.....	13
3.2 MS measurement procedure.....	13
3.3 BSS measurement procedure.....	13
3.4 Strategy	13
4 RF power control.....	14
4.1 Overall process.....	14
4.2 MS implementation	14
4.3 MS power control range	16
4.4 BSS implementation.....	16
4.4.1 VAMOS subchannel power control for BSS in downlink.....	16
4.5 BSS power control range.....	16
4.6 Strategy	16
4.7 Timing.....	17
4.7.1 Normal Power Control.....	17
4.7.2 Fast Power Control	17
4.7.3 Enhanced Power Control	18
4.8 Dedicated channels used for a voice group call or voice broadcast.....	18
5 Radio link failure.....	18
5.1 Criterion	18
5.2 MS procedure	19
5.3 BSS procedure.....	19
6 Idle mode tasks.....	19
6.1 Introduction	19
6.2 Measurements for normal cell selection.....	20
6.3 Measurements for stored list cell selection.....	21
6.4 Criteria for cell selection and reselection	21
6.5 Downlink signalling failure.....	23
6.6 Measurements for Cell Reselection.....	23
6.6.0 General.....	23
6.6.1 Monitoring of received signal level and BCCH data.....	24
6.6.1a Reduced Monitoring of received signal level and BCCH data	25
6.6.2 Path loss criteria and timings for cell re-selection	26
6.6.3 Cell reselection algorithm for SoLSA.....	26
6.6.4 Measurements on cells of other radio access technologies	27
6.6.5 Algorithm for cell re-selection from GSM to UTRAN based on cell ranking.....	31
6.6.6 Algorithm for inter-RAT cell re-selection based on priority information.....	32
6.6.7 Cell selection and re-selection to CSG cells and hybrid cells.....	35
6.6.7.1 Cell re-selection to CSG cells	35
6.6.7.1a Cell re-selection to hybrid cells.....	36
6.6.7.2 Manual CSG ID selection	36

6.7	Release of TCH, SDCCH and DBPSCH.....	36
6.7.1	Normal case	36
6.7.2	Call re-establishment	37
6.8	Abnormal cases and emergency calls.....	37
7	Network pre-requisites	38
7.1	BCCH carriers	38
7.2	Identification of surrounding BSS for handover measurements.....	40
7.3	Handover measurements on other radio access technologies	41
7.4	Handover measurements on UTRAN CSG cells and hybrid cells	44
8	Radio link measurements	45
8.1	Signal level.....	45
8.1.1	General.....	45
8.1.2	Physical parameter.....	45
8.1.3	Statistical parameters	46
8.1.4	Range of parameter.....	46
8.1.5	Measurement quantity for other radio access technologies	47
8.1.5.1	UTRAN FDD.....	47
8.1.5.2	UTRAN TDD.....	47
8.1.5.3	cdma2000.....	47
8.1.5.4	E-UTRAN FDD	48
8.1.5.5	E-UTRAN TDD.....	49
8.2	Signal quality.....	49
8.2.1	General.....	49
8.2.2	Physical parameter.....	49
8.2.3	Statistical parameters	50
8.2.3.1	RXQUAL	50
8.2.3.2	MEAN_BEP and CV_BEP	50
8.2.4	Range of parameter RXQUAL	51
8.2.5	Range of parameters MEAN_BEP and CV_BEP	52
8.3	Aspects of discontinuous transmission (DTX).....	56
8.4	Measurement reporting.....	57
8.4.1	Measurement reporting for the MS.....	57
8.4.1a	Measurement reporting for the MS in FPC mode	59
8.4.1b	Measurement reporting for the MS in EPC mode	59
8.4.2	Measurement reporting for the MS on a SDCCH.....	60
8.4.3	Additional cell reporting requirements for multi band MS	60
8.4.4	Common aspects for the MS on a TCH, a SDCCH or a DBPSCH.....	61
8.4.5	Measurement reporting for the BSS	61
8.4.6	Extended measurement reporting	62
8.4.7	Additional cell reporting requirements for multi-RAT MS	62
8.4.8	Enhanced Measurement Reporting	64
8.4.8.1	Reporting Priority	64
8.4.8.2	Measurement Reporting	65
8.4.8.3	NBR_RCVD_BLOCKS for FLO.....	66
8.4.9	Requirements for measurement and reporting of CSG cells and hybrid cells	66
8.5	Absolute MS-BTS distance	67
8.5.1	General.....	67
8.5.2	Physical parameter.....	67
9	Control parameters	68
10	GPRS mode tasks	76
10.1	Cell Re-selection	76
10.1.0	General.....	76
10.1.1	Monitoring the received signal level and PBCCH data	77
10.1.1.0	General	77
10.1.1.1	Packet idle mode or MAC-Idle state	78
10.1.1.2	Packet transfer mode or MAC-Shared state	78
10.1.1.2a	Broadcast/multicast receive mode.....	79
10.1.1.3	Monitoring cells of other radio access technologies	80
10.1.2	Cell Re-selection Criteria.....	84

10.1.3	Cell Re-selection Algorithm	85
10.1.3.1	Abnormal cell reselection	86
10.1.3.2	Algorithm for cell re-selection from GSM to UTRAN based on cell ranking	87
10.1.3.3	Algorithm for inter-RAT cell re-selection based on priority information	88
10.1.3.4	Cell selection and re-selection to CSG cells and hybrid cells	88
10.1.4	Network controlled Cell re-selection	88
10.1.4.1	Measurement reporting	89
10.1.4.2	Cell re-selection command	94
10.1.4.3	Exceptional cases	94
10.1a	Measurement and Reporting of CSG Cells and hybrid cells	94
10.2	RF Power Control	95
10.2.1	MS output power	95
10.2.2	BTS output power	96
10.2.3	Measurements at MS side	97
10.2.3.1	Deriving the C value	98
10.2.3.1.1	Packet idle mode or MAC-Idle state	98
10.2.3.1.2	Packet transfer mode or MAC-Shared state	98
10.2.3.2	Derivation of Channel Quality Report	100
10.2.3.2.1	Packet transfer mode or MAC-Shared state	100
10.2.3.2.2	Void	103
10.2.3.2.3	Measurement reporting	103
10.2.3.2.4	Measurement reporting - additional requirements for downlink dual carrier	104
10.2.3.2.5	Measurement reporting - additional requirements for downlink multi carrier	105
10.2.3.3	Range of parameters MEAN_BEP and CV_BEP for EGPRS2	105
10.2.4	Measurements at BSS side	109
10.2a	Packet-switched Handover	109
10.3	Measurement requirements	109
10.4	Control parameters	109
11	CTS mode tasks	117
11.1	CTS idle mode tasks	117
11.1.1	CTS cell selection	118
11.1.1.1	Synchronization and measurements for CTS cell selection	118
11.1.1.2	Initial sychronization of CTS-MS	118
11.1.2	Criterion for CTS cell selection	118
11.1.3	Monitoring of CTSBCH and CTSPCH	119
11.1.3.1	Monitoring of received signal level	119
11.1.3.2	Downlink beacon failure	119
11.1.3.3	Downlink paging failure	119
11.1.4	Procedures with reporting to the CTS-FP	119
11.1.4.1	AFA monitoring	119
11.1.4.2	BCCH detection	120
11.1.4.3	Observed Frequency Offset (OFO) measurement	120
11.2	Intra-cell handover	120
11.2.1	Overall process	120
11.2.2	CTS-MS measurement procedure	120
11.2.3	CTS-FP measurement procedure	121
11.2.4	Strategy	121
11.3	RF power control	121
11.3.1	Overall process	121
11.3.2	CTS-MS implementation	121
11.3.3	CTS-MS power control range	121
11.3.4	CTS-FP implementation	122
11.3.5	CTS-FP power control range	122
11.3.6	Strategy	122
11.3.7	Timing	122
11.4	Radio link failure	122
11.4.1	Criterion	122
11.4.2	CTS-MS procedure	122
11.4.3	CTS-FP procedure	123
11.5	Radio link measurements	123
11.5.1	Signal strength	123

11.5.1.1	General	123
11.5.1.2	Physical parameter	123
11.5.1.3	Statistical parameters	123
11.5.1.4	Range of parameter	123
11.5.2	Signal quality	124
11.5.2.1	General	124
11.5.2.2	Physical parameter	124
11.5.2.3	Statistical parameters	124
11.5.2.4	Range of parameter	124
11.5.3	Aspects of discontinuous transmission (DTX)	124
11.5.4	Measurement reporting for the CTS-MS on a TCH	124
11.6	Control of CTS-FP service range	125
11.7	Control parameters	125
12	COMPACT Mode Tasks	127
12.1	Introduction	127
12.2	Network Pre-requisites	127
12.2.1	CPBCCCH carriers	127
12.3	COMPACT Idle Mode Tasks	127
12.3.1	Introduction	127
12.3.2	Measurements for COMPACT Cell Selection	127
12.3.3	Measurements for COMPACT Stored List Cell Selection	128
12.3.4	Criteria for COMPACT Cell Selection	128
12.3.5	Downlink Signalling Failure	128
12.4	COMPACT Cell Reselection	128
12.4.1	Monitoring the received signal level and CPBCCCH data	129
12.4.1.1	Packet idle mode or MAC-Idle state	129
12.4.1.2	Packet transfer mode or MAC-Shared state	129
12.4.2	COMPACT cell reselection criteria	130
12.4.3	COMPACT cell reselection algorithm	130
12.4.4	Network controlled Cell reselection	130
12.4.5	COMPACT cell reselection measurement opportunities	130
Annex A (informative): Definition of a basic GSM or DCS 1 800 handover and RF power control algorithm		
		131
A.1	Scope	131
A.2	Functional requirement	131
A.3	BSS pre-processing and threshold comparisons	132
A.3.1	Measurement averaging process	132
A.3.2	Threshold comparison process	133
A.3.2.1	RF power control process	133
A.3.2.2	Handover Process	134
A.4	BSS decision algorithm	135
A.4.1	Internal intracell handover according to radio criteria: (Interference problems)	135
A.4.2	Internal handover according to other criteria	136
A.4.3	General considerations	136
A.5	Channel allocation	136
A.6	Handover decision algorithm in the MSC	137
Annex B (informative): Power Control Procedures		
		139
B.1	Open loop control	139
B.2	Closed loop control	140
B.3	Quality based control	140
B.4	BTS power control	141
B.5	Example	141

B.6 Interworking between normal and fast power control for ECSD142

B.7 Interworking between normal and enhanced power control (EPC)143

Annex C (informative): Example Interference Measurement Algorithm145

Annex D (informative): Example Selection of Modulation and Coding Schemes based on Link Quality Reports.....146

Annex E (informative): Change history147

History157

iTeh STANDARD PREVIEW
 (standards.iteh.ai)
 Full standard:
<https://standards.iteh.ai/catalog/standards/sist/380faa61-b9a2-43d7-a7a4-38a614b03a51/etsi-ts-145-008-v13.0.0-2016-01>

Foreword

This Technical Specification has been produced by the 3rd Generation Partnership Project (3GPP).

The contents of the present document are subject to continuing work within the TSG and may change following formal TSG approval. Should the TSG modify the contents of the present document, it will be re-released by the TSG with an identifying change of release date and an increase in version number as follows:

Version x.y.z

where:

- x the first digit:
 - 1 presented to TSG for information;
 - 2 presented to TSG for approval;
 - 3 or greater indicates TSG approved document under change control.
- y the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- z the third digit is incremented when editorial only changes have been incorporated in the document.

iTeh STANDARD PREVIEW
(standards.iteh.ai)
Full standard:
<https://standards.iteh.ai/catalog/standards/sist/38a614b03a514b03a514b03a514b03a51/etsi-ts-145-008-v13.0.0-2016-01>

1 Scope

The present document specifies the Radio sub-system link control implemented in the Mobile Station (MS), Base Station System (BSS) and Mobile Switching Centre (MSC) of the digital cellular telecommunications systems GSM.

Unless otherwise specified, references to GSM also include operation in any band.

1.1 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- References are either specific (identified by date of publication, edition number, version number, etc.) or non-specific.
- For a specific reference, subsequent revisions do not apply.
- For a non-specific reference, the latest version applies. In the case of a reference to a 3GPP document (including a GSM document), a non-specific reference implicitly refers to the latest version of that document *in the same Release as the present document*.

- [1] 3GPP TR 21.905: 'Vocabulary for 3GPP Specifications'.
- [2] 3GPP TS 23.003: 'Numbering, addressing and identification'.
- [3] 3GPP TS 23.009: 'Handover procedures'.
- [4] 3GPP TS 23.122: 'NAS Functions related to Mobile Station (MS) in idle mode'.
- [5] 3GPP TS 25.101: 'UE Radio transmission and reception (FDD)'.
- [6] 3GPP TS 25.123: 'Requirements for support of Radio Resource Management (TDD)'.
- [7] 3GPP TS 25.133: 'Requirements for support of Radio Resource Management (FDD)'.
- [8] 3GPP TS 25.304: 'UE Procedures in Idle Mode and Procedures for Cell Reselection in Connected Mode'.
- [9] 3GPP TS 25.331: 'Radio Resource Control (RRC); Protocol Specification'.
- [10] 3GPP TS 26.093: 'AMR Speech Codec; Source Controlled Rate operation'.
- [11] 3GPP TS 43.022: 'Functions related to Mobile Station (MS) in idle mode and group receive mode'.
- [12] 3GPP TS 43.064: 'Overall description of the GPRS Radio Interface; Stage 2'.
- [13] 3GPP TS 43.246: 'Multimedia Broadcast Multicast Service (MBMS) in the GERAN; Stage 2'.
- [14] 3GPP TS 43.068: 'Voice Group Call Service (VGCS); Stage 2'.
- [15] 3GPP TS 44.004: 'Layer 1; General requirements'.
- [16] 3GPP TS 44.006: 'Mobile Station - Base Station System (MS - BSS) interface; Data Link (DL) layer specification'.
- [17] 3GPP TS 44.018: 'Mobile radio interface layer 3 specification; Radio Resource Control Protocol'.
- [18] 3GPP TS 44.056: 'GSM Cordless Telephony System (CTS), Phase 1; CTS radio interface layer 3 specification'.
- [19] 3GPP TS 44.060: 'General Packet Radio Service (GPRS); Mobile Station (MS) - Base Station System (BSS) interface; Radio Link Control (RLC) / Medium Access Control (MAC) protocol'.

- [20] 3GPP TS 44.118: 'Mobile radio interface layer 3 specification, Radio Resource Control (RRC) Protocol, Iu Mode'.
- [21] 3GPP TS 44.160: 'Mobile Station (MS) - Base Station System (BSS) interface; Radio Link Control/Medium Access Control (RLC/MAC) protocol; Iu mode'.
- [22] 3GPP TS 45.002: 'Multiplexing and multiple access on the radio path'.
- [23] 3GPP TS 45.003: 'Channel coding'
- [24] 3GPP TS 45.005: 'Radio transmission and reception'.
- [25] 3GPP TS 45.010: 'Radio subsystem synchronization'.
- [26] 3GPP TS 45.056: 'CTS-FP radio subsystem'.
- [27] 3GPP TR 45.902: 'Flexible Layer One'.
- [28] 3GPP TS 46.011: 'Full rate speech; Substitution and muting of lost frames for full rate speech channels'.
- [29] 3GPP TS 46.012: 'Full rate speech; Comfort noise aspect for full rate speech traffic channels'.
- [30] 3GPP TS 46.031: 'Full rate speech; Discontinuous Transmission (DTX) for full rate speech traffic channels'.
- [31] 3GPP TS 48.008: 'Mobile-services Switching Centre - Base Station System (MSC - BSS) interface, Layer 3 specification'.
- [32] 3GPP TS 48.058: 'Base Station Controller - Base Transceiver Station (BSC - BTS) interface; Layer 3 specification'.
- [33] 3GPP TS 51.010: 'Mobile Station (MS) conformity specification'.
- [34] 3GPP TS 51.011: 'Specification of the Subscriber Identity Module - Mobile Equipment (SIM - ME) interface'.
- [35] TIA/EIA/IS-2000-5-A: 'Upper Layer (Layer 3) Signaling Standard for cdma2000 Spread Spectrum Systems'.
- [36] TIA/EIA/IS-833: 'Multi-Carrier Specification for Spread Spectrum Systems on GSM MAP (MC-MAP) (Lower Layers Air Interface)'.
- [37] 3GPP TS 36.101: 'Evolved Universal Terrestrial Radio Access (E-UTRA); User Equipment (UE) radio transmission and reception'.
- [38] 3GPP TS 36.104: 'Evolved Universal Terrestrial Radio Access (E-UTRA); Base Station (BS) radio transmission and reception'.
- [39] 3GPP TS 36.133: 'Evolved Universal Terrestrial Radio Access (E-UTRA); Requirements for support of radio resource management'.
- [40] 3GPP TS 36.304: 'Evolved Universal Terrestrial Radio Access (E-UTRA); User Equipment (UE) procedures in idle mode'.
- [41] 3GPP TS 36.331: 'Evolved Universal Terrestrial Radio Access (E-UTRA); Radio Resource Control (RRC); Protocol Specification'.
- [42] 3GPP TS 31.102: 'Characteristics of the Universal Subscriber Identity Module (USIM) application'.
- [43] 3GPP TS 24.301: 'Non-Access-Stratum (NAS) protocol for Evolved Packet System (EPS); Stage 3'.
- [44] 3GPP TS 22.268: 'Public Warning System (PWS) requirements; Stage 1'.
- [45] 3GPP TS 23.251: "Network sharing; Architecture and functional description".

- [46] 3GPP TS 24.008: "Mobile Radio Interface Layer 3 specification; Core Network Protocols - Stage 3".
- [47] 3GPP TS 25.306: "UE Radio Access capabilities".
- [48] 3GPP TR 45.926: 'Solutions for GSM/EDGE BTS Energy Saving'.

1.2 Abbreviations

Abbreviations used in the present document are listed in 3GPP TR 21.905.

UFPS Unique Frequency Parameter Set

1.3 Definitions

CSG Whitelist: A list provided by NAS containing all the CSG identities and their PLMN IDs of the CSGs to which the subscriber belongs, see 3GPP TS 23.122 [4].

NOTE: This list is known as 'Allowed CSG List' in Rel-8 specifications.

CSG cell: The definition of CSG cell for UTRAN is given in 3GPP TS 25.304 [8]; the definition of CSG cell for E-UTRAN is given in 3GPP TS 36.304 [40].

Hybrid cell: The definition of hybrid cell for UTRAN is given in 3GPP TS 25.304 [8]; the definition of hybrid cell for E-UTRAN is given in 3GPP TS 36.304 [40].

Network sharing: network sharing is an optional feature that allows different core network operators to connect to the same shared radio access network (see 3GPP TS 23.251 [45]). When network sharing is in use within a given cell, the network broadcasts within system information the PLMN identities of the PLMNs sharing the cell. A mobile station supporting network sharing uses this information for its PLMN (re)selection processes and indicates the selected PLMN to the BSS.

Power Efficient Operation (PEO): see definition in 3GPP TS 43.064 [12].

Power Saving Mode (PSM): see definition in 3GPP TS 43.064 [12].

Unique Frequency Parameter Set: defined by a single ARFCN or a MA. In case of a radio frequency channel assigned a frequency parameter set consisting of a single ARFCN, the UFPS is defined by that ARFCN. In case of a radio frequency channel assigned a frequency parameter set consisting of a MA, MAIO and HSN, that radio frequency channel belong to the same UFPS as other radio frequency channels assigned the same MA.

1.4 Restrictions

Independently of what is stated elsewhere in this and other 3GPP specifications, mobile station support for PBCCH and PCCCH is optional for A/Gb-mode of operation. The network shall never enable PBCCH and PCCCH.

2 General

The radio sub-system link control aspects that are addressed are as follows:

- Handover;
- RF Power control in *A/Gb mode*, including fast power control for E-TCH and enhanced power control for TCH and O-TCH;
- RF Power control in *Iu mode*, including fast power control for E-TCH and enhanced power control for DBPSCH (in MAC-Dedicated and MAC-DTM states);
- Radio link Failure;

- Cell selection and re-selection in Idle mode, in Group Receive mode, in GPRS mode and in broadcast/multicast receive mode (see 3GPP TS 43.022);
- CTS mode tasks.

NOTE: A distinction is made between *A/Gb mode* and *Iu mode* only when necessary. Procedures and mechanisms described in this TS apply to both modes of operation unless otherwise stated. In *Iu mode*, unless otherwise stated, DBPSCH covers TCH, PDTCH and FLO.

Handover is required to maintain a call in progress as a MS engaged in a point-to-point call or with access to the uplink of a channel used for a voice group call passes from one cell coverage area to another and may also be employed to meet network management requirements, e.g. relief of congestion.

Handover may occur during a call from one TCH or multiple TCHs (in the case of multislot configuration) to another TCH or multiple TCHs. It may also occur from DCCH to DCCH or from DCCH to one or multiple TCH(s), e.g. during the initial signalling period at call set-up. Additionally in *Iu mode*, handover may occur in MAC-Dedicated and MAC-DTM states:

- on PDTCH or multiple PDTCHs (in the case of multislot configuration) on DBPSCH(s) to another PDTCH or multiple PDTCHs on DBPSCH(s);
- for FLO, from one DBPSCH or multiple DBPSCHs (in the case of multislot configuration) to another DBPSCH or multiple DBPSCHs.

The handover may be either from channel(s) on one cell to other channel(s) on a surrounding cell, or between channels on the same cell which are carried on the same frequency band. Examples are given of handover strategies, however, these will be determined in detail by the network operator.

For a multiband MS, the handover described is also allowed between any channels on different cells which are carried on different frequency bands, e.g. between a GSM 900/TCH and a DCS 1-800/TCH. Handover between two co-located cells, carried on different frequency bands, is considered as inter-cell handover irrespective of the handover procedures used.

For a multi-RAT MS, i.e. an MS supporting multiple radio access technologies, handover is allowed between GSM and other radio access technologies.

NOTE: At handover, the MS will normally not be able to verify the PLMN of the target cell and will thus assume that the same system information apply after the handover unless the network provides new system information.

Adaptive control of the RF transmit power from an MS and optionally from the BSS is implemented in order to optimize the uplink and downlink performance and minimize the effects of co-channel interference in the system.

The criteria for determining radio link failure are specified in order to ensure that calls which fail either from loss of radio coverage or unacceptable interference are satisfactorily handled by the network. Radio link failure may result in either re-establishment or release of the call in progress. For channels used for a voice group call, a radio uplink failure results in the freeing up of the uplink.

Procedures for cell selection and re-selection whilst in Idle mode (i.e. not actively processing a call), are specified in order to ensure that a mobile is camped on a cell with which it can reliably communicate on both the radio uplink and downlink. The operations of an MS in Idle Mode are specified in 3GPP TS 43.022.

Cell re-selection is also performed by the MS when attached to GPRS, except when the MS simultaneously has a circuit switched connection. Optional procedures are also specified for network controlled cell re-selection for GPRS. Cell re-selection for GPRS is defined in subclause 10.1.

For a multi-RAT MS, cell selection and re-selection is allowed between GSM and other radio access technologies.

An MS listening to a voice group call or a voice broadcast use cell re-selection procedures to change cell. This may be supported by a list of cells carrying the voice group or voice broadcast call downlink, provided to the MS by the network. The operations of an MS in Group Receive Mode are specified in 3GPP TS 43.022.

Information signalled between the MS and BSS is summarized in tables 1, 2 and 3. A full specification of the Layer 1 header is given in 3GPP TS 44.004, of the Layer 3 fields in 3GPP TS 44.018 and 3GPP TS 44.118, and of the Layer 2 fields in 3GPP TS 44.060 and 3GPP TS 44.160.