



**Digital cellular telecommunications system (Phase 2+) (GSM);
General Packet Radio Service (GPRS);
Overall description of the GPRS radio interface;
Stage 2
(3GPP TS 43.064 version 13.1.0 Release 13)**

TEh STANdARd PREvIEw
<https://standards.etsi.org/standard/etsi-ts-143-064-v13.1.0-9c42-4011-bc30-fad4-82a9-4e0f-8204-16-04>



Reference

RTS/TSGG-0143064vd10

Keywords

GSM

ETSI

650 Route des Lucioles
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - NAF 742 C
Association à but non lucratif enregistrée à la
Sous-Préfecture de Grasse (06) N° 7803/88

Important notice

The present document can be downloaded from:

<http://www.etsi.org/standards-search>

The present document may be made available in electronic versions and/or in print. The content of any electronic and/or print versions of the present document shall not be modified without the prior written authorization of ETSI. In case of any existing or perceived difference in contents between such versions and/or in print, the only prevailing document is the print of the Portable Document Format (PDF) version kept on a specific network drive within ETSI Secretariat.

Users of the present document should be aware that the document may be subject to revision or change of status.

Information on the current status of this and other ETSI documents is available at

<http://portal.etsi.org/tb/status/status.asp>

If you find errors in the present document, please send your comment to one of the following services:

<https://portal.etsi.org/People/CommitteeSupportStaff.aspx>

Copyright Notification

No part may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm except as authorized by written permission of ETSI.

The content of the PDF version shall not be modified without the written authorization of ETSI.

The copyright and the foregoing restriction extend to reproduction in all media.

© European Telecommunications Standards Institute 2016.
All rights reserved.

DECT™, PLUGTESTS™, UMTS™ and the ETSI logo are Trade Marks of ETSI registered for the benefit of its Members.
3GPP™ and **LTE™** are Trade Marks of ETSI registered for the benefit of its Members and
of the 3GPP Organizational Partners.

GSM® and the GSM logo are Trade Marks registered and owned by the GSM Association.

Intellectual Property Rights

IPRs essential or potentially essential to the present document may have been declared to ETSI. The information pertaining to these essential IPRs, if any, is publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: "*Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards*", which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (<https://ipr.etsi.org/>).

Pursuant to the ETSI IPR Policy, no investigation, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

Foreword

This Technical Specification (TS) has been produced by ETSI 3rd Generation Partnership Project (3GPP).

The present document may refer to technical specifications or reports using their 3GPP identities, UMTS identities or GSM identities. These should be interpreted as being references to the corresponding ETSI deliverables.

The cross reference between GSM, UMTS, 3GPP and ETSI identities can be found under <http://webapp.etsi.org/key/queryform.asp>.

Modal verbs terminology

In the present document "shall", "shall not", "should", "should not", "may", "need not", "will", "will not", "can" and "cannot" are to be interpreted as described in clause 3.2 of the [ETSI Drafting Rules](#) (Verbal forms for the expression of provisions).

"must" and "must not" are NOT allowed in ETSI deliverables except when used in direct citation.

Contents

Intellectual Property Rights	2
Foreword.....	2
Modal verbs terminology.....	2
Foreword.....	7
1 Scope	8
2 References	9
3 Abbreviations, symbols and definitions	9
3.1 Abbreviations	9
3.2 Symbols.....	11
3.2a Restrictions.....	11
3.2b Definitions	11
3.3 Network and mobile station capabilities	11
3.3.1 General.....	11
3.3.2 EGPRS mobile station	12
3.3.3 Dual Transfer Mode.....	12
3.3.4 Downlink dual carrier configuration.....	12
3.3.5 Reduced Latency TBF	12
3.3.5.1 Fast Ack/Nack Reporting procedure.....	12
3.3.5.2 RTTI configuration	13
3.3.6 EGPRS2 mobile station	14
3.3.6.1 EGPRS2 in the downlink	14
3.3.6.1.1 EGPRS2-A and EGPRS2-B in the downlink.....	14
3.3.6.2 EGPRS2 in the uplink	14
3.3.6.2.1 EGPRS2-A and EGPRS2-B in the uplink.....	14
3.3.7 Downlink multi carrier configuration	14
3.3.8 Power Efficient Operation (PEO)	15
3.3.8.1 General	15
3.3.9 Extended Coverage EGPRS (EC-EGPRS)	15
3.3.9.1 General	15
3.3.9.2 Extended coverage	16
3.3.9.3 Energy efficient operation.....	16
3.3.9.4 Improved security	17
3.3.10 Overlaid CDMA	17
4 Packet data logical channels	17
4.1 General	17
4.2 Packet Common Control Channel (PCCCH) and Compact (CPCCCH)	17
4.2.1 Packet Random Access Channel (PRACH) and Compact Packet Random Access Channel (CPRACH) - uplink only	17
4.2.2 Packet Paging Channel (PPCH) and Compact Packet Paging Channel (CPPCH) - downlink only	17
4.2.3 Packet Access Grant Channel (PAGCH) and Compact Packet Access Grant Channel (CPAGCH) - downlink only	17
4.3 Packet Broadcast Control Channel (PBCCH) and Compact Packet Broadcast Control Channel (CPBCCCH) - downlink only	18
4.4 Packet Traffic Channels	18
4.4.1 Packet Data Traffic Channel (PDTCH, EC-PDTCH).....	18
4.5 Packet Dedicated Control Channels	18
4.5.1 Packet Associated Control Channel (PACCH, EC-PACCH)	18
4.5.2 Packet Timing advance Control Channel, uplink (PTCCH/U).....	18
4.5.3 Packet Timing advance Control Channel, downlink (PTCCH/D)	18
4.6 MBMS Common Control Channels	19
4.6.1 MBMS Packet Random Access Channel (MPRACH) - uplink only	19
5 Mapping of packet data logical channels onto physical channels	19

5.1	General	19
5.2	Packet Common Control Channels (PCCCH and CPCCCH)	19
5.2.1	Packet Random Access Channel (PRACH and CPRACH)	20
5.2.2	Packet Paging Channel (PPCH and CPPCH)	20
5.2.3	Packet Access Grant Channel (PAGCH and CPAGCH)	20
5.2.4	Void	20
5.2a	MBMS Common Control Channels (MPRACH).....	20
5.2b	Extended Coverage Common Control Channels (EC-CCCH)	21
5.2b.1	General.....	21
5.2b.2	Extended Coverage Random Access Channel (EC-RACH)	21
5.2b.3	Extended Coverage Paging Channel (EC-PCH)	21
5.2b.4	Extended Coverage Access Grant Channel (EC-AGCH)	21
5.3	Packet Broadcast Control Channel (PBCCH and CPBCCH).....	21
5.3a	Compact Frequency Correction Channel (CFCCH).....	22
5.3b	Compact Synchronization Channel (CSCH)	22
5.3c	Extended Coverage Broadcast Control Channel (EC-BCCH)	22
5.4	Packet Timing advance Control Channel (PTCCH).....	22
5.5	Packet Traffic Channels	22
5.5.1	Packet Data Traffic Channel (PDTCH)	22
5.5.1a	Extended Coverage Packet Data Traffic Channel (EC-PDTCH).....	22
5.5.2	Packet Associated Control Channel (PACCH)	23
5.5.2a	Extended Coverage Packet Associated Control Channel (EC-PACCH)	23
5.6	Downlink resource sharing.....	23
5.7	Uplink resource sharing.....	24
6	Radio Interface (Um).....	24
6.1	Radio Resource management principles.....	24
6.1.1	Allocation of resources for the GPRS.....	24
6.1.1.1	Master-Slave concept	24
6.1.1.2	Capacity on demand concept.....	25
6.1.1.3	Procedures to support capacity on demand	25
6.1.1.4	Release of PDCH not carrying PCCCH	25
6.1.2	Multiframe structure for PDCH.....	26
6.1.2a	Multiframe structure for Compact PDCH.....	27
6.1.2b	Multiframe structure for PDCH/H	28
6.1.3	Scheduling of PBCCH information.....	28
6.1.4	SMS cell broadcast	28
6.1.5	MS Multislot Capability	29
6.2	Radio Resource operating modes.....	29
6.2.1	Packet idle mode	29
6.2.2	Packet transfer mode.....	30
6.2.3	Dual transfer mode.....	30
6.2.3a	Broadcast/Multicast receive mode	30
6.2.4	Correspondence between Radio Resource operating modes and Mobility Management States	31
6.2.5	Transitions between RR operating modes	31
6.3	Layered overview of radio interface.....	32
6.4	Physical RF Layer	33
6.5	Physical Link Layer.....	33
6.5.1	Layer Services	33
6.5.2	Layer Functions	33
6.5.3	Service Primitives	34
6.5.4	Radio Block Structure	34
6.5.4.1	Radio Block structure for data transfer for GPRS	34
6.5.4.2	Radio Block structure for data transfer for EC-EGPRS and for EGPRS with FANR not activated	35
6.5.4.3	Radio Block structure for data transfer for EGPRS with FANR activated or for EGPRS2	35
6.5.4.4	Radio Block structure for control message transfer	36
6.5.4.4.1	General format (CS-1).....	36
6.5.4.4.2	Format for downlink control message for RTTI configuration (MCS-0)	36
6.5.4.4.3	Format for alternative uplink control message for DLMC configuration (CS-3)	37
6.5.4.4.4	Format for control message for EC-EGPRS configuration (EC-PACCH)	37
6.5.5	Channel Coding	37
6.5.5.0	General	37

6.5.5.1	Channel coding for PDTCH.....	38
6.5.5.1.1	Channel coding for GPRS PDTCH	38
6.5.5.1.2	Channel coding for EGPRS PDTCH and EC-EGPRS EC-PDTCH.....	40
6.5.5.1.3	Channel coding for EGPRS2 PDTCH.....	47
6.5.5.2	Channel coding for PACCH, EC-PACCH, PBCCH, PAGCH, EC-AGCH, PPCH, EC-PCH and PTCCH.....	69
6.5.5.2a	Channel coding for CPBCCCH, CPAGCH, CPPCH and CSCH	71
6.5.5.3	Channel Coding for the PRACH, CPRACH and MPRACH.....	71
6.5.5.3.1	Coding of the 8 data bit Packet Access Burst.....	71
6.5.5.3.2	Coding of the 11 data bit Packet Access Burst.....	71
6.5.6	Cell Re-selection.....	72
6.5.6.1	Measurements for Cell Re-selection	72
6.5.6.2	Broadcast Information.....	72
6.5.6.3	Optional measurement reports and network controlled cell re-selection	72
6.5.6.4	Network Assisted Cell Change	73
6.5.7	Timing Advance	73
6.5.7.1	Initial timing advance estimation	74
6.5.7.2	Continuous timing advance update	74
6.5.7.2.1	Mapping on the multiframe structure	75
6.5.8	Power control procedure	76
6.5.8.0	General	76
6.5.8.1	MS output power.....	76
6.5.8.2	BTS output power	77
6.5.8.3	Measurements at MS side	77
6.5.8.3.1	Deriving the C value.....	77
6.5.8.3.2	Derivation of Channel Quality Report.....	77
6.5.8.4	Measurements at BSS side	78
6.5.9	Scheduling the MS activities during the PTCCCH and idle frames	78
6.5.10	Discontinuous Reception (DRX).....	79
6.6	Medium Access Control and Radio Link Control Layer.....	80
6.6.1	Layer Services	80
6.6.2	Layer Functions	80
6.6.3	Service Primitives	81
6.6.4	Model of Operation.....	81
6.6.4.1	Multiplexing MSs on the same PDCH.....	86
6.6.4.1.1	Uplink State Flag: Dynamic Allocation	86
6.6.4.1.1.1	Multiplexing of GPRS, EGPRS or EGPRS2 MSs	86
6.6.4.1.1.2	Multiplexing of GPRS, EGPRS and EGPRS2 MSs.....	87
6.6.4.1.2	Void.....	87
6.6.4.1.3	Exclusive Allocation	87
6.6.4.1.4	Fixed Uplink Allocation (FUA)	87
6.6.4.1.4.1	Multiplexing of GPRS, EGPRS, EC-EGPRS and EGPRS2 MSs.....	87
6.6.4.2	Temporary Block Flow	87
6.6.4.3	Temporary Flow Identity	88
6.6.4.4	Medium Access modes	88
6.6.4.5	Acknowledged mode for RLC/MAC operation	88
6.6.4.5.1	GPRS	88
6.6.4.5.2	EGPRS and EGPRS2	89
6.6.4.6	Unacknowledged mode for RLC/MAC operation	89
6.6.4.6.1	Non-persistent mode for RLC/MAC operation.....	89
6.6.4.7	Mobile Originated Packet Transfer	90
6.6.4.7.1	Uplink Access.....	90
6.6.4.7.1.1	On the (P)RACH.....	90
6.6.4.7.1.2	On the main DCCH.....	92
6.6.4.7.2	Dynamic/Extended Dynamic allocation	93
6.6.4.7.2.1	Uplink Packet Transfer	93
6.6.4.7.2.2	Release of the Resources	94
6.6.4.7.3	Void.....	95
6.6.4.7.4	Exclusive Allocation	95
6.6.4.7.4.1	Fixed Uplink Allocation	95
6.6.4.7.5	Contention Resolution	96
6.6.4.8	Mobile Terminated Packet Transfer.....	97

6.6.4.8.1	Packet Paging	97
6.6.4.8.2	Downlink Packet Transfer	97
6.6.4.8.3	Release of the Resources	100
6.6.4.8.4	Packet Paging Notification	100
6.6.4.9	Simultaneous Uplink and Downlink Packet Transfer	101
6.6.4.9.1	MS Does Not Support Multiple TBF Procedures	101
6.6.4.9.2	MS Supports Multiple TBF Procedures	101
6.7	Abnormal cases in GPRS MS Ready State	102
6.8	Void	102
6.9	MBMS Data Transfer	102

Annex A (informative): Bibliography.....103

Annex B (informative): Multiple TBF Feature.....104

B.1	General	104
B.2	Multiple TBF capability	104
B.3	Multiple TBF procedures	105
B.3.1	Data multiplexing options	105
B.3.1.1	Single TBF per upper layer flow	105
B.3.1.2	DL TBF sharing	105
B.3.1.3	Explicit UL TBF switching	105
B.3.2	RLC/MAC Signalling	105
B.3.3	TBF establishment	105
B.3.3.1	TFI allocation	105
B.3.3.2	Single TBF request / establishment	106
B.3.3.3	Multiple TBF establishment / reconfiguration	106
B.3.3.3.1	Multiple uplink TBF request / establishment	106
B.3.3.3.2	Multiple downlink TBF establishment	107
B.3.3.3.3	Usage of multiple TBF assignment messages	107
B.4	RLC/MAC Timers	108
B.4.1	TBF timers	108
B.4.2	Contention resolution timer	108
B.5	CSN.1 coding of multiple TBF messages	108
B.5.1	MULTIPLE TBF UPLINK ASSIGNMENT message	108
B.5.2	MULTIPLE TBF DOWNLINK ASSIGNMENT message	109
B.5.3	MULTIPLE TBF TIMESLOT RECONFIGURE message	110

Annex C (informative): Change history111

History	115
---------------	-----

Foreword

This Technical Specification has been produced by the 3rd Generation Partnership Project (3GPP).

The contents of the present document are subject to continuing work within the TSG and may change following formal TSG approval. Should the TSG modify the contents of the present document, it will be re-released by the TSG with an identifying change of release date and an increase in version number as follows:

Version x.y.z

where:

- x the first digit:
 - 1 presented to TSG for information;
 - 2 presented to TSG for approval;
 - 3 or greater indicates TSG approved document under change control.
- y the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- z the third digit is incremented when editorial only changes have been incorporated in the document.

iteh STANDARD PREVIEW
iteh (standards.iteh.ai)
Full standard:
<https://standards.iteh.ai/catalog/standards/sist/000012b94-9c42-4011-bc30-fadd0482cda4/etsi-ts-143-064-v13.1.0>

1 Scope

The present document provides the overall description for lower-layer functions of the General Packet Radio Service (GPRS and EGPRS) radio interface (Um). Within this TS the term GPRS refers to GPRS and EGPRS unless explicitly stated otherwise.

The overall description provides the following information:

- The services offered to higher-layer functions,
- The distribution of required functions into functional groups,
- A definition of the capabilities of each functional group,
- Service primitives for each functional group, including a description of what services and information flows are to be provided, and
- A model of operation for information flows within and between the functions.

The present document is applicable to the following GPRS Um functional layers:

- Radio Link Control functions,
- Medium Access Control functions, and
- Physical Link Control functions.

The present document describes the information transfer and control functions to be used across the radio (Um) interface for communication between the MS and the Network, see Figure 1.

3GPP TS 23.060 [3] describes the overall GPRS logical architecture and the GPRS functional layers above the Radio Link Control and Medium Access Control layer.

3GPP TS 24.007 [5] contains a description in general terms of the structured functions and procedures of this protocol and the relationship of this protocol with other layers and entities.

3GPP TS 44.018 [6] contains the definition of GPRS RLC/MAC procedures when operating on the Common Control Channel (CCCH).

3GPP TS 44.060 [7] contains the definition of RLC/MAC functions when operating on a Packet Data Channel (PDCH).

3GPP TS 44.064 [8] contains functional procedures for the Logical Link Control (LLC) layer above the RLC/MAC.

3GPP TS 45 series defines the Physical Link layer and Physical RF layer.




Figure 1: Scope of GPRS Logical Radio Interface Architecture

2 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- References are either specific (identified by date of publication, edition number, version number, etc.) or non-specific.
- For a specific reference, subsequent revisions do not apply.
- For a non-specific reference, the latest version applies. In the case of a reference to a 3GPP document (including a GSM document), a non-specific reference implicitly refers to the latest version of that document *in the same Release as the present document*.

- [1] 3GPP TR 21.905: "Vocabulary for 3GPP Specifications".
- [2] 3GPP TS 22.060: "General Packet Radio Service (GPRS); Stage 2".
- [3] 3GPP TS 23.060: "General Packet Radio Service (GPRS); Service description; Stage 2".
- [4] 3GPP TS 44.004: "Digital cellular telecommunications system; Layer 1; General requirements".
- [5] 3GPP TS 24.007: "Mobile radio interface signalling layer 3 General aspects"
- [6] 3GPP TS 44.018: "Mobile radio interface layer 3 specification; Radio Resource Control Protocol"
- [7] 3GPP TS 44.060: "Radio Link Control/Medium Access Control (RLC/MAC) protocol".
- [8] 3GPP TS 44.064: "General Packet Radio Service (GPRS); Logical Link Control (LLC)".
- [9] 3GPP TS 44.065: "General Packet Radio Service (GPRS); Subnetwork Dependent Convergence Protocol (SNDCP)".
- [10] 3GPP TS 45.001: "Physical layer on the radio path, General description".
- [11] 3GPP TS 45.002: "Multiplexing and multiple access on the radio path".
- [12] 3GPP TS 45.003: "Channel coding".
- [13] 3GPP TS 45.004: "Modulation".
- [14] 3GPP TS 45.005: "Radio transmission and reception".
- [15] 3GPP TS 45.008: "Radio subsystem link control".
- [16] 3GPP TS 45.010: "Radio subsystem synchronisation".
- [17] 3GPP TS 43.246: "Multimedia Broadcast Multicast Service (MBMS) in the GERAN; Stage 2".
- [18] 3GPP TS 23.682: 'Architecture enhancements to facilitate communications with packet data networks and applications'.
- [19] 3GPP TS 24.008: 'Mobile radio interface Layer 3 specification; Core network protocols; Stage 3'.
- [20] 3GPP TS 43.020: "Security related network functions"

3 Abbreviations, symbols and definitions

3.1 Abbreviations

In addition to abbreviations in 3GPP TR 21.905 [1] and 3GPP TS 22.060 [2] the following abbreviations apply:

ARQ	Automatic Repeat reQuest
-----	--------------------------

BCS	Block Check Sequence
BEC	Backward Error Correction
BH	Block Header
BTTI	Basic Transmission Time Interval
CC	Coverage Class
CCN	Cell Change Notification
CFCCH	Compact Frequency Correction Channel
CPAGCH	Compact Packet Access Grant Channel
CPBCCCH	Compact Packet Broadcast Control Channel
CPCCCH	Compact Packet Common Control Channel
CPPCH	Compact Packet Paging Channel
CPRACH	Compact Packet Random Access Channel
CSCH	Compact Synchronization Channel
CS- <i>i</i>	GPRS Coding Scheme <i>i</i>
CU	Cell Update
DAS- <i>i</i>	EGPRS2 Downlink level A modulation and coding Scheme <i>i</i>
DBS- <i>i</i>	EGPRS2 Downlink level B modulation and coding Scheme <i>i</i>
DLMC	Downlink Multi Carrier
DTM	Dual Transfer Mode
eDRX	Extended Discontinuous Reception
EGPRS	Enhanced GPRS
EGPRS2	Enhanced GPRS phase 2
EC-EGPRS	Extended Coverage EGPRS
EC-SI	EC-EGPRS System Information
eTFI	Extended Temporary Flow Identity
FANR	Fast Ack/Nack Reporting
FBI	Final Block Indicator
FH	Frame Header
GGSN	Gateway GPRS Support Node
HCS	Header Check Sequence
HSR	Higher Symbol Rate
IR	Incremental Redundancy
LLC	Logical Link Control
MAC	Medium Access Control
MBMS	Multimedia Broadcast/Multicast Service
MCS- <i>i</i>	EGPRS Modulation and Coding Scheme <i>i</i>
MPRACH	MBMS Packet Random Access Channel
NSS	Network and Switching Subsystem
PACCH	Packet Associate Control Channel
PAGCH	Packet Access Grant Channel
PAN	Piggy-backed Ack/Nack
PBCCH	Packet Broadcast Control Channel
PC	Power Control
PCCCH	Packet Common Control Channel
PCS	PAN Check Sequence
PDCH	Packet Data Channel
PDTCH	Packet Data Traffic Channel
PDU	Protocol Data Unit
PEO	Power Efficient Operation
PFC	Packet Flow Context
PFI	Packet Flow Identifier
PL	Physical Link
PPCH	Packet Paging Channel
PRACH	Packet Random Access Channel
PSI	Packet System Information
PSM	Power Saving Mode
PTCCH	Packet Timing Advance Control Channel
p-t-m	point-to-multipoint
RLC	Radio Link Control
RTTI	Reduced Transmission Time Interval
SGSN	Serving GPRS Support Node
SNDC	Subnetwork Dependent Convergence

TA	Timing Advance
TBF	Temporary Block Flow
TFI	Temporary Flow Identity
TTI	Transmission Time Interval
UAS- <i>i</i>	EGPRS2 Uplink level A modulation and coding Scheme <i>i</i>
UBS- <i>i</i>	EGPRS2 Uplink level B modulation and coding Scheme <i>i</i>
USF	Uplink State Flag

3.2 Symbols

For the purposes of the present document, the following symbols apply:

Gb	Interface between an SGSN and a BSC.
Um	Interface between MS and GPRS fixed network part. The Um interface is the GPRS network interface for providing packet data services over the radio to the MS.

3.2a Restrictions

Independently of what is stated elsewhere in this and other 3GPP specifications, mobile station support for PBCCH and PCCCH is optional for A/Gb-mode of operation. The network shall never enable PBCCH and PCCCH.

3.2b Definitions

Blind Physical Layer Transmissions: Repetitions performed on physical layer by blindly, without feedback from the receiving end, transmitting multiple instances of the same block. To maximize the processing gain at the receiver, phase coherency at the transmitter between blind transmissions transmitted within the same TDMA frame is required, see 3GPP TS 45.005 [14].

Coverage Class: A predetermined number of logical channel specific blind physical layer transmissions used by Extended Coverage logical channels, EC-channels, to be able to support a certain level of extended coverage. The number of blind physical layer transmissions may differ between logical channels for the same coverage class. A Coverage Class defines a maximum coverage limit supported in EC-EGPRS operation, see 3GPP TS 45.005. Four Coverage Classes are defined where Coverage Class 1 (CC1) can operate at the approximate coverage range interval of GPRS/EGPRS..

EC-EGPRS operation: An EC-EGPRS capable MS in a cell supporting EC-EGPRS may enable EC-EGPRS operation, in which case CS operation and GPRS/EGPRS operation are disabled, relaxed mobility requirements apply, and the MS shall always use EC-channels, except for FCCH, RACH and AGCH which are also used in EC-EGPRS operation. A MS in Packet Transfer Mode using EC-channels is referred to as being in EC-EGPRS operation.

Extended coverage: Coverage level exceeding the reference sensitivity and reference interference performance of GPRS/EGPRS, see 3GPP TS 45.005 [14].

Fixed Uplink Allocation: Static allocation (and assignment) of limited resources in the uplink over one or more TTIs, using one or more PDCH, that does not make use of USF based allocation.

Power Efficient Operation: A PEO capable mobile station in a cell supporting PEO may enable PEO operation in which case it reduces its power consumption through the use of relaxed mobility related requirements and the use of eDRX or PSM - see 3GPP TS 23.060 [3]. A PEO capable MS in a cell supporting PEO, that has negotiated the use of eDRX or PSM is said to have enabled PEO.

3.3 Network and mobile station capabilities

3.3.1 General

In addition to GPRS specific definitions which can be found in 3GPP TS 22.060 [2] and 3GPP TS 23.060 [3] the following apply.

When referring to radio resources (i.e. physical channels) provided by the network to the mobile station, the term "assignment" refers to granting of resources on a semi-static basis, whereas "allocation" refers to the dynamically

changing permission to use those resources that have been "assigned" to it and are shared with other users. An exception applies when granting resources using Fixed Uplink Allocation where only the term 'allocation' is used. In this case, resources are assigned and allocated by the same message.

Multislot Capability: the capability of the mobile station to support Multislot Configurations.

Multislot Class: a value which implicitly determines the Multislot Capability of the mobile station.

Multislot Configuration: the set of receive and transmit timeslots assigned to the MS.

3.3.2 EGPRS mobile station

An EGPRS mobile station is a GPRS mobile station with additional capabilities for new radio access protocol features and new modulation and coding schemes. An EGPRS mobile station shall comply with GPRS requirements and the additional requirements defined for an EGPRS mobile station. The support of EGPRS is optional for the mobile station and the network.

An EGPRS mobile station may additionally indicate support for EGPRS2 in uplink and/or downlink direction. In this case an EGPRS mobile station supports additional modulation and coding schemes, and may also support higher symbol rate, see sub-clause 3.3.6. The support of EGPRS2 is optional for the mobile station and the network.

An EGPRS mobile station may additionally indicate the support of Reduced Latency. In this case an EGPRS mobile station may be assigned a TBF with FANR activated either in BTTI configuration or in RTTI configuration, see sub-clause 3.3.5. The support of Reduced Latency is optional for the mobile station and the network.

3.3.3 Dual Transfer Mode

In dual transfer mode, the mobile station is assigned resources providing an RR connection and one or more Temporary Block Flows on one or more physical channels. This feature is optional for the mobile station and the network. It is only applicable for a mobile station supporting GPRS, EGPRS or EGPRS2. Dual transfer mode is a subset of class A mode of operation, which is only possible if there is radio resource assignment co-ordination in the network.

3.3.4 Downlink dual carrier configuration

In a downlink dual carrier configuration, one or more PDCHs are assigned to a single MS on each of two different radio frequency channels on either the uplink or downlink, or both. On the downlink, radio blocks may be allocated on both radio frequency channels in any radio block period. On the uplink, radio blocks shall not be allocated on both radio frequency channels in any given radio block period.

NOTE: A radio frequency channel in this context is defined by the frequency parameter(s) ARFCN for a non-hopping radio frequency channel or MA, MAIO and HSN for a hopping radio frequency channel.

A downlink dual carrier configuration shall support multislot configurations either for packet switched connections or dual transfer mode. For a Dual Transfer Mode capable MS which supports Downlink Dual Carrier, support of Downlink Dual Carrier configurations for Dual Transfer Mode is optional.

Downlink dual carrier is not supported in GPRS mode.

3.3.5 Reduced Latency TBF

A TBF applying Reduced Latency shall operate according to all EGPRS/EGPRS2 requirements, unless otherwise stated, with the Fast Ack/Nack Reporting procedure (see sub-clause 3.3.5.1). In addition, a TBF applying Reduced Latency is characterized by either RTTI configuration or BTTI configuration (see sub-clause 3.3.5.2).

3.3.5.1 Fast Ack/Nack Reporting procedure

The Fast Ack/Nack reporting procedure (FANR) refers to the possibility to include, in a radio block for data transfer sent in one direction, piggy-backed ack/nack information relative to a TBF with FANR activated in the other direction.

This is achieved by inserting a fixed-size piggy-backed ack/nack (PAN) field in the radio block. When a PAN field is inserted, a suitable Puncturing Scheme variant for the modulation and coding schemes in use is chosen, so that the RLC data field and the PAN field fit together in the radio block along with the RLC/MAC header. The presence of the PAN