



**Speech and multimedia Transmission Quality (STQ);  
Transmission Requirements for IP-based Narrowband and  
Wideband Home and Network Media Gateways from  
a QoS Perspective as Perceived by the User**

*Standard PREVIEW*  
*Full Standard*  
<https://standards.iteh.ai/catalog/standards/sis/37413748-e-b566-4fc8-836e-e131269dcd49/etsi-es-202-718-v1-3-1-2017-07>

---

Reference

RES/STQ-252

---

Keywords

QoS, speech

**ETSI**

650 Route des Lucioles  
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - NAF 742 C  
Association à but non lucratif enregistrée à la  
Sous-Préfecture de Grasse (06) N° 7803/88

---

**Important notice**

The present document can be downloaded from:

<http://www.etsi.org/standards-search>

The present document may be made available in electronic versions and/or in print. The content of any electronic and/or print versions of the present document shall not be modified without the prior written authorization of ETSI. In case of any existing or perceived difference in contents between such versions and/or in print, the only prevailing document is the print of the Portable Document Format (PDF) version kept on a specific network drive within ETSI Secretariat.

Users of the present document should be aware that the document may be subject to revision or change of status. Information on the current status of this and other ETSI documents is available at

<https://portal.etsi.org/TB/ETSI/DeliverableStatus.aspx>

If you find errors in the present document, please send your comment to one of the following services:

<https://portal.etsi.org/People/CommitteeSupportStaff.aspx>

---

**Copyright Notification**

No part may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm except as authorized by written permission of ETSI.

The content of the PDF version shall not be modified without the written authorization of ETSI.

The copyright and the foregoing restriction extend to reproduction in all media.

© ETSI 2017.  
All rights reserved.

DECT™, PLUGTESTS™, UMTS™ and the ETSI logo are trademarks of ETSI registered for the benefit of its Members.  
3GPP™ and LTE™ are trademarks of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners.

oneM2M logo is protected for the benefit of its Members.

GSM® and the GSM logo are trademarks registered and owned by the GSM Association.

# Contents

Intellectual Property Rights .....	5
Foreword.....	5
Modal verbs terminology.....	5
Introduction .....	5
1 Scope .....	6
2 References .....	6
2.1 Normative references .....	6
2.2 Informative references.....	8
3 Definitions and abbreviations.....	8
3.1 Definitions.....	8
3.2 Abbreviations .....	9
4 General considerations .....	10
4.1 Default Coding Algorithm.....	10
4.2 End-to-end considerations .....	10
4.3 Parameters to be investigated .....	11
4.3.1 Applicability of parameters to different MGWs .....	11
5 Test equipment .....	12
5.1 IP half channel measurement adaptor.....	12
5.2 Environmental conditions for tests.....	12
5.3 Accuracy of measurements and test signal generation.....	13
5.4 Network impairment simulation.....	13
6 Requirements and associated Measurement Methodologies.....	14
6.0 General .....	14
6.1 Test setup.....	14
6.1.0 General.....	14
6.1.1 Setup for Media Gateways with 4-wire interface .....	15
6.1.2 Setup for Media Gateways with 2-wire interface .....	15
6.1.3 Setup for Media Gateways with Wireless Access.....	16
6.1.4 Setup for IP-to-IP Media Gateways .....	17
6.1.5 Test Signal Levels.....	17
6.1.6 Background noise simulation.....	17
6.1.7 Echo paths.....	18
6.2 Coding independent parameters .....	19
6.2.1 Send Frequency response.....	19
6.2.2 Circuit Loudness Rating in Send .....	20
6.2.3 Linearity Range for CLR (SND).....	20
6.2.4 Send Distortion .....	22
6.2.5 Spurious Out-of-Band Signals in Send direction .....	22
6.2.6 Send Noise .....	23
6.2.7 Receive Frequency Response .....	23
6.2.8 Circuit Loudness Rating in Receive .....	24
6.2.9 Linearity Range for CLR (RCV) .....	25
6.2.10 Receive Distortion .....	26
6.2.11 Out-of-Band Signals Wideband to Narrowband Transcoding .....	27
6.2.12 Spurious Out-of-band Signals Narrowband to Wideband Transcoding.....	27
6.2.13 Minimum Activation Level and Sensitivity in Receive Direction .....	28
6.2.14 Receive Noise .....	28
6.2.15 Double Talk Performance.....	29
6.2.15.0 General .....	29
6.2.15.1 Attenuation Range in Send Direction during Double Talk $A_{H,S,dt}$ .....	29
6.2.15.2 Attenuation Range in Receive Direction during Double Talk $A_{H,R,dt}$ .....	30
6.2.15.3 Detection of Echo Components during Double Talk .....	31

6.2.15.4	Minimum Activation Level and Sensitivity of Double Talk Detection .....	33
6.2.16	Switching Characteristics .....	33
6.2.16.0	General .....	33
6.2.16.1	Activation in Send Direction .....	34
6.2.16.2	Activation in Receive Direction .....	34
6.2.16.3	Silence Suppression and Comfort Noise Generation .....	35
6.2.17	Background Noise Performance .....	35
6.2.17.0	General .....	35
6.2.17.1	Performance in Send Direction in the Presence of Background Noise .....	35
6.2.17.2	Quality of Speech with Background Noise .....	36
6.2.17.3	Quality of Background Noise Transmission (with Far End Speech) .....	37
6.2.17.4	Quality of Background Noise Transmission (with Near End Speech) .....	38
6.2.18	Quality of Echo Cancellation .....	38
6.2.18.0	General .....	38
6.2.18.1	Echo Performance According to Recommendation ITU-T G.168 .....	38
6.2.18.2	Terminal Coupling Loss (TCLw, NB) .....	39
6.2.18.3	Terminal Coupling Loss (TCL, WB) .....	39
6.2.18.4	Temporal Echo Effects .....	40
6.2.18.5	Spectral Echo Attenuation .....	41
6.2.18.6	Occurrence of Artefacts .....	41
6.2.18.7	Variable Echo Paths .....	41
6.2.19	Variant Impairments; Network dependant .....	42
6.2.19.1	Clock Accuracy Send .....	42
6.2.19.2	Clock Accuracy Receive .....	42
6.2.19.3	Send Packet Delay Variation .....	42
6.2.20	Immunity to DTMF False Detection in Send Direction .....	43
6.2.21	Send and receive delay - round trip delay .....	43
6.3	Codec Specific Requirements .....	44
6.3.1	Objective Listening Speech Quality MOS-LQO in Send direction .....	44
6.3.2	Objective Listening Quality MOS-LQO in Receive direction .....	45
6.3.3	Quality of Jitter buffer adjustment .....	48
<b>Annex A (informative):</b>	<b>Impulse Response of a Narrowband and Wideband DECT PP .....</b>	<b>50</b>
<b>Annex B (normative):</b>	<b>Test signal for immunity to DTMF false detection in send direction .....</b>	<b>52</b>
<b>Annex C (informative):</b>	<b>Example IP Delay variation .....</b>	<b>53</b>
<b>Annex D (informative):</b>	<b>Bibliography .....</b>	<b>54</b>
History .....		55

---

# Intellectual Property Rights

## Essential patents

IPRs essential or potentially essential to the present document may have been declared to ETSI. The information pertaining to these essential IPRs, if any, is publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: "*Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards*", which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (<https://ipr.etsi.org/>).

Pursuant to the ETSI IPR Policy, no investigation, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

## Trademarks

The present document may include trademarks and/or tradenames which are asserted and/or registered by their owners. ETSI claims no ownership of these except for any which are indicated as being the property of ETSI, and conveys no right to use or reproduce any trademark and/or tradename. Mention of those trademarks in the present document does not constitute an endorsement by ETSI of products, services or organizations associated with those trademarks.

---

# Foreword

This final draft ETSI Standard (ES) has been produced by ETSI Technical Committee Speech and multimedia Transmission Quality (STQ), and is now submitted for the ETSI standards Membership Approval Procedure.

---

# Modal verbs terminology

In the present document "**shall**", "**shall not**", "**should**", "**should not**", "**may**", "**need not**", "**will**", "**will not**", "**can**" and "**cannot**" are to be interpreted as described in clause 3.2 of the [ETSI Drafting Rules](#) (Verbal forms for the expression of provisions).

"**must**" and "**must not**" are **NOT** allowed in ETSI deliverables except when used in direct citation.

---

# Introduction

Traditionally, the analogue and digital telephones were interfacing switched-circuit 64 kbit/s PCM networks. With the fast growth of IP networks, packet-switched networks (VoIP) interfacing PSTN networks and mobile networks, as well as different types of IP-terminals, are being rapidly introduced. Different types of gateways are used to interconnect to such IP networks. Since the IP networks will be in many cases interworking with the traditional PSTN and private networks, many of the basic transmission requirements have to be harmonized between these different types of network from an end-to-end perspective, including specifications for the edge points.

The present document covers IP-based narrowband and wideband home and network media gateways. It aims to enhance the interoperability and end-to-end quality.

In contrast to other standards which define minimum performance requirements, it is the intention of the present document to specify gateway equipment requirements which enable manufacturers and service providers to enable end-to-end speech performance as perceived by the user. These requirements are absolutely necessary to ensure a good quality, but they are not sufficient. They have to be combined with requirements (and associated relevant measurement methods) for other elements in the transmission chain (core IP network, PSTN, terminals), as well as for the whole mouth-to-ear transmission path.

---

# 1 Scope

The present document provides speech transmission performance requirements for narrowband and wideband media gateways from a QoS perspective as perceived by the user. Media gateways can be network or home based, they may include a transcoding function. The present document covers the following types of IP-based media gateways:

- ATA (Analogue Terminal Adapter), home gateway IP to POTS
- ITA (ISDN Terminal Adapter), home gateway IP to ISDN
- IAD (Integrated Access device), home router including ATA or ITA
- Network based ATA and ITA
- Carrier grade media gateway, network gateway IP to TDM
- IP-to-IP media gateway, network gateway with transcoding and/or other media processing
- New Generation DECT Fixed part with IP interface (only parameters not covered by New Generation DECT)

Interfaces of media gateways used together with terminals as a system (i.e. connected via Ethernet or with a proprietary interface) are excluded in the present document and should be measured according to the relevant terminal standard.

If a media gateway includes more than one interface type (e.g. POTS and ISDN), each interface has to be dealt with differently.

The requirements available in the present document will ensure a high compatibility with IP-and TDM-based fixed and wireless terminals and networks, including DECT and mobile terminals.

It is the aim to optimize interoperability, the listening and talking quality and the conversational performance. Related requirements and test methods are defined in the present document.

The present document does not apply to media gateways with 4-wire analogue interfaces.

The requirements for MGWs with respect to voiceband data (VBD) are out of scope in the present document. These requirements are covered in ETSI TS 102 929 [i.5].

---

## 2 References

### 2.1 Normative references

References are either specific (identified by date of publication and/or edition number or version number) or non-specific. For specific references, only the cited version applies. For non-specific references, the latest version of the referenced document (including any amendments) applies.

Referenced documents which are not found to be publicly available in the expected location might be found at <https://docbox.etsi.org/Reference/>.

NOTE: While any hyperlinks included in this clause were valid at the time of publication, ETSI cannot guarantee their long term validity.

The following referenced documents are necessary for the application of the present document.

- [1] ETSI EN 300 726: "Digital cellular telecommunications system (Phase 2+) (GSM); Enhanced Full Rate (EFR) speech transcoding (GSM 06.60)".
- [2] ETSI TS 126 171: "Digital cellular telecommunications system (Phase 2+); Universal Mobile Telecommunications System (UMTS); AMR speech codec, wideband; General description (3GPP TS 26.171 version 6.0.0 Release 6)".

- [3] Recommendation ITU-T G.107: "The E-model, a computational model for use in transmission planning".
- [4] Recommendation ITU-T G.108, including amendments 1 and 2: "Application of the E-model: A planning guide".
- [5] Recommendation ITU-T G.109: "Definition of categories of speech transmission quality".
- [6] Recommendation ITU-T G.100.1: "The use of the decibel and of relative levels in speechband telecommunications".
- [7] Recommendation ITU-T G.111: "Loudness Ratings (LRs) in an international connection".
- [8] Recommendation ITU-T G.122: "Influence of national systems on stability and talker echo in international connections".
- [9] Recommendation ITU-T G.711: "Pulse code modulation (PCM) of voice frequencies".
- [10] Recommendation ITU-T G.723.1: "Dual rate speech coder for multimedia communications transmitting at 5.3 and 6.3 kbit/s".
- [11] Recommendation ITU-T G.726: "40, 32, 24, 16 kbit/s Adaptive Differential Pulse Code Modulation (ADPCM)".
- [12] Recommendation ITU-T G.729: "Coding of speech at 8 kbit/s using conjugate-structure algebraic-code-excited linear prediction (CS-ACELP)".
- [13] Recommendation ITU-T G.729.1: "G.729-based embedded variable bit-rate coder: An 8-32 kbit/s scalable wideband coder bitstream interoperable with G.729".
- [14] Void
- [15] Recommendation ITU-T P.863.1: "Application guide for Recommendation ITU-T P.863".
- [16] Recommendation ITU-T P.340: "Transmission characteristics and speech quality parameters of hands-free terminals".
- [17] Recommendation ITU-T P.501: "Test signals for use in telephony".
- [18] Recommendation ITU-T P.502: "Objective test methods for speech communication systems using complex test signals".
- [19] Recommendation ITU-T P.56: "Objective measurement of active speech level".
- [20] IEC 61260-1: "Electroacoustics - Octave-band and fractional-octave-band filters. - Part 1: Specification".
- [21] Recommendation ITU-T P.800.1: "Mean Opinion Score (MOS) terminology".
- [22] ETSI TS 102 971: "Access and Terminals (AT); Public Switched Telephone Network (PSTN); Harmonized specification of physical and electrical characteristics of a 2-wire analogue interface for short line interface".
- [23] ETSI ES 201 970: "Access and Terminals (AT); Public Switched Telephone Network (PSTN); Harmonized specification of physical and electrical characteristics at a 2-wire analogue presented Network Termination Point (NTP)".
- [24] Recommendation ITU-T G.168: "Digital network echo cancellers".
- [25] Recommendation ITU-T P.863: "Perceptual objective listening quality assessment".
- [26] Recommendation ITU-T G.722: "7 kHz audio-coding within 64 kbit/s".
- [27] Recommendation ITU-T G.722.1: "Low-complexity coding at 24 and 32 kbit/s for hands-free operation in systems with low frame loss".

- [28] Recommendation ITU-T G.722.2: "Wideband coding of speech at around 16 kbit/s using Adaptive Multi-Rate Wideband (AMR-WB)".
- [29] Recommendation ITU-T P.1010: "Fundamental voice transmission objectives for VoIP terminals and gateways".
- [30] IETF RFC 3550: "RTP: A Transport Protocol for Real-Time Applications".
- [31] ETSI EG 202 396-3: "Speech and multimedia Transmission Quality (STQ); Speech Quality performance in the presence of background noise Part 3: Background noise transmission - Objective test methods".

## 2.2 Informative references

References are either specific (identified by date of publication and/or edition number or version number) or non-specific. For specific references, only the cited version applies. For non-specific references, the latest version of the referenced document (including any amendments) applies.

NOTE: While any hyperlinks included in this clause were valid at the time of publication, ETSI cannot guarantee their long term validity.

The following referenced documents are not necessary for the application of the present document but they assist the user with regard to a particular subject area.

- [i.1] ETSI EG 202 425: "Speech Processing, Transmission and Quality Aspects (STQ); Definition and implementation of VoIP reference point".
- [i.2] IETF RFC 2833: "RTP Payload for DTMF Digits, Telephony Tones and Telephony Signals".
- [i.3] IETF RFC 4733: "RTP Payload for DTMF Digits, Telephony Tones, and Telephony Signals".
- [i.4] Void.
- [i.5] ETSI TS 102 929: "Speech and multimedia Transmission Quality (STQ); Procedures for the identification and selection of common modes of de-jitter buffers and echo cancellers".
- [i.6] ETSI TS 103 224: "Speech and multimedia Transmission Quality (STQ); A sound field reproduction method for terminal testing including a background noise database".

---

## 3 Definitions and abbreviations

### 3.1 Definitions

For the purposes of the present document, the following terms and definitions apply:

**0dB<sub>r</sub> point:** reference point always located at the digital side of the gateway, for IP-IP gateways located at the input of the MGW under test

NOTE: See Recommendation ITU-T G.100.1 [6].

**2-wire interface:** in the context of the present document, telephony analogue interface over 2-wires used in the local loop

**4-wire interface:** in the context of the present document, 4-wire digital interface with separate channels for both directions, irrespective of the physical transmission technology

**codec:** combination of an analogue-to-digital encoder and a digital-to-analogue decoder operating in opposite directions of transmission in the same equipment

**Composite Source Signal (CSS):** signal composed in time by various signal elements

**MGW with 2-wire interface:** MGW with an analogue 2-wire interface (ATA)



**MGW with 4-wire interface:** MGW with only 4-wire interfaces

EXAMPLE: ITA, IP-to-IP and wireless access points.

**receive direction:** direction from packet switched interfaces towards a synchronous interface (e.g. ISDN, analogue) or between two packet switched interfaces (for media gateways with packet switched transport on only one side)

NOTE: For media gateways with packet switched transport on both sides (IP-to-IP-MGW), the requirements of the receive direction have to be applied in both directions.

**receive interface:** interface in the measurement setup, where a receive signal is injected and/or a send signal is measured

**send direction:** direction from a synchronous interface (e.g. ISDN, analogue) towards a packet switched interface (for media gateways with packet switched interface on only one side)

NOTE: For media gateways with packet switched interfaces on both sides the requirements of the send direction are not relevant.

**send interface:** interface in the measurement setup, where a send signal is injected and/or a receive signal is measured

**wireless home MGW:** home MGW with wireless interface to the phone

EXAMPLE: Wifi or DECT.

## 3.2 Abbreviations

For the purposes of the present document, the following abbreviations apply:

AM-FM	Amplitude Modulation - Frequency Modulation
AMR	Adaptive Multi Rate codec
ATA	Analogue Terminal Adapter
CLR	Circuit Loudness Rating
CS	Composite Source
CSS	Composite Source Signal
DECT	Digital Enhanced Cordless Telecommunications
DSL	Digital Subscriber Line
DSLAM	Digital Subscriber Line Access Multiplexer
DTMF	Dual Tone Multi Frequency
EC	Echo Canceller
EFR	Enhance Full Rate codec
EL	Echo Loss
ETH	Eidgenössische Technische Hochschule
FFT	Fast Fourier Transformation
FP	DECT Fixed Part
G-MOS-LQOn	Overall transmission quality narrowband
G-MOS-LQOw	Overall transmission quality wideband
GSM	Global System for Mobile communication
GW	GateWay
HATS	Head And Torso Simulator
IAD	Integrated Access Device
IP	Internet Protocol
IPDV	IP Packet Delay Variation
IRS	Intermediate Reference System
ISDN	Integrated Service Digital Network
ITA	ISDN Terminal Adapter
MGW	Media GateWay
MOS-LQOy	Mean Opinion Score - Listening Quality Objective

NOTE: See Recommendation ITU-T P.800.1 [21].

NB	Narrowband
NLP	Non Linear Processor

N-MOS-LQOn	Transmission quality of the background noise narrowband
N-MOS-LQOw	Transmission quality of the background noise wideband
PBX	Private Branch eXchange
PC	Personal Computer
PCM	Pulse Code Modulation
PLC	Packet Loss Concealment
POI	Point Of Interconnect
POTS	Plain Old Telephone Service
PP	DECT Portable Part
PSTN	Public Switched Telephone Network
QoS	Quality of Service
RCV	Receiving Direction
RLR	Receive Loudness Rating
RMS	Root Mean Square
RTP	Real Time Protocol
SIP	Session Initiation Protocol
SLR	Send Loudness Rating
S-MOS-LQOn	Transmission quality of the speech narrowband
S-MOS-LQOw	Transmission quality of the speech wideband
SND	Sending Direction
TCL	Terminal Coupling Loss
TCN™	Trace Control for Netem™
TDM	Time Division Multiplexing
VAD	Voice Activity Detection
VBD	Voice Band Data
VoIP	Voice over Internet Protocol
WB	Wideband

---

## 4 General considerations

### 4.1 Default Coding Algorithm

Narrowband VoIP gateways shall support the coding algorithm according to Recommendation ITU-T G.711 [9] (both  $\mu$ -law and A-law). VoIP gateways may support other coding algorithms.

Wideband VoIP gateways shall support the coding algorithm according to Recommendation ITU-T G.722 [26]. VoIP gateways may support other coding algorithms.

NOTE: Associated Packet Loss Concealment (PLC) e.g. as defined in Recommendation ITU-T G.711 [9] appendix I should be used.

### 4.2 End-to-end considerations

In order to achieve a desired end-to-end speech transmission performance (mouth-to-ear) it is recommended that the general rules of transmission planning are carried out with the E-model of Recommendation ITU-T G.107 [3]; this includes the a-priori determination of the desired category of speech transmission quality as defined in Recommendation ITU-T G.109 [5].

While, in general, the transmission characteristics of single circuit-oriented network elements, such as switches or terminals can be assumed to have a single input value for the planning tasks of Recommendation ITU-T G.108 [4] with its amendments, this approach is not applicable in packet based systems and thus there is a need for the transmission planner's specific attention.

In particular the decision as to which delay measured according to the present document is acceptable or representative for the specific configuration is the responsibility of the individual transmission planner.

Recommendation ITU-T G.108 [4] with its amendments provides further guidance on this important issue.

The following optimum parameters from a users' perspective need to be considered:

- Minimized delay in send and receive direction.
- Optimum Circuit Loudness Rating (CLR).
- Compensation for network delay variation.
- Packet loss recovery performance.
- Maximized echo loss.
- Immunity to false detection of DTMF in speech signal.

## 4.3 Parameters to be investigated

### 4.3.1 Applicability of parameters to different MGWs

Table 1: Parameter applicability

	2-wire home and network MGW	4-wire MGW (excl. IP-to-IP MGW)	4-wire MGW (IP-to-IP-MGW)	wireless home MGW (DECT FP)
<b>6.2 Codec independent parameters</b>				
6.2.1 Send frequency response	M	M	NA	M
6.2.2 Circuit Loudness Rating in Send	M	M	NA	M
6.2.3 Linearity Range for CLR(SND)	M	M	NA	M
6.2.4 Send Distortion	M	M	NA	M
6.2.5 Spurious Out-of-Band Signals in Send direction	M	NA	NA	NA
6.2.6 Send Noise	M	M	NA	M
6.2.7 Receive frequency response	M	M	MM	M
6.2.8 Circuit Loudness Rating in Receive	M	M	MM	M
6.2.9 Linearity Range for CLR(RCV)	M	M	MM	M
6.2.10 Receive Distortion	M	M	MM	M
6.2.11 Out-of-Band Signals in Wideband to Narrowband Transcoding	NA	M	M	M
6.2.12 Spurious Out-of-band Signals Narrowband to Wideband Transcoding	NA	M	M	M
6.2.13 Minimum activation level and sensitivity in Receive direction	FFS	FFS	FFS	FFS
6.2.14 Receive Noise	M	M	MM	M
<b>6.2.15 Double Talk Performance</b>				
6.2.15.1 Attenuation Range in Send Direction during Double Talk	M (note 1)	M (note 1)	M	M (note 1)
6.2.15.2 Attenuation Range in Receive Direction during Double Talk	M (note 1)	M (note 1)	M	M (note 1)
6.2.15.3 Detection of Echo Components during Double Talk	M (note 1)	M (note 1)	M	M (note 2)
6.2.15.4 Minimum activation level and sensitivity of double talk detection	FFS	FFS	FFS	FFS
<b>6.2.16 Switching characteristics</b>				
6.2.16.1 Activation in Send Direction	M	M	NA	M
6.2.16.2 Activation in Receive Direction	M	M	M	M
6.2.16.3 Silence Suppression and Comfort Noise Generation	FFS	FFS	FFS	FFS
<b>6.2.17 Background Noise Performance</b>				
6.2.17.1 Performance in send direction in the presence of background noise	M	M	MM	M
6.2.17.2 Quality of Speech with Background Noise	M	M	MM	M
6.2.17.3 Quality of Background Noise Transmission (with Far End Speech)	M (note 1)	M (note 1)	MM	M (note 1)

	2-wire home and network MGW	4-wire MGW (excl. IP-to-IP MGW)	4-wire MGW (IP-to-IP-MGW)	wireless home MGW (DECT FP)
6.2.17.4 Quality of Background Noise Transmission (with Near End Speech)	M	M	MM	M
6.2.18 Quality of echo cancellation				
6.2.18.1 Echo Performance acc. To G.168	NA	M (note 1)	NA	NA
6.2.18.2 TCLw (NB)	M (note 1)	M (note 1) (NB)	NA	M (note 2) (NB)
6.2.18.3 TCL (WB)	NA	M (note 1) (WB)	NA	M (note 2) (WB)
6.2.18.4 Temporal echo effects	M (note 1)	M (note 1)	NA	M (note 2)
6.2.18.5 Spectral Echo Attenuation	M (note 1)	M (note 1)	NA	M (note 2)
6.2.18.6 Occurrence of Artefacts	FFS	FFS	NA	FFS
6.2.19 Variant Impairments; Network dependant				
6.2.19.1 Clock accuracy send	M	M	MM	M
6.2.19.2 Clock accuracy receive	M	M	MM	NA
6.2.19.3 Send delay variation	M	M	MM	M
6.2.20 Immunity to DTMF false detection in send direction	M	M	MM	M
6.2.21 Roundtrip Delay	M	M	M	NA
6.3 Codec Specific Requirements				
6.3.1 Objective Listening Speech Quality MOS-LQO in Send direction	M	M	M	M
6.3.2 Objective Listening Speech Quality MOS-LQO in Receive direction	M	M	M	M
6.3.3 Quality of Jitter buffer adjustment	M	M	M	M (note 3)
M:	Mandatory			
MM:	Mandatory for both interfaces of the MGW			
NA:	Not applicable			
FFS:	For further study			
NOTE 1:	Measurement to be done with different echopaths (see clause 6.1.7).			
NOTE 2:	Measurement to be done with Ref PP settings "34/42dB TCLw" only. Echopath set accordingly (see clause 6.1.7).			
NOTE 3:	Measurement mandatory, if PP does not support PLC.			

## 5 Test equipment

### 5.1 IP half channel measurement adaptor

The IP half channel measurement adaptor is described in ETSI EG 202 425 [i.1]. Such an apparatus is required to code and insert audio signals into IP packets send to the IP receive interface of the gateway under test, as well as to capture and decode audio signals constituting the payload of IP packets received from the IP sending interface of the gateway under test.

### 5.2 Environmental conditions for tests

The following conditions shall apply for the testing environment:

- a) Ambient temperature: 15 °C to 35 °C (inclusive);
- b) Relative humidity: 5 % to 85 %;
- c) Air pressure: 86 kPa to 106 kPa (860 mbar to 1 060 mbar).

## 5.3 Accuracy of measurements and test signal generation

Unless specified otherwise, the accuracy of measurements made by test equipment shall be equal to or better than:

**Table 2: Measurement Accuracy**

Item	Accuracy
Electrical signal level	$\pm 0,2$ dB for levels $\geq -50$ dBV $\pm 0,4$ dB for levels $< -50$ dBV
Frequency	$\pm 0,2$ %
Time	$\pm 0,2$ %

Unless specified otherwise, the accuracy of the signals generated by the test equipment shall be better than:

**Table 3: Accuracy of test signal generation**

Quantity	Accuracy
Electrical excitation levels	$\pm 0,4$ dB across the whole frequency range
Frequency generation	$\pm 2$ % (see note)
Time	$\pm 0,2$ %
Specified component values	$\pm 1$ %
NOTE:	This tolerance may be used to avoid measurements at critical frequencies, e.g. those due to sampling operations within the terminal under test.

If the equipment is powered by other means and those means are not supplied as part of the apparatus, all tests shall be carried out within the power supply limit declared by the supplier. If the power supply is a.c. the test shall be conducted within  $\pm 4$  % of the rated frequency.

## 5.4 Network impairment simulation

At least one set of requirements is based on the assumption of an error free packet network, and at least one other set of requirements is based on a defined simulated malperformance of the packet network.

An appropriate network simulator has to be used, for example Netem™.

The key points of Netem™ can be summarized as follows:

- Netem™ is part of most Linux™ distributions, it only has to be switched on, when compiling a kernel. With Netem™, there are the same possibilities as with Nistnet™, there can be generated loss, duplication, delay and jitter (and the distribution can be chosen during runtime). Netem™ can be run on a Linux™-PC running as a bridge or a router (Nistnet™ only runs on routers).
- With an amendment of Netem™, TCN (Trace Control for Netem™) which was developed by ETH Zurich™, it is even possible, to control the behaviour of single packets via a trace file. So it is for example possible to generate a single packet loss, or a specific delay pattern. This amendment is planned to be included in new Linux™ Kernels, nowadays it is available as a patch to a specific kernel and to the iproute2 tool (iproute2 contains Netem™).
- It is not advised to define specific distortion patterns for testing in standards, because it will be easy to adapt devices to these patterns (as it is already done for test signals). But if a pattern is unknown to a manufacturer, the same pattern can be used by a test lab for different devices and gives comparable results. It is also possible to take a trace of Nistnet™ distortions, generate a file out of this and playback the exact same distortions with Netem™.

NOTE: Nistnet™ and Netem™ are examples of suitable products available commercially. This information is given for the convenience of users of the present document and does not constitute an endorsement by ETSI of these products.