INTERNATIONAL STANDARD

ISO/IEC 12862

First edition 2009-06-15

Information technology — 120 mm (8,54 Gbytes per side) and 80 mm (2,66 Gbytes per side) DVD recordable disk for dual layer (DVD-R for DL)

Technologies de l'information — Disques DVD enregistrables de 120 mm (8,54 Go par face) et 80 mm (2,66 Go par face) pour double

iTeh STCOuche (DYD-R pour DREVIEW

(standards.iteh.ai)

ISO/IEC 12862:2009

https://standards.iteh.ai/catalog/standards/sist/b58a5113-6481-4c8f-b9ca-df4b3e5c34d3/iso-iec-12862-2009



PDF disclaimer

This PDF file may contain embedded typefaces. In accordance with Adobe's licensing policy, this file may be printed or viewed but shall not be edited unless the typefaces which are embedded are licensed to and installed on the computer performing the editing. In downloading this file, parties accept therein the responsibility of not infringing Adobe's licensing policy. The ISO Central Secretariat accepts no liability in this area.

Adobe is a trademark of Adobe Systems Incorporated.

Details of the software products used to create this PDF file can be found in the General Info relative to the file; the PDF-creation parameters were optimized for printing. Every care has been taken to ensure that the file is suitable for use by ISO member bodies. In the unlikely event that a problem relating to it is found, please inform the Central Secretariat at the address given below.

iTeh STANDARD PREVIEW (standards.iteh.ai)

ISO/IEC 12862:2009 https://standards.iteh.ai/catalog/standards/sist/b58a5113-6481-4c8f-b9ca-df4b3e5c34d3/iso-iec-12862-2009



COPYRIGHT PROTECTED DOCUMENT

© ISO/IEC 2009

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either ISO at the address below or ISO's member body in the country of the requester.

ISO copyright office
Case postale 56 • CH-1211 Geneva 20
Tel. + 41 22 749 01 11
Fax + 41 22 749 09 47
E-mail copyright@iso.org
Web www.iso.org

Published in Switzerland

Contents

Page

Foreword	vi
Introduction	vii
1 Scope	1
2 Conformance	
3 Normative references	2
4 Terms and definitions	2
5 Conventions and notations	6
6 Abbreviated terms	
7 General description of a disk	
8.1 Environments (standards.iteh.ai) 8.1.1 Test environment (Operating environment (SO/IEC 12862:2009) 8.1.3 Storage environment (SO/IEC 12862:2009) 8.1.4 Transportations://standards.iteh.ai/catalog/standards/sist/b58a5113-6481-4c8f-b9ca- 8.2 Safety requirements (df2b3e5c34d3/iso-iec-12862-2009) 8.3 Flammability	8 9 9 10
9 Reference measurement devices 9.1 Pick-Up Head (PUH) 9.1.1 PUH for measuring recorded disks 9.2 PUH for measuring unrecorded disks 9.2 Measurement conditions 9.2.1 Recorded and unrecorded disk 9.2.2 Recorded disk 9.2.3 Unrecorded disk 9.4 Reference servo for axial tracking 9.5 Reference servo for radial tracking	
9.5.1 Recorded disk	
10 Dimensional characteristics 10.1 Overall dimensions 10.2 First transition area 10.3 Second transition area 10.4 Clamping Zone 10.5 Third transition area	
10.6 R-Information Zone	22 22

ISO/IEC 12862:2009(E)

		~~
10.8	Track geometry	
10.8.1	Track Path	
10.9	Channel bit length	. 24
10.10	Rim area	. 24
10.11	Remark on tolerances	
10.12	Label	
10.12		
11	Mechanical parameters	. 25
11.1	Mass	. 25
11.2	Moment of inertia	
11.3	Dynamic imbalance	
11.4	Sense of rotation	
11. 4 11.5	Runout	
11.5.1	Axial runout	
11.5.2	Radial runout	. 26
12	Optical parameters	26
12.1	Recorded and unrecorded disk parameters	
12.1.1	Index of refraction	
	Thickness of the transparent substrate	
12.1.2		
12.1.3	Angular deviation	
12.1.4	Birefringence of the transparent substrate	
12.2	Recorded disk reflectivity	
12.3	Unrecorded disk parameters	. 28
12.3.1	Polarity of reflectivity modulation	. 28
12.3.2	Recording power sensitivity variation	. 28
	Operational signals for recorded disk NDARD PREVIEW	
13	Operational signals for recorded disk	. 28
13.1	Measurement conditions	. 28
13.2	Measurement conditions (Standards.iteh.ai)	. 28
13.3	Recorded disk high frequency (HF) signals	. 28
13.3.1	Modulated amplitude	. 28
13.3.2	Signal asymmetry	. 29
13.3.2 13.3.3	Signal asymmetry https://standards.itch:ai/catalog/standards/sist/b58a5113-6481-4c8f-b9ca-	. 29 29
13.3.3	Cross-track signal	. 29
13.3.3 13.4	Cross-track signal	. 29 . 29
13.3.3 13.4 13.4.1	Cross-track signal	. 29 . 29 . 29
13.3.3 13.4 13.4.1 13.4.2	Cross-track signal df4b3e5c34d3/isu-jee-12862-2009 Quality of signals Jitter Random errors	. 29 . 29 . 29 . 29
13.3.3 13.4 13.4.1 13.4.2 13.4.3	Cross-track signal df4b3e5c34d3/so-iec=12862-2009 Quality of signals Jitter Random errors. Defects	. 29 . 29 . 29 . 29
13.3.3 13.4 13.4.1 13.4.2 13.4.3 13.5	Cross-track signal df4b3u5c34d3/su-ieu-12862-2009 Quality of signals Jitter Random errors Defects Servo signals	. 29 . 29 . 29 . 30 . 30
13.3.3 13.4 13.4.1 13.4.2 13.4.3	Cross-track signal drib3e5e34d3/se-iee-12862-2009 Quality of signals Jitter Random errors Defects Servo signals Differential phase tracking error signal	. 29 . 29 . 29 . 30 . 30
13.3.3 13.4 13.4.1 13.4.2 13.4.3 13.5 13.5.1 13.5.1	Cross-track signal dith3u5c94d3/so-ieu-12862-2009 Quality of signals Jitter	. 29 . 29 . 29 . 30 . 30 . 30
13.3.3 13.4 13.4.1 13.4.2 13.4.3 13.5 13.5.1	Cross-track signal drib3e5e34d3/se-iee-12862-2009 Quality of signals Jitter Random errors Defects Servo signals Differential phase tracking error signal	. 29 . 29 . 29 . 30 . 30 . 30
13.3.3 13.4 13.4.1 13.4.2 13.4.3 13.5 13.5.1 13.5.2 13.6	Cross-track signal dith3u5c34d3/su-ieu-12802-2009 Quality of signals Jitter Random errors Defects Servo signals Differential phase tracking error signal Tangential push-pull signal Groove wobble signal	. 29 . 29 . 29 . 30 . 30 . 30
13.3.3 13.4 13.4.1 13.4.2 13.4.3 13.5 13.5.1 13.5.2 13.6	Cross-track signal dith3u5c94d3/so-ieu-12862-2009 Quality of signals Jitter	. 29 . 29 . 29 . 30 . 30 . 30 . 32
13.3.3 13.4 13.4.1 13.4.2 13.4.3 13.5 13.5.1 13.5.2 13.6	Cross-track signal dith3u5c94d3/so-ieu-12862-2009 Quality of signals Jitter Random errors Defects Servo signals Differential phase tracking error signal Tangential push-pull signal Groove wobble signal Operational signals for the unrecorded disk Measurement conditions	. 29 . 29 . 29 . 30 . 30 . 30 . 32 . 33
13.3.3 13.4 13.4.1 13.4.2 13.4.3 13.5 13.5.1 13.5.2 13.6 14 14.1	Cross-track signal dith3u5c94d3/su-ieu-12862-2009 Quality of signals Jitter	. 29 . 29 . 29 . 30 . 30 . 30 . 32 . 33 . 33
13.3.3 13.4 13.4.1 13.4.2 13.4.3 13.5 13.5.1 13.5.2 13.6 14 14.1 14.2	Cross-track signal dith3u5c94d3/su-ieu-12862-2009 Quality of signals Jitter	. 29 . 29 . 29 . 30 . 30 . 30 . 33 . 33 . 33
13.3.3 13.4 13.4.1 13.4.2 13.4.3 13.5 13.5.1 13.5.2 13.6 14 14.1 14.2 14.3 14.3.1	Cross-track signal dith3u5c94d3/su-ieu-12862-2009 Quality of signals Jitter	. 29 . 29 . 29 . 30 . 30 . 30 . 32 . 33 . 33 . 33
13.3.3 13.4 13.4.1 13.4.2 13.4.3 13.5 13.5.1 13.5.2 13.6 14 14.1 14.2 14.3 14.3.1	Cross-track signal	. 29 . 29 . 29 . 30 . 30 . 30 . 32 . 33 . 33 . 33 . 34 . 35
13.3.3 13.4 13.4.1 13.4.2 13.4.3 13.5 13.5.1 13.5.2 13.6 14 14.1 14.2 14.3 14.3.1 14.4	Cross-track signal	. 29 . 29 . 29 . 30 . 30 . 30 . 30 . 33 . 33 . 33 . 35 . 35
13.3.3 13.4 13.4.1 13.4.2 13.4.3 13.5 13.5.1 13.5.2 13.6 14 14.1 14.2 14.3.1 14.3.1 14.4.1 14.4.1	Cross-track signal drib3e5e34d3/so-icc-12862-2009 Quality of signals Jitter Random errors Defects Servo signals Differential phase tracking error signal Tangential push-pull signal Groove wobble signal Operational signals for the unrecorded disk Measurement conditions Recording conditions Write strategy for media testing Definition of the write pulse Servo signals Radial push-pull tracking error signal Defects	. 29 . 29 . 29 . 30 . 30 . 30 . 33 . 33 . 33 . 35 . 35 . 36
13.3.3 13.4 13.4.1 13.4.2 13.4.3 13.5 13.5.1 13.5.2 13.6 14 14.1 14.2 14.3 14.3.1 14.4	Cross-track signal	. 29 . 29 . 29 . 30 . 30 . 30 . 33 . 33 . 33 . 35 . 35 . 36
13.3.3 13.4 13.4.1 13.4.2 13.4.3 13.5 13.5.1 13.5.2 13.6 14 14.1 14.2 14.3.1 14.3.1 14.4.1 14.4.1	Cross-track signal drib3e5e34d3/so-icc-12862-2009 Quality of signals Jitter Random errors Defects Servo signals Differential phase tracking error signal Tangential push-pull signal Groove wobble signal Operational signals for the unrecorded disk Measurement conditions Recording conditions Write strategy for media testing Definition of the write pulse Servo signals Radial push-pull tracking error signal Defects	. 29 . 29 . 29 . 30 . 30 . 30 . 33 . 33 . 33 . 35 . 35 . 36 . 36
13.3.3 13.4 13.4.1 13.4.2 13.4.3 13.5 13.5.1 13.5.2 13.6 14 14.1 14.2 14.3 14.3.1 14.4.1 14.4.1	Cross-track signal	. 29 . 29 . 29 . 30 . 30 . 30 . 32 . 33 . 33 . 33 . 35 . 36 . 36 . 36
13.3.3 13.4 13.4.1 13.4.2 13.4.3 13.5 13.5 13.5.1 13.5.2 13.6 14 14.1 14.2 14.3 14.3 14.4.1 14.4.2 14.5 14.5 14.5.1 14.5.2	Cross-track signal	. 29 . 29 . 29 . 30 . 30 . 30 . 33 . 33 . 33 . 35 . 36 . 36 . 36 . 36
13.3.3 13.4 13.4.1 13.4.2 13.4.3 13.5 13.5.1 13.5.2 13.6 14 14.1 14.2 14.3 14.3.1 14.4.1 14.4.1 14.4.2 14.5.1 14.5.2 14.5.3	Cross-track signal Quality of signals Jitter Random errors Defects Servo signals Differential phase tracking error signal Tangential push-pull signal Groove wobble signal Operational signals for the unrecorded disk Measurement conditions Recording conditions Write strategy for media testing Definition of the write pulse Servo signals Radial push-pull tracking error signal Defects Addressing signals Land Pre-Pit signal Groove wobble signal. Relation in phase between wobble and Land Pre-Pit	. 29 . 29 . 29 . 30 . 30 . 30 . 32 . 33 . 33 . 33 . 35 . 36 . 36 . 38 . 38
13.3.3 13.4 13.4.1 13.4.2 13.4.3 13.5 13.5 13.5.1 13.5.2 13.6 14 14.1 14.2 14.3 14.3 14.4.1 14.4.2 14.5 14.5 14.5.1 14.5.2	Cross-track signal	. 29 . 29 . 29 . 30 . 30 . 30 . 32 . 33 . 33 . 33 . 35 . 36 . 36 . 38 . 38
13.3.3 13.4 13.4.1 13.4.2 13.4.3 13.5 13.5.1 13.5.2 13.6 14 14.1 14.2 14.3 14.3 14.3.1 14.4.1 14.4.1 14.4.2 14.5.1 14.5.2 14.5.3	Cross-track signal	. 29 . 29 . 29 . 30 . 30 . 30 . 30 . 33 . 33 . 33 . 35 . 36 . 36 . 38 . 38 . 38
13.3.3 13.4 13.4.1 13.4.2 13.4.3 13.5 13.5.1 13.5.2 13.6 14 14.1 14.2 14.3 14.3.1 14.4.1 14.4.1 14.4.2 14.5 14.5.1 14.5.2 14.5.3	Cross-track signals Quality of signals Jitter Random errors Defects Servo signals Differential phase tracking error signal Tangential push-pull signal Groove wobble signal Operational signals for the unrecorded disk Measurement conditions Recording conditions Write strategy for media testing Definition of the write pulse Servo signals Radial push-pull tracking error signal Defects Addressing signals Land Pre-Pit signal Groove wobble signal Relation in phase between wobble and Land Pre-Pit General Data Frames	. 29 . 29 . 29 . 30 . 30 . 30 . 30 . 33 . 33 . 33 . 34 . 35 . 36 . 38 . 38 . 38 . 38 . 38 . 38 . 38 . 38
13.3.3 13.4 13.4.1 13.4.2 13.4.3 13.5 13.5.1 13.5.2 13.6 14 14.1 14.2 14.3 14.3.1 14.4.1 14.4.2 14.5 14.5.1 14.5.3 15 16 16 16	Cross-track signals Quality of signals Jitter Random errors Defects Servo signals Differential phase tracking error signal Tangential push-pull signal Groove wobble signal Operational signals for the unrecorded disk Measurement conditions Recording conditions Write strategy for media testing Definition of the write pulse Servo signals Radial push-pull tracking error signal Defects Addressing signals Land Pre-Pit signal Groove wobble signal Relation in phase between wobble and Land Pre-Pit General Data Frames Identification Data (ID)	. 29 . 29 . 30 . 30 . 30 . 32 . 33 . 33 . 33 . 35 . 36 . 36 . 38 . 38 . 38 . 38 . 38 . 38 . 38 . 38
13.3.3 13.4 13.4.1 13.4.2 13.4.3 13.5 13.5.1 13.5.2 13.6 14 14.1 14.2 14.3 14.3.1 14.4.1 14.4.2 14.5 14.5.1 14.5.2 14.5.3 15	Cross-track signals Quality of signals Jitter Random errors Defects Servo signals Differential phase tracking error signal Tangential push-pull signal. Groove wobble signal Operational signals for the unrecorded disk Measurement conditions Recording conditions Write strategy for media testing Definition of the write pulse Servo signals Radial push-pull tracking error signal Defects Addressing signals Land Pre-Pit signal Groove wobble signal Relation in phase between wobble and Land Pre-Pit General Data Frames Identification Data (ID) ID Error Detection Code	. 29 . 29 . 29 . 30 . 30 . 30 . 32 . 33 . 33 . 33 . 35 . 36 . 36 . 36 . 38 . 38 . 38 . 39 . 39 . 30 . 30 . 30 . 30 . 30 . 30 . 30 . 30
13.3.3 13.4 13.4.1 13.4.2 13.4.3 13.5 13.5.1 13.5.2 13.6 14 14.1 14.2 14.3 14.3.1 14.4.1 14.4.2 14.5 14.5.1 14.5.3 15 16 16 16	Cross-track signals Quality of signals Jitter Random errors Defects Servo signals Differential phase tracking error signal Tangential push-pull signal Groove wobble signal Operational signals for the unrecorded disk Measurement conditions Recording conditions Write strategy for media testing Definition of the write pulse Servo signals Radial push-pull tracking error signal Defects Addressing signals Land Pre-Pit signal Groove wobble signal Relation in phase between wobble and Land Pre-Pit General Data Frames Identification Data (ID)	. 29 . 29 . 29 . 30 . 30 . 30 . 32 . 33 . 33 . 34 . 35 . 36 . 36 . 36 . 38 . 38 . 39 . 40 . 41 . 41

17	Scrambled Frames	42
18	ECC Block configuration	43
19	Recording Frames	44
20	Modulation	45
21	Physical Sectors	46
22	Suppress control of the d.c. component	47
23	Linking scheme	
23.1	Structure of linking	
23.2	2K-Link and 32K-Link	
23.3	Lossless-Link	_
24	General description of the Information Zone	
24.1 24.2	Layout of the Information Zone	
25 25.1	Lead-in Zone, Middle Zone and Lead-out Zone	
25.1 25.1.1	Lead-in ZoneInitial Zone	
25.1.1 25.1.2	Buffer Zone 0	
25.1.3	R-Physical Format Information Zone	
25.1.4	Reference Code Zone	
25.1.5 25.1.6	Buffer Zone 1	
25.1.6 25.1.7	Control Data Zone Extra Border Zone A. S.T. A. N.D. A.R.D. P.R.E. V. I.E. V.	58 73
25.1. <i>1</i> 25.2	Middle Zone	74
25.3	Lead-out Zone (standards itch ai)	. 74
25.3.1	Structure of Lead-out Zone with Format4 RMD	
25.3.2	Superficial Extra Border Zone	75
26	General description of the Unrecorded Zone st/b58a5112-6481-4e8f-b0ea	75
26.1	Layout of the Unrecorded Zone 5c34d3/iso-ico-12862-2009	
26.2 26.3	ECC Block address	
27 27.1	Pre-pit Data format	
27.1 27.2	Pre-pit block structure	
27.3	Pre-pit data block configuration	
27.3.1	Relative address	
27.3.2	ECC Block address data configuration	
27.3.3 27.3.4	Parity A and Parity B	
27.3. 4 27.3.5	Field ID1	
27.3.6	Field ID2	86
27.3.7	Field ID3 and Field ID4	
27.3.8	Field ID5	
28	Data structure of R-Information Zone and ODTA	
28.1	Layout of Disk Testing Area and Recording Management Area	
28.2 28.3	Structure of the Disk Testing Area Data configuration of the Recording Management Area (RMA)	
28.3.1	Sector format of the Recording Management Area	
28.3.2	Recording Management Data (Format1 RMD and Format4 RMD)	
Annex	A (normative) Measurement of the angular deviation α	127
Annex	B (normative) Measurement of birefringence	129
Annex	C (normative) Measurement of the differential phase tracking error	132
Annex	D (normative) Measurement of light reflectance	136
	- · · · · · · · · · · · · · · · · · · ·	

ISO/IEC 12862:2009(E)

Annex E (normative) Tapered cone for disk clamping	138
Annex F (normative) Measurement of jitter	139
Annex G (normative) 8-to-16 Modulation with RLL (2,10) requirements	142
Annex H (normative) Optimum Power Control	152
Annex I (normative) Measurement of the groove wobble amplitude	154
Annex J (normative) Measurement methods for the operational signals for an unrecorded disk	156
Annex K (normative) NBCA Code	157
Annex L (normative) Border Zone	163
Annex M (normative) Measurement method of the Land Pre-Pit signal	176
Annex N (normative) Construction of Information Zone	177
Annex O (normative) Recording order	179
Annex P (normative) Clearance in the number of sectors	180
Annex Q (normative) Anchor Point Re-mapping	182
Annex R (informative) Measurement method of the Space layer thickness in a disk	184
Annex S (informative) Transportation	185

iTeh STANDARD PREVIEW (standards.iteh.ai)

ISO/IEC 12862:2009 https://standards.iteh.ai/catalog/standards/sist/b58a5113-6481-4c8f-b9ca-df4b3e5c34d3/iso-iec-12862-2009

Foreword

ISO (the International Organization for Standardization) and IEC (the International Electrotechnical Commission) form the specialized system for worldwide standardization. National bodies that are members of ISO or IEC participate in the development of International Standards through technical committees established by the respective organization to deal with particular fields of technical activity. ISO and IEC technical committees collaborate in fields of mutual interest. Other international organizations, governmental and non-governmental, in liaison with ISO and IEC, also take part in the work. In the field of information technology, ISO and IEC have established a joint technical committee, ISO/IEC JTC 1.

International Standards are drafted in accordance with the rules given in the ISO/IEC Directives, Part 2.

The main task of the joint technical committee is to prepare International Standards. Draft International Standards adopted by the joint technical committee are circulated to national bodies for voting. Publication as an International Standard requires approval by at least 75 % of the national bodies casting a vote.

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. ISO and IEC shall not be held responsible for identifying any or all such patent rights.

ISO/IEC 12862 was prepared by Ecma International (as ECMA-382) and was adopted, under a special "fast-track procedure", by Joint Technical Committee ISO/IEC UTC 1. *Information technology*, in parallel with its approval by national bodies of ISO and IEC.

(standards.iteh.ai)

ISO/IEC 12862:2009 https://standards.iteh.ai/catalog/standards/sist/b58a5113-6481-4c8f-b9ca-df4b3e5c34d3/iso-iec-12862-2009

Introduction

Ecma Technical Committee TC31 was established in 1984 for the standardization of optical disks and optical disk cartridges (ODC). Since its establishment, the committee has made major contributions to ISO/IEC JTC 1/SC 23 toward the development of International Standards for optical disks. Numerous standards have been developed by TC31 and published by Ecma, almost all of which have also been adopted by ISO/IEC under the fast-track procedure as International Standards. The following International Standards for 120 mm and 80 mm DVD have been published by Ecma and adopted by ISO/IEC JTC 1. They are based on original specifications from The DVD Forum.

ISO/IEC 16448, Information technology — 120 mm DVD — Read-only disk

ISO/IEC 16449, Information technology — 80 mm DVD — Read-only disk

ISO/IEC 16824, Information technology — 120 mm DVD rewritable disk (DVD-RAM)

ISO/IEC 16825, Information technology — Case for 120 mm DVD-RAM disks

ISO/IEC 17342, Information technology — 80 mm (1,46 Gbytes per side) and 120 mm (4,70 Gbytes per side) DVD re-recordable disk (DVD-RW)

ISO/IEC 17594, Information technology — Cases for 120 mm and 80 mm DVD-RAM disks

ISO/IEC 20563, Information technology — 80 mm (1,23 Gbytes per side) and 120 mm (3,95 Gbytes per side) DVD-recordable disk (DVD-R) ISO/IEC 12862:2009 https://standards.iteh.ai/catalog/standards/sist/b58a5113-6481-4c8f-b9ca-

ISO/IEC 23912, Information technology — 80 mm5(1,46 Gbytes per side) and 120 mm (4,70 Gbytes per side) DVD Recordable Disk (DVD-R)

In April 2007, nine members proposed that TC31 develop a standard for 120 mm and 80 mm dual layer DVD Recordable optical disks using organic dye recording technology. TC31 adopted this project, which has resulted in this International Standard.

This International Standard specifies two Types of dual layer recordable optical disks: one (Type 1S) making use of recording on only a single side of the disk and yielding a nominal capacity of 8,54 Gbytes for a 120 mm disk and 2,66 Gbytes for an 80 mm disk, the other (Type 2S) making use of recording on both sides of the disk and yielding a nominal capacity of 17,08 Gbytes for a 120 mm disk and 5,32 Gbytes for an 80 mm disk.

Information technology — 120 mm (8,54 Gbytes per side) and 80 mm (2,66 Gbytes per side) DVD recordable disk for dual layer (DVD-R for DL)

1 Scope

This International Standard specifies the mechanical, physical and optical characteristics of a 120 mm and an 80 mm dual layer DVD recordable disk to enable the interchange of such disks. It specifies the quality of the pre-recorded, unrecorded and the recorded signals, the format of the data, the format of the information zone, the format of the unrecorded zone and the recording method, thereby allowing for information interchange by means of such disks. This disk is identified as a DVD recordable disk for dual layer (DVD-R for DL).

This International Standard specifies the following:

- 120 mm and 80 mm nominal diameter disks that may be either single or double sided;
- the conditions for conformance; TANDARD PREVIEW
- the environments in which the disk is to be operated and stored;
- the mechanical and physical characteristics of the disky so as to provide mechanical interchange between data processing systems ards.iteh.ai/catalog/standards/sist/b58a5113-6481-4c8f-b9cadf4b3e5c34d3/iso-iec-12862-2009
- the format of the pre-recorded information on an unrecorded disk, including the physical disposition of the tracks and sectors, the error correcting codes and the coding method used;
- the format of the data and the recorded information on the disk, including the physical disposition of the tracks and sectors, the error correcting codes and the coding method used;
- the characteristics of the signals from pre-recorded and unrecorded areas on the disk, enabling data processing systems to read the pre-recorded information and to write to the disks;
- the characteristics of the signals recorded on the disk, enabling data processing systems to read the data from the disk.

This International Standard provides for interchange of disks between disk drives. Together with a standard for volume and file structure, it provides for full data interchange between data processing systems.

2 Conformance

2.1 Optical disk

A claim of conformance specifies the type of the disk, i.e. its size and whether it is single-sided or double sided. An optical disk is in conformance with this International Standard if it meets the mandatory requirements specified for this type.

2.2 Generating system

A generating system is in conformance with this International Standard if the optical disk it generates is in accordance with 2.1.

2.3 Receiving system

A receiving system is in conformance with this International Standard if it is able to handle an optical disk according to 2.1.

3 Normative references

The following referenced documents are indispensable for the application of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

ISO/IEC 8859-1, Information technology — 8-bit single-byte coded graphic character sets — Part 1: Latin alphabet No. 1

ISO/IEC 8859-2, Information technology — 8-bit single-byte coded graphic character sets — Part 2: Latin alphabet No. 2

ISO/IEC 8859-3, Information technology — 8-bit single-byte coded graphic character sets — Part 3: Latin alphabet No. 3

Teh STANDARD PREVIEW

ISO/IEC 8859-4, Information technology 8-bit single-byte coded graphic character sets — Part 4: Latin alphabet No. 4

ECMA-287, Safety of electronic equipment (2002) ISO/IEC 12862:2009
https://standards.iteh.a/catalog/standards/sist/b58a5113-6481-4c8f-b9cadf4b3e5c34d3/iso-iec-12862-2009

4 Terms and definitions

For the purposes of this document, the following terms and definitions apply.

4.1

anchor point

physical sector number corresponding to the specific logical sector number such as 16, 256, N-256 and N, where N is the maximum last recorded address in logical volume space

NOTE The information in those sector numbers is used to fix Volume and File structure.

4.2

basic recording speed

recording speed at which a disk is under an obligation to be recorded

NOTE A Basic recording speed is mandatory for each Class.

4.3

block SYNC guard area

recorded area in the first ECC block of the contiguous area of which recording is started from the unrecorded area by using 32K-Link

4.4

border zone

linking region that prevents the pick-up head from over running on an unrecorded area when a disk is played back in a partially recorded state

channel bit

elements by which, after modulation, the binary values ZERO and ONE are represented on the disk by marks

4.6

clamping zone

annular part of the disk within which a clamping force is applied by a clamping device

4.7

class

integer number, including 0, that indicates Basic recording speed supported by a disk

NOTE A group of recording speeds in a disk must contain at least one Basic recording speed which is mandatory for recording device and disk.

4.8

data zone

zone between the Lead-in Zone and the Middle Zone on Layer 0 and zone between the Middle Zone and the Lead-out Zone on Layer 1, in which user data is recorded

NOTE In Border recording mode, Border Zone is included in Data Zone.

4.9

data recordable zone

zone that is available to record user data

iTeh STANDARD PREVIEW

4.10

Digital Sum Value

DSV

(standards.iteh.ai)

arithmetic sum obtained from a bit stream by allocating the decimal value 1 to bits set to ONE and the decimal value –1 to bits set to Zero

ISO/IEC 12862:2009

https://standards.iteh.ai/catalog/standards/sist/b58a5113-6481-4c8f-b9ca-

4.11 df4b3e5c34d3/iso-iec-12862-2009

disk at once recording

recording mode in which the Lead-in Zone, the user data and the Lead-out Zone are recorded sequentially

4.12

disk reference plane

plane defined by the perfectly flat annular surface of an ideal spindle onto which the Clamping Zone of the disk is clamped, and which is normal to the axis of rotation

4.13

Disk Testing Area

DTA

area used for Optimum Power Control

- NOTE 1 There are two kinds of the Disk Testing Area on a disk. Inner Disk Testing Area (IDTA) is located in the R-Information Zone and situated adjacent to the inside of the Recording Management Area. Outer Disk Testing Area (ODTA) is fixed and situated adjacent to the outside of the fixed Middle Zone.
- NOTE 2 The optional IDTA can be located on Layer 1 facing the special allocation in the Initial zone on Layer 0 as an option for devices, when NBCA is not applied on a disk.
- NOTE 3 The ODTA can be added when shifted Middle Zone exists as an option for devices. In this case, added ODTA is called flexible Outer Disk Testing Area (flexible ODTA) and that is situated adjacent to the outside of the shifted Middle Zone on Layer 0 and Layer 1 respectively.

ECC Block address

absolute physical address used to define the recording position on the land of each area

NOTE 1 This address is pre-recorded as Land Pre-Pits and equal to the bit-inverted numbers from b23 to b4 of the Physical sector number recorded in the groove. Serially decremented numbers are assigned to blocks from the inner radius to the outer radius on Layer 0 and from the outer radius to the inner radius on Layer 1. The first ECC Block address in the Data Recordable Zone on Layer 0 is (FF CFFF). The bit-inverted number is calculated so that the bit value of one becomes that of zero and vice versa.

NOTE 2 The "ECC Block address" definition is specific to this Standard.

4.15

Error Correction Code

ECC

mathematical computation yielding check bytes used for the detection and correction of errors in data

4.16

Error Detection Code

EDC

code designed to detect certain kinds of errors in data

NOTE Error Detection Code consists of data and the error detection parity.

4.17

finalization

action for changing into the state where the Lead-in, the Lead-out and the Middle Zones are recorded

NOTE 1 After Finalization, the information Zone from the Lead-in Zone to the Middle Zone on Layer 0 and from the Middle Zone to the Lead-out Zone on Layer 1 shall be recorded without any unrecorded areas.

NOTE 2 The disk will become write protected once finalized dards/sist/b58a5113-6481-4c8f-b9ca-

df4b3e5c34d3/iso-iec-12862-2009

4.18

groove

wobbled guidance track

4.19

incremental recording

recording mode in which the disk is recorded in several distinct recording operations (for example at different times and using different recording drives)

NOTE In this recording mode, the specified linking scheme shall be used.

4.20

information zone

zone comprising the Lead-in Zone, the Data Zone, the Middle Zone and the Lead-out Zone

4.21

initial information zone

zone comprising the Lead-in Zone, the Data Recordable Zone, the fixed Middle Zone and the Lead-out Zone

4.22

land

area between the grooves

4.23

Land Pre-Pit

I PP

pits embossed on the land during the manufacture of the disk substrate, which contain address information

lead-in zone

zone comprising Physical sectors adjacent to the inside of the Data Zone on Layer 0

4 25

lead-out zone

zone comprising Physical sectors adjacent to the inside of the Data Zone on Layer 1

NOTE When the recording of user data is finished on Layer 0, the Lead-out Zone is located adjacent to the inside of the Middle Zone on Layer 1.

4.26

middle zone

zone comprising physical sectors adjacent to the outside of the Data Zone on Layer 0 and Layer 1 respectively

NOTE 1 The fixed Middle Zone is located outside of Data Recordable Zone of a disk.

NOTE 2 The shifted Middle Zone can be added at the inner radius than the fixed Middle Zone as an option for devices, depending on the size of the Data Zone and located outside of the Data Zone.

4.27

Recording Management Area

RMA

area containing the Recording Management Data (RMD), situated adjacent to the inside of the Lead-in Zone on Layer 0 and the Lead-out Zone on Layer 1 respectively

iTeh STANDARD PREVIEW

Recording Management Data

(standards.iteh.ai)

information about the recording on the disk, including information on each recording mode

NOTE Two kinds not RMD dormat have specified a Format 1.5 RMD contains the information related to Incremental recording mode and Disk at once recording mode. Format 4. RMD contains the information related to Incremental recording mode including Layer jump recording mode.

4.29

r-information zone

zone comprising the Inner Disk Testing Area (IDTA) and the Recording Management Area (RMA)

4.30

re-mapping

replacement mechanism for physical layer to replace original Anchor point with renewed Anchor point

4.31

rzone

ECC blocks that are continuous on a layer and assigned to user data on Layer 0 and/or Layer 1 during Incremental recording mode

4.32

sector

smallest addressable part of a track in the information zone of a disk that can be accessed independently of other addressable parts

4.33

substrate

transparent layer of the disk, provided for mechanical support of the recording or recorded layer, through which the optical beam accesses the recordable/recorded layer

4.34

track

360° turn of a continuous spiral of recorded marks or groove

track pitch

distance between adjacent average physical track centrelines of the wobbled grooves for the unrecorded disk, or between adjacent physical track centrelines of the successive recorded marks for the recorded disk, measured in the radial direction

4.36

zone

annular area of the disk

5 Conventions and notations

5.1 Representation of numbers

A measured value is rounded off to the least significant digit of the corresponding specified value. For instance, it implies that a specified value of 1,26 with a positive tolerance of + 0,01 and a negative tolerance of - 0,02 allows a range of measured values from 1,235 to 1,275.

Numbers in decimal notations are represented by the digits 0 to 9.

Numbers in hexadecimal notation are represented by the hexadecimal digits 0 to 9 and A to F in parentheses.

The setting of bits is denoted by ZERO and ONE.

Numbers in binary notations and bit patterns are represented by strings of digits 0 and 1, with the most significant bit shown to the left.

Negative values of numbers in binary notation are given as Two's complement.

In each field the data is recorded so that the most significant byte (MSB), identified as Byte 0, is recorded first and the least significant byte (LSB) last sine a field of 8 mbits; bit b (8 m 5) shall be the most significant bit (msb) and bit b₀ the least significant bit (lsb). Bit b (8 m 5) is recorded first 2862-2009

5.2 Names

The names of entities, e.g. specific tracks, fields, areas, zones, etc. are given a capital initial.

6 Abbreviated terms

AP	Amplitude of the land Pre-Pit signal (without wobble amplitude)
AF	Amplitude of the land Fre-Fit signal (without wobble amplitude)

AR Aperture Ratio (of the Land Pre-Pit after recording)

BP Byte Position

BPF Band Pass Filter

CLV Constant Linear Velocity

CNR Carrier to Noise Ratio

DCC DC Component suppress control

DSV Digital Sum Value

ECC Error Correction Code

EDC Error Detection Code

HF High Frequency

ID Identification Data

LA Lead-out Attribute

IDTA Inner Disk Testing Area

IED ID Error Detection (code)

LPF Low-Pass Filter

LPP Land Pre-Pit

LSB Least Significant Byte

lsb least significant bit

MSB Most Significant Byte

msb most significant bit

NBCA Narrow Burst Cutting Area

NRZI Non Return to Zero Inverted TI ANDARD PREVIEW

ODTA Outer Disk Testing Area (standards.iteh.ai)

OPC Optimum Power Control

ISO/IEC 12862:2009

OTP Opposite Track: Path ds. itch. ai/catalog/standards/sist/b58a5113-6481-4c8f-b9ca-

df4b3e5c34d3/iso-iec-12862-2009

PBS Polarizing Beam Splitter

PI Parity (of the) Inner (code)

PLL Phase Locked Loop

PO Parity (of the) Outer (code)

PSN Physical Sector Number

PTP Parallel Track Path

PUH Pick-Up Head

RBP Relative Byte Position

RBW Resolution Bandwidth

RESYNC Re-Synchronization

RMA Recording Management Area

RMD Recording Management Data

RS Reed-Solomon (code)

SYNC Synchronization