



**SLOVENSKI STANDARD**  
**oSIST prEN 303 348 V1.2.0:2021**  
**01-maj-2021**

---

**Gonilniki za avdiofrekvenčne indukcijske zanke do 45 A v frekvenčnem območju od 10 Hz do 9 kHz - Harmonizirani standard za dostop do radijskega spektra**

Audio frequency induction loop drivers up to 45 A in the frequency range 10 Hz to 9 kHz - Harmonised Standard for access to radio spectrum

**iTeh STANDARD PREVIEW**  
**(standards.iteh.ai)**

**Ta slovenski standard je istoveten z: ETSI EN 303 348 V1.2.0 (2021-02)**

oSIST prEN 303 348 V1.2.0:2021  
<https://standards.iteh.ai/catalog/standards/sist/8d13ba9b-6dbc-41d6-919a-4ca569c43f4e/osist-pren-303-348-v1-2-0-2021>

**ICS:**

11.180.15	Pripomočki za gluhe osebe in osebe z okvaro sluha	Aids for deaf and hearing impaired people
33.160.50	Pribor	Accessories

**oSIST prEN 303 348 V1.2.0:2021**                      **en**

**iTeh STANDARD PREVIEW**  
**(standards.iteh.ai)**

[oSIST prEN 303 348 V1.2.0:2021](https://standards.iteh.ai/catalog/standards/sist/8d13ba9b-6dbc-41d6-919a-4ca569c43f4e/osist-pren-303-348-v1-2-0-2021)

<https://standards.iteh.ai/catalog/standards/sist/8d13ba9b-6dbc-41d6-919a-4ca569c43f4e/osist-pren-303-348-v1-2-0-2021>

# Draft ETSI EN 303 348 V1.2.0 (2021-02)



## **Audio frequency induction loop drivers up to 45 A in the frequency range 10 Hz to 9 kHz; Harmonised Standard for access to radio spectrum**

[oSIST prEN 303 348 V1.2.0:2021](https://standards.iteh.ai/catalog/standards/sist/8d13ba9b-6dbc-41d6-919a-4ca569c43f4e/osist-pren-303-348-v1-2-0-2021)

<https://standards.iteh.ai/catalog/standards/sist/8d13ba9b-6dbc-41d6-919a-4ca569c43f4e/osist-pren-303-348-v1-2-0-2021>

---

**Reference**

REN/ERM-TG17-161

---

**Keywords**cochlear implant, harmonised standard,  
hearing aid, inductive**ETSI**650 Route des Lucioles  
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - NAF 742 C  
Association à but non lucratif enregistrée à la  
Sous-Préfecture de Grasse (06) N° 7803/88

**iTeh STANDARD PREVIEW**  
**(standards.iteh.ai)**

---

**Important notice**

<https://standards.iteh.ai/catalog/standards/sist/8d13ba9b-6dbc-41d6-919a-4ca31994314c/osist-pr-en-303-348-v1-2-0-2021>  
The present document can be downloaded from:  
<http://www.etsi.org/standards-search>

The present document may be made available in electronic versions and/or in print. The content of any electronic and/or print versions of the present document shall not be modified without the prior written authorization of ETSI. In case of any existing or perceived difference in contents between such versions and/or in print, the prevailing version of an ETSI deliverable is the one made publicly available in PDF format at [www.etsi.org/deliver](http://www.etsi.org/deliver).

Users of the present document should be aware that the document may be subject to revision or change of status. Information on the current status of this and other ETSI documents is available at <https://portal.etsi.org/TB/ETSIDeliverableStatus.aspx>

If you find errors in the present document, please send your comment to one of the following services:  
<https://portal.etsi.org/People/CommiteeSupportStaff.aspx>

---

**Copyright Notification**

No part may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm except as authorized by written permission of ETSI.

The content of the PDF version shall not be modified without the written authorization of ETSI.

The copyright and the foregoing restriction extend to reproduction in all media.

© ETSI 2021.  
All rights reserved.

**DECT™**, **PLUGTESTS™**, **UMTS™** and the ETSI logo are trademarks of ETSI registered for the benefit of its Members.  
**3GPP™** and **LTE™** are trademarks of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners.

**oneM2M™** logo is a trademark of ETSI registered for the benefit of its Members and of the oneM2M Partners.

**GSM®** and the GSM logo are trademarks registered and owned by the GSM Association.

# Contents

Intellectual Property Rights .....	5
Foreword.....	5
Modal verbs terminology.....	5
Introduction .....	6
1 Scope .....	7
2 References .....	7
2.1 Normative references .....	7
2.2 Informative references.....	7
3 Definition of terms, symbols and abbreviations.....	8
3.1 Terms.....	8
3.2 Symbols.....	9
3.3 Abbreviations .....	10
4 Technical requirements specifications .....	10
4.1 Environmental conditions.....	10
4.1.1 Environmental profile .....	10
4.2 General requirements .....	10
4.2.1 Presentation of induction loop driver equipment for testing purposes.....	10
4.2.2 Choice of model for testing .....	11
4.2.3 Controls .....	11
4.2.4 Driver shut-off facility .....	11
4.2.5 No input signal, no output signal.....	11
4.2.6 Information from the manufacturer.....	11
4.2.7 Test jig .....	11
5 Testing for compliance with technical requirements.....	11
5.1 Environmental conditions for testing.....	11
5.1.1 General requirements.....	11
5.1.2 Normal temperature and humidity.....	12
5.1.3 Test power source .....	12
5.1.3.1 General requirements .....	12
5.1.3.2 External test power source .....	12
5.1.3.2.0 General .....	12
5.1.3.2.1 Mains voltage .....	12
5.1.3.2.2 Other power sources .....	12
5.2 General conditions.....	13
5.2.1 Normal test signals.....	13
5.2.1.0 General.....	13
5.2.1.1 Signal input for testing.....	13
5.2.2 Loop connections.....	13
5.2.2.1 General.....	13
5.2.2.2 Artificial Loop.....	13
5.3 Induction loop driver .....	14
5.3.1 General.....	14
5.3.2 In band and out of band emission limits .....	14
5.3.2.1 Definition .....	14
5.3.2.2 Methods of measurement .....	14
5.3.2.3 Values .....	14
5.3.3 Spurious domain emission limits .....	14
5.3.3.1 Definition .....	14
5.3.3.2 Methods of measurement .....	15
5.3.3.3 Values .....	15
5.4 Interpretation of the measurement results .....	15

<b>Annex A (informative):</b>	<b>Relationship between the present document and the essential requirements of Directive 2014/53/EU .....</b>	<b>16</b>
<b>Annex B (informative):</b>	<b>Technical overview .....</b>	<b>17</b>
B.1	Induction loop drivers .....	17
B.1.1	General .....	17
B.1.2	Frequency response .....	17
B.1.3	Field strength.....	17
B.1.4	General performance criteria.....	17
B.2	Translation of H-Field values to loop current values .....	17
<b>Annex C (informative):</b>	<b>The relationship between loop current and H-Field strength.....</b>	<b>19</b>
<b>Annex D (informative):</b>	<b>How to construct a test fixture incorporating an artificial loop .....</b>	<b>21</b>
<b>Annex E (normative):</b>	<b>Induction loop driver emission levels and spectrum mask measurements.....</b>	<b>23</b>
<b>Annex F (informative):</b>	<b>Maximum Measurement Uncertainty.....</b>	<b>24</b>
<b>Annex G (informative):</b>	<b>Bibliography.....</b>	<b>25</b>
<b>Annex H (informative):</b>	<b>Change history .....</b>	<b>26</b>
History .....		27

## iTeh STANDARD PREVIEW (standards.iteh.ai)

[oSIST prEN 303 348 V1.2.0:2021](https://standards.iteh.ai/catalog/standards/sist/8d13ba9b-6dbc-41d6-919a-4ca569c43f4e/osist-pren-303-348-v1-2-0-2021)

<https://standards.iteh.ai/catalog/standards/sist/8d13ba9b-6dbc-41d6-919a-4ca569c43f4e/osist-pren-303-348-v1-2-0-2021>

---

## Intellectual Property Rights

### Essential patents

IPRs essential or potentially essential to normative deliverables may have been declared to ETSI. The information pertaining to these essential IPRs, if any, is publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: "*Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards*", which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (<https://ipr.etsi.org/>).

Pursuant to the ETSI IPR Policy, no investigation, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

### Trademarks

The present document may include trademarks and/or tradenames which are asserted and/or registered by their owners. ETSI claims no ownership of these except for any which are indicated as being the property of ETSI, and conveys no right to use or reproduce any trademark and/or tradename. Mention of those trademarks in the present document does not constitute an endorsement by ETSI of products, services or organizations associated with those trademarks.

---

## Foreword

This draft Harmonised European Standard (EN) has been produced by ETSI Technical Committee Electromagnetic compatibility and Radio spectrum Matters (ERM), and is now submitted for the combined Public Enquiry and Vote phase of the ETSI standards EN Approval Procedure.

The present document has been prepared under the Commission's standardisation request C(2015) 5376 final [i.8] to provide one voluntary means of conforming to the essential requirements of Directive 2014/53/EU on the harmonisation of the laws of the Member States relating to the making available on the market of radio equipment and repealing Directive 1999/5/EC [i.1].

Once the present document is cited in the Official Journal of the European Union under that Directive, compliance with the normative clauses of the present document given in table A.1 confers, within the limits of the scope of the present document, a presumption of conformity with the corresponding essential requirements of that Directive, and associated EFTA regulations.

Proposed national transposition dates	
Date of latest announcement of this EN (doa):	3 months after ETSI publication
Date of latest publication of new National Standard or endorsement of this EN (dop/e):	6 months after doa
Date of withdrawal of any conflicting National Standard (dow):	18 months after doa

---

## Modal verbs terminology

In the present document "**shall**", "**shall not**", "**should**", "**should not**", "**may**", "**need not**", "**will**", "**will not**", "**can**" and "**cannot**" are to be interpreted as described in clause 3.2 of the [ETSI Drafting Rules](#) (Verbal forms for the expression of provisions).

"**must**" and "**must not**" are **NOT** allowed in ETSI deliverables except when used in direct citation.

---

## Introduction

Audio Frequency Induction Loop System (AFILS) has been on the market since the middle of the twentieth century, with the first recognizable patents appearing circa 1938. AFILS are primarily used to facilitate improved communication to people with impaired hearing and are an important tool in the reduction of discrimination against disabled people. They are also used in a number of industries including Broadcast and studio.

The present document covers the "drivers" for the loop antenna and represents the performance of equipment which is currently on the market, which has not previously been subjected to compliance to a "radio" directive.

AFILS are installed in places of worship, places of entertainment, places of education, ticket booths and service counters, etc. as well as in domestic situations, providing huge benefits to users with impaired hearing.

AFILS provide an audio frequency magnetic field that couples with a receiving coil (telecoil) fitted in hearing aids, cochlear implants, loop listeners and testing devices. This magnetic field is generated in a wire loop that is fed by an audio frequency driver which is capable of driving current through the "induction loop" which, in turn, is fed from external signals such as those generated by microphones, audio-visual equipment and musical instruments.

AFILS operate below 9 kHz and have a very limited range (some few metres) and there is no known evidence of interference with radio equipment.

AFILS are provided in a range of sizes and can cover areas up to approximately 3 000 m<sup>2</sup>. They are also used in vehicles and lifts and interaction with structural metal means that a complete AFILS can only be tested when fitted in their final location. This means that the "Loop" is as an external antenna which is not covered by the Radio Equipment Directive [i.1] and the present document only covers "Drivers".

The market for AFILS is relatively small compared with technologies such as RFID, and is physically separated from most radio systems, so the opportunity for mutual-interference problems is reduced compared to other users of the spectrum in this frequency range.

As AFILS drivers use base band audio signals without additional carrier tones, and so when no input signal is present, there will be no output signal and so no magnetic field will be generated, ensuring spectrum efficiency.

The present document has been developed in response to Directive 2014/53/EU [i.1] and is the first radio standard that has been produced for AFILS equipment and has been prepared to allow the assessment of audio frequency induction loop drivers and receivers for compliance with Directive 2014/53/EU [i.1].

---

# 1 Scope

The present document specifies technical characteristics and methods of measurements for audio frequency induction loop drivers operating from 10 Hz to 9 kHz used in Audio Frequency Induction Loop System (AFILS) with an upper limit of 45 A<sub>rms</sub>.

NOTE 1: The object of an AFILS is to transmit an audio signal to people with hearing difficulties. The receiver in this case is normally a hearing aid or cochlear implant with a built in telecoil, both of which are covered by ETSI EN 300 422-4 [i.11].

These radio equipment types are capable of operating in the frequency band within the 10 Hz to 9 kHz range:

- with (an) output connection(s);
- for audio frequency baseband transmission (un-modulated and without the use of a carrier).

The present document covers induction loop drivers with output connectors. Integral antenna systems are covered by ETSI EN 300 422-4 [i.11].

NOTE 2: The relationship between the present document and essential requirements of article 3.2 of Directive 2014/53/EU [i.1] is given in annex A.

---

# 2 References

## 2.1 Normative references

References are either specific (identified by date of publication and/or edition number or version number) or non-specific. For specific references, only the cited version applies. For non-specific references, the latest version of the referenced document (including any amendments) applies.

Referenced documents which are not found to be publicly available in the expected location might be found at <https://docbox.etsi.org/Reference/>.

NOTE: While any hyperlinks included in this clause were valid at the time of publication, ETSI cannot guarantee their long term validity.

The following referenced document are necessary for the application of the present document.

- |     |   |
|-----|---|
| [1] | Void.   |
| [2] | CEPT/ERC/Recommendation 74-01E (Siófok 98, Nice 99, Sesimbra 02, Hradec Kralove 05, Cardiff 11): "Unwanted Emissions in the Spurious Domain". |

## 2.2 Informative references

References are either specific (identified by date of publication and/or edition number or version number) or non-specific. For specific references, only the cited version applies. For non-specific references, the latest version of the referenced document (including any amendments) applies.

NOTE: While any hyperlinks included in this clause were valid at the time of publication, ETSI cannot guarantee their long term validity.

The following referenced documents are not necessary for the application of the present document but they assist the user with regard to a particular subject area.

- |       |  |
|-------|--|
| [i.1] | Directive 2014/53/EU of the European Parliament and of the Council of 16 April 2014 on the harmonisation of the laws of the Member States relating to the making available on the market of radio equipment and repealing Directive 1999/5/EC. |
| [i.2] | Void.  |

- [i.3] Void.
- [i.4] IEC 60118-4:2014: "Electroacoustics - Hearing aids - Part 4: Induction loop systems for hearing aid purposes - Magnetic field strength".
- [i.5] Void.
- [i.6] Void.
- [i.7] Void.
- [i.8] Commission Implementing Decision C(2015) 5376 final of 4.8.2015 on a standardisation request to the European Committee for Electrotechnical Standardisation and to the European Telecommunications Standards Institute as regards radio equipment in support of Directive 2014/53/EU of the European Parliament and of the Council.
- [i.9] Void.
- [i.10] Void.
- [i.11] ETSI EN 300 422-4: "Wireless Microphones; Audio PMSE up to 3 GHz; Part 4: Assistive Listening Devices including personal sound amplifiers and inductive systems up to 3 GHz; Harmonised Standard covering the essential requirements of article 3.2 of Directive 2014/53/EU".

## 3 Definition of terms, symbols and abbreviations

### 3.1 Terms

iTeh STANDARD PREVIEW  
(standards.iteh.ai)

For the purposes of the present document, the terms given in Directive 2014/53/EU [i.1] and the following apply:

**artificial loop:** load equal to the nominal resistance and impedance of the loop specified by the manufacturer

**audio frequency induction loop driver:** audio amplifier designed to drive audio-frequency current in an inductive loop, thus generating an audio-frequency magnetic field

**Audio Frequency Induction Loop System (AFILS):** system including induction loop driver(s), microphones and/or other signal sources, in which a magnetic field is created by the flow of audio-frequency current in a conductor arranged in the form of a loop or coil

**clipping:** form of waveform distortion that occurs when an induction loop driver is overdriven and attempts to deliver an output voltage or current beyond its maximum capability

**conducted measurements:** measurements that are made using a direct connection to the equipment under test

**hearing aid:** personal amplification system, worn entirely on the listener, which is designed to enable a person with impaired hearing to hear more easily

**hearing instrument:** hearing aid or cochlear implant

**hearing loop system:** non-technical name for AFILS used by the hard-of-hearing community

**in band emissions:** emissions on a frequency or frequencies which are inside the necessary bandwidth (10 Hz to 9 kHz)

**induction loop:** current carrying loop or coil of an AFILS used to create the magnetic field

NOTE: This is equivalent to the term "antenna" used in other ETSI documents and is used in the present document as it is the term commonly understood by the AFILS industry.

**induction loop driver:** audio driver designed to drive an induction loop

NOTE: This is equivalent to the term "transmitter" used in other ETSI documents and is used in the present document as it is the term commonly understood by the AFILS industry.

**induction loop listener:** portable listening device that is designed to give an audible output in response to signals produced by an AFILS

**induction loop monitor receiver:** equipment designed to verify the performance of an AFILS by audio and visual means:

- a) providing visible indication that it is powered and indicating when the strength of the magnetic field produced by the loop falls within a specified range; and
- b) providing an audio-frequency output by which the sound quality of the AFILS transmissions can be assessed

**induction loop system:** See AFILS.

**internal loop:** loop designed as a fixed part of the equipment, without the use of an external connector and as such which cannot be disconnected from the equipment by the user

**loop:** See induction loop.

**loop listener:** See induction loop listener.

**metal compensation:** method of compensating for amplitude and frequency dependant magnetic field losses due to the interaction of the magnetic field generated by the loop with nearby metal

**mobile audio frequency induction loop driver:** equipment normally installed in a vehicle (bus, coach, train, etc.)

**out of band emissions:** emissions on a frequency or frequencies immediately outside the necessary bandwidth (10 Hz to 9 kHz), but excluding spurious emissions

**phased loop array:** system of overlapping loops in which the currents are out of phase with each other used to provide an even field strength and to limit overspill of the magnetic field

**portable audio frequency induction loop driver:** driver intended to be carried or attached

**radiated measurements:** measurements which involve the absolute measurement of a radiated field

**rated load:** load, stated by the manufacturer, to which the driver output is connected for measurement purposes

**reference magnetic field strength level:** 0 dB reference for magnetic field strength levels, which is  $400 \text{ mA m}^{-1}$

**spurious emissions:** emissions on a frequency or frequencies which are outside the necessary bandwidth (10 Hz to 9 kHz) and the level of which may be reduced without affecting the corresponding transmission of information

NOTE: Spurious emissions include harmonic emissions, parasitic emissions, intermodulation products and frequency conversion products, but exclude out-of-band emissions.

**telecoil:** magnetic pickup coil intended to receive signals from an audio frequency induction loop system

NOTE: A telecoil can be part of a hearing aid, cochlear implant, or of any other device for receiving signals from an audio frequency induction loop system in accordance with IEC 60118-4 [i.4].

## 3.2 Symbols

For the purposes of the present document, the following symbols apply:

A	loop area
C	correction factor
E	electrical field strength
f	frequency
$f_C$	centre frequency in Hz
H	magnetic field strength
H <sub>f</sub>	H-field-strength limit
H <sub>C</sub>	H-field strength at the centre of the frequency of interest
H <sub>S</sub>	H-field-strength limit for radiated spurious emissions
I <sub>C</sub>	audio frequency in band output current