



**Publicly Available Specification (PAS);
Intelligent Transport Systems (ITS);
MirrorLink®;
Part 23: Bluetooth® Out-of-Band Pairing Data Service**

CAUTION

The present document has been submitted to ETSI as a PAS produced by CCC and approved by the ETSI Technical Committee Intelligent Transport Systems (ITS).

CCC is owner of the copyright of the document CCC-TS-076 and/or had all relevant rights and had assigned said rights to ETSI on an "as is basis". Consequently, to the fullest extent permitted by law, ETSI disclaims all warranties whether express, implied, statutory or otherwise including but not limited to merchantability, non-infringement of any intellectual property rights of third parties. No warranty is given about the accuracy and the completeness of the content of the present document.

Reference

RTS/ITS-98-23

Keywords

interface, ITS, PAS, smartphone

ETSI

650 Route des Lucioles
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - NAF 742 C
Association à but non lucratif enregistrée à la
Sous-Préfecture de Grasse (06) N° 7803/88

Important notice

The present document can be downloaded from:

<http://www.etsi.org/standards-search>

The present document may be made available in electronic versions and/or in print. The content of any electronic and/or print versions of the present document shall not be modified without the prior written authorization of ETSI. In case of any existing or perceived difference in contents between such versions and/or in print, the prevailing version of an ETSI deliverable is the one made publicly available in PDF format at www.etsi.org/deliver.

Users of the present document should be aware that the document may be subject to revision or change of status.

Information on the current status of this and other ETSI documents is available at

<https://portal.etsi.org/TB/ETSIDeliverableStatus.aspx>

If you find errors in the present document, please send your comment to one of the following services:

<https://portal.etsi.org/People/CommiteeSupportStaff.aspx>

Copyright Notification

No part may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm except as authorized by written permission of ETSI.

The content of the PDF version shall not be modified without the written authorization of ETSI.

The copyright and the foregoing restriction extend to reproduction in all media.

©ETSI 2019.

© Car Connectivity Consortium 2011-2019.

All rights reserved.

ETSI logo is a Trade Mark of ETSI registered for the benefit of its Members.

MirrorLink® is a registered trademark of Car Connectivity Consortium LLC.

RFB® and VNC® are registered trademarks of RealVNC Ltd.

UPnP® is a registered trademark of Open Connectivity Foundation, Inc.

Other names or abbreviations used in the present document may be trademarks of their respective owners.

DECT™, **PLUGTESTS™**, **UMTS™** and the ETSI logo are trademarks of ETSI registered for the benefit of its Members.

3GPP™ and **LTE™** are trademarks of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners.

oneM2M™ logo is a trademark of ETSI registered for the benefit of its Members and of the oneM2M Partners.

GSM® and the GSM logo are trademarks registered and owned by the GSM Association.

Contents

| | |
|--|-----------|
| Intellectual Property Rights | 4 |
| Foreword..... | 4 |
| Modal verbs terminology..... | 4 |
| 1 Scope | 5 |
| 2 References | 5 |
| 2.1 Normative references | 5 |
| 2.2 Informative references..... | 6 |
| 3 Definition of terms, symbols and abbreviations..... | 6 |
| 3.1 Terms..... | 6 |
| 3.2 Symbols..... | 6 |
| 3.3 Abbreviations | 6 |
| 4 Data Service Definition..... | 6 |
| 4.1 Bluetooth Out-of-Band Pairing over MirrorLink Version 1.0..... | 6 |
| 5 SBP Binding..... | 9 |
| 5.1 Service Registry | 9 |
| 6 Theory of Operation | 9 |
| 6.1 General | 9 |
| 6.2 SBP Protocol | 9 |
| 6.2.1 General..... | 9 |
| 6.2.2 Bluetooth Radio Status Monitoring | 10 |
| 6.2.3 Out-of-Band Pairing Configuration..... | 10 |
| 6.2.4 Handover Request & Selection..... | 10 |
| 6.2.5 SSP Commencement..... | 11 |
| 6.2.6 Post-Pairing Connection | 11 |
| 6.2.7 Timeout Considerations..... | 11 |
| Annex A (informative): Authors and Contributors..... | 12 |
| History | 13 |

Intellectual Property Rights

Essential patents

IPRs essential or potentially essential to the present document may have been declared to ETSI. The information pertaining to these essential IPRs, if any, is publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: "*Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards*", which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (<https://ipr.etsi.org/>).

Pursuant to the ETSI IPR Policy, no investigation, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

Trademarks

The present document may include trademarks and/or tradenames which are asserted and/or registered by their owners. ETSI claims no ownership of these except for any which are indicated as being the property of ETSI, and conveys no right to use or reproduce any trademark and/or tradename. Mention of those trademarks in the present document does not constitute an endorsement by ETSI of products, services or organizations associated with those trademarks.

Foreword

This Technical Specification (TS) has been produced by ETSI Technical Committee Intelligent Transport Systems (ITS).

The present document is part 23 of a multi-part deliverable. Full details of the entire series can be found in part 1 [i.1].

Modal verbs terminology

In the present document "**shall**", "**shall not**", "**should**", "**should not**", "**may**", "**need not**", "**will**", "**will not**", "**can**" and "**cannot**" are to be interpreted as described in clause 3.2 of the [ETSI Drafting Rules](#) (Verbal forms for the expression of provisions).

"**must**" and "**must not**" are **NOT** allowed in ETSI deliverables except when used in direct citation.

1 Scope

The present document is part of the MirrorLink® specification which specifies an interface for enabling remote user interaction of a mobile device via another device. The present document is written having a vehicle head-unit to interact with the mobile device in mind, but it will similarly apply for other devices, which provide a colour display, audio input/output and user input mechanisms.

The purpose of the Automatic Bluetooth Pairing feature is to eliminate the complexity of Bluetooth Pairing an IVI with a the MirrorLink connected phone by utilizing the trusted MirrorLink connection as a Bluetooth Out of Band (OOB) pairing transport. Some potential benefits include:

- Single connection (USB or Wi-Fi) user configuration of a complete MirrorLink connection.
- Obfuscation of protocol/transport complexity from the user (USB/Wi-Fi + Bluetooth).
- More security around information used for link key generation due to OOB information exchange.
- Net-neutral cost to enable OOB pairing on head units that already include USB ports.

The MirrorLink Secure Bluetooth Out-of-Band pairing using MirrorLink CDB/SBP is modelled after Bluetooth Out-of-Band pairing using NFC.

2 References

2.1 Normative references

References are either specific (identified by date of publication and/or edition number or version number) or non-specific. For specific references, only the cited version applies. For non-specific references, the latest version of the referenced document (including any amendments) applies.

Referenced documents which are not found to be publicly available in the expected location might be found at <https://docbox.etsi.org/Reference>.

NOTE: While any hyperlinks included in this clause were valid at the time of publication, ETSI cannot guarantee their long-term validity.

The following referenced documents are necessary for the application of the present document.

- [1] NFC Forum, Bluetooth SIG: "Bluetooth Secure Simple Pairing Using NFC", Application Document, NFC Forum™, NFCForum-AD-BTSSP-1.0, 2011-10-18.

NOTE: Available at https://members.nfc-forum.org/resources/AppDocs/NFCForum_AD_BTSSP_1_0.pdf.

- [2] Bluetooth SIG: "Bluetooth Specification version 4.2", December 04, 2014.

NOTE: Available at https://www.bluetooth.org/docman/handlers/downloaddoc.ashx?doc_id=441541.

- [3] ETSI TS 103 544-12 (V1.3.1): "Publicly Available Specification (PAS); Intelligent Transport Systems (ITS); MirrorLink®; Part 12: UPnP Server Device".

- [4] ETSI TS 103 544-10 (V1.3.1): "Publicly Available Specification (PAS); Intelligent Transport Systems (ITS); MirrorLink®; Part 10: UPnP Client Profile Service".

2.2 Informative references

References are either specific (identified by date of publication and/or edition number or version number) or non-specific. For specific references, only the cited version applies. For non-specific references, the latest version of the referenced document (including any amendments) applies.

NOTE: While any hyperlinks included in this clause were valid at the time of publication, ETSI cannot guarantee their long-term validity.

The following referenced documents are not necessary for the application of the present document but they assist the user with regard to a particular subject area.

- [i.1] ETSI TS 103 544-1 (V1.3.1): "Publicly Available Specification (PAS); Intelligent Transport Systems (ITS); MirrorLink®; Part 1: Connectivity".

3 Definition of terms, symbols and abbreviations

3.1 Terms

Void.

3.2 Symbols

Void.

3.3 Abbreviations

For the purposes of the present document, the following abbreviations apply:

| | |
|-----|--------------------------------|
| CDB | Common Data Bus |
| EIR | Extended Inquiry Response |
| IVI | In-Vehicle Infotainment system |
| MAC | Medium Access Control |
| NFC | Near Field Communication |
| OOB | Out of Band |
| SBP | Service Binary Protocol |
| SSP | Secure Simple Pairing |
| USB | Universal Serial Bus |

4 Data Service Definition

4.1 Bluetooth Out-of-Band Pairing over MirrorLink Version 1.0

```
/** The present document defines data objects for the Bluetooth out-of-
 * band pairing using SBP is modelled after the Bluetooth out-of-band
 * pairing using NFC as described in [1]. Objects and data structures
 * are similar to the ones defined in that document.
 * @version 1.0
 */
SERVICE com.mirrorlink.ml_bt_oob_pairing {
/** STRUCTURE holding the static Bluetooth configuration of the
 * MirrorLink device. Details shall not change during a MirrorLink
 * session.
 */
}
```

```

STRUCTURE StaticConfig {
  /** Bluetooth MAC address, as a UTF-8 encoded string representing an
   * unsigned 48-bit integer in hexadecimal format (without any '0x'
   * prefix). The value shall be identical to the value in the Device
   * XML [3] or Client Profile [4].
   * @mandatory, @uid 0xbb96bbf8
   */
  BYTES bdAddr;
  /** Flag, specifying whether the device supports Out-of-Band Pairing.
   * @mandatory, @uid 0x7fbf046b
   */
  BOOLEAN oobPairing;
  /** Boolean flag, specifying whether the Bluetooth connection can be
   * initiated from the device. The value shall be identical to the
   * value in the Device XML [3] or Client Profile [4].
   * @mandatory, @uid 0x979f16fb
   */
  BOOLEAN startConnection;
};
/** STRUCTURE holding the dynamic Bluetooth configuration of the
 * MirrorLink device. Details may change during a MirrorLink session.
 */
STRUCTURE DynamicConfig {
  /** Flag, specifying whether the Bluetooth radio is switched on
   * @mandatory, @uid 0x6d93ffa8
   */
  BOOLEAN radioStatus;
  /** Flag, specifying whether the Bluetooth radio is paired. If set to
   * "true", the MirrorLink device has a Bluetooth pairing (linkkey);
   * i.e. the other MirrorLink device's Bluetooth MAC address is in the
   * known device list. If the element is not available, the pairing
   * status is unknown.
   * @optional, @uid 0xe44a0455
   */
  BOOLEAN pairingStatus;
};
/** STRUCTURE holding the optional EIR_data
 * The structure of the data is defined in [2] Volume 3, Part C, Figure
 * 8.1. The SBP Sink/Source shall be prepared to receive all possible
 * EIR data type values, including values that are currently reserved
 * for future use, in any order. Any EIR data type that is not supported
 * by an implementation is ignored without inspecting the associated
 * EIR data.
 */
STRUCTURE EIR_data {
  /** EIR data length
   * @mandatory, @uid 0xd24a72a5
   */
  BYTE EIR_data_Length;
  /** EIR data type
   * the following data types are of interest for the OOB procedure:
   * - 0x09, 0x08: Bluetooth logical name
   * - 0x0E: Simple Pairing Hash C
   * - 0x0F: Simple Pairing Randomizer R
   * - 0x02-0x07: Service Class UUID
   * - 0x0D: Class of Device
   * The MirrorLink device requesting a Bluetooth handover shall set the
   * following EIR data types:
   * - Simple Pairing Hash C
   * - Simple Pairing Randomizer R
   * @mandatory, @uid 0x80f03299
   */
  BYTE EIR_data_type;
  /** EIR data payload
   * @mandatory, @uid 0xc99c15af
   */
  BYTES EIR_data_payload;
};
/** Object holding the static Bluetooth configuration of the MirrorLink
 * Server.
 * @mandatory, @configurable, @uid 0xb748c238
 */
OBJECT StaticServerConfig {
  /** Static Bluetooth configuration of the MirrorLink Server
   * @mandatory, @uid 0xe648cc95
   */

```

```

STRUCTURE<StaticConfig> StaticConfig;
};
/** Object holding the static Bluetooth configuration of the MirrorLink
 * Client.
 * @mandatory, @readable, @uid 0xdaefdf40
 */
OBJECT StaticClientConfig {
/** Static Bluetooth configuration of the MirrorLink Client
 * @mandatory, @uid 0xe648cc95
 */
STRUCTURE<StaticConfig> StaticConfig;
};
/** Object holding the dynamic Bluetooth configuration of the MirrorLink
 * Server.
 * @mandatory, @configurable, @uid 0x0694d67f
 */
OBJECT DynamicServerConfig {
/** Dynamic Bluetooth configuration of the MirrorLink Server
 * @mandatory, @uid 0x959a7b5c
 */
STRUCTURE<DynamicConfig> DynamicConfig;
};
/** Object holding the dynamic Bluetooth configuration of the MirrorLink
 * Client.
 * @mandatory, @readable, @uid 0x2a3bf387
 */
OBJECT DynamicClientConfig {
/** Dynamic Bluetooth configuration of the MirrorLink Client
 * @mandatory, @uid 0x959a7b5c
 */
STRUCTURE<DynamicConfig> DynamicConfig;
};
/** Bluetooth handover request message;
 * @mandatory, @configurable, @uid 0x43c8eb11
 */
OBJECT Bluetooth_Handover_Request_Message {
/** Out-of-Band Data Length
 * @mandatory, @configurable, @uid 0x0c7bcb6b
 */
INT length;
/** Bluetooth MAC address; the Bluetooth MAC address is 48-bit unsigned
 * integer; it shall be put into the LSB of the 64-bit BD_ADDR variable;
 * i.e. the MSBs 49-63 shall be zero.
 * @mandatory, @writable, @uid 0xe47ae6e9
 */
LONG BD_ADDR;
/** Optional OOB data, in EIR format
 * @mandatory, @writable, @uid 0x206e1427
 */
STRUCTURE_ARRAY<EIR_data> OOB_Optional_Data;
};
/** Bluetooth handover request message
 * @mandatory, @readable, @uid 0xee9231ea
 */
OBJECT Bluetooth_Handover_Select_Message {
/** Out-of-Band Data Length;
 * @mandatory, @uid 0x0c7bcb6b
 */
INT length;
/** Bluetooth MAC address; the Bluetooth MAC address is 48-bit unsigned
 * integer; it shall be put into the LSB of the 64-bit BD_ADDR variable;
 * i.e. the MSBs 49-63 shall be zero.
 * @mandatory, @uid 0xe47ae6e9
 */
LONG BD_ADDR;
/** Optional OOB data, in EIR format
 * @mandatory, @uid 0x206e1427
 */
STRUCTURE_ARRAY<EIR_data> OOB_Optional_Data;
};
/** MirrorLink Server confirmation; the MirrorLink Server should set
 * this object to TRUE; the MirrorLink Client shall not initiate the
 * pairing prior the Server has set the value to TRUE. The MirrorLink
 * Server need not set the object value, if it is expected to start the
 * pairing;
 * @mandatory, @configurable, @uid 0xb965fef8
 */

```



```

OBJECT serverConfirm {
  /** Confirmation that MirrorLink Server is ready to start the pairing;
   * @mandatory, @uid 0x003400db
   */
  BOOLEAN confirm;
};
};

```

5 SBP Binding

5.1 Service Registry

The Bluetooth Out-of-Band Data Services uses the following objects and their access capabilities.

Table 1

| Object Name | Access Type | Subscription Type |
|------------------------------------|--------------|-------------------|
| StaticClientConfig | READABLE | NONE |
| StaticServerConfig | CONFIGURABLE | NONE |
| DynamicClientConfig | READABLE | ON_CHANGE |
| DynamicServerConfig | CONFIGURABLE | NONE |
| Bluetooth_Handover_Request_Message | CONFIGURABLE | NONE |
| Bluetooth_Handover_Select_Message | READABLE | NONE |
| serverConfirm | CONFIGURABLE | NONE |

6 Theory of Operation

6.1 General

The obligation for this feature is **CONDITIONAL**. A MirrorLink Client and Server, supporting Bluetooth within a MirrorLink session, shall support this feature. The user may disable/enable the automatic pairing feature.

MirrorLink Clients and Servers shall both support sending OOB information to enable *OOB authentication where both devices have some OOB information to use* per [2] [Vol 2] Part F, clause 4.2.16 *Figure 4.20*.

The MirrorLink device requesting a Bluetooth handover shall set the following EIR data types:

- Simple Pairing Hash C.
- Simple Pairing Randomizer R.

6.2 SBP Protocol

6.2.1 General

The MirrorLink Client shall include the *ml_bt_oob_pairing* Service into the CDB service listing, prior to launching any Bluetooth module via an UPnP launch application action, unless the MirrorLink Client is already paired with the MirrorLink Server.

The MirrorLink Client shall include the *ml_bt_oob_pairing* Service into the CDB service listing, immediately after a MirrorLink session setup, if the Client uses legacy Bluetooth connection mechanisms (i.e. no UPnP launch application action), unless the MirrorLink Client is already paired with the MirrorLink Server.