

ETSI TS 129 389 V14.2.0 (2019-10)



LTE;
Inter-V2X Control Function Signalling aspects (V6);
Stage 3
(3GPP TS 29.389 version 14.2.0 Release 14)



ReferenceRTS/TSGC-0429389ve20

Keywords

LTE

ETSI

650 Route des Lucioles
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - NAF 742 C
Association à but non lucratif enregistrée à la
Sous-Préfecture de Grasse (06) N° 7803/88

Important notice

The present document can be downloaded from:

<http://www.etsi.org/standards-search>

The present document may be made available in electronic versions and/or in print. The content of any electronic and/or print versions of the present document shall not be modified without the prior written authorization of ETSI. In case of any existing or perceived difference in contents between such versions and/or in print, the prevailing version of an ETSI deliverable is the one made publicly available in PDF format at www.etsi.org/deliver.

Users of the present document should be aware that the document may be subject to revision or change of status. Information on the current status of this and other ETSI documents is available at

<https://portal.etsi.org/TB/ETSIDeliverableStatus.aspx>

If you find errors in the present document, please send your comment to one of the following services:

<https://portal.etsi.org/People/CommitteeSupportStaff.aspx>

Copyright Notification

No part may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm except as authorized by written permission of ETSI.

The content of the PDF version shall not be modified without the written authorization of ETSI.

The copyright and the foregoing restriction extend to reproduction in all media.

© ETSI 2019.

All rights reserved.

DECT™, **PLUGTESTS™**, **UMTS™** and the ETSI logo are trademarks of ETSI registered for the benefit of its Members.

3GPP™ and **LTE™** are trademarks of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners.

oneM2M™ logo is a trademark of ETSI registered for the benefit of its Members and of the oneM2M Partners.

GSM® and the GSM logo are trademarks registered and owned by the GSM Association.

Intellectual Property Rights

Essential patents

IPRs essential or potentially essential to normative deliverables may have been declared to ETSI. The information pertaining to these essential IPRs, if any, is publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: *"Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards"*, which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (<https://ipr.etsi.org/>).

Pursuant to the ETSI IPR Policy, no investigation, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

Trademarks

The present document may include trademarks and/or tradenames which are asserted and/or registered by their owners. ETSI claims no ownership of these except for any which are indicated as being the property of ETSI, and conveys no right to use or reproduce any trademark and/or tradename. Mention of those trademarks in the present document does not constitute an endorsement by ETSI of products, services or organizations associated with those trademarks.

Legal Notice

This Technical Specification (TS) has been produced by ETSI 3rd Generation Partnership Project (3GPP).

The present document may refer to technical specifications or reports using their 3GPP identities. These shall be interpreted as being references to the corresponding ETSI deliverables.

The cross reference between 3GPP and ETSI identities can be found under <http://webapp.etsi.org/key/queryform.asp>.

Modal verbs terminology

In the present document "**shall**", "**shall not**", "**should**", "**should not**", "**may**", "**need not**", "**will**", "**will not**", "**can**" and "**cannot**" are to be interpreted as described in clause 3.2 of the [ETSI Drafting Rules](#) (Verbal forms for the expression of provisions).

"**must**" and "**must not**" are **NOT** allowed in ETSI deliverables except when used in direct citation.

Contents

Intellectual Property Rights	2
Legal Notice	2
Modal verbs terminology.....	2
Foreword.....	5
1 Scope	6
2 References	6
3 Definitions and abbreviations.....	7
3.1 Definitions	7
3.3 Abbreviations	7
4 General Description.....	7
4.1 Introduction	7
5 Procedure Description	7
5.1 Introduction	7
5.2 V2X Service Authorization	7
5.2.1 General.....	7
5.2.2 Detailed behaviour of the V2X Control Function in the HPLMN	8
5.2.3 Detailed behaviour of the V2X Control Function in the VPLMN.....	9
6 Protocol Specification and Implementations	9
6.1 Introduction	9
6.1.1 Use of Diameter base protocol.....	9
6.1.2 Securing Diameter Messages.....	9
6.1.3 Accounting functionality	9
6.1.4 Use of sessions.....	9
6.1.5 Transport protocol	10
6.1.6 Routing considerations	10
6.1.7 Advertising Application Support	10
6.1.8 Diameter Application Identifier.....	10
6.1.9 Use of the Supported-Features AVP.....	10
6.2 Commands.....	11
6.2.1 Introduction.....	11
6.2.2 Command-Code values	11
6.2.3 ProSe-Authorization-Request (PAR) Command	11
6.2.4 ProSe-Authorization-Answer (PAA) Command.....	12
6.3 Information Elements	12
6.3.1 General.....	12
6.3.2 V2X-Authorization-Data	13
6.3.3 V2X-Permission-in-VPLMN.....	14
6.3.4 V2X-Application-Server.....	14
6.3.5 Application-Server.....	14
6.3.6 Geographical-Information	14
6.3.7 OC-Supported-Features	14
6.3.8 OC-OLR	14
6.3.9 DRMP	15
6.3.10 Load.....	15
6.4 Result-Code AVP and Experimental-Result AVP Values	15
6.4.1 General.....	15
6.4.2 Success.....	15
6.4.3 Permanent Failures	15
6.4.3.1 General	15
6.4.3.2 DIAMETER_ERROR_USER_UNKNOWN (5001).....	15
6.4.3.3 DIAMETER_ERROR_UNKNOWN_V2X_SUBSCRIPTION (5690)	15
6.4.3.4 DIAMETER_ERROR_V2X_NOT_ALLOWED (5691).....	15

Annex A (normative):	Diameter overload control mechanism	16
A.1	General	16
A.2	Responding V2X Control Function behaviour	16
A.3	Requesting V2X Control Function behaviour	16
Annex B (Informative):	Diameter overload node behaviour	17
B.1	Message prioritization	17
Annex C (normative):	Diameter message priority mechanism.....	18
C.1	General	18
C.2	V6 interfaces	18
C.2.1	General.....	18
C.2.2	V2X Control Function behaviour	18
D.1	General	18
D.2	Responding V2X Control Function behaviour	18
D.3	Requesting V2X Control Function behaviour	19
Annex E (informative):	Change history	20
History		21

iTeh STANDARD PREVIEW
 (standards.iteh.ai)
 Full standard:
<https://standards.iteh.ai/catalog/standards/sist/3aa56b09-5737-491c-8905-28220f59e88c/etsi-ts-129-389-v14.2.0-2019-10>

Foreword

This Technical Specification has been produced by the 3rd Generation Partnership Project (3GPP).

The contents of the present document are subject to continuing work within the TSG and may change following formal TSG approval. Should the TSG modify the contents of the present document, it will be re-released by the TSG with an identifying change of release date and an increase in version number as follows:

Version x.y.z

where:

- x the first digit:
 - 1 presented to TSG for information;
 - 2 presented to TSG for approval;
 - 3 or greater indicates TSG approved document under change control.
- y the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- z the third digit is incremented when editorial only changes have been incorporated in the document.

iTeh STANDARD PREVIEW
(standards.iteh.ai)
Full standard:
<https://standards.iteh.ai/catalog/standards/sist/3aa56b09-5737-491c-8905-28220f59e88c/etsi-ts-129-389-v14.2.0-2019-10>

1 Scope

The present document describes the Diameter-based interfaces between the V2X Control Function in the HPLMN and the V2X Control Function in the VPLMN (V6 interface).

This specification defines the Diameter application for V6 reference points between the V2X Control Functions. The interactions between the V2X Control Functions are specified.

The stage 2 description for V2X service features in EPS is specified in 3GPP TS 23.285 [2].

2 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- References are either specific (identified by date of publication, edition number, version number, etc.) or non-specific.
- For a specific reference, subsequent revisions do not apply.
- For a non-specific reference, the latest version applies. In the case of a reference to a 3GPP document (including a GSM document), a non-specific reference implicitly refers to the latest version of that document *in the same Release as the present document*.

- [1] 3GPP TR 21.905: "Vocabulary for 3GPP Specifications".
- [2] 3GPP TS 23.285: "Architecture enhancements for V2X services; Stage 2".
- [3] IETF RFC 6733: "Diameter Base Protocol".
- [4] 3GPP TS 33.210: "3G Security; Network Domain Security; IP Network Layer Security".
- [5] IETF RFC 4960: "Stream Control Transmission Protocol".
- [6] 3GPP TS 29.229: "Cx and Dx interfaces based on the Diameter protocol".
- [7] IETF RFC 5234: "Augmented BNF for Syntax Specifications: ABNF".
- [8] 3GPP TS 23.003: "Numbering, addressing and identification".
- [9] 3GPP TS 29.228: "IP multimedia (IM) Subsystem Cx and Dx Interfaces; Signalling flows and Message Elements".
- [10] 3GPP TS 29.272: "Evolved Packet System; MME and SGSN Related Interfaces Based on Diameter Protocol".
- [11] 3GPP TS 29.329: "Sh Interface based on the Diameter protocol".
- [12] IETF RFC 7683: "Diameter Overload Indication Conveyance".
- [13] 3GPP TS 29.336: "Home Subscriber Server (HSS) diameter interfaces for interworking with packet data networks and applications".
- [14] 3GPP TS 32.299: "Telecommunication management; Charging management; Diameter charging applications".
- [15] IETF RFC 7944: "Diameter Routing Message Priority".
- [16] 3GPP TS 29.388: "V2X Control Function to V2X Control Function to Home Subscriber Server (HSS) aspects (V4)".
- [17] 3GPP TS 29.345: "Inter-Proximity-services (ProSe) Function signalling aspects".
- [18] IETF RFC 8583: "Diameter Load Information Conveyance".

3 Definitions and abbreviations

3.1 Definitions

For the purposes of the present document, the terms and definitions given in 3GPP TR 21.905 [1] and the following apply. A term defined in the present document takes precedence over the definition of the same term, if any, in 3GPP TR 21.905 [1].

example: text used to clarify abstract rules by applying them literally.

3.3 Abbreviations

For the purposes of the present document, the abbreviations given in 3GPP TR 21.905 [1] and the following apply. An abbreviation defined in the present document takes precedence over the definition of the same abbreviation, if any, in 3GPP TR 21.905 [1].

ProSe	Proximity-based Services
V2X	Vehicle-to-Everything

4 General Description

4.1 Introduction

The V6 reference point is defined between a V2X Control Function in the HPLMN and a V2X Control Function in the VPLMN.

The definition of the V6 reference points and related functionalities are given in 3GPP TS 23.285 [2].

As defined in 3GPP TS 23.285 [2], the V6 reference point is used for:

- HPLMN control of service authorization for V2X.

5 Procedure Description

5.1 Introduction

This clause describes the Diameter-based V6 interface related procedures and Information elements exchanged between functional entities.

In the tables that describe the Information Elements transported by each Diameter command, each Information Element is marked as (M) Mandatory, (C) Conditional or (O) Optional in the "Cat." column. For the correct handling of the Information Element according to the category type, see the description detailed in clause 6 of the 3GPP TS 29.228 [9].

5.2 V2X Service Authorization

5.2.1 General

The V2X Service Authorization Procedure shall be used between the V2X Control Function in the HPLMN and the V2X Control Function in the VPLMN to obtain service authorization information for V2X services. The procedure shall be invoked by the V2X Control Function in the HPLMN of the UE and is used:

- to request service authorization information for V2X related to the UE from the V2X Control Function in the VPLMN;
- to provide the V2X Control Function in the VPLMN with the UE identity (IMSI or MSISDN) in order to allow to perform charging;

This procedure is mapped to the commands ProSe-Authorization-Request/Answer (PAR/PAA) in the Diameter application specified in clause 6.

Table 5.2.1-1 specifies the involved information elements for the request.

Table 5.2.1-2 specifies the involved information elements for the answer.

Table 5.2.1-1: V2X Service Authorization Request

Information element name	Mapping to Diameter AVP	Cat.	Description
UE Identity (See 3GPP TS 29.336 [13])	User-Identifier	M	This information element shall contain either the user IMSI, formatted according to 3GPP TS 23.003 [8], clause 2.2, or the user MSISDN, formatted according to 3GPP TS 29.329 [11].
PLMN Id (See 3GPP TS 29.272 [10])	Visited-PLMN-Id	M	This IE shall contain the PLMN-Id (3GPP TS 23.003 [8]) of the network in which the V2X Control Function is located.
Supported Features (See 3GPP TS 29.229 [6])	Supported-Features	O	If present, this information element shall contain the list of features supported by the origin host.

Table 5.2.1-2: V2X Service Authorization Answer

Information element name	Mapping to Diameter AVP	Cat.	Description
Result (See 6.4)	Result-Code / Experimental-Result	M	This IE shall contain the result of the operation. The Result-Code AVP shall be used to indicate success / errors as defined in the Diameter Base Protocol. The Experimental-Result AVP shall be used for V6 errors. This is a grouped AVP which shall contain the 3GPP Vendor ID in the Vendor-Id AVP, and the error code in the Experimental-Result-Code AVP. The following errors are applicable: - User Unknown - Unauthorized Service - Unauthorized Service in this PLMN
Supported Features (See 3GPP TS 29.229 [6])	Supported-Features	O	If present, this information element shall contain the list of features supported by the origin host.
V2X Authorization Data (See 6.3.2)	V2X-Authorization-Data	C	This Information Element shall contain the V2X authorization information of the user. It shall be present if success is reported.

5.2.2 Detailed behaviour of the V2X Control Function in the HPLMN

The V2X Control Function in the HPLMN shall make use of this procedure to request service authorization information for V2X related to the UE from the V2X Control Function in the VPLMN. The V2X Control Function shall include in the request the UE identity (IMSI or MSISDN) and the PLMN-Id identifying the PLMN of the requesting V2X Control Function.

When receiving a V2X Service Authorization response from the V2X Control Function in the VPLMN, the V2X Control Function in the HPLMN shall check the result code. If it indicates SUCCESS, the V2X Control Function shall merge with its own policy.

5.2.3 Detailed behaviour of the V2X Control Function in the VPLMN

When receiving a V2X Service Authorization request, the V2X Control Function in the VPLMN shall, in the following order:

1. Check whether the UE Identity (IMSI or MSISDN) exists. If not, a Result Code of DIAMETER_ERROR_USER_UNKNOWN shall be returned.
2. Check whether V2X is authorized for this UE Identity. If not, a Result Code of DIAMETER_ERROR_UNAUTHORIZED_SERVICE shall be returned.

If there is an error in any of the above steps then the V2X Control Function shall stop processing the request and shall return the error code specified in the respective step.

If the V2X Control Function cannot fulfil the received request for reasons not stated in the above steps, e.g. due to a database error or any of the required actions cannot be performed, it shall stop processing the request and set the Result Code to "DIAMETER_UNABLE_TO_COMPLY".

Otherwise, when the UE is authorized to use V2X over PC5 or V2X over MBMS in this PLMN, the V2X Control Function shall include the V2X-Authorization-Data AVP in the response to return V2X permissions and the V2X Application Server information, and shall set the Result Code to "DIAMETER_SUCCESS".

6 Protocol Specification and Implementations

6.1 Introduction

6.1.1 Use of Diameter base protocol

The Diameter base protocol as specified in IETF RFC 6733 [3] shall apply except as modified by the defined support of the methods and the defined support of the commands and AVPs, result and error codes as specified in this specification. Unless otherwise specified, the procedures (including error handling and unrecognised information handling) shall be used unmodified.

6.1.2 Securing Diameter Messages

For secure transport of Diameter messages, see 3GPP TS 33.210 [4].

6.1.3 Accounting functionality

Accounting functionality (Accounting Session State Machine, related command codes and AVPs) shall not be used on the V6 interface.

6.1.4 Use of sessions

Between the V2X Control Functions, Diameter sessions shall be implicitly terminated. An implicitly terminated session is one for which the server does not maintain state information. The client shall not send any re-authorization or session termination requests to the server.

The Diameter base protocol includes the Auth-Session-State AVP as the mechanism for the implementation of implicitly terminated sessions.

The client (server) shall include in its requests (responses) the Auth-Session-State AVP set to the value NO_STATE_MAINTAINED (1), as described in IETF RFC 6733 [3]. As a consequence, the server shall not maintain