

ETSI TS 145 010 V14.5.0 (2020-04)



Digital cellular telecommunications system (Phase 2+) (GSM); GSM/EDGE Radio subsystem synchronization (3GPP TS 45.010 version 14.5.0 Release 14)

Standard Preview
(standards.iteh.ai)
Full standard available at
https://standards.iteh.ai/catalog/standards/sist/6681ab-0481-4828-b13d-67381412098d/etsi-ts-145-010-v14-5-0-2020-04



ReferenceRTS/TSGR-0645010ve50

KeywordsGSM

ETSI

650 Route des Lucioles
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - NAF 742 C
Association à but non lucratif enregistrée à la
Sous-Préfecture de Grasse (06) N° 7803/88

Important notice

The present document can be downloaded from:
<http://www.etsi.org/standards-search>

The present document may be made available in electronic versions and/or in print. The content of any electronic and/or print versions of the present document shall not be modified without the prior written authorization of ETSI. In case of any existing or perceived difference in contents between such versions and/or in print, the prevailing version of an ETSI deliverable is the one made publicly available in PDF format at www.etsi.org/deliver.

Users of the present document should be aware that the document may be subject to revision or change of status. Information on the current status of this and other ETSI documents is available at <https://portal.etsi.org/TB/ETSIDeliverableStatus.aspx>

If you find errors in the present document, please send your comment to one of the following services:
<https://portal.etsi.org/People/CommitteeSupportStaff.aspx>

Copyright Notification

No part may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm except as authorized by written permission of ETSI.

The content of the PDF version shall not be modified without the written authorization of ETSI.

The copyright and the foregoing restriction extend to reproduction in all media.

© ETSI 2020.

All rights reserved.

DECT™, **PLUGTESTS™**, **UMTS™** and the ETSI logo are trademarks of ETSI registered for the benefit of its Members. **3GPP™** and **LTE™** are trademarks of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners.

oneM2M™ logo is a trademark of ETSI registered for the benefit of its Members and of the oneM2M Partners.

GSM® and the GSM logo are trademarks registered and owned by the GSM Association.

Intellectual Property Rights

Essential patents

IPRs essential or potentially essential to normative deliverables may have been declared to ETSI. The information pertaining to these essential IPRs, if any, is publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: "*Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards*", which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (<https://ipr.etsi.org/>).

Pursuant to the ETSI IPR Policy, no investigation, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

Trademarks

The present document may include trademarks and/or tradenames which are asserted and/or registered by their owners. ETSI claims no ownership of these except for any which are indicated as being the property of ETSI, and conveys no right to use or reproduce any trademark and/or tradename. Mention of those trademarks in the present document does not constitute an endorsement by ETSI of products, services or organizations associated with those trademarks.

Legal Notice

This Technical Specification (TS) has been produced by ETSI 3rd Generation Partnership Project (3GPP).

The present document may refer to technical specifications or reports using their 3GPP identities. These shall be interpreted as being references to the corresponding ETSI deliverables.

The cross reference between 3GPP and ETSI identities can be found under <http://webapp.etsi.org/key/queryform.asp>.

Modal verbs terminology

In the present document "**shall**", "**shall not**", "**should**", "**should not**", "**may**", "**need not**", "**will**", "**will not**", "**can**" and "**cannot**" are to be interpreted as described in clause 3.2 of the [ETSI Drafting Rules](#) (Verbal forms for the expression of provisions).

"**must**" and "**must not**" are **NOT** allowed in ETSI deliverables except when used in direct citation.

Contents

Intellectual Property Rights	2
Legal Notice	2
Modal verbs terminology.....	2
Foreword.....	5
1 Scope	6
1.1 References	6
1.2 Definitions and abbreviations.....	6
2 General description of synchronization system.....	8
3 Timebase counters.....	9
3.1 Timing state of the signals.....	9
3.2 Relationship between counters	9
4 Timing of transmitted signals.....	9
5 BTS Requirements for Synchronization.....	10
5.0 General	10
5.1 Frequency source.....	11
5.2 Timebase counters	11
5.3 Internal BTS carrier timing	11
5.4 Timing advance estimation.....	11
5.4.1 Initial timing advance estimation.....	11
5.4.2 BTS Timing Advance Estimation for Positioning	11
5.5 Maximum timing advance value	13
5.6 Delay tracking	13
5.6.1 For circuit switched channels.....	13
5.6.2 For packet switched channels	13
5.6.3 Delay assessment error	14
5.6.4 Pico-BTS and Local Area multicarrier BTS delay tracking	14
5.7 Timeslot length.....	14
5.7.0 Implementation options	14
5.7.1 Regular implementation with timeslot lengths of non-integral symbol periods	14
5.7.2 Implementation option for reduced symbol period bursts when integral symbol period option is used for normal symbol period bursts	16
5.8 Range of Timing advance.....	17
6 MS Requirements for Synchronization	17
6.0 General	17
6.1 MS carrier frequency.....	17
6.2 Internal timebase	17
6.3 Assessment of BTS timing	18
6.3.1 General.....	18
6.3.2 MS Assessment of BTS timing for Positioning	18
6.4 Timing of transmission.....	19
6.5 Application of Timing Advance	19
6.5.1 For circuit switched channels.....	19
6.5.2 For packet switched channels	20
6.6 Access to a new BTS.....	20
6.7 Temporary loss of signal	21
6.8 Timing of channel change	21
6.9 Application of new Timing Advance value.....	22
6.10 Definition of "ready to transmit within x ms"	22
6.11 Definition of additional reaction times for GPRS mobile stations	22
6.11.1 Uplink and downlink assignment reaction times	22
6.11.2 Change in channel coding scheme commanded by network.....	23
6.11.3 Contention resolution reaction time	23

6.11.4	Reaction time in response to other commanding messages	24
6.11.5	PAN related reaction times	24
6.11.6	DTR related reaction times	24
6.12	Observed Frequency Offset (OFO) reported by the CTS-MS	25
6.13	Timing of inter-RAT channel change from GSM to UTRAN.....	25
6.13a	Timing of inter-RAT channel change from GSM to E-UTRAN.....	26
6.14	Timing of combined intracell channel change and packet assignment.....	26
7	CTS-FP Requirements for Synchronization.....	27
7.1	Frequency source default requirements	27
7.2	Frequency source for a CTS-FP assisted by a CTS-MS	27
7.3	Internal CTS-FP carrier timing.....	27
7.4	Timeslot length.....	27
7.5	Assessment of CTS-MS delay.....	27
Annex A (normative): Additional requirements for pseudo-synchronization, synchronized handovers and pseudo-synchronized handovers.....28		
A.1	General descriptions and definitions	28
A.1.1	Conventions.....	28
A.1.2	Definitions.....	28
A.1.3	Details of operations.....	28
A.2	BTS requirements.....	29
A.2.1	The pseudo-synchronization scheme	29
A.2.1.1	BTS a time difference estimate.....	29
A.2.1.2	The reception epoch criterion	29
A.2.1.3	Pseudo-synchronized handover	29
A.2.2	The synchronization scheme	29
A.3	MS requirements	29
A.3.1	Provision of time difference information	29
A.3.2	After each successful circuit-switched handover	30
A.3.3	Synchronized or a pseudo synchronized handover.....	30
Annex B (informative): CTSBCH timeslot shifting properties for CTS-MS synchronization.....31		
B.1	Determination of TN by the CTS-MS when CTSBCH shifting is not active	31
B.2	Determination of TN by the CTS-MS when CTSBCH shifting is active	31
Annex C (informative): BTS frequency source stability and E-OTD LMU reporting periods for LCS32		
C.1	BTS frequency source stability and E-OTD LMU reporting periods	32
C.2	Frequency source stability.....	32
C.3	Relationship to E-OTD reporting periods	32
Annex D (informative): Change history34		
History		38

Foreword

This Technical Specification has been produced by the 3rd Generation Partnership Project (3GPP).

The contents of the present document are subject to continuing work within the TSG and may change following formal TSG approval. Should the TSG modify the contents of the present document, it will be re-released by the TSG with an identifying change of release date and an increase in version number as follows:

Version x.y.z

where:

- x the first digit:
 - 1 presented to TSG for information;
 - 2 presented to TSG for approval;
 - 3 or greater indicates TSG approved document under change control.
- y the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- z the third digit is incremented when editorial only changes have been incorporated in the document.

iTeh STANDARD PREVIEW
(standards.iteh.ai)
Full standard:
<https://standards.iteh.ai/catalog/standards/sist/668611ab-04814828-b3d-67381412098d/etsi-ts-145-010-v14.5.0-2020-04>

1 Scope

The present document defines the requirements for synchronization on the radio sub-system of the digital cellular telecommunications systems GSM. However, it does not define the synchronization algorithms to be used in the Base Transceiver Station (BTS), CTS Fixed Part (CTS-FP) and Mobile Station (MS). These are up to the manufacturer to specify.

1.1 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- References are either specific (identified by date of publication, edition number, version number, etc.) or non-specific.
- For a specific reference, subsequent revisions do not apply.
- For a non-specific reference, the latest version applies. In the case of a reference to a 3GPP document (including a GSM document), a non-specific reference implicitly refers to the latest version of that document *in the same Release as the present document*.

- [1] 3GPP TR 21.905: "Vocabulary for 3GPP Specifications".
- [2] 3GPP TS 25.123: "Requirements for support of radio resource management (TDD)".
- [3] 3GPP TS 25.133: "Requirements for support of radio resource management (FDD)".
- [4] 3GPP TR 43.030: "Radio network planning aspects".
- [5] 3GPP TS 43.052: "Lower layers of the Cordless Telephony System (CTS) Radio Interface; Stage 2".
- [6] 3GPP TS 43.059: "Functional stage 2 description of Location Services (LCS) in GERAN".
- [7] 3GPP TS 43.064: "Overall description of the GPRS radio interface; Stage 2".
- [8] 3GPP TS 44.018: "Mobile radio interface layer 3 specification, Radio Resource Control Protocol".
- [9] 3GPP TS 44.060: "General Packet Radio Service (GPRS); Mobile Station (MS) - Base Station System (BSS) interface; Radio Link Control/ Medium Access Control (RLC/MAC) protocol".
- [10] 3GPP TS 45.002: "Multiplexing and multiple access on the radio path".
- [11] 3GPP TS 45.005: "Radio transmission and reception".
- [12] 3GPP TS 45.008: "Radio subsystem link control".
- [13] 3GPP TS 45.050: "Background for RF Requirements".
- [14] 3GPP TS 45.056: "CTS-FP Radio Sub-system".
- [15] 3GPP TS 45.004: "Modulation".
- [16] 3GPP TS 36.133: "Evolved Universal Terrestrial Radio Access (E-UTRA); Requirements for support of radio resource management".
- [17] 3GPP TS 36.211: "Evolved Universal Terrestrial Radio Access (E-UTRA); Physical Channels and Modulation".
- [18] 3GPP TS 49.031: "Location Services (LCS); Base Station System Application Part, LCS Extension (BSSAP-LE)".

1.2 Definitions and abbreviations

In addition to those below, abbreviations used in the present document are listed in 3GPP TR 21.905.

BTS: Base Transceiver Station.

BTTI: Basic TTI.

Coverage Class: see definition in 3GPP TS 43.064.

CTS-FP: CTS Fixed Part.

CTS-MS: MS operating in CTS mode.

Current Serving BTS: BTS on one of whose channels (TCH, DCCH, CCCH or PDCH) the MS is currently operating.

Current Serving CTS-FP: CTS-FP on one of whose channels (TCH or CTS control channels) the CTS-MS is currently operating.

EC: Extended Coverage, see definition in 3GPP TS 43.064.

EC operation: see definition in 3GPP TS 43.064.

EC-GSM-IoT: Extended Coverage GSM for Internet of Things.

FANR (Fast Ack/Nack Reporting): Fast Ack/Nack Reporting enables the use of a PAN field within an RLC/MAC block for EGPRS data transfer or for EGPRS2 data transfer. FANR enables the mobile station to transmit in the uplink direction a PAN field corresponding to a downlink TBF. Similarly FANR enables the network to transmit in the downlink direction a PAN field corresponding to an uplink TBF.

MS timing offset: delay of the received signal relative to the expected signal from an MS at zero distance under static channel conditions with zero timing advance. This is accurate to ± 1 symbol, and reported once per SACCH or after a RACH as required (i.e. at the same rate as timing advance). For example, for an MS with a round trip propagation delay of P symbols, but with a timing advance of T symbols, the reported timing offset will be P-T quantized to the nearest symbol. For GPRS the MS timing offset is not reported.

Normal Symbol Period: duration of a symbol for bursts using a modulating symbol rate of 1625/6 ksymb/s (see 3GPP TS 45.004); it is equal to 48/13 μ s. This symbol duration is used for transmission of GMSK, 8PSK, 16QAM and 32QAM modulated bursts on downlink and GMSK, 8PSK and 16QAM modulated bursts on uplink (see 3GPP TS 45.004).

Observed Frequency Offset (OFO): difference of frequency of signals received by a CTS-MS from a CTS-FP and a BTS. The Observed Frequency Offset is measured and reported by the CTS-MS on CTS-FP requirement. The Observed Frequency Offset is expressed in ppm with an accuracy of 1/64 ppm (i.e. about 0,016 ppm).

PAN: Piggy-backed Ack/Nack.

Quarter symbol number: timing of quarter symbol periods (12/13 μ s or 10/13 μ s depending on the actual symbol period used) within a timeslot. A symbol can represent 1 to 5 bits depending upon modulation.

Reduced Latency: refers to the use of FANR either in BTTI configuration or in RTTI configuration for EGPRS and EGPRS2.

Reduced Symbol Period: duration of a symbol for bursts using a modulating symbol rate of 325 ksymb/s (see 3GPP TS 45.004); it is equal to 40/13 μ s. This symbol duration is used for transmission of QPSK, 16QAM and 32QAM modulated bursts on uplink and downlink (see 3GPP TS 45.004).

RTTI: Reduced TTI.

Symbol Period: symbol period is the duration of a symbol and shall refer to normal symbol period unless explicitly clarified to be the reduced symbol period.

TDMA frame number: count of TDMA frames relative to an arbitrary start point.

Timebase counters: set of counters which determine the timing state of signals transmitted by a BTS or MS.

Time group (TG): used for compact, time groups shall be numbered from 0 to 3 and a particular time group shall be referred to by its time group number (TG) (see 3GPP TS 45.002).

Timeslot number (TN): timing of timeslots within a TDMA frame.

Timing Advance: signal sent by the BTS to the MS which the MS uses to advance its timings of transmissions to the BTS so as to compensate for propagation delay.

Timing Advance Index: Timing Advance Index TAI used for GPRS, which determines the position of the subchannel on PTCCH (see 3GPP TS 45.002) used by the MS to send an access burst, from which the network can derive the timing advance.

TTI: Transmission Time Interval.

2 General description of synchronization system

This clause gives a general description of the synchronization system. Detailed requirements are given in clauses 3 to 7.

The BTS sends signals on the BCCH carrier or, for COMPACT on the CPBCCCH carrier, to enable the MS to synchronize itself to the BTS and if necessary correct its frequency standard to be in line with that of the BTS. The signals sent by the BTS for these purposes are:

- a) Frequency correction bursts;
- b) Synchronization bursts.

The timings of timeslots, TDMA frames, TCH frames, control channel frames, and (for COMPACT) the rotation of time groups are all related to a common set of counters which run continuously whether the MS and BTS are transmitting or not. Thus, once the MS has determined the correct setting of these counters, all its processes are synchronized to the current serving BTS.

The MS times its transmissions to the BTS in line with those received from the BTS. The BTS sends to each MS a "timing advance" parameter (TA) according to the perceived round trip propagation delay BTS-MS-BTS. The MS advances its timing by this amount, with the result that signals from different MS's arriving at the BTS and compensated for propagation delay. This process is called "adaptive frame alignment".

Additionally, synchronization functions may be implemented in both the MS and the BTS to support the so-called pseudo synchronization scheme for circuit-switched handovers. The support of this scheme is optional except that MS shall measure and report the Observed Timing Difference (OTD), which is a mandatory requirement. The detailed specifications of the pseudo-synchronization scheme for circuit-switched handovers are included in annex A.

While in dual transfer mode an MS performs all the tasks of dedicated mode. In addition, upper layers can require the release of all the packet resources, which triggers the transition to dedicated mode, or the release of the RR resources, which triggers the transition either to idle mode and packet idle mode or, depending upon network and MS capabilities, to packet transfer mode.

When handed over to a new cell, the MS leaves the dual transfer mode, enters the dedicated mode where it switches to the new cell, may read the system information messages sent on the SACCH and may then enter dual transfer mode in the new cell (see 3GPP TS 44.060).

In CTS, the CTS-FP sends signals on the CTSBCH to enable the MS to synchronize itself to the CTS-FP and if necessary correct its frequency standard to be in line with that of the CTS-FP.

The signals sent by the CTS-FP for these purposes are:

- a) Frequency correction bursts;
- b) Synchronization bursts.

The timings of timeslots, TDMA frames, CTSBCH, CTSARCH, CTSAGCH and CTSPCH frames are all related to a first common set of counters which run continuously whether the CTS-MS and CTS-FP are transmitting or not. Thus, once the CTS-MS has determined the correct setting of these first counters, the CTS-MS is able to attach to the current serving CTS-FP. In addition, during CTS-MS attachment, the CTS-FP sends to the CTS-MS the remaining counters for SACCH and TCH frames. Then, all processes of the CTS-MS are synchronized to the current serving CTS-FP.

The CTS-MS times its transmissions to the CTS-FP in line with those received from the CTS-FP. The timing advance parameter is set to zero for CTS.

Additionally, the CTS-FP may be assisted by a CTS-MS to adjust its frequency source. When required by the CTS-FP, the CTS-MS estimates if possible and reports the Observed Frequency Offset of the CTS-FP with a specified BTS. The CTS-FP may then adjust its frequency source according to this value.

3 Timebase counters

3.1 Timing state of the signals

The timing state of the signals transmitted by a BTS (for normal symbol period), a MS (for normal symbol period), a CTS-FP, or an Compact BTS and MS is defined by the following counters:

- Quarter symbol number QN (0 - 624)
- Symbol number BN (0 - 156);
- Timeslot number TN (0 - 7);
- TDMA frame number FN (0 to $(26 \times 51 \times 2048) - 1 = 2715647$); or
- for a non attached CTS-MS, TDMA frame number modulo 52 T4 (0 - 51); or
- for Compact, TDMA frame number FN (0 to $(52 \times 51 \times 1024) - 1 = 2715647$).

In CTS, the CTS-MS shall manage different sets of counters for CTS operation and GSM operation.

Alternatively, in case of transmission using reduced symbol period, for a BTS or an MS the following counters have the following ranges:

- Quarter symbol number QN (0-749)
- Symbol number BN (0-187)

3.2 Relationship between counters

The relationship between these counters is as follows:

- QN increments every $12/13 \mu\text{s}$ for normal symbol period and every $10/13\mu\text{s}$ for Reduced Symbol Period;
- $\text{BN} = \text{Integer part of } \text{QN}/4$;
- TN increments whenever QN changes from count 624 to 0 for normal symbol period and whenever QN changes from count 749 to 0 for reduced symbol period;
- FN increments whenever TN changes from count 7 to 0; or
- for a CTS-MS, T4 increments whenever TN changes from count 7 to 0.

4 Timing of transmitted signals

The timing of signals transmitted by the MS, BTS and CTS-FP is defined in 3GPP TS 45.002.

- i) The MS can use the timing of receipt of the synchronization burst to set up its timebase counters as follows:
 - QN is set by the timing of the training sequence;
 - TN = 0 when the synch burst is received;

$FN = 51 ((T3-T2) \bmod (26)) + T3 + 51 \times 26 \times T1$ when the synch burst is received, (where $T3 = (10 \times T3') + 1$, $T1$, $T2$ and $T3'$ being contained in information fields in synchronization burst).

- ii) For Compact, the MS can use the timing of receipt of the synchronization burst to set up its timebase counters as follows:

QN is set by the timing of the training sequence;

$FN = (R1 \times 51 + R2) \times 52 + 51$ when the synch burst is received (where $R1$ and $R2$ are contained in information fields in synchronization burst);

TN is determined from TG as described in 3GPP TS 45.002, where TG is contained in information fields in synchronization burst.

- iii) For CTS, the timebase counters are set as follows:

QN is set by the timing of the training sequence;

TN is set according to the CTSBCH-SB position (see Annex C);

$T4 = 51$ when the CTSBCH-SB is received (prior to attachment);

$FN = (51 ((T3-T2) \bmod (26)) + T3 + 51 \times 26 \times T1) \bmod (2715648)$ when the CTS-MS receives the last CTSAGCH burst of the non-hopping access procedure, where $T2 = T4 \bmod (26)$, and $T1$ and $T3$ being contained in this CTS immediate assignment message.

- iv) For EC-GSM-IoT, the MS can use the timing of receipt of the synchronization burst on EC-SCH to set up its timebase counters as follows:

QN is set by the timing of the training sequence;

$TN = 1$ when the synch burst is received

$FN = RFN_{QH} + 51 \times 26 \times 512 \times \text{QUARTER_HYPERFRAME_INDICATOR}$

where,

$RFN_{QH} = FN$ within a quarter hyperframe $= (51 \times 52 \times T1') + (4 \times 51 \times T2' + 51 \times T2'') + T3$ when the synch burst is received,

$T1'$, $T2'$ are contained in information fields in the synchronization burst, and,

$T2''$ is signalled through the cyclic shift pattern used on the EC-SCH, see 3GPP TS 45.003.

$T3$ is determined e.g. by the device through the identification of the mapping of the FCCH, or EC-SCH, onto the specific TDMA frames within the 51-multiframe.

$\text{QUARTER_HYPERFRAME_INDICATOR}$ is obtained in the immediate assignment, see 3GPP TS 44.018.

- NOTE: Depending on the coverage condition, the MS may optionally use the timing of receipt of the synchronization burst (SCH) to set up its timebase counters as described in i).

Thereafter, the timebase counters are incremented as in subclause 3.2.

(When adjacent BTS's are being monitored for handover purposes, or for cell reselection purposes in group receive mode, the MS may choose to store the values of QN , TN and FN for all the BTS's whose synchronization bursts have been detected relative to QN , TN and FN for its current serving BTS).