

ETSI TS 149 031 V14.4.0 (2020-04)



**Digital cellular telecommunications system (Phase 2+) (GSM);
Location Services (LCS);
Base Station System Application
Part LCS Extension (BSSAP-LE)
(3GPP TS 49.031 version 14.4.0 Release 14)**



ReferenceRTS/TSGR-0649031ve40

KeywordsGSM

ETSI

650 Route des Lucioles
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - NAF 742 C
Association à but non lucratif enregistrée à la
Sous-Préfecture de Grasse (06) N° 7803/88

Important notice

The present document can be downloaded from:
<http://www.etsi.org/standards-search>

The present document may be made available in electronic versions and/or in print. The content of any electronic and/or print versions of the present document shall not be modified without the prior written authorization of ETSI. In case of any existing or perceived difference in contents between such versions and/or in print, the prevailing version of an ETSI deliverable is the one made publicly available in PDF format at www.etsi.org/deliver.

Users of the present document should be aware that the document may be subject to revision or change of status. Information on the current status of this and other ETSI documents is available at <https://portal.etsi.org/TB/ETSIDeliverableStatus.aspx>

If you find errors in the present document, please send your comment to one of the following services:
<https://portal.etsi.org/People/CommiteeSupportStaff.aspx>

Copyright Notification

No part may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm except as authorized by written permission of ETSI.

The content of the PDF version shall not be modified without the written authorization of ETSI.

The copyright and the foregoing restriction extend to reproduction in all media.

© ETSI 2020.

All rights reserved.

DECT™, **PLUGTESTS™**, **UMTS™** and the ETSI logo are trademarks of ETSI registered for the benefit of its Members. **3GPP™** and **LTE™** are trademarks of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners.

oneM2M™ logo is a trademark of ETSI registered for the benefit of its Members and of the oneM2M Partners.

GSM® and the GSM logo are trademarks registered and owned by the GSM Association.

Intellectual Property Rights

Essential patents

IPRs essential or potentially essential to normative deliverables may have been declared to ETSI. The information pertaining to these essential IPRs, if any, is publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: "*Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards*", which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (<https://ipr.etsi.org/>).

Pursuant to the ETSI IPR Policy, no investigation, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

Trademarks

The present document may include trademarks and/or tradenames which are asserted and/or registered by their owners. ETSI claims no ownership of these except for any which are indicated as being the property of ETSI, and conveys no right to use or reproduce any trademark and/or tradename. Mention of those trademarks in the present document does not constitute an endorsement by ETSI of products, services or organizations associated with those trademarks.

Legal Notice

This Technical Specification (TS) has been produced by ETSI 3rd Generation Partnership Project (3GPP).

The present document may refer to technical specifications or reports using their 3GPP identities. These shall be interpreted as being references to the corresponding ETSI deliverables.

The cross reference between 3GPP and ETSI identities can be found under <http://webapp.etsi.org/key/queryform.asp>.

Modal verbs terminology

In the present document "**shall**", "**shall not**", "**should**", "**should not**", "**may**", "**need not**", "**will**", "**will not**", "**can**" and "**cannot**" are to be interpreted as described in clause 3.2 of the [ETSI Drafting Rules](#) (Verbal forms for the expression of provisions).

"**must**" and "**must not**" are **NOT** allowed in ETSI deliverables except when used in direct citation.

Contents

Intellectual Property Rights	2
Legal Notice	2
Modal verbs terminology.....	2
Foreword.....	7
1 Scope	8
2 References	8
3 Definitions, abbreviations and symbols	9
4 Definition of BSSAP-LE.....	9
4.1 DTAP-LE Messages.....	9
4.2 BSSMAP-LE Messages	10
5 Procedures applicable to use of BSSAP-LE.....	10
5.1 Location Request.....	10
5.1.1 Successful Operation	11
5.1.2 Unsuccessful Operation	12
5.1.3 Abnormal Conditions.....	12
5.1.4 Overload	12
5.2 Connection Oriented Information Transfer	13
5.2.1 Successful Operation	13
5.2.2 Abnormal Conditions.....	13
5.2.3 Segmentation	13
5.3 Connectionless Information Transfer	14
5.3.1 Successful Operation	14
5.3.2 Unsuccessful Operation	14
5.3.3 Abnormal Conditions.....	15
5.3.4 Segmentation	15
5.4 LMU Connection Establishment	15
5.4.1 LMU Connection Establishment initiated by the SMLC	15
5.4.1.1 Successful Operation.....	15
5.4.1.2 Unsuccessful Operation	16
5.4.1.3 Abnormal Conditions	16
5.4.2 LMU Connection Establishment initiated by the MSC	16
5.4.2.1 Successful Operation.....	16
5.4.2.2 Unsuccessful Operation	16
5.4.2.3 Abnormal Conditions	16
5.5 (void).....	17
5.6 DTAP-LE Information Transfer.....	17
5.6.1 DTAP-LE Information Transfer Initiated by the SMLC	17
5.6.2 DTAP-LE Information Transfer Initiated by the BSC.....	17
5.7 Reset.....	17
5.7.1 Normal Operation	17
5.7.2 Abnormal Conditions.....	17
5.8 Perform Location Information.....	18
6 Usage of BSSAP-LE and BSSAP on the Lb Interface.....	18
6.1 Applicable Message Sets.....	18
6.2 MTP Functions	19
6.3 SCCP Functions	19
6.3.1 General.....	19
6.3.2 Modifications for Connectionless SCCP	20
6.3.3 Modifications for Connection Oriented SCCP	20
6.3.4 Contents of the SCCP Data Field.....	20
6.3.5 Abnormal Conditions.....	21
7 (void).....	21

8	Use of BSSAP-LE on the Lp Interface.....	21
8.1	Applicable Message Sets.....	21
8.2	MTP Functions.....	21
8.3	SCCP functions.....	22
8.3.1	General.....	22
8.3.2	Allowed Exceptions to ITU-T Recommendations Q.711-714.....	22
8.3.3	Allowed Exceptions to ANSI T1.112.....	22
8.3.4	Usage of Connectionless SCCP.....	22
8.3.5	Usage of Connection Oriented SCCP.....	23
8.3.6	Contents of the SCCP Data Field.....	23
9	Message Functional Definitions and Contents.....	23
9.1	BSSMAP-LE PERFORM LOCATION REQUEST message.....	24
9.1.1	Location Type.....	24
9.1.2	Cell Identifier.....	24
9.1.3	Classmark Information Type 3.....	24
9.1.4	LCS Client Type.....	25
9.1.5	Chosen Channel.....	25
9.1.6	LCS Priority.....	25
9.1.6a	LCS QoS.....	25
9.1.7	Requested GPS Assistance Data.....	25
9.1.8	BSSLAP APDU.....	25
9.1.9	LCS Capability.....	25
9.1.10	Packet Measurement Report.....	25
9.1.11	Measured Cell Identity List.....	25
9.1.12	IMSI.....	25
9.1.13	IMEI.....	25
9.1.14	GANSS Location Type.....	25
9.1.15	Requested GANSS Assistance Data.....	26
9.1.16	BSS Multilateration Capability.....	26
9.1.17	Multilateration Timing Advance.....	26
9.1.18	MS Sync Accuracy.....	26
9.1.19	BTS Reception Accuracy Level.....	26
9.1.20	Coverage Class.....	26
9.2	BSSMAP-LE PERFORM LOCATION RESPONSE message.....	26
9.2.1	Location Estimate.....	26
9.2.2	Positioning Data.....	26
9.2.3	Deciphering Keys.....	27
9.2.4	LCS Cause.....	27
9.2.5	Velocity Data.....	27
9.2.6	GANSS Positioning Data.....	27
9.3	BSSMAP-LE PERFORM LOCATION ABORT message.....	27
9.3.1	LCS Cause.....	27
9.4	(void).....	28
9.5	(void).....	28
9.6	(void).....	28
9.7	(void).....	28
9.8	BSSMAP-LE CONNECTION ORIENTED INFORMATION message.....	28
9.8.1	BSSLAP APDU.....	28
9.8.2	Segmentation.....	28
9.8.3	Multilateration Positioning Method.....	29
9.8.4	Cell Identifier.....	29
9.8.5	Multilateration Timing Advance.....	29
9.8.6	MS Sync Accuracy.....	29
9.8.7	BTS Reception Accuracy Level.....	29
9.8.8	Short ID.....	29
9.8.9	Random ID.....	29
9.9	BSSMAP-LE CONNECTIONLESS INFORMATION message.....	29
9.9.1	Source Identity.....	30
9.9.2	Destination Identity.....	30
9.9.3	APDU.....	30
9.9.4	Segmentation.....	30

9.9.5	Return Error Request	30
9.9.6	Return Error Cause	30
9.10	BSSMAP-LE RESET message	30
9.11	BSSMAP-LE RESET ACKNOWLEDGE message	31
9.12	BSSMAP-LE PERFORM LOCATION INFORMATION message	31
9.12.1	Cell Identifier	31
9.12.2	BSSLAP APDU	31
9.13	BSSMAP-LE ASSISTANCE INFORMATION REQUEST message	31
9.13.1	Serving Cell Identifier	32
9.13.2	Cell Identity List	32
9.13.3	Short ID Set	32
9.13.4	Random ID Set	32
9.14	BSSMAP-LE ASSISTANCE INFORMATION RESPONSE message	32
9.14.1	Cell Information List	32
9.14.2	Short BSS ID	32
10	Message format and information element coding	33
10.1	Message type	33
10.2	Information Element Identifiers	34
10.3	APDU	34
10.4	Cause	35
10.5	Cell Identifier	35
10.6	Chosen Channel	35
10.7	Classmark Information Type 3	36
10.8	Deciphering Keys	36
10.9	Geographic Location	36
10.10	Requested GPS Assistance Data	37
10.11	IMSI	39
10.12	(void)	39
10.13	LCS Cause	39
10.14	LCS Client Type	40
10.15	LCS Priority	41
10.16	LCS QoS	41
10.17	(void)	42
10.18	Location Type	42
10.19	Network Element Identity	43
10.20	Positioning Data	44
10.21	Return Error Request	45
10.22	Return Error Cause	45
10.23	(void)	46
10.24	Segmentation	46
10.25	(void)	47
10.26	LCS Capability	47
10.27	Packet Measurement Report	47
10.28	Cell Identity List	47
10.29	IMEI	48
10.30	Velocity Data	48
10.31	Requested GANSS Assistance Data	48
10.32	GANSS Positioning Data	55
10.33	GANSS Location Type	55
10.34	BSS Multilateration Capability IE	56
10.35	Cell Information List IE	56
10.36	BTS Reception Accuracy Level IE	60
10.37	Multilateration Positioning Method IE	62
10.38	Multilateration Timing Advance IE	63
10.39	MS Sync Accuracy IE	63
10.40	Short ID Set IE	64
10.41	Random ID Set	64
10.42	Short BSS ID IE	65
10.43	Random ID	65
10.44	Short ID IE	65
10.45	Coverage Class IE	65

Annex A (informative): **Change history**67
History68

iTeh STANDARD PREVIEW
(standards.iteh.ai)
Full standard:
<https://standards.iteh.ai/catalog/standards/sist/c0d3d582-45d3-441b-bb9f-d3d1d0c44d0b/etsi-ts-149-031-v14.4.0-2020-04>

Foreword

This Technical Specification has been produced by the 3rd Generation Partnership Project (3GPP).

The present document defines the coding of information in an extension of the Base Station System Application Part (BSSAP) that is needed to support location services on interfaces based on use of BSSAP.

The contents of the present document are subject to continuing work within the TSG and may change following formal TSG approval. Should the TSG modify the contents of the present document, it will be re-released by the TSG with an identifying change of release date and an increase in version number as follows:

Version x.y.z

where:

- x the first digit:
 - 1 presented to TSG for information;
 - 2 presented to TSG for approval;
 - 3 or greater indicates TSG approved document under change control.
- y the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- z the third digit is incremented when editorial only changes have been incorporated in the document.

iTeh STANDARD PREVIEW
(standards.iteh.ai)
Full standard:
<https://standards.iteh.ai/catalog/standards/sist/c0d35582-45d3-441b-bb9f-d3d1d0c44d0b/etsi-ts-149-031-v14.4.0-2020-04>

1 Scope

The present document specifies procedures and information coding that are needed to define and support the BSSAP LCS Extension (BSSAP-LE). The BSSAP-LE message set is applicable to the following GSM interfaces defined in 3GPP TS 43.059:

- Lb interface (BSC-SMLC).
- Lp interface (SMLC-SMLC).

The present document defines message formats and encoding for BSSAP-LE and the particular subsets of it that are applicable to each of the above interfaces. The present document also defines the support for BSSAP-LE message transfer on each of these interfaces using either ITU-T and ANSI versions of SS7 MTP or IETF M3UA/SCTP and SCCP. Additional requirements for the above interfaces that are applicable to BSSAP-LE are also defined – e.g. usage of BSSAP (as defined in 3GPP TS 24.008 and 48.008) on the Lb interface.

2 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- References are either specific (identified by date of publication, edition number, version number, etc.) or non-specific.
- For a specific reference, subsequent revisions do not apply.
- For a non-specific reference, the latest version applies. In the case of a reference to a 3GPP document (including a GSM document), a non-specific reference implicitly refers to the latest version of that document *in the same Release as the present document*.

- [1] 3GPP TR 21.905: "Vocabulary for 3GPP Specifications".
- [1a] 3GPP TS 23.032: "Universal Geographical Area Description (GAD)".
- [2] 3GPP TS 43.059: "Functional Stage 2 Description of Location Services in GERAN".
- [3] 3GPP TS 44.018: "Mobile radio interface layer 3 specification; Radio Resource Control Protocol".
- [3a] 3GPP TS 24.008: "Mobile radio interface layer 3 specification; Core Network Protocols; Stage 3".
- [4] 3GPP TS 44.031: "Location Services (LCS); Mobile Station (MS) – Serving Mobile Location Center (SMLC); Radio Resource LCS Protocol (RRLP)".
- [5] 3GPP TS 44.071: "Location Services (LCS); Mobile radio interface layer 3 Location Services (LCS) specification".
- [6] 3GPP TS 48.006: "Signaling transport mechanism specification for the Base Station Subsystem – Mobile-services Switching Centre (BSS - MSC) interface".
- [7] 3GPP TS 48.008: "Mobile-services Switching Centre – Base Station System (MSC-BSS) interface; Layer 3 specification".
- [8] 3GPP TS 48.031: "Location Services (LCS); Serving Mobile Location Center – Serving Mobile Location Center (SMLC - SMLC); SMLCPP specification".
- [9] 3GPP TS 48.071: "Serving Mobile Location Center – Base Station Subsystem (SMLC-BSS) interface Layer 3 specification".
- [10] 3GPP TS 29.002: "Mobile Application Part (MAP) specification".
- [10a] 3GPP TS 23.003: "Numbering, addressing and identification".
- [11] ITU-T Recommendation Q.702: "Signalling data link".

- [12] ITU-T Recommendation Q.703: "Signalling link".
- [13] ITU-T Recommendation Q.704: "Signalling network functions and messages".
- [14] ITU-T Recommendation Q.707: "Testing and maintenance".
- [15] ITU-T Recommendation Q.711: "Functional description of the signalling connection control part".
- [16] ITU-T Recommendation Q.712: "Definition and function of signalling connection control part messages".
- [17] ITU-T Recommendation Q.713: "Signalling connection control part formats and codes".
- [18] ITU-T Recommendation Q.714: "Signalling connection control part procedures".
- [19] ANSI T1.111 (1996): "Signalling System Number 7 – Message Transfer Part".
- [20] ANSI T1.112 (1996): "Signalling System Number 7 (SS7) - Signalling Connection Control Part Functional Description".
- [21] TIA/EIA/IS-J-STD-036 (2000): "Wireless Enhanced Emergency Services".
- [22] 3GPP TS 48.018: "General Packet Radio Service (GPRS); Base Station System (BSS) - Serving GPRS Support Node (SGSN); BSS GPRS Protocol (BSSGP)".
- [23] IETF STD 51, RFC 1661(07/1994): "The Point-To-Point Protocol (PPP)".
- [24] IETF STD 51, RFC 1662(07/1994): "PPP in HDLC-like Framing".
- [25] IETF RFC 2507(02/1999): "IP header compression".
- [26] IETF RFC 1990(07/1994): "The PPP Multilink Protocol (MP)".
- [27] IETF RFC 2686(09/1999): "The Multi-Class Extension to Multi-Link PPP".
- [28] IETF RFC 2509(02/1999): "IP Header Compression over PPP".
- [29] 3GPP TS 29.202: "SS7 Signalling Transport in Core Network; Stage 3".
- [30] Galileo OS SIS ICD/D.0 "Galileo Open Service, Signal In Space Interface Control Document/Draft 0".
- [31] Global Navigation Satellite System GLONASS Interface Control Document, Version 5, 2002.
- [32] BDS-SIS-ICD-B1I-1.0: "BeiDou Navigation Satellite System Signal In Space Interface Control Document Open Service Signal B1I (Version 1.0)", December 2012.

3 Definitions, abbreviations and symbols

For the purposes of the present document, the definitions, symbols and abbreviations listed in 3GPP TS 21.905 and 3GPP TS 43.059 apply.

4 Definition of BSSAP-LE

BSSAP-LE is an extension to BSSAP that contains messages and parameters specific to the support of LCS. The following subsets of BSSAP-LE are defined: DTAP-LE, BSSMAP-LE.

4.1 DTAP-LE Messages

DTAP-LE messages are transferred between an SMLC and a Type A LMU and comprise the following individual messages:

- REGISTER;
- FACILITY;
- RELEASE COMPLETE.

The content, encoding and certain procedures associated with DTAP-LE messages are defined in 3GPP TS 44.071.

4.2 BSSMAP-LE Messages

BSSMAP-LE messages are transferred between a BSS and SMLC and comprise the following individual messages:

BSSMAP-LE Positioning Messages:

- Perform Location Request;
- Perform Location Response;
- Perform Location Abort;
- Perform Location Information.

BSSMAP-LE Information Messages:

- Connection Oriented Information;
- Connectionless Information.

BSSMAP-LE General Messages:

- Reset;
- Reset Acknowledge.

The content and encoding of BSSMAP-LE messages are defined in the present document.

5 Procedures applicable to use of BSSAP-LE

5.1 Location Request

The Location Request procedure is applicable to the Lb interface. Its purpose is to obtain a location estimate for a target MS that is already in dedicated mode, in packet transfer mode, in packet idle mode, or in dual transfer mode. It is also used to provide an MS with LCS assistance data or with a deciphering key for LCS broadcast assistance data. The initiator of a location request is the BSS. The procedure makes use of SCCP connection oriented signaling on the Lb interface.

5.1.1 Successful Operation

The initiator of the location request sends a BSSMAP-LE Perform Location Request to the SMLC associated with the current serving cell for the target MS. The message contains the following mandatory (M), conditional (C) and optional (O) information, where conditional parameters are required if available.

- Location Type (M).
- GANSS Location Type (C)
- Cell Identifier (M).
- Classmark Information Type 3 (C).
- LCS Client Type (C).
- Chosen Channel (C).
- LCS Priority (C).
- LCS QoS (C).
- Requested GPS Assistance Data (C).
- BSSLAP APDU (C).
- LCS Capability (O).
- Packet Measurement Report (O).
- Measured Cell Identity List (O).
- IMSI of target MS (O).
- IMEI of target MS (O).
- Requested GANSS Assistance Data (C).

If requested, the SMLC performs positioning of the target MS using a particular position method or a combination of more than one positioning method. If neither the Classmark Information Type 3 IE nor the LCS Capability IE is present, the SMLC shall instigate only network based positioning methods (e.g. TA and U-TDOA but not GPS or E-OTD).

Alternatively, if requested otherwise, the SMLC may provide positioning assistance data to the MS. The SMLC may invoke the following other BSSAP-LE procedures to perform these procedures:

- connection oriented information transfer;
- connectionless information transfer;
- LMU connection establishment;
- LMU connection release;
- DTAP-LE information transfer.

Additional procedures defined in 3GPP TS 24.008 and 3GPP TS 48.008 may also be performed. If a location estimate was requested and was subsequently obtained, the SMLC shall return a BSSMAP-LE Perform Location Response to the initiator of the location request. This message contains the following mandatory, conditional and optional parameters.

- Location Estimate (M).
- Positioning Data (C).
- GANSS Positioning Data (C).

Restrictions on the geographic shape encoded within the Location Estimate parameter may exist for certain LCS client types. The SMLC shall comply with any restrictions defined in 3GPP specifications and, in a particular country, with any restrictions defined for a specific LCS client type in relevant national standards. For example, in the US, national

interim standard TIA/EIA/IS-J-STD-036 [21] restricts the geographic shape for an emergency services LCS client to minimally either an "ellipsoid point" or an "ellipsoid point with uncertainty circle and confidence" as defined in 3GPP TS 23.032.

If assistance data was instead requested for an MS and the SMLC was able successfully to transfer this to the MS, the SMLC shall return a BSSMAP-LE Perform Location Response to the initiator of the location request (serving BSC). This message shall contain no parameters. The absence of an LCS Cause parameter in this case implies that the transfer was successful.

Otherwise, if a deciphering key was requested for LCS broadcast assistance data and the SMLC has access to the appropriate keys, the SMLC shall return a BSSMAP-LE Perform Location Response to the initiator of the location request. This message contains the following mandatory parameters.

- Deciphering Keys (M).

5.1.2 Unsuccessful Operation

If the SMLC is unable to obtain any of the location information requested or if requested LCS assistance data could not be transferred or requested deciphering keys for broadcast assistance data could not be returned, the SMLC shall return a BSSMAP-LE Perform Location Response to the initiator of the Location Request carrying the following parameters:

- LCS Cause (M);
- Positioning Data (O).
- GANSS Positioning Data (O).

If assistance data or deciphering keys for a specific positioning method is not supported in the network or in the location area, the SMLC shall indicate this with LCS Cause value "Position method failure" accompanied with diagnostic value "Position Method Not Available in Network" or "Position Method Not Available in Location Area".

5.1.3 Abnormal Conditions

If an ongoing location request is preempted at the initiator by an inter-BSC handover or if the main signaling link to the target MS is lost or released or if there is a timeout waiting for the positioning response, or if there is an Inter NSE cell change in the PS Domain (e.g. detected by the BSS at receipt of BSSGP FLUSH-LL PDU) for which the BSS is unable to maintain the positioning procedure, the initiator shall send a BSSMAP-LE Perform Location Abort to the SMLC containing the following parameters.

- LCS Cause (M).

On receipt of this message, the SMLC shall stop positioning of the target MS and may release any resources (e.g. LMUs) previously allocated. If the SMLC has not yet returned a BSSMAP-LE Perform Location Response to the initiator, it shall return this message containing an LCS Cause indicating an abort and, optionally, positioning data, GANSS positioning data. The initiator shall then release the SCCP connection. If the SMLC cannot proceed with positioning due to some protocol violation or error condition (e.g. inter-BSC handover indication received from the serving BSC), it shall return a BSSMAP-LE Perform Location Response to the initiator containing an LCS cause and, optionally, positioning data, GANSS positioning data. The initiator need not reply at the BSSAP-LE level to this message. However, the initiator may return a BSSMAP-LE perform Location Abort which shall not be treated as an error by the SMLC.

5.1.4 Overload

If the SMLC is in an overload condition, it may reject a BSSMAP-LE Perform Location request by returning a BSSMAP-LE Perform Location response containing an LCS Cause parameter indicating congestion. The initiator of the location service request (BSC) may reduce the frequency of future location service requests until rejection due to overload has ceased. In reducing the frequency of location service requests, a BSC shall reduce lower priority requests, to zero if necessary, before reducing the frequency of higher priority requests. An SMLC shall similarly reject location service requests of a lower priority, to zero if necessary, due to overload before rejecting location service requests of a higher priority. An SMLC in an overload condition may optionally employ the following procedures to alleviate overload: