INTERNATIONAL STANDARD

ISO/IEC 10373-6

Second edition 2011-01-15

AMENDMENT 4 2012-12-15

Identification cards — Test methods —

Part 6: Proximity cards

AMENDMENT 4: Bit rates of fc/8, fc/4 and fc/2 and frame size from 512 to 4096 bytes **iTeh STANDARD PREVIEW**

Cartes d'identification — Méthodes d'essai —

Partie 6: Cartes de proximité

ISAMENDEMENT 4: Debits binaires de fc/8, fc/4 et fc/2 et tailles de trame https://standards.iteh.allano.det512rd=4096 octets-e781-4a81-b305-8d33c94226d4/iso-iec-10373-6-2011-amd-4-2012



Reference number ISO/IEC 10373-6:2011/Amd.4:2012(E)

iTeh STANDARD PREVIEW (standards.iteh.ai)

ISO/IEC 10373-6:2011/Amd 4:2012 https://standards.iteh.ai/catalog/standards/sist/647d198c-e781-4a81-b305-8d33c94226d4/iso-iec-10373-6-2011-amd-4-2012



© ISO/IEC 2012

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either ISO at the address below or ISO's member body in the country of the requester.

ISO copyright office Case postale 56 • CH-1211 Geneva 20 Tel. + 41 22 749 01 11 Fax + 41 22 749 09 47 E-mail copyright@iso.org Web www.iso.org

Published in Switzerland

Foreword

ISO (the International Organization for Standardization) and IEC (the International Electrotechnical Commission) form the specialized system for worldwide standardization. National bodies that are members of ISO or IEC participate in the development of International Standards through technical committees established by the respective organization to deal with particular fields of technical activity. ISO and IEC technical committees collaborate in fields of mutual interest. Other international organizations, governmental and non-governmental, in liaison with ISO and IEC, also take part in the work. In the field of information technology, ISO and IEC have established a joint technical committee, ISO/IEC JTC 1.

International Standards are drafted in accordance with the rules given in the ISO/IEC Directives, Part 2.

The main task of the joint technical committee is to prepare International Standards. Draft International Standards adopted by the joint technical committee are circulated to national bodies for voting. Publication as an International Standard requires approval by at least 75 % of the national bodies casting a vote.

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. ISO and IEC shall not be held responsible for identifying any or all such patent rights.

Amendment 4 to ISO/IEC 10373-6:2011 was prepared by Joint Technical Committee ISO/IEC JTC 1, *Information technology*, Subcommittee SC 17, Cards and personal identification.

(standards.iteh.ai)

ISO/IEC 10373-6:2011/Amd 4:2012 https://standards.iteh.ai/catalog/standards/sist/647d198c-e781-4a81-b305-8d33c94226d4/iso-iec-10373-6-2011-amd-4-2012

iTeh STANDARD PREVIEW (standards.iteh.ai)

ISO/IEC 10373-6:2011/Amd 4:2012 https://standards.iteh.ai/catalog/standards/sist/647d198c-e781-4a81-b305-8d33c94226d4/iso-iec-10373-6-2011-amd-4-2012

Identification cards — Test methods —

Part 6: Proximity cards

AMENDMENT 4: Bit rates of fc/8, fc/4 and fc/2 and frame size from 512 to 4096 bytes

Page 10, Figure 5

Replace component "C3" in Figure 5 with the following:





Add the following two paragraphs at the end of 5.4.2:

"Position 'a' of J2 shall be used for testing bit rates of *fc*/128, *fc*/64, *fc*/32 and *fc*/16.

Position 'b' of J2 shall be used for testing bit rates of fc/8, fc/4 and fc/2."

Page 16, 7.1.4.1

Replace paragraph with the following:

"This test is used to determine the index of modulation of the PCD field as well as the rise and fall times and the overshoot values as defined in ISO/IEC 14443-2 for all supported PCD to PICC bit rates."

Page 17, 7.1.4.2

Replace step g) with the following:

g) Repeat steps c) to f) for various positions within the operating volume and all supported PCD to PICC bit rates.

Page 17, 7.1.5.1

Replace paragraph with the following:

"This test is used to verify that a PCD correctly detects the load modulation of a PICC which conforms to ISO/IEC 14443-2 for PICC to PCD bit rates of *fc*/128, *fc*/8, *fc*/4 and *fc*/2, if supported."

Page 17, 7.1.5.2

Replace step h) with the following:

h) Repeat steps b) to g) for various positions within the operating volume for PICC to PCD bit rates of *fc*/128, *fc*/8, *fc*/4 and *fc*/2, if supported.

Page 18, 7.2.1.1

Delete NOTE and replace first sentence of paragraph with the following:

"The purpose of this test is to determine the load modulation amplitude V_{LMA} of the PICC within the operating field range [H_{min} , H_{max}] as specified in ISO/IEC 14443-2 for PICC to PCD bit rates of *fc*/128, *fc*/8, *fc*/4 and *fc*/2, if supported."

iTeh STANDARD PREVIEW (standards.iteh.ai)

Page 18, 7.2.1.2

ISO/IEC 10373-6:2011/Amd 4:2012

Replace second paragraph of Step 2 with the following and ards/sist/647d198c-e781-4a81-b305-

8d33c94226d4/iso-iec-10373-6-2011-amd-4-2012

"A REQA or a REQB command sequence as defined in ISO/IEC 14443-3 shall be sent by the Test PCD to obtain a signal or load modulation response from the PICC when testing PICC transmission at a bit rate of *fc*/128. An S(PARAMETERS) sequence as defined in ISO/IEC 14443-4 and an I-block shall be sent by the Test PCD to obtain a signal or load modulation response from the PICC when testing optional PICC transmission bit rates of *fc*/8, *fc*/4 and *fc*/2."

Add Note 1 after second paragraph of Step 2 and renumber subsequent Notes:

"NOTE 1 No load modulation test is required for bit rates of *fc*/64, *fc*/32 and *fc*/16 because these bit rates use the same subcarrier frequency of *fc*/128."

Page 19, 7.2.2.2

Replace 7.2.2.2 heading text with the following:

"PICC Type A for bit rates of *fc*/128, *fc*/64, *fc*/32 and *fc*/16"

Page 20, 7.2.2.3

Replace 7.2.2.3 heading text with the following:

"PICC Type B for bit rates of fc/128, fc/64, fc/32 and fc/16"

Page 20, 7.2.2.3.1

Replace first paragraph with the following:

"Three test conditions are defined with timings at the border of the PICC modulation waveform timing parameters zone defined in ISO/IEC 14443-2, 9.1.2:"

Replace last dash text with the following:

— minimum and maximum modulation index *m* for the associated field strength applied (see ISO/IEC 14443-2, 9.1.2).

Page 20, 7.2.2.3.2

Replace second, third and fourth paragraph with the following:

"For each optional PCD to PICC bit rate supported by the PICC, the PICC shall operate under the conditions defined in 7.2.2.3.1 after selection of that optional bit rate. This PICC shall respond correctly to an I-block transmitted at that optional bit rate."

Page 20 **iTeh STANDARD PREVIEW** Renumber existing subclause 7.2.2.4 to 7.2.2.5 and add new subclause 7.2.2.4: **istandards.iten.al** 7.2.2.4 PICC Type A or Type B for bit rates of fc/8, fc/4 and fc/2

 ISO/IEC 10373-6:2011/Amd 4:2012

 See 7.2.2.3.
 https://standards.iteh.ai/catalog/standards/sist/647d198c-e781-4a81-b305-8d33c94226d4/iso-iec-10373-6-2011-amd-4-2012

Page 23, Annex A

Replace all occurrences of "for bit rates of fc/64, fc/32 and fc/16" with "for bit rates higher than fc/128".

Page 27, Table A.1

Replace "From *fc*/128 to *fc*/16" with "All bit rates".

Page 34

Add new subclause E.2.1 and move second sentence of E.2 and Figure E.2 to this subclause:

E.2.1 Sampling for bit rates of fc/128, fc/64, fc/32 and fc/16

ISO/IEC 10373-6:2011/Amd.4:2012(E)

Page 35

Add new subclause E.2.2:

E.2.2 Sampling for bit rates of fc/8, fc/4 and fc/2

The time and voltage data of a PCD frame containing short and long modulation pulses (preferably a complete S(DESELECT) command) as illustrated in Figure E.3, with at least 20 carrier periods before the first and after the last modulation pulse, shall be transferred to a suitable computer.



Figure E.3 — Modulation pulses

Page 35

Add new subclause E.3.1 and move existing paragraph of E.3 and Figure E.3 to this subclause:

E.3.1 Filtering for bit rates of fc/128, fc/64, fc/32 and fc/16

Page 35

Add new subclause E.3.2:

E.3.2 Filtering for bit rates of *fc*/8, *fc*/4 and *fc*/2

A 4th order, Butterworth type band pass filter with center frequency of 13,56 MHz and 15 MHz 3-dB bandwidth shall be used for filtering the DC and higher harmonic components.

Page 36

Add new subclause E.5.1 and move existing paragraph of E.5 and Figure E.4 to this subclause:

E.5.1 Envelope smoothing for bit rates of fc/128, fc/64, fc/32 and fc/16

Page 36

Add new subclause E.5.2:

E.5.2 Envelope smoothing for bit rates of fc/8, fc/4 and fc/2

No smoothing of signal envelope shall be applied.

Page 36, E.6

Add the following paragraph and figure after the paragraph:

For bit rates of fc/8, fc/4 and fc/2 the minimum value of modulation index *m* shall be determined within the complete PCD frame (see Figure E.5.). The PCD frame shall contain (10101010)b.



Figure E.5 — Minimum value of modulation index m

Page 36, E.7

Add at the end of paragraph:

For bit rates of fc/8, fc/4 and fc/2 the timings shall be determined at positions with long modulation pulse positions e.g. t_f at transition to SOF low and t_r at transition to EOF high.

ISO/IEC 10373-6:2011/Amd.4:2012(E)

Page 38

Add after line "double b; //Type B":

"double bVHBR; //Bit rates of fc/8, fc/4 and fc/2"

Page 53

Replace function "createtime" with:

"void createtime(TIMES *new, double tr, double tf, double b, double bVHBR, double trstartind, double trendind, double tfstartind, double tfendind, double t1, double t1startind, double t1start, double t1endind, double t2, double t2startind, double t3, double t3end, double t3endind, double t4, double t4endind, double t5, double t5startind, double t6, double t6end, double t6endind, double t9"

Add after line "new->b=b;":

"new->bVHBR=bVHBR;"

```
Page 59
```

iTeh STANDARD PREVIEW (standards.iteh.ai)

```
Add following function:
```

// Finds the value of m_min for $hit_{rates_3050fc/8} 4fc/4$ and fc/2https://standards.iteh.ai/catalog/standards/sist/647d198c-e781-4a81-b305-void Mminfinder(double *env_{8d}double_dHmax_c_double_dHmax_c_double *HmaxVHBR, TIMES *timeres, int numsamples) { int i=0; int j=0; double compare hi=0.0; double compare lo=0.0; double compare=0.0; double difference=0.0; int going up=0; double ampl=0.0; double ampl max=0.0; // represents the amplitude (Hmax-b), and indirectly "m". double m deviation=0.0; // countermeasure 1: m min < 0.2*m is not considered // countermeasure 2: m min does not start or end on double Hmax cm=0.0; borders double b cm=0.0; double mmin=0.0; double mmin cum=0.0; // Skip all zeros while (env[j]==0) j++; // where do we start? difference=env[j]-env[j+1]; if (difference<0)

```
{
      going up=1; // going up
      compare_lo=env[j];
   }
   else if (difference>0)
   {
      going up=0; // going down
      compare hi=env[j];
   }
   compare=env[j];
   ampl max=(Hmax-Hmin);
   m deviation=ampl max*0.2;
   Hmax cm=Hmax*0.95;
   b cm=Hmin*1.05;
   timeres->bVHBR=0;
   for (i=j; i<=numsamples-j; i++)</pre>
   {
      if (going up==0) // GOING DOWN
       {
          if (compare>=env[i])
          {
             compare=env[i];
          }
          else if (compare < en [1] DARD PREVIEW
          {
             compare=env[{standards.iteh.ai)
compare_lo=env[i];
             going_up=1; // change direction
             mm1111=/(amp11/s(tebmpatelenterdertheat/64711380*1760-4a81-b305-
             if (ampl 3 deviation we ampl < ampl and 20 2 (compare hi< Hmax cm ||
compare lo>b cm))
                  //Countermeasures
              {
                 *HmaxVHBR=compare hi;
                 timeres->bVHBR=compare lo;
                 ampl max=ampl;
              }
          }
       }
      if (going up==1) // GOING UP
       {
          if (compare<=env[i])</pre>
          {
             compare=env[i];
          }
          else if (compare>env[i])
          {
             compare=env[i];
             compare hi=env[i];
             going up=0; // change direction
             ampl=(compare hi-compare lo);
             mmin=(ampl/(compare hi+compare_lo))*100;
             if (ampl>m deviation && ampl<ampl max && (compare hi<Hmax cm ||
compare_lo>b_cm)) //Countermeasures
              {
                 *HmaxVHBR=compare hi;
                 timeres->bVHBR=compare lo;
                 ampl max=ampl;
```

```
mmin_cum=mmin;
}

}
if (*HmaxVHBR==0 || timeres->bVHBR==0) // in case Waveform has only two
levels (typical 1M7) Mmin=M
{
 *HmaxVHBR=Hmax;
 timeres->bVHBR=Hmin;
}
```

Page 59

Replace function "envfilt" with the following:

int envfilt(int rate, double *output, double *toutput, int filterlength, double tini, double tend, int lengthp, double *envelope)

Page 60

iTeh STANDARD PREVIEW Replace line "LinearConvolution(cof, output, envelope, lengthf, lengthp);" with the following: (standards.iteh.ai)

Page 62

Add in function "tfinder" after line " int i=0;" the following:

```
double *toutput2=NULL;
int counter=0;
int rev_counter=0;
int VHBR_step=0;
double VHBR_tr=0.0;
double VHBR_tf=0.0;
double tr_accum=0.0;
```