
**Elektromagnetna združljivost (EMC) in zadeve v zvezi z radijskim spektrom (ERM) -
Izboljšanje zvezdastih merilnih metod (z uporabo merilnih mest) in ovrednotenje
ustreznih merilnih negotovosti - 3. del: Neodmevna komora z referenčno
ozemljilno ravnino**

ElectroMagnetic Compatibility and Radio Spectrum Matters (ERM); Improvement of
radiated methods of measurement (using test sites) and evaluation of the corresponding
measurement uncertainties; Part 3: Anechoic chamber with a ground plane

iTeh STANDARD PREVIEW
(standards.iteh.ai)

[PSIST ETR 273-3:1999](https://standards.iteh.ai/catalog/standards/sist/d2b60bac-46a8-4bbc-970a-b3b0e316b896/psist-etr-273-3-1999)

[https://standards.iteh.ai/catalog/standards/sist/d2b60bac-46a8-4bbc-970a-
b3b0e316b896/psist-etr-273-3-1999](https://standards.iteh.ai/catalog/standards/sist/d2b60bac-46a8-4bbc-970a-b3b0e316b896/psist-etr-273-3-1999)

Ta slovenski standard je istoveten z: ETR 273-3 Edition 1

ICS:

33.060.01	Radijske komunikacije na splošno	Radiocommunications in general
33.100.01	Elektromagnetna združljivost na splošno	Electromagnetic compatibility in general

PSIST ETR 273-3:1999

en

iTeh STANDARD PREVIEW
(standards.iteh.ai)

[PSIST ETR 273-3:1999](#)

<https://standards.iteh.ai/catalog/standards/sist/d2b60bac-46a8-4bbc-970a-b3b0e316b896/psist-etr-273-3-1999>



ETSI
TECHNICAL
REPORT

ETR 273-3

February 1998

Source: ERM

Reference: DTR/ERM-RP01-018-3

ICS: 33.020

Key words: Analogue, data, measurement uncertainty, mobile, radio, testing

**Electromagnetic compatibility
and Radio spectrum Matters (ERM);
Improvement of radiated methods of
measurement (using test sites) and
evaluation of the corresponding
measurement uncertainties;
Part 3: Anechoic chamber with a ground plane**

ETSI

European Telecommunications Standards Institute

ETSI Secretariat

Postal address: F-06921 Sophia-Antipolis CEDEX - FRANCE

Office address: 650 Route des Lucioles - Sophia Antipolis - Valbonne - FRANCE

X.400: c=fr, a=atlas, p=etsi, s=secretariat - **Internet:** secretariat@etsi.fr

Tel.: +33 4 92 94 42 00 - Fax: +33 4 93 65 47 16

Copyright Notification: No part may be reproduced except as authorized by written permission. The copyright and the foregoing restriction extend to reproduction in all media.

© European Telecommunications Standards Institute 1998. All rights reserved.

iTeh STANDARD PREVIEW (standards.iteh.ai)

[PSIST ETR 273-3:1999](https://standards.iteh.ai/catalog/standards/sist/d2b60bac-46a8-4bbc-970a-b3b0e316b896/psist-etr-273-3-1999)

<https://standards.iteh.ai/catalog/standards/sist/d2b60bac-46a8-4bbc-970a-b3b0e316b896/psist-etr-273-3-1999>

Contents

Foreword	7
1 Scope	9
2 References	9
3 Definitions, symbols and abbreviations	10
3.1 Definitions	10
3.2 Symbols	14
3.3 Abbreviations	16
4 Introduction	17
5 Uncertainty contributions specific to an anechoic chamber with a ground plane	18
5.1 Effects of the metal shielding	18
5.1.1 Resonances	18
5.1.2 Imaging of antennas (or an EUT)	19
5.2 Effects of the radio absorbing materials	20
5.2.1 Introduction	20
5.2.2 Pyramidal absorbers	20
5.2.3 Wedge absorbers	22
5.2.4 Ferrite tiles	22
5.2.5 Ferrite grids	23
5.2.6 Urethane/ferrite hybrids	23
5.2.7 Performance comparison	23
5.2.8 Reflection in an anechoic chamber with a ground plane	25
5.2.9 Mutual coupling due to imaging in the absorbing material	27
5.2.10 Extraneous reflections	28
5.3 Effects of the ground plane	28
5.3.1 Reflections	28
5.3.2 Mutual coupling between antennas and in the ground plane	29
5.4 Other effects	33
5.4.1 Range length and measurement distance	33
5.4.2 Antenna mast, turntable and mounting fixtures	35
5.4.3 Test antenna height limitations	36
5.4.4 Test antenna cabling	37
5.4.5 EUT cabling	37
5.4.6 Positioning of the EUT and antennas	38
6 Verification procedure for an anechoic chamber with a ground plane	38
6.1 Introduction	38
6.2 Normalized site attenuation	39
6.2.1 Anechoic chamber	40
6.2.2 Anechoic chamber with a ground plane	41
6.2.3 Improvements to the formulae for EDH^{\max} and EDV^{\max}	44
6.2.4 Mutual coupling	46
6.3 Overview of the verification procedure	47
6.3.1 Apparatus required	48
6.3.2 Site preparation	49
6.3.3 Measurement configuration	49
6.3.4 What to record	51
6.4 Verification procedure	52
6.4.1 Procedure 1: 30 MHz to 1 000 MHz	52
6.4.2 Alternative procedure: 30 MHz to 1 000 MHz	58

6.4.3	Procedure 2: 1 GHz to 12,75 GHz.....	59
6.5	Processing the results of the verification procedure	64
6.5.1	Introduction	64
6.5.2	Procedure 1: 30 MHz to 1 000 MHz	64
6.5.3	Procedure 2: 1 GHz to 12,75 GHz.....	69
6.5.4	Report format.....	72
6.6	Calculation of measurement uncertainty (Procedure 1)	72
6.6.1	Uncertainty contribution, direct attenuation measurement	73
6.6.2	Uncertainty contribution, NSA measurement.....	74
6.6.3	Expanded uncertainty of the verification procedure	75
6.7	Calculation of measurement uncertainty (Procedure 2)	76
6.7.1	Uncertainty contribution, direct attenuation measurement	76
6.7.2	Uncertainty contribution, NSA measurement.....	77
6.7.3	Expanded uncertainty of the verification procedure	78
6.8	Summary	79
7	Test methods	79
7.1	Introduction	79
7.1.1	Site preparation.....	79
7.1.2	Preparation of the EUT.....	81
7.1.3	Standard antennas.....	81
7.1.4	Mutual coupling and mismatch loss correction factors	82
7.1.5	Power supplies to the EUT	82
7.1.6	Restrictions	82
7.2	Transmitter tests	83
7.2.1	Frequency error (30 MHz to 1 000 MHz).....	83
7.2.1.1	Apparatus required.....	83
7.2.1.2	Method of measurement.....	83
7.2.1.3	Procedure for completion of the overall results sheet	84
7.2.1.4	Log book entries	85
7.2.1.5	Statement of results	85
7.2.2	Expanded uncertainty for Frequency error test.....	85
7.2.3	Effective radiated power (30 to 1 000 MHz).....	86
7.2.3.1	Apparatus required.....	86
7.2.3.2	Method of measurement.....	86
7.2.3.3	Procedure for completion of the overall results sheet	89
7.2.3.4	Log book entries	91
7.2.3.5	Statement of results	92
7.2.4	Measurement uncertainty for Effective radiated power.....	92
7.2.4.1	Uncertainty contributions: Stage one: EUT measurement....	92
7.2.4.2	Uncertainty contributions: Stage 2: Substitution measurement.....	94
7.2.4.3	Expanded uncertainty of the ERP measurement	96
7.2.5	Spurious emissions (30 MHz to 4 or 12,75 GHz)	96
7.2.5.1	Apparatus required.....	97
7.2.5.2	Method of measurement.....	97
7.2.5.3	Procedure for completion of the results sheets	102
7.2.5.4	Log book entries	105
7.2.5.5	Statement of results	107
7.2.6	Measurement uncertainty for Spurious emissions	107
7.2.6.1	Uncertainty contributions: Stage 1: EUT measurement	107
7.2.6.2	Uncertainty contributions: Stage 2: Substitution measurement.....	108
7.2.6.3	Expanded uncertainty of the Spurious emission.....	110
7.2.7	Adjacent channel power	110
7.3	Receiver tests	110
7.3.1	Sensitivity tests (30 MHz to 1 000 MHz)	110
7.3.1.1	Apparatus required.....	111
7.3.1.2	Method of measurement.....	112
7.3.1.3	Procedure for completion of the overall results sheet	117

	7.3.1.4	Log book entries.....	118
	7.3.1.5	Statement of results.....	121
7.3.2		Measurement uncertainty for Receiver sensitivity	121
	7.3.2.1	Uncertainty contributions: Stage one: Determination of transform factor.....	121
	7.3.2.2	Uncertainty contributions: Stage 2: EUT measurement	123
	7.3.2.3	Expanded uncertainty of the receiver sensitivity measurement.....	124
7.3.3		Co-channel rejection	124
7.3.4		Adjacent channel selectioning	124
7.3.5		Insenmodulation immunity.....	124
7.3.6		Blocking immunity in desensization	124
7.3.7		Spurious response immuning to radiated fields (30 MHz to 4 GHz)	124
Annex A (informative):		Bibliography.....	125
History			127

iTeh STANDARD PREVIEW (standards.iteh.ai)

[PSIST ETR 273-3:1999](https://standards.iteh.ai/catalog/standards/sist/d2b60bac-46a8-4bbc-970a-b3b0e316b896/psist-etr-273-3-1999)

<https://standards.iteh.ai/catalog/standards/sist/d2b60bac-46a8-4bbc-970a-b3b0e316b896/psist-etr-273-3-1999>

Blank page

iTeh STANDARD PREVIEW
(standards.iteh.ai)

[PSIST ETR 273-3:1999](https://standards.iteh.ai/catalog/standards/sist/d2b60bac-46a8-4bbc-970a-b3b0e316b896/psist-etr-273-3-1999)

<https://standards.iteh.ai/catalog/standards/sist/d2b60bac-46a8-4bbc-970a-b3b0e316b896/psist-etr-273-3-1999>

Foreword

This ETSI Technical Report (ETR) has been produced by the Electromagnetic compatibility and Radio spectrum Matters (ERM) Technical Committee of the European Telecommunications Standards Institute (ETSI).

ETRs are informative documents resulting from ETSI studies which are not appropriate for European Telecommunication Standard (ETS) or Interim European Telecommunication Standard (I-ETS) status. An ETR may be used to publish material which is either of an informative nature, relating to the use or the application of ETSs or I-ETSs, or which is immature and not yet suitable for formal adoption as an ETS or an I-ETS.

The present document is part 3 of a multi-part Technical Report (ETR) covering Electromagnetic compatibility and Radio spectrum Matters (ERM); Improvement of radiated methods of measurement (using test sites) and evaluation of the corresponding measurement uncertainties, as identified below:

Part 1-1: "Uncertainties in the measurement of mobile radio equipment characteristics; Sub-part 1: Introduction";

Part 1-2: "Uncertainties in the measurement of mobile radio equipment characteristics; Sub-part 2: Examples and annexes";

Part 2: "Anechoic chamber";

Part 3: "Anechoic chamber with a ground plane";

Part 4: "Open area test site";

Part 5: "Striplines";

Part 6: "Test fixtures";

Part 7: "Artificial human beings";

ITih STANDARD PREVIEW

(standards.iteh.ai)

[PSIST ETR 273-3:1999](#)

<https://standards.iteh.ai/catalog/standards/sist/d2b60bac-46a8-4bbc-970a-b960e316b896/psist-etr-273-3-1999>

Blank page

iTeh STANDARD PREVIEW
(standards.iteh.ai)

[PSIST ETR 273-3:1999](https://standards.iteh.ai/catalog/standards/sist/d2b60bac-46a8-4bbc-970a-b3b0e316b896/psist-etr-273-3-1999)

<https://standards.iteh.ai/catalog/standards/sist/d2b60bac-46a8-4bbc-970a-b3b0e316b896/psist-etr-273-3-1999>

1 Scope

This ETR covers the methods of radiated measurements on mobile radio equipment in anechoic chambers and applies to the assessment of the associated measurement uncertainties.

This ETR also provides the methods for evaluation and calculation of the measurement uncertainties for each of the measured parameters and the required corrections for measurement conditions and results.

2 References

Within this ETR the following references apply:

- [1] ANSI C63.5 (1988): "Electromagnetic Compatibility-Radiated Emission Measurements in Electromagnetic Interference (EMI) Control - Calibration of Antennas".
- [2] "*Antenna theory*", C. Balanis, J. E. Wiley 1982.
- [3] "*Calculation of site attenuation from antenna factors*" A. A. Smith Jr, RF German and J B Pate. IEEE transactions EMC. Vol. EMC 24 pp 301-316 Aug 1982.
- [4] CCITT Recommendation O.41: "Psophometer for use on telephone-type circuits".
- [5] CCITT Recommendation O.153: "Basic parameters for the measurement of error performance at bit rates below the primary rate".
- [6] CISPR 16-1: "Specification for radio disturbance and immunity measuring apparatus and methods - Part 1: Radio disturbance and immunity measuring apparatus". [PSIST ETR 273-3:1999](https://standards.iteh.ai/catalog/standards/sist/d2b60bae-46a8-45bc-970a-b3b0a316b896/psist-etr-273-3-1999)
- [7] EN 50147-2 (1996): "Anechoic chambers -- Part 2: Alternative test site suitability with respect to site attenuation".
- [8] ETR 273-1-1: "Electromagnetic compatibility and Radio spectrum Matters (ERM); Improvement of radiated methods of measurement (using test sites) and evaluation of the corresponding measurement uncertainties; Part 1: Uncertainties in the measurement of mobile radio equipment characteristics; Sub-part 1: Introduction".
- [9] ETR 273-1-2: "Electromagnetic compatibility and Radio spectrum Matters (ERM); Improvement of radiated methods of measurement (using test sites) and evaluation of the corresponding measurement uncertainties; Part 1: Uncertainties in the measurement of mobile radio equipment characteristics; Sub-part 2: Examples and annexes".
- [10] "*The gain resistance product of the half-wave dipole*", W. Scott Bennet Proceedings of IEEE vol. 72 No. 2 Dec 1984 pp 1824-1826.
- [11] *The new IEEE standard dictionary of electrical and electronic terms*. Fifth edition, IEEE Piscataway, NJ USA 1993.

3 Definitions, symbols and abbreviations

3.1 Definitions

For the purposes of this ETR, the following definitions apply:

Audio Frequency (AF) load: Normally a resistor of sufficient power rating to accept the maximum audio output power from the EUT. The value of the resistor is normally that stated by the manufacturer and is normally the impedance of the audio transducer at 1 000 Hz.

NOTE 1: In some cases it may be necessary to place an isolating transformer between the output terminals of the receiver under test and the load.

AF termination: Any connection other than the audio frequency load which may be required for the purpose of testing the receiver. (i.e. in a case where it is required that the bit stream be measured, the connection may be made, via a suitable interface, to the discriminator of the receiver under test).

NOTE 2: The termination device is normally agreed between the manufacturer and the testing authority and details included in the test report. If special equipment is required then it is normally provided by the manufacturer.

A-M1: A test modulation consisting of a 1 000 Hz tone at a level which produces a deviation of 12 % of the channel separation.

A-M2: A test modulation consisting of a 1 250 Hz tone at a level which produces a deviation of 12 % of the channel separation.

A-M3: A test modulation consisting of a 400 Hz tone at a level which produces a deviation of 12 % of the channel separation. This signal is used as an unwanted signal for analogue and digital measurements.

antenna: That part of a transmitting or receiving system that is designed to radiate or to receive electromagnetic waves.

antenna factor: Quantity relating the strength of the field in which the antenna is immersed to the output voltage across the load connected to the antenna. When properly applied to the meter reading of the measuring instrument, yields the electric field strength in V/m or the magnetic field strength in A/m.

antenna gain: The ratio of the maximum radiation intensity from an (assumed lossless) antenna to the radiation intensity that would be obtained if the same power were radiated isotropically by a similarly lossless antenna.

bit error ratio: The ratio of the number of bits in error to the total number of bits.

combining network: A multipole network allowing the addition of two or more test signals produced by different sources for connection to a receiver input.

NOTE 3: Sources of test signals are normally connected in such a way that the impedance presented to the receiver is 50 Ω . Combining networks are so designed that the combining networks are designed so that effects of any intermodulation products and noise produced in the signal generators are negligible.

correction factor: The numerical factor by which the uncorrected result of a measurement is multiplied to compensate for an assumed systematic error.

confidence level: The probability of the accumulated error of a measurement being within the stated range of uncertainty of measurement.

directivity: The ratio of the maximum radiation intensity in a given direction from the antenna to the radiation intensity averaged over all directions (i.e. directivity = antenna gain + losses).

duplex filter: A device fitted internally or externally to a transmitter/receiver combination to allow simultaneous transmission and reception with a single antenna connection.

DM-0: A test modulation consisting of a signal representing an infinite series of "0" bits.

DM-1: A test modulation consisting of a signal representing an infinite series of "1" bits.

DM-2: A test modulation consisting of a signal representing a pseudorandom bit sequence of at least 511 bits in accordance with CCITT Recommendation O.153 [5].

DM-3: A test signal agreed between the testing authority and the manufacturer in the cases where it is not possible to measure a bit stream or if selective messages are used and are generated or decoded within an equipment.

NOTE 4: The agreed test signal may be formatted and may contain error detection and correction. Details of the test signal should be supplied in the test report.

error of measurement (absolute): The result of a measurement minus the true value of the measurand.

error (relative): The ratio of an error to the true value.

estimated standard deviation: From a sample of n results of a measurement the estimated standard deviation is given by the formula:

$$\sigma = \sqrt{\frac{\sum_{i=1}^n (x_i - \bar{x})^2}{n-1}}$$

iTeh STANDARD PREVIEW
(standards.iteh.ai)

x_i being the i^{th} result of measurement ($i = 1, 2, 3, \dots, n$) and \bar{x} the arithmetic mean of the n results considered.

[https://standards.iteh.ai/catalog/standards/sist/d2b60bac-46a8-4bbc-970a-](https://standards.iteh.ai/catalog/standards/sist/d2b60bac-46a8-4bbc-970a-3b0e316b896/psist-etr-273-3-1999)

A practical form of this formula is: [3b0e316b896/psist-etr-273-3-1999](https://standards.iteh.ai/catalog/standards/sist/d2b60bac-46a8-4bbc-970a-3b0e316b896/psist-etr-273-3-1999)

$$\sigma = \sqrt{\frac{Y - \frac{X^2}{n}}{n-1}}$$

Where X is the sum of the measured values and Y is the sum of the squares of the measured values.

extreme test conditions: Conditions defined in terms of temperature and supply voltage. Tests are normally made with the extremes of temperature and voltage applied simultaneously. The upper and lower temperature limits are specified in the relevant testing standard. The test report states the actual temperatures measured.

error (of a measuring instrument): The indication of a measuring instrument minus the (conventional) true value.

free field: A field (wave or potential) which has a constant ratio between the electric and magnetic field intensities.

free Space: A region free of obstructions and characterized by the constitutive parameters of a vacuum.

impedance: A measure of the complex resistive and reactive attributes of a component in an alternating current circuit.

impedance (wave): The complex factor relating the transverse component of the electric field to the transverse component of the magnetic field at every point in any specified plane, for a given mode.

influence quantity: A quantity which is not the subject of the measurement but which influences the value of the quantity to be measured or the indications of the measuring instrument.

intermittent operation: Operation where the manufacturer states the maximum time that the equipment is intended to transmit and the necessary standby period before repeating a transmit period.

isotropic radiator: A hypothetical, lossless antenna having equal radiation intensity in all directions.

limited Frequency Range: A specified smaller frequency range within the full frequency range over which the measurement is made.

NOTE 5: The details of the calculation of the limited frequency range are normally given in the relevant testing standard.

maximum permissible frequency deviation: The maximum value of frequency deviation stated for the relevant channel separation in the relevant testing standard.

measuring system: A complete set of measuring instruments and other equipment assembled to carry out a specified measurement task.

measurement repeatability: The closeness of the agreement between the results of successive measurements of the same measurand carried out subject to all the following conditions:

- the same method of measurement;
- the same observer;
- the same measuring instrument;
- the same location;
- the same conditions of use;
- repetition over a short period of time.

iTeh STANDARD PREVIEW
(standards.iteh.ai)

measurement reproducibility: The closeness of agreement between the results of measurements of the same measurand, where the individual measurements are carried out changing conditions such as:

- method of measurement;
- observer;
- measuring instrument;
- location;
- conditions of use;
- time.

measurand: A quantity subjected to measurement.

noise gradient of EUT: A function characterizing the relationship between the RF input signal level and the performance of the EUT, e.g., the SINAD of the AF output signal.

nominal frequency: One of the channel frequencies on which the equipment is designed to operate.

nominal mains voltage: The declared voltage or any of the declared voltages for which the equipment was designed.

normal test conditions: The conditions defined in terms of temperature, humidity and supply voltage stated in the relevant testing standard.

normal deviation: The frequency deviation for analogue signals which is equal to 12 % of the channel separation.

psophometric weighting network: As described in CCITT Recommendation O.41 [4].

polarization: For an electromagnetic wave, the figure traced as a function of time by the extremity of the electric vector at a fixed point in space.

quantity (measurable): An attribute of a phenomenon or a body which may be distinguished qualitatively and determined quantitatively.

rated audio output power: The maximum audio output power under normal test conditions, and at standard test modulations, as declared by the manufacturer.

rated radio frequency output power: The maximum carrier power under normal test conditions, as declared by the manufacturer.

shielded enclosure: A structure that protects its interior from the effects of an exterior electric or magnetic field, or conversely, protects the surrounding environment from the effect of an interior electric or magnetic field.

SINAD sensitivity: The minimum standard modulated carrier-signal input required to produce a specified SINAD ratio at the receiver output.

stochastic (random) variable: A variable whose value is not exactly known, but is characterized by a distribution or probability function, or a mean value and a standard deviation (e.g. a measurand and the related measurement uncertainty).

test load: The test load is a 50 Ω substantially non-reactive, non-radiating power attenuator which is capable of safely dissipating the power from the transmitter.

test modulation: The test modulating signal is a baseband signal which modulates a carrier and is dependent upon the type of EUT and also the measurement to be performed.

trigger device: A circuit or mechanism to trigger the oscilloscope timebase at the required instant. It may control the transmit function or inversely receive an appropriate command from the transmitter.

uncertainty (random): A component of the uncertainty of measurement which, in the course of a number of measurements of the same measurand, varies in an unpredictable way.

uncertainty (systematic): A component of the uncertainty of measurement which, in the course of a number of measurements of the same measurand remains constant or varies in a predictable way.

uncertainty (limits of uncertainty of a measuring instrument): The extreme values of uncertainty permitted by specifications, regulations etc. for a given measuring instrument.

NOTE 6: This term is also known as "tolerance".

uncertainty (standard): The representation of each individual uncertainty component that contributes to the overall measurement uncertainty by an estimated standard deviation is termed the standard uncertainty.

uncertainty (combined standard): The combined standard uncertainty of a measurement is calculated by combining the standard uncertainties for each of the individual contributions identified.

NOTE 7: This combination is carried out by applying the Root of the Sum of the Squares (the RSS) method under the assumption that all contributions are stochastic i.e. independent of each other.

uncertainty (expanded): The combined standard uncertainty is multiplied by a constant to give the expanded uncertainty limits.

upper specified AF limit: The maximum audio frequency of the audio pass-band. It is dependent on the channel separation.