



# SLOVENSKI STANDARD PSIST ETR 273-6:1999

01-april-1999

---

**Elektromagnetna združljivost (EMC) in zadeve v zvezi z radijskim spektrom (ERM) -  
Izboljšanje zvezdastih merilnih naprav (z uporabo merilnih mest) in ovrednotenje  
ustreznih merilnih negotovosti 6. del: Pravila preskušanj**

ElectroMagnetic Compatibility and Radio Spectrum Matters (ERM); Improvement of  
radiated methods of measurement (using test sites) and evaluation of the corresponding  
measurement uncertainties; Part 6: Test fixtures

**iTeh STANDARD PREVIEW**  
**(standards.iteh.ai)**

[PSIST ETR 273-6:1999](https://standards.iteh.ai/catalog/standards/sist/d28d7a8e-f903-4e2b-8d58-8f9520852c8f/psist-etr-273-6-1999)

[https://standards.iteh.ai/catalog/standards/sist/d28d7a8e-f903-4e2b-8d58-  
8f9520852c8f/psist-etr-273-6-1999](https://standards.iteh.ai/catalog/standards/sist/d28d7a8e-f903-4e2b-8d58-8f9520852c8f/psist-etr-273-6-1999)

**Ta slovenski standard je istoveten z: ETR 273-6 Edition 1**

---

**ICS:**

33.060.01	Radijske komunikacije na splošno	Radiocommunications in general
33.100.01	Elektromagnetna združljivost na splošno	Electromagnetic compatibility in general

**PSIST ETR 273-6:1999**

**en**

**iTeh STANDARD PREVIEW**  
**(standards.iteh.ai)**

[PSIST ETR 273-6:1999](#)

<https://standards.iteh.ai/catalog/standards/sist/d28d7a8e-f903-4e2b-8d58-8f9520852c8f/psist-etr-273-6-1999>



**ETSI**  
**TECHNICAL**  
**REPORT**

**ETR 273-6**

February 1998

Source: ERM

Reference: DTR/ERM-RP01-018-6

ICS: 33.020

**Key words:** Analogue, data, measurement uncertainty, mobile, radio, testing

**Electromagnetic compatibility  
and Radio spectrum Matters (ERM);  
Improvement of radiated methods of  
measurement (using test sites) and  
evaluation of the corresponding  
measurement uncertainties;  
Part 6: Test fixtures**

**ETSI**

European Telecommunications Standards Institute

**ETSI Secretariat**

**Postal address:** F-06921 Sophia-Antipolis CEDEX - FRANCE

**Office address:** 650 Route des Lucioles - Sophia Antipolis - Valbonne - FRANCE

**X.400:** c=fr, a=atlas, p=etsi, s=secretariat - **Internet:** secretariat@etsi.fr

Tel.: +33 4 92 94 42 00 - Fax: +33 4 93 65 47 16

**Copyright Notification:** No part may be reproduced except as authorized by written permission. The copyright and the foregoing restriction extend to reproduction in all media.

© European Telecommunications Standards Institute 1998. All rights reserved.

## iTeh STANDARD PREVIEW (standards.iteh.ai)

[PSIST ETR 273-6:1999](https://standards.iteh.ai/catalog/standards/sist/d28d7a8e-f903-4e2b-8d58-8f9520852c8f/psist-etr-273-6-1999)

<https://standards.iteh.ai/catalog/standards/sist/d28d7a8e-f903-4e2b-8d58-8f9520852c8f/psist-etr-273-6-1999>

## Contents

Foreword .....	7
1 Scope .....	9
2 References .....	9
3 Definitions, symbols and abbreviations .....	9
3.1 Definitions .....	9
3.2 Symbols .....	13
3.3 Abbreviations .....	16
4 Introduction .....	17
4.1 Performance limitations .....	18
4.2 Summary .....	18
5 Uncertainty contributions specific to test fixtures .....	19
5.1 Test fixture effect .....	19
5.2 Climatic facility effect .....	19
5.2.1 Resonances within a climatic facility .....	19
5.2.2 Internal reflections using a climatic facility .....	20
5.2.3 Mutual coupling effects using a climatic facility .....	20
5.2.4 Waveguide-type modes within a climatic facility .....	21
5.2.5 Summary .....	21
6 Verification procedure for a test fixture .....	21
6.1 Definition .....	21
6.2 Overview of the verification procedure .....	21
6.2.1 Apparatus required .....	22
6.2.2 Site preparation .....	22
6.2.3 Measurement configuration .....	22
6.2.4 What to record .....	23
6.3 Verification procedure .....	23
6.4 Processing the results of the verification procedure .....	27
6.5 Calculation of measurement uncertainty .....	27
7 Test methods .....	27
7.1 Introduction .....	27
7.1.1 Site preparation .....	27
7.1.2 Preparation of the EUT .....	28
7.1.3 Power supplies to the EUT .....	28
7.2 Transmitter tests .....	29
7.2.1 Frequency error (30 MHz to 1 000 MHz) .....	29
7.2.1.1 Apparatus required .....	29
7.2.1.2 Method of measurement .....	29
7.2.1.3 Procedure for completion of the results sheets .....	31
7.2.1.4 Log book entries .....	31
7.2.1.5 Statement of results .....	31
7.2.2 Expanded uncertainty for frequency error test .....	32
7.2.3 Effective radiated power (30 MHz to 1 000 MHz) .....	32
7.2.3.1 Apparatus required .....	32
7.2.3.2 Method of measurement .....	33
7.2.3.3 Procedure for the completion of the results sheets .....	35
7.2.3.4 Log book entries .....	36
7.2.3.5 Statement of results .....	37

7.2.4	Uncertainty for effective radiated power measurement.....	37
7.2.4.1	Expanded uncertainty for Effective radiated power measurement.....	37
7.2.5	Spurious emissions (30 MHz to 4 GHz or 12,75 GHz) .....	37
7.2.6	Adjacent channel power (30 MHz to 1 000 MHz) .....	38
7.2.6.1	Apparatus required.....	38
7.2.6.2	Method of measurement.....	38
7.2.6.3	Procedure for completion of the results sheets .....	41
7.2.6.4	Log book entries .....	42
7.2.6.5	Statement of results .....	43
7.2.7	Measurement uncertainty for Adjacent channel power.....	43
7.2.7.1	Expanded uncertainty of the Adjacent channel power measurement.....	44
7.3	Receiver tests .....	44
7.3.1	Maximum usable sensitivity (30 MHz to 1 000 MHz).....	44
7.3.1.1	Apparatus required.....	45
7.3.1.2	Method of measurement.....	46
7.3.1.3	Procedure for the completion of the results sheets.....	49
7.3.1.4	Log book entries .....	50
7.3.1.5	Statement of results .....	52
7.3.2	Measurement uncertainty for Maximum usable sensitivity .....	52
7.3.2.1	Expanded uncertainty of the maximum usable sensitivity measurement.....	52
7.3.3	Average usable sensitivity.....	52
7.3.4	Co-channel rejection.....	53
7.3.4.1	Apparatus required.....	53
7.3.4.2	Method of measurement .....	54
7.3.4.3	Procedure for completion of the results sheets .....	58
7.3.4.4	Log book entries .....	59
7.3.4.5	Overall results sheet.....	62
7.3.5	Measurement uncertainty for Co-channel rejection.....	63
7.3.5.1	Expanded uncertainty of the co-channel rejection measurement.....	63
7.3.6	Adjacent channel selectivity .....	63
7.3.6.1	Apparatus required.....	64
7.3.6.2	Method of measurement.....	64
7.3.6.3	Procedure for completion of the results sheets .....	68
7.3.6.4	Log book entries .....	70
7.3.6.5	Overall results sheet.....	73
7.3.7	Measurement uncertainty for adjacent channel selectivity .....	73
7.3.7.1	Expanded uncertainty of the adjacent channel selectivity measurement.....	73
7.3.8	Intermodulation immunity .....	73
7.3.8.1	Apparatus required.....	74
7.3.8.2	Method of measurement.....	74
7.3.8.3	Procedure for completion of the results sheets .....	79
7.3.8.4	Log book entries .....	81
7.3.8.5	Overall results sheet.....	84
7.3.9	Measurement uncertainty for Intermodulation immunity .....	84
7.3.9.1	Expanded uncertainty of the Intermodulation immunity measurement.....	84
7.3.10	Blocking immunity (or desensitization).....	84
7.3.10.1	Apparatus required.....	85
7.3.10.2	Method of measurement.....	86
7.3.10.3	Procedure for completion of the results sheets .....	90
7.3.10.4	Log book entries .....	91
7.3.10.5	Overall results sheet.....	96
7.3.11	Measurement uncertainty for blocking immunity (or desensitization) .....	96
7.3.11.1	Expanded uncertainty of the blocking immunity (or desensitization) measurement .....	97

7.3.12 Spurious response rejection..... 97

Annex A (informative): Bibliography..... 98

History ..... 100

**iTeh STANDARD PREVIEW**  
**(standards.iteh.ai)**

[PSIST ETR 273-6:1999](https://standards.iteh.ai/catalog/standards/sist/d28d7a8e-f903-4e2b-8d58-8f9520852c8f/psist-etr-273-6-1999)

<https://standards.iteh.ai/catalog/standards/sist/d28d7a8e-f903-4e2b-8d58-8f9520852c8f/psist-etr-273-6-1999>

Blank page

**iTeh STANDARD PREVIEW**  
**(standards.iteh.ai)**

[PSIST ETR 273-6:1999](https://standards.iteh.ai/catalog/standards/sist/d28d7a8e-f903-4e2b-8d58-8f9520852c8f/psist-etr-273-6-1999)

<https://standards.iteh.ai/catalog/standards/sist/d28d7a8e-f903-4e2b-8d58-8f9520852c8f/psist-etr-273-6-1999>



## Foreword

This ETSI Technical Report (ETR) has been produced by the Electromagnetic compatibility and Radio spectrum Matters (ERM) Technical Committee of the European Telecommunications Standards Institute (ETSI).

ETRs are informative documents resulting from ETSI studies which are not appropriate for European Telecommunication Standard (ETS) or Interim European Telecommunication Standard (I-ETS) status. An ETR may be used to publish material which is either of an informative nature, relating to the use or the application of ETSs or I-ETSs, or which is immature and not yet suitable for formal adoption as an ETS or an I-ETS.

The present document is part 6 of a multi-part Technical Report (ETR) covering Electromagnetic compatibility and Radio spectrum Matters (ERM); Improvement of radiated methods of measurement (using test sites) and evaluation of the corresponding measurement uncertainties, as identified below:

Part 1-1: "Uncertainties in the measurement of mobile radio equipment characteristics; Sub-part 1: Introduction";

Part 1-2: "Uncertainties in the measurement of mobile radio equipment characteristics; Sub-part 2: Examples and annexes";

Part 2: "Anechoic chamber";

Part 3: "Anechoic chamber with a ground plane";

Part 4: "Open area test site";

Part 5: "Striplines";

**Part 6: "Test fixtures";**

Part 7: "Artificial human beings";

ITih STANDARD PREVIEW  
(standards.iteh.ai)

[PSIST ETR 273-6:1999](https://standards.iteh.ai/catalog/standards/sist/d28d7a8e-f903-4e2b-8d58-8d520852c8f/psist-etr-273-6-1999)

<https://standards.iteh.ai/catalog/standards/sist/d28d7a8e-f903-4e2b-8d58-8d520852c8f/psist-etr-273-6-1999>

Blank page

**iTeh STANDARD PREVIEW**  
**(standards.iteh.ai)**

[PSIST ETR 273-6:1999](https://standards.iteh.ai/catalog/standards/sist/d28d7a8e-f903-4e2b-8d58-8f9520852c8f/psist-etr-273-6-1999)

<https://standards.iteh.ai/catalog/standards/sist/d28d7a8e-f903-4e2b-8d58-8f9520852c8f/psist-etr-273-6-1999>

## 1 Scope

This ETR covers the methods of radiated measurements on mobile radio equipment using test fixtures and applies to the assessment of the associated measurement uncertainties.

This ETR provides the methods for evaluation and calculation of the measurement uncertainties for each of the measured parameters and the required corrections for measurement conditions and results.

## 2 References

Within this ETR the following references apply:

- [1] CCITT Recommendation O.41: "Psophometer for use on telephone-type circuits".
- [2] CCITT Recommendation O.153: "Basic parameters for the measurement of error performance at bit rates below the primary rate".
- [3] ETR 027 1991: "Radio Equipment and Systems (RES); Methods of measurement for private mobile radio equipment".
- [4] ETR 273-1-1: "Electromagnetic compatibility and Radio spectrum Matters (ERM); Improvement of radiated methods of measurement (using test sites) and evaluation of the corresponding measurement uncertainties; Part 1: Uncertainties in the measurement of mobile radio equipment characteristics; Sub-part 1: Introduction".
- [5] ETR 273-2: "Electromagnetic compatibility and Radio spectrum Matters (ERM); Improvement of radiated methods of measurement (using test sites) and evaluation of the corresponding measurement uncertainties; Part 2: Anechoic chamber". [PSIST ETR 273-6:1999](https://standards.iteh.ai/catalog/standards/sist/d28d7a8e-f903-4e2b-8d58-6b520652c87psist-etr-273-6-1999)
- [6] <https://standards.iteh.ai/catalog/standards/sist/d28d7a8e-f903-4e2b-8d58-6b520652c87psist-etr-273-6-1999>  
ETR 273-3: "Electromagnetic compatibility and Radio spectrum Matters (ERM); Improvement of radiated methods of measurement (using test sites) and evaluation of the corresponding measurement uncertainties; Part 3: Anechoic chamber with a ground plane".
- [7] ETR 273-4: "Electromagnetic compatibility and Radio spectrum Matters (ERM); Improvement of radiated methods of measurement (using test sites) and evaluation of the corresponding measurement uncertainties; Part 4: Open area test site".

## 3 Definitions, symbols and abbreviations

### 3.1 Definitions

For the purposes of this ETR, the following definitions apply:

**Audio Frequency (AF) load:** Normally a resistor of sufficient power rating to accept the maximum audio output power from the EUT. The value of the resistor is normally that stated by the manufacturer and is normally the impedance of the audio transducer at 1 000 Hz.

NOTE 1: In some cases it may be necessary to place an isolating transformer between the output terminals of the receiver under test and the load.

**AF termination:** Any connection other than the audio frequency load which may be required for the purpose of testing the receiver. (i.e. in a case where it is required that the bit stream be measured, the connection may be made, via a suitable interface, to the discriminator of the receiver under test).

NOTE 2: The termination device is normally agreed between the manufacturer and the testing authority and details included in the test report. If special equipment is required then it is normally provided by the manufacturer.

**antenna:** That part of a transmitting or receiving system that is designed to radiate or to receive electromagnetic waves.

**antenna factor:** Quantity relating the strength of the field in which the antenna is immersed to the output voltage across the load connected to the antenna. When properly applied to the meter reading of the measuring instrument, yields the electric field strength in V/m or the magnetic field strength in A/m.

**antenna gain:** The ratio of the maximum radiation intensity from an (assumed lossless) antenna to the radiation intensity that would be obtained if the same power were radiated isotropically by a similarly lossless antenna.

**bit error ratio:** The ratio of the number of bits in error to the total number of bits.

**combining network:** A multipole network allowing the addition of two or more test signals produced by different sources for connection to a receiver input.

NOTE 3: Sources of test signals are normally connected in such a way that the impedance presented to the receiver is 50  $\Omega$ . The combining networks are designed so that effects of any intermodulation products and noise produced in the signal generators are negligible.

**correction factor:** The numerical factor by which the uncorrected result of a measurement is multiplied to compensate for an assumed systematic error.

**confidence level:** The probability of the accumulated error of a measurement being within the stated range of uncertainty of measurement.

**directivity:** The ratio of the maximum radiation intensity in a given direction from the antenna to the radiation intensity averaged over all directions (i.e. directivity = antenna gain + losses).

**duplex filter:** A device fitted internally or externally to a transmitter/receiver combination to allow simultaneous transmission and reception with a single antenna connection.

**error of measurement (absolute):** The result of a measurement minus the true value of the measurand.

**error (relative):** The ratio of an error to the true value.

**estimated standard deviation:** From a sample of n results of a measurement the estimated standard deviation is given by the formula:

$$\sigma = \sqrt{\frac{\sum_{i=1}^n (x_i - \bar{x})^2}{n-1}}$$

$x_i$  being the  $i^{\text{th}}$  result of measurement ( $i = 1, 2, 3, \dots, n$ ) and  $\bar{x}$  the arithmetic mean of the n results considered.

A practical form of this formula is:

$$\sigma = \sqrt{\frac{Y - \frac{X^2}{n}}{n-1}}$$

Where X is the sum of the measured values and Y is the sum of the squares of the measured values.

**extreme test conditions:** Conditions defined in terms of temperature and supply voltage. Tests are normally made with the extremes of temperature and voltage applied simultaneously. The upper and lower temperature limits are specified in the relevant testing standard. The test report states the actual temperatures measured.

**error (of a measuring instrument):** The indication of a measuring instrument minus the (conventional) true value.

**free field:** A field (wave or potential) which has a constant ratio between the electric and magnetic field intensities.

**free Space:** A region free of obstructions and characterized by the constitutive parameters of a vacuum.

**impedance:** A measure of the complex resistive and reactive attributes of a component in an alternating current circuit.

**impedance (wave):** The complex factor relating the transverse component of the electric field to the transverse component of the magnetic field at every point in any specified plane, for a given mode.

**influence quantity:** A quantity which is not the subject of the measurement but which influences the value of the quantity to be measured or the indications of the measuring instrument.

**intermittent operation:** Operation where manufacturer states the maximum time that the equipment is intended to transmit and the necessary standby period before repeating a transmit period.

**isotropic radiator:** A hypothetical, lossless antenna having equal radiation intensity in all directions.

**limited Frequency Range:** The limited frequency range is a specified smaller frequency range within the full frequency range over which the measurement is made.

NOTE 4: The details of the calculation of the limited frequency range are normally given in the relevant testing standard.

**maximum permissible frequency deviation:** The maximum value of frequency deviation stated for the relevant channel separation in the relevant testing standard.

**measuring system:** A complete set of measuring instruments and other equipment assembled to carry out a specified measurement task.

**measurement repeatability:** The closeness of the agreement between the results of successive measurements of the same measurand carried out subject to all the following conditions:

- the same method of measurement;
- the same observer;
- the same measuring instrument;
- the same location;
- the same conditions of use;
- repetition over a short period of time.

**measurement reproducibility:** The closeness of agreement between the results of measurements of the same measurand, where the individual measurements are carried out changing conditions such as:

- method of measurement;
- observer;
- measuring instrument;
- location;
- conditions of use;
- time.

**measurand:** A quantity subjected to measurement.

**noise gradient of EUT:** A function characterizing the relationship between the RF input signal level and the performance of the EUT, e.g., the SINAD of the AF output signal.

**nominal frequency:** One of the channel frequencies on which the equipment is designed to operate.

**nominal mains voltage:** The declared voltage or any of the declared voltages for which the equipment was designed.

**normal test conditions:** The conditions defined in terms of temperature, humidity and supply voltage stated in the relevant testing standard.

**normal deviation:** The frequency deviation for analogue signals which is equal to 12 % of the channel separation.

**psophometric weighting network:** As described in CCITT Recommendation O.41 [1].

**polarization:** For an electromagnetic wave, the figure traced as a function of time by the extremity of the electric vector at a fixed point in space.

**quantity (measurable):** An attribute of a phenomenon or a body which may be distinguished qualitatively and determined quantitatively.

**rated audio output power:** The maximum audio output power under normal test conditions, and at standard test modulations, as declared by the manufacturer.

**rated radio frequency output power:** The maximum carrier power under normal test conditions, as declared by the manufacturer.

**shielded enclosure:** A structure that protects its interior from the effects of an exterior electric or magnetic field, or conversely, protects the surrounding environment from the effect of an interior electric or magnetic field.

**SINAD sensitivity:** The minimum standard modulated carrier-signal input required to produce a specified SINAD ratio at the receiver output.

**stochastic (random) variable:** A variable whose value is not exactly known, but is characterized by a distribution or probability function, or a mean value and a standard deviation (e.g. a measurand and the related measurement uncertainty).

**test load:** The test load is a 50  $\Omega$  substantially non-reactive, non-radiating power attenuator which is capable of safely dissipating the power from the transmitter.

**test modulation:** The test modulating signal is a baseband signal which modulates a carrier and is dependent upon the type of EUT and also the measurement to be performed.

**trigger device:** A circuit or mechanism to trigger the oscilloscope timebase at the required instant. It may control the transmit function or inversely receive an appropriate command from the transmitter.

**uncertainty (random):** A component of the uncertainty of measurement which, in the course of a number of measurements of the same measurand, varies in an unpredictable way.

**uncertainty (systematic):** A component of the uncertainty of measurement which, in the course of a number of measurements of the same measurand remains constant or varies in a predictable way.

**uncertainty (limits of uncertainty of a measuring instrument):** The extreme values of uncertainty permitted by specifications, regulations etc. for a given measuring instrument.

NOTE 5: This term is also known as "tolerance".

**uncertainty (standard):** The representation of each individual uncertainty component that contributes to the overall measurement uncertainty by an estimated standard deviation is termed the standard uncertainty.

**uncertainty (combined standard):** The combined standard uncertainty of a measurement is calculated by combining the standard uncertainties for each of the individual contributions identified.

NOTE 6: This combination is carried out by applying the Root of the Sum of the Squares (the RSS) method under the assumption that all contributions are stochastic i.e. independent of each other.

**uncertainty (expanded):** The combined standard uncertainty is multiplied by a constant to give the expanded uncertainty limits.

**upper specified AF limit:** The maximum audio frequency of the audio pass-band. It is dependent on the channel separation.

**wanted signal level:** For conducted measurements Pa level of +6 dB $\mu$ V emf referred to the receiver input under normal test conditions. Under *extreme test conditions* the value is +12 dB $\mu$ V emf.

NOTE 7: For analogue measurements the wanted signal level has been chosen to be equal to the limit value of the measured usable sensitivity. For bit stream and message measurements the wanted signal has been chosen to be +3 dB above the limit value of measured usable sensitivity.

### 3.2 Symbols

For the purposes of this ETR, the following symbols apply:

$\beta$	$2\pi/\lambda$ (radians/m);
$\gamma$	incidence angle with ground plane ( $^{\circ}$ )
$\lambda$	wavelength (m)
$\phi_H$	phase angle of reflection coefficient ( $^{\circ}$ )
$\eta$	$120\pi$ Ohms - the intrinsic impedance of free space ( $\Omega$ )
$\mu$	permeability (H/m)
$AF_R$	antenna factor of the receive antenna (dB/m)
$AF_T$	antenna factor of the transmit antenna (dB/m)
$AF_{TOT}$	mutual coupling correction factor (dB)
$C_{cross}$	cross correlation coefficient
$D(\theta, \phi)$	directivity of the source
$d$	distance between dipoles (m)
$\delta$	skin depth (m)
$d_1$	an antenna or EUT aperture size (m)
$d_2$	an antenna or EUT aperture size (m)
$d_{dir}$	path length of the direct signal (m)
$d_{refl}$	path length of the reflected signal (m)
$E$	electric field intensity (V/m)