

ETSI TS 136 104 V15.15.0 (2022-04)



iTeh STANDARD
LTE;
Evolved Universal Terrestrial Radio Access (E-UTRA);
Base Station (BS) radio transmission and reception
(3GPP TS 36.104 version 15.15.0 Release 15)

[ETSI TS 136 104 V15.15.0 \(2022-04\)](https://standards.iteh.ai/catalog/standards/sist/6fc74974-eb47-4dba-81c0-72e4777f53e2/etsi-ts-136-104-v15-15-0-2022-04)
[https://standards.iteh.ai/catalog/standards/sist/6fc74974-
eb47-4dba-81c0-72e4777f53e2/etsi-ts-136-104-v15-15-
0-2022-04](https://standards.iteh.ai/catalog/standards/sist/6fc74974-eb47-4dba-81c0-72e4777f53e2/etsi-ts-136-104-v15-15-0-2022-04)



Reference

RTS/TSGR-0436104vff0

Keywords

LTE

ETSI

650 Route des Lucioles
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - APE 7112B
Association à but non lucratif enregistrée à la
Sous-Préfecture de Grasse (06) N° w061004871

Important notice

The present document can be downloaded from:

<http://www.etsi.org/standards-search>

The present document may be made available in electronic versions and/or in print. The content of any electronic and/or print versions of the present document shall not be modified without the prior written authorization of ETSI. In case of any existing or perceived difference in contents between such versions and/or in print, the prevailing version of an ETSI deliverable is the one made publicly available in PDF format at www.etsi.org/deliver.

Users of the present document should be aware that the document may be subject to revision or change of status.

Information on the current status of this and other ETSI documents is available at

<https://portal.etsi.org/TB/ETSIDeliverableStatus.aspx>

If you find errors in the present document, please send your comment to one of the following services:

<https://portal.etsi.org/People/CommitteeSupportStaff.aspx>

If you find a security vulnerability in the present document, please report it through our

Coordinated Vulnerability Disclosure Program:

<https://www.etsi.org/standards/coordinated-vulnerability-disclosure>

Notice of disclaimer & limitation of liability

The information provided in the present deliverable is directed solely to professionals who have the appropriate degree of experience to understand and interpret its content in accordance with generally accepted engineering or other professional standard and applicable regulations.

No recommendation as to products and services or vendors is made or should be implied.

No representation or warranty is made that this deliverable is technically accurate or sufficient or conforms to any law and/or governmental rule and/or regulation and further, no representation or warranty is made of merchantability or fitness for any particular purpose or against infringement of intellectual property rights.

In no event shall ETSI be held liable for loss of profits or any other incidental or consequential damages.

Any software contained in this deliverable is provided "AS IS" with no warranties, express or implied, including but not limited to, the warranties of merchantability, fitness for a particular purpose and non-infringement of intellectual property rights and ETSI shall not be held liable in any event for any damages whatsoever (including, without limitation, damages for loss of profits, business interruption, loss of information, or any other pecuniary loss) arising out of or related to the use of or inability to use the software.

Copyright Notification

No part may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm except as authorized by written permission of ETSI.

The content of the PDF version shall not be modified without the written authorization of ETSI.

The copyright and the foregoing restriction extend to reproduction in all media.

© ETSI 2022.
All rights reserved.

Intellectual Property Rights

Essential patents

IPRs essential or potentially essential to normative deliverables may have been declared to ETSI. The declarations pertaining to these essential IPRs, if any, are publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: *"Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards"*, which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (<https://ipr.etsi.org/>).

Pursuant to the ETSI Directives including the ETSI IPR Policy, no investigation regarding the essentiality of IPRs, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

Trademarks

The present document may include trademarks and/or tradenames which are asserted and/or registered by their owners. ETSI claims no ownership of these except for any which are indicated as being the property of ETSI, and conveys no right to use or reproduce any trademark and/or tradename. Mention of those trademarks in the present document does not constitute an endorsement by ETSI of products, services or organizations associated with those trademarks.

DECT™, **PLUGTESTS™**, **UMTS™** and the ETSI logo are trademarks of ETSI registered for the benefit of its Members. **3GPP™** and **LTE™** are trademarks of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners. **oneM2M™** logo is a trademark of ETSI registered for the benefit of its Members and of the oneM2M Partners. **GSM®** and the GSM logo are trademarks registered and owned by the GSM Association.

Legal Notice

(standards.iteh.ai)

This Technical Specification (TS) has been produced by ETSI 3rd Generation Partnership Project (3GPP).

The present document may refer to technical specifications or reports using their 3GPP identities. These shall be interpreted as being references to the corresponding ETSI deliverables.

The cross reference between 3GPP and ETSI identities can be found under <http://webapp.etsi.org/key/queryform.asp>.

Modal verbs terminology

In the present document "**shall**", "**shall not**", "**should**", "**should not**", "**may**", "**need not**", "**will**", "**will not**", "**can**" and "**cannot**" are to be interpreted as described in clause 3.2 of the [ETSI Drafting Rules](#) (Verbal forms for the expression of provisions).

"**must**" and "**must not**" are **NOT** allowed in ETSI deliverables except when used in direct citation.

Contents

Intellectual Property Rights	2
Legal Notice	2
Modal verbs terminology.....	2
Foreword.....	8
1 Scope	9
2 References	9
3 Definitions, symbols and abbreviations	10
3.1 Definitions	10
3.2 Symbols.....	13
3.3 Abbreviations	14
4 General	16
4.1 Relationship between minimum requirements and test requirements	16
4.2 Base station classes	16
4.3 Regional requirements.....	16
4.4 Applicability of requirements.....	17
4.5 Requirements for BS capable of multi-band operation	18
5 Operating bands and channel arrangement.....	19
5.1 General	19
5.2 Void.....	19
5.3 Void.....	19
5.4 Void.....	19
5.5 Operating bands.....	19
5.6 Channel bandwidth.....	52
5.7 Channel arrangement.....	56
5.7.1 Channel spacing.....	56
5.7.1A CA Channel spacing.....	56
5.7.2 Channel raster.....	57
5.7.3 Carrier frequency and EARFCN.....	57
5.7.4 EARFCN sets for Type B multi-carrier downlink transmissions and conversion to Type 2 channel access for multi-carrier uplink transmissions on multiple Scells configured in Band 46	60
5.8 Requirements for contiguous and non-contiguous spectrum.....	61
6 Transmitter characteristics	61
6.1 General	61
6.2 Base station output power	62
6.2.1 Minimum requirement	63
6.2.2 Additional requirement (regional)	63
6.2.3 Home BS output power for adjacent UTRA channel protection.....	63
6.2.4 Home BS output power for adjacent E-UTRA channel protection.....	64
6.2.5 Home BS Output Power for co-channel E-UTRA protection.....	65
6.3 Output power dynamics.....	66
6.3.1 RE Power control dynamic range	66
6.3.1.1 Minimum requirements.....	66
6.3.2 Total power dynamic range	67
6.3.2.1 Minimum requirements.....	67
6.3.3 NB-IoT RB power dynamic range for in-band or guard band operation	67
6.3.3.1 Minimum Requirement	68
6.4 Transmit ON/OFF power	68
6.4.1 Transmitter OFF power	68
6.4.1.1 Minimum Requirement	68
6.4.2 Transmitter transient period.....	68
6.4.2.1 Minimum requirements.....	69
6.5 Transmitted signal quality	69

6.5.1	Frequency error.....	69
6.5.1.1	Minimum requirement	69
6.5.2	Error Vector Magnitude.....	70
6.5.3	Time alignment error	70
6.5.3.1	Minimum Requirement	70
6.5.4	DL RS power	71
6.5.4.1	Minimum requirements	71
6.6	Unwanted emissions.....	71
6.6.1	Occupied bandwidth	71
6.6.1.1	Minimum requirement	72
6.6.2	Adjacent Channel Leakage power Ratio (ACLR)	72
6.6.2.1	Minimum requirement	72
6.6.2.2	Cumulative ACLR requirement in non-contiguous spectrum	75
6.6.3	Operating band unwanted emissions	76
6.6.3.1	Minimum requirements for Wide Area BS (Category A)	78
6.6.3.2	Minimum requirements for Wide Area BS (Category B)	81
6.6.3.2.1	Category B requirements (Option 1)	81
6.6.3.2.2	Category B (Option 2).....	85
6.6.3.2A	Minimum requirements for Local Area BS (Category A and B)	87
6.6.3.2B	Minimum requirements for Home BS (Category A and B)	88
6.6.3.2C	Minimum requirements for Medium Range BS (Category A and B)	89
6.6.3.2D	Minimum requirements for Local Area and Medium Range BS in Band 46 (Category A and B).....	91
6.6.3.2E	Minimum requirements for standalone NB-IoT Wide Area BS.....	92
6.6.3.2F	Minimum requirements for standalone NB-IoT Local Area BS	92
6.6.3.2G	Minimum requirements for standalone NB-IoT Home BS (Category A and B).....	93
6.6.3.2H	Minimum requirements for standalone NB-IoT Medium Range BS	95
6.6.3.3	Additional requirements.....	96
6.6.4	Transmitter spurious emissions.....	101
6.6.4.1	Mandatory Requirements.....	101
6.6.4.1.1	Spurious emissions (Category A).....	101
6.6.4.1.2	Spurious emissions (Category B)	102
6.6.4.2	Protection of the BS receiver of own or different BS	102
6.6.4.2.1	Minimum Requirement	102
6.6.4.3	Additional spurious emissions requirements	102
6.6.4.3.1	Minimum Requirement	103
6.6.4.4	Co-location with other base stations	118
6.6.4.4.1	Minimum Requirement	118
6.7	Transmitter intermodulation.....	130
6.7.1	Minimum requirement	130
6.7.2	Additional requirement for Band 41	131
7	Receiver characteristics	132
7.1	General	132
7.2	Reference sensitivity level.....	133
7.2.1	Minimum requirement	133
7.3	Dynamic range	137
7.3.1	Minimum requirement	138
7.4	In-channel selectivity	144
7.4.1	Minimum requirement	144
7.5	Adjacent Channel Selectivity (ACS) and narrow-band blocking.....	151
7.5.1	Minimum requirement	151
7.6	Blocking	162
7.6.1	General blocking requirement.....	162
7.6.1.1	Minimum requirement	162
7.6.2	Co-location with other base stations	177
7.6.2.1	Minimum requirement	177
7.6.3	Additional requirement (regional)	189
7.7	Receiver spurious emissions.....	189
7.7.1	Minimum requirement	189
7.8	Receiver intermodulation	190
7.8.1	Minimum requirement	190

8	Performance requirement	205
8.1	General	205
8.2	Performance requirements for PUSCH	205
8.2.1	Requirements in multipath fading propagation conditions	205
8.2.1.1	Minimum requirements	206
8.2.2	Requirements for UL timing adjustment	225
8.2.2.1	Minimum requirements	226
8.2.3	Requirements for high speed train	226
8.2.3.1	Minimum requirements	227
8.2.4	Requirements for HARQ-ACK multiplexed on PUSCH	227
8.2.4.1	Minimum requirement	228
8.2.5	Requirements for PUSCH with TTI bundling and enhanced HARQ pattern	228
8.2.5.1	Minimum requirements	229
8.2.6	Enhanced performance requirement type A in multipath fading propagation conditions with synchronous interference	229
8.2.6.1	Minimum requirements	230
8.2.6A	Enhanced performance requirement type A in multipath fading propagation conditions with asynchronous interference	232
8.2.6A.1	Minimum requirements	233
8.2.7	Requirements for PUSCH supporting coverage enhancement	234
8.2.8	Requirements for PUSCH of Frame structure type 3	236
8.2.9	Enhanced performance requirement type B in multipath fading propagation conditions	237
8.2.9.1	Minimum requirements	239
8.2.10	Requirements for PUSCH supporting subPRB transmission	241
8.3	Performance requirements for PUCCH	243
8.3.1	DTX to ACK performance	243
8.3.1.1	Minimum requirement	243
8.3.2	ACK missed detection requirements for single user PUCCH format 1a	243
8.3.2.1	Minimum requirements	244
8.3.3	CQI performance requirements for PUCCH format 2	244
8.3.3.1	Minimum requirements	244
8.3.4	ACK missed detection requirements for multi user PUCCH format 1a	245
8.3.4.1	Minimum requirement	245
8.3.5	ACK missed detection requirements for PUCCH format 1b with Channel Selection	245
8.3.5.1	Minimum requirements	246
8.3.6	ACK missed detection requirements for PUCCH format 3	246
8.3.6.1	Minimum requirements	246
8.3.7	NACK to ACK requirements for PUCCH format 3	247
8.3.7.1	Minimum requirement	247
8.3.8	CQI performance requirements for PUCCH format 2 with DTX detection	247
8.3.8.1	Minimum requirements	248
8.3.9	PUCCH performance requirements for coverage enhancement	248
8.3.9.1	DTX to ACK performance	248
8.3.9.1.1	Minimum requirement	248
8.3.9.2	ACK missed detection requirements for single user PUCCH format 1a	248
8.3.9.2.1	Minimum requirements	249
8.3.9.3	CQI performance requirements for PUCCH format 2	249
8.3.9.3.1	Minimum requirements	249
8.3.10	ACK missed detection requirements for PUCCH format 4	249
8.3.10.1	Minimum requirements	250
8.3.11	ACK missed detection requirements for PUCCH format 5	250
8.3.11.1	Minimum requirements	250
8.4	Performance requirements for PRACH	251
8.4.1	PRACH False alarm probability	251
8.4.1.1	Minimum requirement	251
8.4.2	PRACH detection requirements	251
8.4.2.1	Minimum requirements	251
8.5	Performance requirements for Narrowband IoT	253
8.5.1	Requirements for NPUSCH format 1	253
8.5.1.1	Requirements	253
8.5.1.1.1	Minimum requirements	254
8.5.2	Performance requirements for NPUSCH format 2	255

8.5.2.1	DTX to ACK performance	255
8.5.2.1.1	Minimum requirement	255
8.5.2.2	ACK missed detection requirements	255
8.5.2.2.1	Minimum requirements	255
8.5.3	Performance requirements for NPRACH	256
8.5.3.1	NPRACH False alarm probability	256
8.5.3.1.1	Minimum requirement	256
8.5.3.2	NPRACH detection requirements	256
8.5.3.2.1	Minimum requirements	256
8.6	Performance requirements for subslot-PUSCH	257
8.6.1	Requirements	257
8.6.1.1	Minimum requirements	257
8.7	Performance requirements for SPUCCH	258
8.7.1	ACK missed detection requirements for single user SPUCCH format 1a	258
8.7.1.1	Minimum requirements	258
8.7.2	ACK missed detection requirements for SPUCCH format 4	258
8.7.2.1	Minimum requirements	258
9	Void	260
Annex A (normative): Reference measurement channels		261
A.1	Fixed Reference Channels for reference sensitivity and in-channel selectivity (QPSK, R=1/3)	262
A.2	Fixed Reference Channels for dynamic range (16QAM, R=2/3)	263
A.3	Fixed Reference Channels for performance requirements (QPSK 1/3)	263
A.4	Fixed Reference Channels for performance requirements (16QAM 3/4)	264
A.5	Fixed Reference Channels for performance requirements (64QAM 5/6)	264
A.6	PRACH Test preambles	264
A.7	Fixed Reference Channels for UL timing adjustment (Scenario 1)	265
A.8	Fixed Reference Channels for UL timing adjustment (Scenario 2)	266
A.9	Multi user PUCCH test	266
A.10	PUCCH transmission on two antenna ports test	266
A.11	Fixed Reference Channel for PUSCH with TTI bundling and enhanced HARQ pattern	267
A.12	Fixed Reference Channels for performance requirements (QPSK 0.36)	267
A.13	Fixed Reference Channels for performance requirements (16QAM 1/2)	268
A.14	Fixed Reference Channels for NB-IOT reference sensitivity ($\pi/2$ BPSK, R=1/3)	268
A.15	Fixed Reference Channels for NB-IoT dynamic range ($\pi/4$ QPSK, R=2/3)	268
A.16	Fixed Reference Channels for NB-IoT NPUSCH format 1	269
A.16.1	One PRB	269
A.17	Fixed Reference Channels for performance requirements (256QAM 5/6)	270
A.18	Fixed Reference Channels for PUSCH transmission in UpPTS (16QAM 0.65)	270
A.19	Fixed Reference Channels for PUSCH transmission in UpPTS (256QAM 0.69)	271
A.20	Fixed Reference Channels for PUSCH of Frame structure type 3	271
A.21	Fixed Reference Channels for performance requirements (QPSK 3/5)	272
A.22	Fixed Reference Channels for performance requirements (64QAM 1/2)	273
A.23	Fixed Reference Channels for SubPRB allocation reference sensitivity ($\pi/2$ BPSK, R=1/3)	273
A.24	Fixed Reference Channel for subslot-PUSCH	274
A.25	Fixed Reference Channels for PUSCH with SubPRB transmission	274

Annex B (normative):	Propagation conditions.....	275
B.1	Static propagation condition.....	275
B.2	Multi-path fading propagation conditions.....	275
B.3	High speed train condition	276
B.4	Moving propagation conditions.....	277
B.5	Multi-Antenna channel models	278
B.5.1	Definition of MIMO Correlation Matrices.....	278
B.5.2	MIMO Correlation Matrices at High, Medium and Low Level	279
B.5A	Multi-Antenna channel models using cross polarized antennas.....	281
B.5A.1	Definition of MIMO Correlation Matrices using cross polarized antennas.....	282
B.5A.2	Spatial Correlation Matrices at UE and eNB sides.....	282
B.5A.2.1	Spatial Correlation Matrices at UE side.....	282
B.5A.2.2	Spatial Correlation Matrices at eNB side.....	283
B.5A.3	MIMO Correlation Matrices using cross polarized antennas	283
B.6	Interference model for enhanced performance requirements type A and type B	283
B.6.1	Dominant interferer proportion	283
B.6.2	Interference model for synchronous scenario.....	284
B.6.3	Interference model for asynchronous scenario	284
Annex C (normative):	Characteristics of the interfering signals.....	285
Annex D (normative):	Environmental requirements for the BS equipment	286
Annex E (normative):	Error Vector Magnitude.....	287
E.1	Reference point for measurement.....	287
E.2	Basic unit of measurement	287
E.3	Modified signal under test.....	288
E.4	Estimation of frequency offset.....	288
E.5	Estimation of time offset	288
E.5.1	Window length	289
E.6	Estimation of TX chain amplitude and frequency response parameters	290
E.7	Averaged EVM	291
Annex F (Informative):	Unwanted emission requirements for multi-carrier BS	293
F.1	General	293
F.2	Multi-carrier BS of different E-UTRA channel bandwidths	293
F.3	Multi-carrier BS of E-UTRA and UTRA.....	293
Annex G (Informative):	Regional requirement for protection of DTT	294
G.1	Regional requirement for protection of DTT	294
G.2	Regional requirement for Public Safety LTE BS in Korea	294
Annex H (Informative):	Calculation of EIRP based on manufacturer declarations and site specific conditions	297
H.1	Calculation of EIRP based on manufacturer declarations and site specific conditions.....	297
Annex I (Informative):	Change history	298
History		312

Foreword

This Technical Specification has been produced by the 3rd Generation Partnership Project (3GPP).

The contents of the present document are subject to continuing work within the TSG and may change following formal TSG approval. Should the TSG modify the contents of the present document, it will be re-released by the TSG with an identifying change of release date and an increase in version number as follows:

Version x.y.z

where:

- x the first digit:
 - 1 presented to TSG for information;
 - 2 presented to TSG for approval;
 - 3 or greater indicates TSG approved document under change control.
- y the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- z the third digit is incremented when editorial only changes have been incorporated in the document.

**iTeh STANDARD
PREVIEW
(standards.iteh.ai)**

ETSI TS 136 104 V15.15.0 (2022-04)

[https://standards.iteh.ai/catalog/standards/sist/6fc74974-
eb47-4dba-81c0-72e4777f53e2/etsi-ts-136-104-v15-15-
0-2022-04](https://standards.iteh.ai/catalog/standards/sist/6fc74974-eb47-4dba-81c0-72e4777f53e2/etsi-ts-136-104-v15-15-0-2022-04)

1 Scope

The present document establishes the minimum RF characteristics and minimum performance requirements of E-UTRA, E-UTRA with NB-IoT or NB-IoT Base Station (BS).

2 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- References are either specific (identified by date of publication, edition number, version number, etc.) or non-specific.
- For a specific reference, subsequent revisions do not apply.
- For a non-specific reference, the latest version applies. In the case of a reference to a 3GPP document (including a GSM document), a non-specific reference implicitly refers to the latest version of that document *in the same Release as the present document*.

- [1] 3GPP TR 21.905: "Vocabulary for 3GPP Specifications".
- [2] ITU-R Recommendation SM.329: "Unwanted emissions in the spurious domain".
- [3] ITU-R Recommendation M.1545: "Measurement uncertainty as it applies to test limits for the terrestrial component of International Mobile Telecommunications-2000".
- [4] 3GPP TS 36.141: "Evolved Universal Terrestrial Radio Access (E-UTRA); Base Station (BS) conformance testing".
- [5] ITU-R recommendation SM.328: "Spectra and bandwidth of emissions".
- [6] 3GPP TS 25.104: "Base Station (BS) radio transmission and reception (FDD)".
- [7] 3GPP TS 25.105: "Base Station (BS) radio transmission and reception (TDD)".
- [8] 3GPP TR 25.942: "RF system scenarios".
- [9] 3GPP TR 36.942: "E-UTRA RF system scenarios".
- [10] 3GPP TS 36.211: "Evolved Universal Terrestrial Radio Access (E-UTRA); Physical Channels and Modulation".
- [11] 3GPP TS 36.213: "Evolved Universal Terrestrial Radio Access (E-UTRA); Physical layer procedures".
- [12] ECC/DEC/(09)03 "Harmonised conditions for MFCN in the band 790-862 MHz", 30 Oct. 2009
- [13] IEC 60721-3-3 (2002): "Classification of environmental conditions - Part 3: Classification of groups of environmental parameters and their severities - Section 3: Stationary use at weather protected locations".
- [14] IEC 60721-3-4 (1995): "Classification of environmental conditions - Part 3: Classification of groups of environmental parameters and their severities - Section 4: Stationary use at non-weather protected locations".
- [15] 3GPP TS 37.104: "E-UTRA, UTRA and GSM/EDGE; Multi-Standard Radio (MSR) Base Station (BS) radio transmission and reception".
- [16] CEPT ECC Decision (13)03, "The harmonised use of the frequency band 1452-1492 MHz for Mobile/Fixed Communications Networks Supplemental Downlink (MFCN SDL)".
- [17] 3GPP TS 36.211: "Evolved Universal Terrestrial Radio Access (E-UTRA); Physical channels and modulation".

- [18] 3GPP TS 36.213: "Evolved Universal Terrestrial Radio Access (E-UTRA); Physical layer procedures".
- [19] CEPT ECC Decision (17)06, "The harmonised use of the frequency bands 1427-1452 MHz and 1492-1518 MHz for Mobile/Fixed Communications Networks Supplemental Downlink (MFCN SDL)".
- [20] 3GPP TS 37.213: "Physical layer procedures for shared spectrum channel access".

3 Definitions, symbols and abbreviations

3.1 Definitions

For the purposes of the present document, the terms and definitions given in TR 21.905 [1] and the following apply. A term defined in the present document takes precedence over the definition of the same term, if any, in TR 21.905 [1].

Aggregated Channel Bandwidth: RF bandwidth in which a base station transmits and/or receives multiple contiguously aggregated carriers.

NOTE: The Aggregated Channel Bandwidth is measured in MHz.

Base station receive period: time during which the base station is receiving data subframes or UpPTS.

Base Station RF Bandwidth: RF bandwidth in which a base station transmits and/or receives single or multiple carrier(s) within a supported operating band.

NOTE: In single E-UTRA carrier operation, the Base Station RF Bandwidth is equal to the channel bandwidth.

Base Station RF Bandwidth edge: frequency of one of the edges of the Base Station RF Bandwidth.

Carrier: modulated waveform conveying the E-UTRA or UTRA physical channels

Carrier aggregation: aggregation of two or more component carriers in order to support wider transmission bandwidths

Carrier aggregation band: a set of one or more operating bands across which multiple carriers are aggregated with a specific set of technical requirements.

NOTE: Carrier aggregation band(s) for an E-UTRA BS is declared by the manufacturer according to the designations in Tables 5.5-2 to 5.5-4.

Channel bandwidth: RF bandwidth supporting a single E-UTRA RF carrier with the transmission bandwidth configured in the uplink or downlink of a cell.

NOTE: The channel bandwidth is measured in MHz and is used as a reference for transmitter and receiver RF requirements.

Channel edge: lowest or highest frequency of the E-UTRA carrier, separated by the channel bandwidth.

Contiguous carriers: set of two or more carriers configured in a spectrum block where there are no RF requirements based on co-existence for un-coordinated operation within the spectrum block.

Contiguous spectrum: spectrum consisting of a contiguous block of spectrum with no sub-block gap(s).

DL RS power: resource element power of Downlink Reference Symbol.

DL NRS power: resource element power of Downlink Narrowband Reference Signal.

Downlink operating band: part of the operating band designated for downlink.

Enhanced performance requirements type A: This defines performance requirements assuming baseline receiver as demodulation reference signal based linear minimum mean square error interference rejection combining.

Enhanced performance requirements type B: This defines performance requirements assuming baseline receiver as code word level interference cancellation for intra-cell inter-user interference plus demodulation reference signal based linear minimum mean square error interference rejection combining for inter-cell interference.

Highest carrier: carrier with the highest carrier centre frequency transmitted/received in a specified operating band.

Inter RF Bandwidth gap: frequency gap between two consecutive Base Station RF Bandwidths that are placed within two supported operating bands.

Inter-band carrier aggregation: carrier aggregation of component carriers in different operating bands.

NOTE: Carriers aggregated in each band can be contiguous or non-contiguous.

Inter-band gap: The frequency gap between two supported consecutive operating bands.

Intra-band contiguous carrier aggregation: contiguous carriers aggregated in the same operating band.

Intra-band non-contiguous carrier aggregation: non-contiguous carriers aggregated in the same operating band.

Lower sub-block edge: frequency at the lower edge of one sub-block.

NOTE: It is used as a frequency reference point for both transmitter and receiver requirements.

Lowest carrier: carrier with the lowest carrier centre frequency transmitted/received in a specified operating band.

Maximum output power: mean power level per carrier of the base station measured at the antenna connector in a specified reference condition.

Maximum throughput: maximum achievable throughput for a reference measurement channel.

Mean power: power measured in the channel bandwidth of the carrier.

NOTE: The period of measurement shall be at least one subframe (1ms), unless otherwise stated.

Measurement bandwidth: RF bandwidth in which an emission level is specified.

Multi-band base station: base station characterized by the ability of its transmitter and/or receiver to process two or more carriers in common active RF components simultaneously, where at least one carrier is configured at a different operating band (which is not a sub-band or superseding-band of another supported operating band) than the other carrier(s).

Multi-band transmitter: transmitter characterized by the ability to process two or more carriers in common active RF components simultaneously, where at least one carrier is configured at a different operating band (which is not a sub-band or superseding-band of another supported operating band) than the other carrier(s).

Multi-band receiver: receiver characterized by the ability to process two or more carriers in common active RF components simultaneously, where at least one carrier is configured at a different operating band (which is not a sub-band or superseding-band of another supported operating band) than the other carrier(s).

Multi-carrier transmission configuration: set of one or more contiguous or non-contiguous carriers that a BS is able to transmit simultaneously according to the manufacturer's specification.

NB-IoT In-band operation: NB-IoT is operating in-band when it utilizes the resource block(s) within a normal E-UTRA carrier

NB-IoT guard band operation: NB-IoT is operating in guard band when it utilizes the unused resource block(s) within a E-UTRA carrier's guard-band.

NB-IoT standalone operation: NB-IoT is operating standalone when it utilizes its own spectrum, for example the spectrum currently being used by GERAN systems as a replacement of one or more GSM carriers, as well as scattered spectrum for potential IoT deployment.

Non-contiguous spectrum: spectrum consisting of two or more sub-blocks separated by sub-block gap(s).

Occupied bandwidth: width of a frequency band such that, below the lower and above the upper frequency limits, the mean powers emitted are each equal to a specified percentage $\beta/2$ of the total mean power of a given emission.

Operating band: frequency range in which E-UTRA operates (paired or unpaired), that is defined with a specific set of technical requirements.

NOTE: The operating band(s) for an E-UTRA BS is declared by the manufacturer according to the designations in table 5.5-1.

Output power: mean power of one carrier of the base station, delivered to a load with resistance equal to the nominal load impedance of the transmitter.

Radio Bandwidth: frequency difference between the upper edge of the highest used carrier and the lower edge of the lowest used carrier.

Rated output power: mean power level per carrier that the manufacturer has declared to be available at the antenna connector during the transmitter ON period.

RE power control dynamic range: difference between the power of a RE and the average RE power for a BS at maximum output power for a specified reference condition.

RRC filtered mean power: mean power of an UTRA carrier as measured through a root raised cosine filter with roll-off factor α and a bandwidth equal to the chip rate of the radio access mode.

NOTE 1: The RRC filtered mean power of a perfectly modulated UTRA signal is 0.246 dB lower than the mean power of the same signal.

sTTI: A transmission time interval (TTI) of either one slot or one subslot as defined in [10] on either uplink or downlink.

Sub-band: A sub-band of an operating band contains a part of the uplink and downlink frequency range of the operating band.

Sub-block: one contiguous allocated block of spectrum for transmission and reception by the same base station.

NOTE: There may be multiple instances of sub-blocks within a Base Station RF Bandwidth.

Sub-block bandwidth: bandwidth of one sub-block.

Sub-block gap: frequency gap between two consecutive sub-blocks within a Base Station RF Bandwidth, where the RF requirements in the gap are based on co-existence for un-coordinated operation.

Superseding-band: A superseding-band of an operating band includes the whole of the uplink and downlink frequency range of the operating band.

Synchronized operation: operation of TDD in two different systems, where no simultaneous uplink and downlink occur.

Throughput: number of payload bits successfully received per second for a reference measurement channel in a specified reference condition.

Total power dynamic range: difference between the maximum and the minimum transmit power of an OFDM symbol for a specified reference condition.

Transmission bandwidth: RF Bandwidth of an instantaneous transmission from a UE or BS, measured in resource block units.

Transmission bandwidth configuration: highest transmission bandwidth allowed for uplink or downlink in a given channel bandwidth, measured in resource block units.

Transmitter ON period: time period during which the BS transmitter is transmitting data and/or reference symbols, i.e. data subframes or DwPTS.

Transmitter OFF period: time period during which the BS transmitter is not allowed to transmit.

Transmitter transient period: time period during which the transmitter is changing from the OFF period to the ON period or vice versa.

Unsynchronized operation: operation of TDD in two different systems, where the conditions for synchronized operation are not met.

Uplink operating band: part of the operating band designated for uplink.

Upper sub-block edge: frequency at the upper edge of one sub-block.

NOTE: It is used as a frequency reference point for both transmitter and receiver requirements.

3.2 Symbols

For the purposes of the present document, the following symbols apply:

α	Roll-off factor
β	Percentage of the mean transmitted power emitted outside the occupied bandwidth on the assigned channel
BW	Bandwidth
BW _{Channel}	Channel bandwidth
BW _{Channel,CA}	Aggregated Channel Bandwidth, expressed in MHz. $BW_{Channel,CA} = F_{edge_high} - F_{edge_low}$.
BW _{Channel,block}	Sub-block bandwidth, expressed in MHz. $BW_{Channel,block} = F_{edge_block,high} - F_{edge_block,low}$.
BW _{Config}	Transmission bandwidth configuration, expressed in MHz, where $BW_{Config} = N_{RB} \times 180$ kHz in the uplink and $BW_{Config} = 15$ kHz + $N_{RB} \times 180$ kHz in the downlink.
CA _X	Intra-band contiguous CA of component carriers in one sub-block within band X where X is the applicable E-UTRA operating band
CA _{X-X}	Intra-band non-contiguous CA of component carriers in two sub-blocks within band X where X is the applicable E-UTRA operating band
CA _{X-Y}	Inter-band CA of component carrier(s) in one sub-block within band X and component carrier(s) in one sub-block within Band Y where X and Y are the applicable E-UTRA operating bands
CA _{X-X-Y}	CA of component carriers in two sub-blocks within Band X and component carrier(s) in one sub-block within Band Y where X and Y are the applicable E-UTRA operating bands
f	Frequency
Δf	Separation between the channel edge frequency and the nominal -3dB point of the measuring filter closest to the carrier frequency
Δf_{max}	The largest value of Δf used for defining the requirement
F_C	Carrier centre frequency
$F_{C,block,high}$	Centre frequency of the highest transmitted/received carrier in a sub-block.
$F_{C,block,low}$	Centre frequency of the lowest transmitted/received carrier in a sub-block.
$F_{C,low}$	The carrier centre frequency of the lowest carrier, expressed in MHz.
$F_{C,high}$	The carrier centre frequency of the highest carrier, expressed in MHz.
F_{edge_low}	The lower edge of Aggregated Channel Bandwidth, expressed in MHz. $F_{edge_low} = F_{C,low} - F_{offset}$.
F_{edge_high}	The upper edge of Aggregated Channel Bandwidth, expressed in MHz. $F_{edge_high} = F_{C,high} + F_{offset}$.
$F_{edge_block,low}$	The lower sub-block edge, where $F_{edge_block,low} = F_{C,block,low} - F_{offset}$.
$F_{edge_block,high}$	The upper sub-block edge, where $F_{edge_block,high} = F_{C,block,high} + F_{offset}$.
F_{offset}	Frequency offset from $F_{C,high}$ to the upper Base Station RF Bandwidth edge, or from $F_{C,block,high}$ to the upper sub-block edge, or $F_{C,low}$ to the lower Base Station RF Bandwidth edge, or from $F_{C,block,low}$ to the lower sub-block edge.
F_{filter}	Filter centre frequency
f_{offset}	Separation between the channel edge frequency and the centre of the measuring filter
$f_{offset_{max}}$	The maximum value of f_{offset} used for defining the requirement
F_{DL_low}	The lowest frequency of the downlink operating band
F_{DL_high}	The highest frequency of the downlink operating band
F_{UL_low}	The lowest frequency of the uplink operating band
F_{UL_high}	The highest frequency of the uplink operating band
G_{ant}	Net antenna gain
M_{DL}	Offset of NB-IoT Downlink channel number to Downlink EARFCN
M_{UL}	Offset of NB-IoT Uplink channel number to Uplink EARFCN
N_{ant}	Number of transmitter antennas
N_{DL}	Downlink EARFCN
$N_{Offs-DL}$	Offset used for calculating downlink EARFCN

$N_{\text{Offs-UL}}$	Offset used for calculating uplink EARFCN
N_{CS}	Number of Cyclic shifts for preamble generation in PRACH
N_{RB}	Transmission bandwidth configuration, expressed in units of resource blocks
N_{UL}	Uplink EARFCN
$P_{10\text{MHz}}$	Maximum output Power within 10 MHz
$P_{\text{EIRP},N}$	EIRP level for channel N
$P_{\text{EIRP},N,\text{MAX}}$	Maximum EIRP level for channel N
$P_{\text{EM},N}$	Declared emission level for channel N
$P_{\text{EM},B32,B75,B76,\text{ind}}$	Declared emission level in Band 32, Band 75 and Band 76, ind=a, b, c
$P_{\text{EM},B32,\text{ind}}$	Declared emission level in Band 32, ind=d, e
$P_{\text{EM},B50,B74,B75,\text{ind}}$	Declared emission level for Band 50, Band 74 and Band 75, ind=a,b
$P_{\text{max},c}$	Maximum carrier output power
P_{out}	Output power (per carrier)
$P_{\text{rated},c}$	Rated output power (per carrier)
P_{REFSENS}	Reference Sensitivity power level
T_{A}	Timing advance command, as defined in [11]
T_{s}	Basic time unit, as defined in [10]
W_{gap}	Sub-block gap or Inter RF Bandwidth gap size

3.3 Abbreviations

For the purposes of the present document, the abbreviations given in TR 21.905 [1] and the following apply. An abbreviation defined in the present document takes precedence over the definition of the same abbreviation, if any, in TR 21.905 [1].

ACLR	Adjacent Channel Leakage Ratio
ACK	Acknowledgement (in HARQ protocols)
ACS	Adjacent Channel Selectivity
AWGN	Additive White Gaussian Noise
BS	Base Station
CA	Carrier Aggregation
CACLR	Cumulative ACLR
CP	Cyclic prefix
CRC	Cyclic Redundancy Check
CW	Continuous Wave
DC	Direct Current
DFT	Discrete Fourier Transformation
DIP	Dominant Interferer Proportion
DTT	Digital Terrestrial Television
DTX	Discontinuous Transmission
DwPTS	Downlink part of the special subframe (for TDD operation)
EARFCN	E-UTRA Absolute Radio Frequency Channel Number
EIRP	Effective Isotropic Radiated Power
EPA	Extended Pedestrian A model
ETU	Extended Typical Urban model
E-UTRA	Evolved UTRA
EVA	Extended Vehicular A model
EVM	Error Vector Magnitude
FDD	Frequency Division Duplex
FFT	Fast Fourier Transformation
FRC	Fixed Reference Channel
GP	Guard Period (for TDD operation)
GSM	Global System for Mobile communications
HARQ	Hybrid Automatic Repeat Request
ICS	In-Channel Selectivity
ITU-R	Radiocommunication Sector of the ITU
LA	Local Area
LNA	Low Noise Amplifier
MCS	Modulation and Coding Scheme
MFCN	Mobile/Fixed Communications Network