

INTERNATIONAL STANDARD

IEC 61000-4-4

1995

AMENDMENT 2
2001-07

BASIC EMC PUBLICATION

Amendment 2

Electromagnetic compatibility (EMC) –

Part 4-4:

Testing and measurement techniques –

Electrical fast transient/burst immunity test

(<https://standards.iteh.ai>)
Document Preview

<https://standards.iteh.ai/catalog/standards/iec/61000-4-4-1995/AMD2:2001>

<https://standards.iteh.ai/catalog/standards/iec/61000-4-4-1995/AMD2:2001>

*This **English-language** version is derived from the original **bilingual** publication by leaving out all French-language pages. Missing page numbers correspond to the French-language pages.*

© IEC 2001 Copyright - all rights reserved

No part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from the publisher.

International Electrotechnical Commission, 3, rue de Varembe, PO Box 131, CH-1211 Geneva 20, Switzerland
Telephone: +41 22 919 02 11 Telefax: +41 22 919 03 00 E-mail: inmail@iec.ch Web: www.iec.ch



Commission Electrotechnique Internationale
International Electrotechnical Commission
Международная Электротехническая Комиссия

PRICE CODE

D

For price, see current catalogue

FOREWORD

This amendment has been prepared by subcommittee 77B: High-frequency phenomena, of IEC technical committee 77: Electromagnetic compatibility.

The text of this amendment is based on the following documents:

FDIS	Report on voting
77B/314/FDIS	77B/320/RVD

Full information on the voting for the approval of this amendment can be found in the report on voting indicated in the above table.

The committee has decided that the contents of the base publication and its amendments will remain unchanged until 2003. At this date, the publication will be

- reconfirmed;
- withdrawn;
- replaced by a revised edition or
- amended.

INTRODUCTION

This amendment introduces additional requirements for the calibration of the fast transient/burst generator. The intention is to improve the reproducibility of the test.

Page 19

6.1.1 Characteristics and performance of the fast transient/burst generator

Replace the existing title and text of this subclause by the following:

6.1.1 Characteristics of the fast transient/burst generator

- Output voltage range with 1 000 Ω load shall be at least 0,25 kV to 4 kV.
- Output voltage range with 50 Ω load shall be at least 0,125 kV to 2 kV

The generator shall be capable of operating under short-circuit conditions.

Characteristics

- Polarity positive/negative
- Output type coaxial, 50 Ω
- DC blocking capacitor 10 nF \pm 20 %
- Repetition frequency function of the selected test level (see table 2) \pm 20 %
- Relation to the power supply asynchronous
- Burst duration 15 ms \pm 20 %
(see subclause 6.1.2 and figure 2)
- Burst period 300 ms \pm 20 %
(see subclause 6.1.2 and figure 2)
- Wave shape of the pulse
 - into 50 Ω load rise time $t_r = 5 \text{ ns} \pm 30 \%$
duration t_d (to 50 %) = 50 ns $\pm 30 \%$
peak voltage = according to table 2, $\pm 10 \%$
 - into 1 000 Ω load rise time $t_r = 5 \text{ ns} \pm 30 \%$
duration t_d (to 50 %) = 50 ns with a tolerance of -15 ns to $+100 \text{ ns}$
peak voltage = according to table 2, $+10 \%$ / -15% (see the note below table 2)
- Test load impedance 50 $\Omega \pm 2 \%$
1 000 $\Omega \pm 2 \%$ // $\leq 6 \text{ pF}$. The resistance measurement is made at d.c and the capacitance measurement is made using a commercially available capacitance meter that operates at low frequencies.

6.1.2 Verification of the characteristics of the fast transient/burst generator

Replace the existing test of this subclause by the following new text:

The test generator characteristics shall be verified in order to establish a common reference for all generators. For this purpose the following procedure shall be undertaken:

The test generator output is connected to a 50 Ω and 1 000 Ω coaxial termination respectively and the voltage monitored with an oscilloscope. The -3 dB bandwidth of the measuring equipment and test load impedance shall be at least 400 MHz. The test load impedance at 1 000 Ω is likely to become a complex network. The rise time, impulse duration and repetition rate of the impulses within one burst shall be monitored.

The following EFT/B generator characteristics shall be measured with 50 Ω and 1 000 Ω terminations on the EFT/B generator.

NOTE Measures shall be taken to ensure that stray capacitance is kept to a minimum.