

ETSI TS 138 101-1 V15.18.0 (2022-07)



5G ;
NR;

**User Equipment (UE) radio transmission and reception;
Part 1: Range 1 Standalone
(3GPP TS 38.101-1 version 15.18.0 Release 15)**

<https://standards.iteh.ai/catalog/standards/sist/694f0b5d-7eb3-4d54-abc7-8416b5b24cc7/etsi-ts-138-101-1-v15-18-0-2022-07>



ReferenceRTS/TSGR-0438101-1vfi0

Keywords5G

ETSI

650 Route des Lucioles
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - APE 7112B
Association à but non lucratif enregistrée à la
Sous-Préfecture de Grasse (06) N° w061004871

Important notice

The present document can be downloaded from:

<http://www.etsi.org/standards-search>

The present document may be made available in electronic versions and/or in print. The content of any electronic and/or print versions of the present document shall not be modified without the prior written authorization of ETSI. In case of any existing or perceived difference in contents between such versions and/or in print, the prevailing version of an ETSI deliverable is the one made publicly available in PDF format at www.etsi.org/deliver.

Users of the present document should be aware that the document may be subject to revision or change of status.

Information on the current status of this and other ETSI documents is available at

<https://portal.etsi.org/TB/ETSIDeliverableStatus.aspx>

If you find errors in the present document, please send your comment to one of the following services:

<https://standards-portal.etsi.org/People/CommitteeSupportStaff.aspx>

If you find a security vulnerability in the present document, please report it through our
Coordinated Vulnerability Disclosure Program:

<https://www.etsi.org/standards/coordinated-vulnerability-disclosure>

Notice of disclaimer & limitation of liability

The information provided in the present deliverable is directed solely to professionals who have the appropriate degree of experience to understand and interpret its content in accordance with generally accepted engineering or other professional standard and applicable regulations.

No recommendation as to products and services or vendors is made or should be implied.

No representation or warranty is made that this deliverable is technically accurate or sufficient or conforms to any law and/or governmental rule and/or regulation and further, no representation or warranty is made of merchantability or fitness for any particular purpose or against infringement of intellectual property rights.

In no event shall ETSI be held liable for loss of profits or any other incidental or consequential damages.

Any software contained in this deliverable is provided "AS IS" with no warranties, express or implied, including but not limited to, the warranties of merchantability, fitness for a particular purpose and non-infringement of intellectual property rights and ETSI shall not be held liable in any event for any damages whatsoever (including, without limitation, damages for loss of profits, business interruption, loss of information, or any other pecuniary loss) arising out of or related to the use of or inability to use the software.

Copyright Notification

No part may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm except as authorized by written permission of ETSI.

The content of the PDF version shall not be modified without the written authorization of ETSI.

The copyright and the foregoing restriction extend to reproduction in all media.

© ETSI 2022.
All rights reserved.

Intellectual Property Rights

Essential patents

IPRs essential or potentially essential to normative deliverables may have been declared to ETSI. The declarations pertaining to these essential IPRs, if any, are publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: *"Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards"*, which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (<https://ipr.etsi.org/>).

Pursuant to the ETSI Directives including the ETSI IPR Policy, no investigation regarding the essentiality of IPRs, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

Trademarks

The present document may include trademarks and/or tradenames which are asserted and/or registered by their owners. ETSI claims no ownership of these except for any which are indicated as being the property of ETSI, and conveys no right to use or reproduce any trademark and/or tradename. Mention of those trademarks in the present document does not constitute an endorsement by ETSI of products, services or organizations associated with those trademarks.

DECT™, **PLUGTESTS™**, **UMTS™** and the ETSI logo are trademarks of ETSI registered for the benefit of its Members. **3GPP™** and **LTE™** are trademarks of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners. **oneM2M™** logo is a trademark of ETSI registered for the benefit of its Members and of the oneM2M Partners. **GSM®** and the GSM logo are trademarks registered and owned by the GSM Association.

Legal Notice

This Technical Specification (TS) has been produced by the ETSI 3rd Generation Partnership Project (3GPP).

The present document may refer to technical specifications or reports using their 3GPP identities. These shall be interpreted as being references to the corresponding ETSI deliverables.

The cross reference between 3GPP and ETSI identities can be found under <http://webapp.etsi.org/key/queryform.asp>.

Modal verbs terminology

In the present document **"shall"**, **"shall not"**, **"should"**, **"should not"**, **"may"**, **"need not"**, **"will"**, **"will not"**, **"can"** and **"cannot"** are to be interpreted as described in clause 3.2 of the [ETSI Drafting Rules](#) (Verbal forms for the expression of provisions).

"must" and **"must not"** are **NOT** allowed in ETSI deliverables except when used in direct citation.

Contents

Intellectual Property Rights	2
Legal Notice	2
Modal verbs terminology.....	2
Foreword.....	11
1 Scope	12
2 References	12
3 Definitions, symbols and abbreviations	12
3.1 Definitions	12
3.2 Symbols.....	13
3.3 Abbreviations	15
4 General	16
4.1 Relationship between minimum requirements and test requirements	16
4.2 Applicability of minimum requirements	16
4.3 Specification suffix information.....	16
5 Operating bands and channel arrangement.....	17
5.1 General	17
5.2 Operating bands.....	17
5.2A Operating bands for CA	18
5.2A.1 Intra-band CA	18
5.2A.2 Inter-band CA	19
5.2A.2.1 Inter-band CA (two bands).....	19
5.2B Void.....	19
5.2C Operating band combination for SUL	19
5.3 UE channel bandwidth	20
5.3.1 General.....	20
5.3.2 Maximum transmission bandwidth configuration	21
5.3.3 Minimum guardband and transmission bandwidth configuration.....	21
5.3.4 RB alignment	22
5.3.5 UE channel bandwidth per operating band	22
5.3.6 Asymmetric channel bandwidths	24
5.3A UE channel bandwidth for CA	25
5.3A.1 General.....	25
5.3A.2 Maximum transmission bandwidth configuration for CA	25
5.3A.3 Minimum guardband and transmission bandwidth configuration for CA	25
5.3A.4 Void	27
5.3A.5 UE channel bandwidth per operating band for CA	27
5.4 Channel arrangement.....	27
5.4.1 Channel spacing.....	27
5.4.1.1 Channel spacing for adjacent NR carriers	27
5.4.2 Channel raster	28
5.4.2.1 NR-ARFCN and channel raster.....	28
5.4.2.2 Channel raster to resource element mapping.....	28
5.4.2.3 Channel raster entries for each operating band	29
5.4.3 Synchronization raster	30
5.4.3.1 Synchronization raster and numbering.....	30
5.4.3.2 Synchronization raster to synchronization block resource element mapping.....	31
5.4.3.3 Synchronization raster entries for each operating band.....	31
5.4.4 TX–RX frequency separation	32
5.4A Channel arrangement for CA.....	33
5.4A.1 Channel spacing for CA.....	33
5.4A.2 Channel raster for CA	33
5.4A.3 Synchronization raster for CA	34
5.4A.4 Tx-Rx frequency separation for CA.....	34

5.5	Void.....	34
5.5A	Configurations for CA.....	34
5.5A.1	Configurations for intra-band contiguous CA.....	34
5.5A.2	Void.....	35
5.5A.3	Configurations for inter-band CA.....	35
5.5A.3.1	Configurations for inter-band CA (two bands)	35
5.5B	Void.....	38
5.5C	Configurations for SUL.....	38
6	Transmitter characteristics	39
6.1	General	39
6.2	Transmitter power	39
6.2.1	UE maximum output power.....	39
6.2.2	UE maximum output power reduction.....	40
6.2.3	UE additional maximum output power reduction.....	41
6.2.3.1	General.....	41
6.2.3.2	A-MPR for NS_04	45
6.2.3.3	A-MPR for NS_10	46
6.2.3.4	A-MPR for NS_05 and NS_05U.....	47
6.2.3.5	A-MPR for NS_40	49
6.2.3.6	A-MPR for NS_43 and NS_43U.....	49
6.2.3.7	A-MPR for NS_03 and NS_03U.....	50
6.2.3.8	A-MPR for NS_37	50
6.2.3.9	A-MPR for NS_38	51
6.2.3.10	A-MPR for NS_39	51
6.2.3.11	A-MPR for NS_41	52
6.2.3.12	A-MPR for NS_42	52
6.2.3.13	A-MPR for NS_18	53
6.2.4	Configured transmitted power	54
6.2A	Transmitter power for CA	56
6.2A.1	UE maximum output power for CA.....	56
6.2A.1.1	Void.....	56
6.2A.1.2	Void.....	56
6.2A.1.3	UE maximum output power for Inter-band CA	56
6.2A.2	UE maximum output power reduction for CA.....	56
6.2A.2.1	Void.....	56
6.2A.2.2	Void.....	56
6.2A.2.3	UE maximum output power reduction for Inter-band CA	56
6.2A.3	UE additional maximum output power reduction for CA.....	56
6.2A.3.1.1	Void.....	56
6.2A.3.1.2	Void.....	56
6.2A.3.1.3	UE additional maximum output power reduction for Inter-band CA	56
6.2A.4	Configured output power for CA.....	57
6.2A.4.1	Configured transmitted power level.....	57
6.2A.4.1.1	Void.....	57
6.2A.4.1.2	Void.....	57
6.2A.4.1.3	Configured transmitted power for Inter-band CA	57
6.2A.4.2	$\Delta T_{IB,c}$ for CA	59
6.2A.4.2.1	Void.....	60
6.2A.4.2.2	Void.....	60
6.2A.4.2.3	$\Delta T_{IB,c}$ for Inter-band CA (two bands).....	60
6.2B	Void.....	60
6.2C	Transmitter power for SUL	60
6.2C.1	Configured transmitted power for SUL	60
6.2C.2	$\Delta T_{IB,c}$	60
6.2D	Transmitter power for UL MIMO	61
6.2D.1	UE maximum output power for UL MIMO.....	61
6.2D.2	UE maximum output power reduction for UL MIMO.....	61
6.2D.3	UE additional maximum output power reduction for UL MIMO.....	62
6.2D.4	Configured transmitted power for UL MIMO	62
6.3	Output power dynamics.....	63
6.3.1	Minimum output power	63

6.3.2	Transmit OFF power.....	63
6.3.3	Transmit ON/OFF time mask	63
6.3.3.1	General	63
6.3.3.2	General ON/OFF time mask	64
6.3.3.3	Transmit power time mask for slot and short or long subslot boundaries.....	64
6.3.3.4	PRACH time mask.....	64
6.3.3.5	Void.....	65
6.3.3.6	SRS time mask	65
6.3.3.7	PUSCH-PUCCH and PUSCH-SRS time masks	67
6.3.3.8	Transmit power time mask for consecutive slot or long subslot transmission and short subslot transmission boundaries	68
6.3.3.9	Transmit power time mask for consecutive short subslot transmissions boundaries	68
6.3.4	Power control.....	69
6.3.4.1	General.....	69
6.3.4.2	Absolute power tolerance.....	69
6.3.4.3	Relative power tolerance.....	69
6.3.4.4	Aggregate power tolerance.....	70
6.3A	Output power dynamics for CA	70
6.3A.1	Minimum output power for CA	70
6.3A.1.1	Void.....	70
6.3A.1.2	Void.....	70
6.3A.1.3	Minimum output power for inter-band CA	70
6.3A.2	Transmit OFF power for CA.....	71
6.3A.2.1	Void.....	71
6.3A.2.2	Void.....	71
6.3A.2.3	Transmit OFF power for inter-band CA.....	71
6.3A.3	Transmit ON/OFF time mask for CA	71
6.3A.3.1	Void.....	71
6.3A.3.2	Void.....	71
6.3A.3.3	Transmit ON/OFF time mask for inter-band CA	71
6.3A.4	Power control for CA.....	71
6.3A.4.1	Void.....	71
6.3A.4.2	Void.....	71
6.3A.4.3	Power control for inter-band CA.....	71
6.3D	Output power dynamics for UL MIMO	71
6.3D.1	Minimum output power for UL MIMO	71
6.3D.2	Transmit OFF power for UL MIMO.....	71
6.3D.3	Transmit ON/OFF time mask for UL MIMO	72
6.3D.4	Power control for UL MIMO.....	72
6.4	Transmit signal quality	72
6.4.1	Frequency error.....	72
6.4.2	Transmit modulation quality.....	72
6.4.2.1	Error Vector Magnitude	72
6.4.2.2	Carrier leakage	73
6.4.2.3	In-band emissions	73
6.4.2.4	EVM equalizer spectrum flatness	74
6.4.2.4.1	Requirements for Pi/2 BPSK modulation.....	75
6.4A	Transmit signal quality for CA.....	76
6.4A.1	Frequency error for CA.....	76
6.4A.1.1	Void.....	76
6.4A.1.2	Void.....	76
6.4A.1.3	Frequency error for inter-band CA.....	76
6.4A.2	Transmit modulation quality for CA.....	76
6.4A.2.1	Void.....	76
6.4A.2.2	Void.....	76
6.4A.2.3	Transmit modulation quality for inter-band CA.....	76
6.4D	Transmit signal quality for UL MIMO.....	77
6.4D.1	Frequency error for UL MIMO.....	77
6.4D.2	Transmit modulation quality for UL MIMO.....	77
6.4D.2.1	Error Vector Magnitude	77
6.4D.2.2	Carrier leakage	77
6.4D.2.3	In-band emissions	77

6.4D.2.4	EVM equalizer spectrum flatness for UL MIMO	77
6.4D.3	Time alignment error for UL MIMO	77
6.4D.4	Requirements for coherent UL MIMO	78
6.5	Output RF spectrum emissions.....	78
6.5.1	Occupied bandwidth	78
6.5.2	Out of band emission	78
6.5.2.1	General	78
6.5.2.2	Spectrum emission mask	79
6.5.2.3	Additional spectrum emission mask	79
6.5.2.3.1	Requirements for network signalling value "NS_35"	79
6.5.2.3.2	Requirements for network signalling value "NS_04"	80
6.5.2.3.3	Requirements for network signalling values "NS_03" and "NS_03U"	81
6.5.2.3.4	Requirements for network signalling value "NS_06"	81
6.5.2.3.5	Void	82
6.5.2.3.6	Void	82
6.5.2.3.7	Void	82
6.5.2.4	Adjacent channel leakage ratio	82
6.5.2.4.1	NR ACLR	82
6.5.2.4.2	UTRA ACLR	82
6.5.3	Spurious emissions	83
6.5.3.1	General spurious emissions	83
6.5.3.2	Spurious emissions for UE co-existence	84
6.5.3.3	Additional spurious emissions	88
6.5.3.3.1	Requirement for network signalling value "NS_04"	88
6.5.3.3.2	Requirement for network signalling value "NS_17"	89
6.5.3.3.3	Requirement for network signalling value "NS_18"	89
6.5.3.3.4	Requirement for network signalling values "NS_05" and "NS_05U"	89
6.5.3.3.5	Requirement for network signalling values "NS_43" and "NS_43U"	89
6.5.3.3.6	Requirement for network signalling value "NS_37"	90
6.5.3.3.7	Requirement for network signalling value "NS_38"	90
6.5.3.3.8	Requirement for network signalling value "NS_39"	90
6.5.3.3.9	Requirement for network signalling value "NS_40"	90
6.5.3.3.10	Requirement for network signalling value "NS_41"	91
6.5.3.3.11	Requirement for network signalling value "NS_42"	91
6.5.3.3.12	Void	91
6.5.3.3.13	Void	91
6.5.3.3.14	Void	91
6.5.3.3.15	Void	91
6.5.3.3.16	Requirement for network signalling value "NS_50"	91
6.5.4	Transmit intermodulation	92
6.5A	Output RF spectrum emissions for CA.....	92
6.5A.1	Occupied bandwidth for CA	92
6.5A.1.1	Void	92
6.5A.1.2	Void	92
6.5A.1.3	Occupied bandwidth for Inter-band CA	92
6.5A.2	Out of band emission for CA	93
6.5A.2.1	General	93
6.5A.2.2	Spectrum emission mask	93
6.5A.2.2.1	Void	93
6.5A.2.2.2	Void	93
6.5A.2.2.3	Spectrum emission mask for Inter-band CA	93
6.5A.2.3	Additional spectrum emission mask	93
6.5A.2.3.1	Void	93
6.5A.2.3.2	Void	93
6.5A.2.3.3	Additional spectrum emission mask for Inter-band CA	93
6.5A.2.4	Adjacent channel leakage ratio	93
6.5A.2.4.1	NR ACLR	93
6.5A.2.4.1.1	Void	93
6.5A.2.4.1.2	Void	93
6.5A.2.4.1.3	NR ACLR for Inter-band CA	93
6.5A.2.4.2	UTRA ACLR	93
6.5A.2.4.2.1	Void	93

6.5A.2.4.2.2	Void	93
6.5A.2.4.2.3	UTRA ACLR for Inter-band CA	93
6.5A.3	Spurious emission for CA.....	93
6.5A.3.1	General spurious emissions.....	93
6.5A.3.2	Spurious emissions for UE co-existence.....	94
6.5A.3.2.1	Void.....	94
6.5A.3.2.2	Void.....	94
6.5A.3.2.3	Spurious emissions for UE co-existence for Inter-band CA.....	94
6.5A.4	Transmit intermodulation for CA	95
6.5A.4.1	Void.....	95
6.5A.4.2	Void.....	95
6.5A.4.3	Transmit intermodulation for Inter-band CA	95
6.5D	Output RF spectrum emissions for UL MIMO.....	95
6.5D.1	Occupied bandwidth for UL MIMO	95
6.5D.2	Out of band emission for UL MIMO	95
6.5D.3	Spurious emission for UL MIMO.....	95
6.5D.4	Transmit intermodulation for UL MIMO	95
7	Receiver characteristics.....	96
7.1	General	96
7.2	Diversity characteristics	96
7.3	Reference sensitivity	96
7.3.1	General.....	96
7.3.2	Reference sensitivity power level.....	96
7.3.3	$\Delta R_{IB,c}$	102
7.3A	Reference sensitivity for CA	102
7.3A.1	General.....	102
7.3A.2	Reference sensitivity power level for CA	102
7.3A.2.1	Reference sensitivity power level for Intra-band contiguous CA	102
7.3A.2.2	Void.....	102
7.3A.2.3	Reference sensitivity power level for Inter-band CA.....	102
7.3A.2.4	Void.....	103
7.3A.3	$\Delta R_{IB,c}$ for CA	104
7.3A.3.1	General.....	104
7.3A.3.2	$\Delta R_{IB,c}$ for Inter-band CA.....	104
7.3A.3.2.1	$\Delta R_{IB,c}$ for two bands	104
7.3A.3.2.2	Void.....	104
7.3A.4	Reference sensitivity exceptions due to UL harmonic interference for CA.....	104
7.3A.5	Reference sensitivity exceptions due to intermodulation interference due to 2UL CA	107
7.3A.6	Reference sensitivity exceptions due to cross band isolation for CA	107
7.3B	Void.....	108
7.3C	Reference sensitivity for SUL	108
7.3C.1	General.....	108
7.3C.2	Reference sensitivity power level for SUL	108
7.3C.3	$\Delta R_{IB,c}$ for SUL	110
7.3C.3.1	General.....	110
7.3C.3.2	SUL band combination	110
7.3C.3.2.1	$\Delta R_{IB,c}$ for two bands	110
7.3D	Reference sensitivity for UL MIMO	110
7.4	Maximum input level	110
7.4A	Maximum input level for CA	111
7.4A.1	Maximum input level for Intra-band contiguous CA.....	111
7.4A.2	Void.....	111
7.4A.3	Maximum input level for Inter-band CA	111
7.4D	Maximum input level for UL MIMO	111
7.5	Adjacent channel selectivity.....	112
7.5A	Adjacent channel selectivity for CA.....	116
7.5A.1	Adjacent channel selectivity for Intra-band contiguous CA	116
7.5A.2	Void.....	118
7.5A.3	Adjacent channel selectivity Inter-band CA	118
7.5D	Adjacent channel selectivity for UL MIMO.....	118
7.6	Blocking characteristics	118

7.6.1	General.....	118
7.6.2	In-band blocking.....	118
7.6.3	Out-of-band blocking.....	120
7.6.4	Narrow band blocking	124
7.6A	Blocking characteristics for CA	125
7.6A.1	General.....	125
7.6A.2	In-band blocking for CA.....	125
7.6A.2.1	In-band blocking for Intra-band contiguous CA.....	125
7.6A.2.2	Void.....	126
7.6A.2.3	In-band blocking for Inter-band CA.....	126
7.6A.3	Out-of-band blocking for CA.....	126
7.6A.3.1	Out-of-band blocking for Intra-band contiguous CA.....	126
7.6A.3.2	Void.....	127
7.6A.3.3	Out-of-band blocking for Inter-band CA	127
7.6A.4	Narrow band blocking for CA	128
7.6A.4.1	Narrow band blocking for Intra-band contiguous CA.....	128
7.6A.4.2	Void 129	
7.6A.4.3	Narrow band blocking for Inter-band CA.....	129
7.6C	Blocking characteristics for SUL	129
7.6C.1	General.....	129
7.6C.2	In-band blocking for SUL.....	129
7.6C.3	Out-of-band blocking for SUL.....	129
7.6C.4	Narrow band blocking for SUL	130
7.6D	Blocking characteristics for UL MIMO	130
7.7	Spurious response.....	130
7.7A	Spurious response for CA.....	132
7.7A.1	Spurious response for Intra-band contiguous CA	132
7.7A.2	Void.....	132
7.7A.3	Spurious response for Inter-band CA.....	132
7.7D	Spurious response for UL MIMO.....	132
7.8	Intermodulation characteristics	132
7.8.1	General.....	132
7.8.2	Wide band Intermodulation	132
7.8A	Intermodulation characteristics for CA	135
7.8A.1	General.....	135
7.8A.2	Wide band intermodulation for CA	135
7.8A.2.1	Wide band intermodulation for Intra-band contiguous CA.....	135
7.8A.2.2	Void.....	136
7.8A.2.3	Wide band intermodulation for Inter-band CA	136
7.8D	Intermodulation characteristics for UL MIMO	136
7.9	Spurious emissions	136
7.9A	Spurious emissions for CA.....	137
7.9A.1	Void.....	137
7.9A.2	Void.....	137
7.9A.3	Spurious emissions for Inter-band CA.....	137
Annex A (normative):	Measurement channels.....	138
A.1	General	138
A.2	UL reference measurement channels	138
A.2.1	General	138
A.2.2	Reference measurement channels.....	139
A.2.2.1	DFT-s-OFDM Pi/2-BPSK	139
A.2.2.2	DFT-s-OFDM QPSK.....	140
A.2.2.3	DFT-s-OFDM 16QAM.....	141
A.2.2.4	DFT-s-OFDM 64QAM.....	142
A.2.2.5	DFT-s-OFDM 256QAM.....	143
A.2.2.6	CP-OFDM QPSK	144
A.2.2.7	CP-OFDM 16QAM	146
A.2.2.8	CP-OFDM 64QAM	149
A.2.2.9	CP-OFDM 256QAM	151
A.2.3	Reference measurement channels for TDD.....	153

A.2.3.1	DFT-s-OFDM Pi/2-BPSK	153
A.2.3.2	DFT-s-OFDM QPSK.....	153
A.2.3.3	DFT-s-OFDM 16QAM.....	153
A.2.3.4	DFT-s-OFDM 64QAM.....	153
A.2.3.5	DFT-s-OFDM 256QAM.....	153
A.2.3.6	CP-OFDM QPSK	154
A.2.3.7	CP-OFDM 16QAM	154
A.2.3.8	CP-OFDM 64QAM	154
A.2.3.9	CP-OFDM 256QAM	154
A.3	DL reference measurement channels	155
A.3.1	General	155
A.3.2	DL reference measurement channels for FDD	156
A.3.2.1	General.....	156
A.3.2.2	FRC for receiver requirements for QPSK.....	156
A.3.2.3	FRC for maximum input level for 64QAM	159
A.3.2.4	FRC for maximum input level for 256 QAM	162
A.3.3	DL reference measurement channels for TDD.....	165
A.3.3.1	General.....	165
A.3.3.2	FRC for receiver requirements for QPSK.....	166
A.3.3.3	FRC for maximum input level for 64QAM	169
A.3.3.4	FRC for maximum input level for 256 QAM	172
A.4	CSI reference measurement channels.....	175
A.5	OFDMA Channel Noise Generator (OCNG)	175
A.5.1	OCNG Patterns for FDD	175
A.5.1.1	OCNG FDD pattern 1: Generic OCNG FDD Pattern for all unused REs.....	175
A.5.2	OCNG Patterns for TDD.....	175
A.5.2.1	OCNG TDD pattern 1: Generic OCNG TDD Pattern for all unused REs	175
A.6	Void.....	175
Annex B (informative):	Void	176
Annex C (informative):	Downlink physical channels.....	177
C.1	General	177
C.2	Setup.....	177
C.3	Connection	177
C.3.1	Measurement of Receiver Characteristics	177
Annex D (normative):	Characteristics of the interfering signal	178
D.1	General	178
D.2	Interference signals.....	178
Annex E (normative):	Environmental conditions	180
E.1	General	180
E.2	Environmental	180
E.2.1	Temperature	180
E.2.2	Voltage	180
E.2.3	Vibration.....	181
Annex F (normative):	Transmit modulation.....	182
F.0	General	182
F.1	Measurement Point.....	182
F.2	Basic Error Vector Magnitude measurement	182
F.3	Basic in-band emissions measurement.....	183

F.4	Modified signal under test	183
F.5	Window length	185
F.5.1	Timing offset	185
F.5.2	Window length	185
F.5.3	Window length for normal CP	185
F.5.4	Window length for Extended CP	187
F.5.5	Window length for PRACH	187
F.6	Averaged EVM	188
F.7	Spectrum Flatness	189
Annex G (normative):	Difference of relative phase and power errors	190
G.0	General	190
G.1	Measurement Point	190
G.2	Relative Phase Error Measurement	191
G.2.1	Symbols used	191
G.2.2	CFO (carrier frequency offset) correction	191
G.2.3	Steps of the measurement method	191
Annex H (normative):	ModifiedMPR-Behavior	192
H.1	Indication of modified MPR behavior	192
Annex I (informative):	Void	193
Annex J (informative):	Void	194
Annex K (informative):	Void	195
Annex L (informative):	Change history	196
History	ETSI TS 138 101-1 V15.18.0 (2022-07) https://standards.iteh.ai/catalog/standards/sist/69416b5d-7c63-4d54-abc7-8416b5b24cc7/etsi-ts-138-101-1-v15-18-0-2022-07	208

Foreword

This Technical Specification has been produced by the 3rd Generation Partnership Project (3GPP).

The contents of the present document are subject to continuing work within the TSG and may change following formal TSG approval. Should the TSG modify the contents of the present document, it will be re-released by the TSG with an identifying change of release date and an increase in version number as follows:

Version x.y.z

where:

- x the first digit:
 - 1 presented to TSG for information;
 - 2 presented to TSG for approval;
 - 3 or greater indicates TSG approved document under change control.
- y the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- z the third digit is incremented when editorial only changes have been incorporated in the document.

i T e h S T A N D A R D P R E V I
(s t a n d a r d s . i t e h . a

E T S I T S 1 3 8 1 0 1 - 1 V 1 5 . 1 8 .
h t t p s : / / s t a n d a r d s . i t e h . a i / c a t a l o g / s
8 4 1 6 b 5 b 2 4 c c 7 / e t s i - t s - 1 3 8 - 1 0 1

1 Scope

The present document establishes the minimum RF requirements for NR User Equipment (UE) operating on frequency Range 1.

2 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

References are either specific (identified by date of publication, edition number, version number, etc.) or non-specific.

For a specific reference, subsequent revisions do not apply.

For a non-specific reference, the latest version applies. In the case of a reference to a 3GPP document (including a GSM document), a non-specific reference implicitly refers to the latest version of that document in the same Release as the present document.

- [1] 3GPP TR 21.905: "Vocabulary for 3GPP Specifications".
- [2] 3GPP TS 38.101-2: "NR; User Equipment (UE) radio transmission and reception; Part 2: Range 2 Standalone".
- [3] 3GPP TS 38.101-3: "NR; User Equipment (UE) radio transmission and reception; Part 3: Range 1 and Range 2 Interworking operation with other radios".
- [4] 3GPP TS 38.521-1: "NR; User Equipment (UE) conformance specification; Radio transmission and reception; Part 1: Range 1 Standalone".
- [5] Recommendation ITU-R M.1545: "Measurement uncertainty as it applies to test limits for the terrestrial component of International Mobile Telecommunications-2000".
- [6] 3GPP TS 38.211: "NR; Physical channels and modulation".
- [7] 3GPP TS 38.331: "Radio Resource Control (RRC) protocol specification".
- [8] 3GPP TS 38.213: "NR; Physical layer procedures for control".
- [9] ITU-R Recommendation SM.329-10, "Unwanted emissions in the spurious domain".
- [10] 3GPP TS 38.214: "NR; Physical layer procedures for data".

3 Definitions, symbols and abbreviations

3.1 Definitions

For the purposes of the present document, the terms and definitions given in 3GPP TR 21.905 [1] and the following apply. A term defined in the present document takes precedence over the definition of the same term, if any, in 3GPP TR 21.905 [1].

Aggregated Channel Bandwidth: The RF bandwidth in which a UE transmits and receives multiple contiguously aggregated carriers.

Carrier aggregation: Aggregation of two or more component carriers in order to support wider transmission bandwidths.

Carrier aggregation band: A set of one or more operating bands across which multiple carriers are aggregated with a specific set of technical requirements.

Carrier aggregation bandwidth class: A class defined by the aggregated transmission bandwidth configuration and maximum number of component carriers supported by a UE.

Carrier aggregation configuration: A combination of CA operating band(s) and CA bandwidth class(es) supported by a UE.

Contiguous carriers: A set of two or more carriers configured in a spectrum block where there are no RF requirements based on co-existence for un-coordinated operation within the spectrum block.

Contiguous resource allocation: A resource allocation of consecutive resource blocks within one carrier or across contiguously aggregated carriers. The gap between contiguously aggregated carriers due to the nominal channel spacing is allowed.

Contiguous spectrum: Spectrum consisting of a contiguous block of spectrum with no sub-block gaps.

Inter-band carrier aggregation: Carrier aggregation of component carriers in different operating bands.

NOTE: Carriers aggregated in each band can be contiguous or non-contiguous.

Intra-band contiguous carrier aggregation: Contiguous carriers aggregated in the same operating band.

Intra-band non-contiguous carrier aggregation: Non-contiguous carriers aggregated in the same operating band.

Sub-block: This is one contiguous allocated block of spectrum for transmission and reception by the same UE. There may be multiple instances of sub-blocks within an RF bandwidth.

Sub-block bandwidth: The bandwidth of one sub-block.

Sub-block gap: A frequency gap between two consecutive sub-blocks within an RF bandwidth, where the RF requirements in the gap are based on co-existence for un-coordinated operation.

UE transmission bandwidth configuration: Set of resource blocks located within the UE channel bandwidth which may be used for transmitting or receiving by the UE.

Vehicular UE: A UE embedded in a vehicle, permanently connected to an embedded antenna system that radiates externally for NR operating bands.

NOTE: Vehicular UE does not refer to other UE form factors placed inside the vehicle.

3.2 Symbols

For the purposes of the present document, the following symbols apply:

ΔF_{Global}	Granularity of the global frequency raster
ΔF_{Raster}	Band dependent channel raster granularity
Δf_{OOB}	Δ Frequency of Out Of Band emission
$\Delta F_{\text{TX-RX}}$	Δ Frequency of default TX-RX separation of the FDD <i>operating band</i>
$\Delta P_{\text{PowerClass}}$	Adjustment to maximum output power for a given power class
ΔR_{B}	The starting frequency offset between the allocated RB and the measured non-allocated RB
$\Delta R_{\text{IB},c}$	Allowed reference sensitivity relaxation due to support for inter-band CA operation, for serving cell c
$\Delta R_{\text{IB},4R}$	Reference sensitivity adjustment due to support for 4 antenna ports
Δ_{Shift}	Channel raster offset
ΔT_{C}	Allowed operating band edge transmission power relaxation
$\Delta T_{\text{C},c}$	Allowed operating band edge transmission power relaxation for serving cell c
$\Delta T_{\text{IB},c}$	Allowed maximum configured output power relaxation due to support for inter-band CA operation and due to support for SUL operations, for serving cell c
BW_{Channel}	Channel bandwidth
$BW_{\text{Channel,block}}$	Sub-block bandwidth, expressed in MHz. $BW_{\text{Channel,block}} = F_{\text{edge,block,high}} - F_{\text{edge,block,low}}$
$BW_{\text{Channel_CA}}$	Aggregated channel bandwidth, expressed in MHz
$BW_{\text{Channel,max}}$	Maximum channel bandwidth supported among all bands in a release
BW_{GB}	$\max(BW_{\text{GB,Channel}(k)})$
$BW_{\text{GB,Channel}(k)}$	Minimum guard band defined in clause 5.3A.1 of carrier k
BW_{DL}	Channel bandwidth for DL

BW_{UL}	Channel bandwidth for UL
$BW_{interferer}$	Bandwidth of the interferer
$Ceil(x)$	Rounding upwards; $ceil(x)$ is the smallest integer such that $ceil(x) \geq x$
$Floor(x)$	Rounding downwards; $floor(x)$ is the greatest integer such that $floor(x) \leq x$
F_C	RF reference frequency on the channel raster, given in table 5.4.2.2-1
$F_{C,block, high}$	Fc of the highest transmitted/received carrier in a <i>sub-block</i>
$F_{C,block, low}$	Fc of the lowest transmitted/received carrier in a <i>sub-block</i>
$F_{C,low}$	The Fc of the lowest carrier, expressed in MHz
$F_{C,high}$	The Fc of the highest carrier, expressed in MHz
F_{DL_low}	The lowest frequency of the downlink <i>operating band</i>
F_{DL_high}	The highest frequency of the downlink <i>operating band</i>
F_{UL_low}	The lowest frequency of the uplink <i>operating band</i>
F_{UL_high}	The highest frequency of the uplink <i>operating band</i>
$F_{edge,block,low}$	The lower <i>sub-block</i> edge, where $F_{edge,block,low} = F_{C,block,low} - F_{offset, low}$.
$F_{edge,block,high}$	The upper <i>sub-block</i> edge, where $F_{edge,block,high} = F_{C,block,high} + F_{offset, high}$.
$F_{edge, low}$	The <i>lower edge of aggregated channel bandwidth</i> , expressed in MHz. $F_{edge,low} = F_{C,low} - F_{offset,low}$.
$F_{edge, high}$	The <i>higher edge of aggregated channel bandwidth</i> , expressed in MHz. $F_{edge,high} = F_{C,high} + F_{offset,high}$.
$F_{interferer} (offset)$	Frequency offset of the interferer (between the center frequency of the interferer and the carrier frequency of the carrier measured)
$F_{interferer}$	Frequency of the interferer
$F_{loffset}$	Frequency offset of the interferer (between the center frequency of the interferer and the closest edge of the carrier measured)
F_{offset}	Frequency offset from $F_{C,high}$ to the <i>higher edge</i> or $F_{C,low}$ to the <i>lower edge</i> .
$F_{offset,high}$	Frequency offset from $F_{C,high}$ to the upper <i>UE RF Bandwidth edge</i> , or from $F_{C,block, high}$ to the upper sub-block edge
$F_{offset,low}$	Frequency offset from $F_{C,low}$ to the lower <i>UE RF Bandwidth edge</i> , or from $F_{C,block, low}$ to the lower sub-block edge
F_{OOB}	The boundary between the NR out of band emission and spurious emission domains
F_{REF}	RF reference frequency
$F_{REF-Offs}$	Offset used for calculating F_{REF}
$F_{REF, shift}$	RF reference frequency for Supplementary Uplink (SUL) bands, the uplink of all FDD bands, and TDD bands
$F_{uw} (offset)$	The frequency separation of the center frequency of the carrier closest to the interferer and the center frequency of the interferer
$GB_{Channel}$	Minimum guard band defined in clause 5.3.3
L_{CRB}	Transmission bandwidth which represents the length of a contiguous resource block allocation expressed in units of resources blocks
$Max()$	The largest of given numbers
$Min()$	The smallest of given numbers
n_{PRB}	Physical resource block number
NR_{ACLR}	NR ACLR
N_{RB}	Transmission bandwidth configuration, expressed in units of resource blocks
N_{RB_agg}	The number of the aggregated RBs within the fully allocated aggregated channel bandwidth
N_{RB_agg}	The number of the aggregated RBs within the fully allocated aggregated channel bandwidth
	$N_{RB,agg} = \sum_1^j N_{RBj} * 2^{\mu_j}$ for carrier 1 to j, where μ is defined in TS 38.211 [6]
$N_{RB,c}$	The transmission bandwidth configuration of component carrier c, expressed in units of resource blocks
	$N_{RB,cj} = N_{RBj} * 2^{\mu_j}$ for carrier j, where μ is defined in TS 38.211 [6]
$N_{RB,low}$	The transmission bandwidth configurations according to Table 5.3.2-1 for the lowest assigned component carrier in section 5.3A.1
$N_{RB,high}$	The transmission bandwidth configurations according to Table 5.3.2-1 for the highest assigned component carrier in section 5.3A.1
N_{REF}	NR Absolute Radio Frequency Channel Number (NR-ARFCN)
$N_{REF-Offs}$	Offset used for calculating N_{REF}
P_{CMAX}	The configured maximum UE output power
$P_{CMAX, c}$	The configured maximum UE output power for serving cell c
$P_{CMAX, f, c}$	The configured maximum UE output power for carrier f of serving cell c in each slot
P_{EMAX}	Maximum allowed UE output power signalled by higher layers
$P_{EMAX, c}$	Maximum allowed UE output power signalled by higher layers for serving cell c
$P_{interferer}$	Modulated mean power of the interferer