

ETSI TS 138 323 V16.8.0 (2023-01)



5G;
NR;
iTech STANDARD PREVIEW
Packet Data Convergence Protocol (PDCP) specification
(3GPP TS 38.323 version 16.8.0 Release 16)

[ETSI TS 138 323 V16.8.0 \(2023-01\)](https://standards.iteh.ai/catalog/standards/sist/1ab0f020-d138-44b7-9c18-539d8a4529d4/etsi-ts-138-323-v16-8-0-2023-01)

<https://standards.iteh.ai/catalog/standards/sist/1ab0f020-d138-44b7-9c18-539d8a4529d4/etsi-ts-138-323-v16-8-0-2023-01>



Reference

RTS/TSGR-0238323vg80

Keywords

5G

ETSI

650 Route des Lucioles
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - APE 7112B
Association à but non lucratif enregistrée à la
Sous-Préfecture de Grasse (06) N° w061004871

Important notice

The present document can be downloaded from:

<http://www.etsi.org/standards-search>

The present document may be made available in electronic versions and/or in print. The content of any electronic and/or print versions of the present document shall not be modified without the prior written authorization of ETSI. In case of any existing or perceived difference in contents between such versions and/or in print, the prevailing version of an ETSI deliverable is the one made publicly available in PDF format at www.etsi.org/deliver.

Users of the present document should be aware that the document may be subject to revision or change of status.

Information on the current status of this and other ETSI documents is available at

<https://portal.etsi.org/TB/ETSIDeliverableStatus.aspx>

If you find errors in the present document, please send your comment to one of the following services:

<https://portal.etsi.org/People/CommitteeSupportStaff.aspx>

If you find a security vulnerability in the present document, please report it through our

Coordinated Vulnerability Disclosure Program:

<https://www.etsi.org/standards/coordinated-vulnerability-disclosure>

Notice of disclaimer & limitation of liability

The information provided in the present deliverable is directed solely to professionals who have the appropriate degree of experience to understand and interpret its content in accordance with generally accepted engineering or other professional standard and applicable regulations.

No recommendation as to products and services or vendors is made or should be implied.

No representation or warranty is made that this deliverable is technically accurate or sufficient or conforms to any law and/or governmental rule and/or regulation and further, no representation or warranty is made of merchantability or fitness for any particular purpose or against infringement of intellectual property rights.

In no event shall ETSI be held liable for loss of profits or any other incidental or consequential damages.

Any software contained in this deliverable is provided "AS IS" with no warranties, express or implied, including but not limited to, the warranties of merchantability, fitness for a particular purpose and non-infringement of intellectual property rights and ETSI shall not be held liable in any event for any damages whatsoever (including, without limitation, damages for loss of profits, business interruption, loss of information, or any other pecuniary loss) arising out of or related to the use of or inability to use the software.

Copyright Notification

No part may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm except as authorized by written permission of ETSI.

The content of the PDF version shall not be modified without the written authorization of ETSI.

The copyright and the foregoing restriction extend to reproduction in all media.

© ETSI 2023.
All rights reserved.

Intellectual Property Rights

Essential patents

IPRs essential or potentially essential to normative deliverables may have been declared to ETSI. The declarations pertaining to these essential IPRs, if any, are publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: *"Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards"*, which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (<https://ipr.etsi.org/>).

Pursuant to the ETSI Directives including the ETSI IPR Policy, no investigation regarding the essentiality of IPRs, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

Trademarks

The present document may include trademarks and/or tradenames which are asserted and/or registered by their owners. ETSI claims no ownership of these except for any which are indicated as being the property of ETSI, and conveys no right to use or reproduce any trademark and/or tradename. Mention of those trademarks in the present document does not constitute an endorsement by ETSI of products, services or organizations associated with those trademarks.

DECT™, **PLUGTESTS™**, **UMTS™** and the ETSI logo are trademarks of ETSI registered for the benefit of its Members. **3GPP™** and **LTE™** are trademarks of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners. **oneM2M™** logo is a trademark of ETSI registered for the benefit of its Members and of the oneM2M Partners. **GSM®** and the GSM logo are trademarks registered and owned by the GSM Association.

Legal Notice

This Technical Specification (TS) has been produced by ETSI 3rd Generation Partnership Project (3GPP).

The present document may refer to technical specifications or reports using their 3GPP identities. These shall be interpreted as being references to the corresponding ETSI deliverables.

The cross reference between 3GPP and ETSI identities can be found under <http://webapp.etsi.org/key/queryform.asp>.

Modal verbs terminology

In the present document **"shall"**, **"shall not"**, **"should"**, **"should not"**, **"may"**, **"need not"**, **"will"**, **"will not"**, **"can"** and **"cannot"** are to be interpreted as described in clause 3.2 of the [ETSI Drafting Rules](#) (Verbal forms for the expression of provisions).

"must" and **"must not"** are **NOT** allowed in ETSI deliverables except when used in direct citation.

Contents

| | |
|---|----|
| Intellectual Property Rights | 2 |
| Legal Notice | 2 |
| Modal verbs terminology..... | 2 |
| Foreword..... | 5 |
| 1 Scope | 6 |
| 2 References | 6 |
| 3 Definitions and abbreviations..... | 7 |
| 3.1 Definitions | 7 |
| 3.2 Abbreviations | 7 |
| 4 General | 8 |
| 4.1 Introduction | 8 |
| 4.2 Architecture | 8 |
| 4.2.1 PDCP structure | 8 |
| 4.2.2 PDCP entities..... | 9 |
| 4.3 Services | 10 |
| 4.3.1 Services provided to upper layers..... | 10 |
| 4.3.2 Services expected from lower layers | 10 |
| 4.4 Functions | 11 |
| 5 Procedures | 11 |
| 5.1 PDCP entity handling..... | 11 |
| 5.1.1 PDCP entity establishment | 11 |
| 5.1.2 PDCP entity re-establishment | 11 |
| 5.1.3 PDCP entity release | 13 |
| 5.1.4 PDCP entity suspend | 13 |
| 5.1.5 PDCP entity reconfiguration..... | 13 |
| 5.2 Data transfer | 14 |
| 5.2.1 Transmit operation..... | 14 |
| 5.2.2 Receive operation | 15 |
| 5.2.2.1 Actions when a PDCP Data PDU is received from lower layers | 15 |
| 5.2.2.2 Actions when a <i>t-Reordering</i> expires..... | 16 |
| 5.2.2.3 Actions when the value of <i>t-Reordering</i> is reconfigured | 17 |
| 5.2.3 Sidelink transmit operation..... | 17 |
| 5.2.4 Sidelink receive operation | 17 |
| 5.3 SDU discard | 17 |
| 5.4 Status reporting | 17 |
| 5.4.1 Transmit operation..... | 17 |
| 5.4.2 Receive operation | 18 |
| 5.5 Data recovery | 18 |
| 5.6 Data volume calculation..... | 18 |
| 5.7 Robust header compression and decompression | 19 |
| 5.7.1 Supported header compression protocols and profiles..... | 19 |
| 5.7.2 Configuration of ROHC..... | 20 |
| 5.7.3 Protocol parameters | 20 |
| 5.7.4 Header compression using ROHC | 20 |
| 5.7.5 Header decompression using ROHC | 21 |
| 5.7.6 PDCP Control PDU for interspersed ROHC feedback | 21 |
| 5.7.6.1 Transmit Operation | 21 |
| 5.7.6.2 Receive Operation..... | 21 |
| 5.8 Ciphering and deciphering | 21 |
| 5.9 Integrity protection and verification | 22 |
| 5.10 Handling of unknown, unforeseen, and erroneous protocol data | 23 |
| 5.11 PDCP duplication | 23 |
| 5.11.1 Activation/Deactivation of PDCP duplication..... | 23 |

| | | |
|-------------------------------|--|-----------|
| 5.11.2 | Duplicate PDU discard | 24 |
| 5.12 | Ethernet header compression and decompression | 24 |
| 5.12.1 | Supported header compression protocols | 24 |
| 5.12.2 | Configuration of EHC | 24 |
| 5.12.3 | Protocol parameters | 24 |
| 5.12.4 | Header compression using EHC | 24 |
| 5.12.5 | Header decompression using EHC | 25 |
| 5.12.6 | PDCP Control PDU for EHC feedback | 25 |
| 5.12.6.1 | Transmit Operation | 25 |
| 5.12.6.2 | Receive Operation | 25 |
| 5.12.7 | Simultaneous configuration of ROHC and EHC | 25 |
| 5.13 | Uplink data switching | 25 |
| 6 | Protocol data units, formats, and parameters | 26 |
| 6.1 | Protocol data units | 26 |
| 6.1.1 | Data PDU | 26 |
| 6.1.2 | Control PDU | 26 |
| 6.2 | Formats | 26 |
| 6.2.1 | General | 26 |
| 6.2.2 | Data PDU | 27 |
| 6.2.2.1 | Data PDU for SRBs | 27 |
| 6.2.2.2 | Data PDU for DRBs with 12 bits PDCP SN | 27 |
| 6.2.2.3 | Data PDU for DRBs with 18 bits PDCP SN | 28 |
| 6.2.2.4 | Data PDU for sidelink DRBs for groupcast and broadcast and for the sidelink SRB0 | 28 |
| 6.2.2.5 | Data PDU for sidelink SRBs for unicast | 29 |
| 6.2.2.6 | Data PDU for sidelink DRBs for unicast with 12 bits PDCP SN | 29 |
| 6.2.2.7 | Data PDU for sidelink DRBs for unicast with 18 bits PDCP SN | 30 |
| 6.2.3 | Control PDU | 31 |
| 6.2.3.1 | Control PDU for PDCP status report | 31 |
| 6.2.3.2 | Control PDU for interspersed ROHC feedback | 32 |
| 6.2.3.3 | Control PDU for EHC feedback | 32 |
| 6.3 | Parameters | 32 |
| 6.3.1 | General | 32 |
| 6.3.2 | PDCP SN | 32 |
| 6.3.3 | Data | 33 |
| 6.3.4 | MAC-I | 33 |
| 6.3.5 | COUNT | 33 |
| 6.3.6 | R | 33 |
| 6.3.7 | D/C | 33 |
| 6.3.8 | PDU type | 34 |
| 6.3.9 | FMC | 34 |
| 6.3.10 | Bitmap | 34 |
| 6.3.11 | Interspersed ROHC feedback | 34 |
| 6.3.12 | SDU Type | 34 |
| 6.3.13 | K _{NRP-sess} ID | 34 |
| 7 | State variables, constants, and timers | 35 |
| 7.1 | State variables | 35 |
| 7.2 | Constants | 35 |
| 7.3 | Timers | 36 |
| Annex A (normative): | Ethernet Header Compression (EHC) protocol | 37 |
| A.1 | EHC principle | 37 |
| A.2 | EHC packet format and parameters | 38 |
| A.2.1 | EHC packet format | 38 |
| A.2.1.1 | EHC Full Header packet and EHC Compressed Header packet | 38 |
| A.2.1.2 | EHC feedback packet | 39 |
| A.2.2 | Parameters | 39 |
| A.2.2.1 | F/C | 39 |
| A.2.2.2 | CID | 39 |
| Annex B (informative): | Change history | 40 |
| History | | 41 |

Foreword

This Technical Specification has been produced by the 3rd Generation Partnership Project (3GPP).

The contents of the present document are subject to continuing work within the TSG and may change following formal TSG approval. Should the TSG modify the contents of the present document, it will be re-released by the TSG with an identifying change of release date and an increase in version number as follows:

Version x.y.z

where:

- x the first digit:
 - 1 presented to TSG for information;
 - 2 presented to TSG for approval;
 - 3 or greater indicates TSG approved document under change control.
- y the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- z the third digit is incremented when editorial only changes have been incorporated in the document.

iTeh STANDARD PREVIEW
(standards.iteh.ai)

ETSI TS 138 323 V16.8.0 (2023-01)

<https://standards.iteh.ai/catalog/standards/sist/1ab0f020-d138-44b7-9c18-539d8a4529d4/etsi-ts-138-323-v16-8-0-2023-01>

1 Scope

The present document provides the description of the Packet Data Convergence Protocol (PDCP).

2 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- References are either specific (identified by date of publication, edition number, version number, etc.) or non-specific.
- For a specific reference, subsequent revisions do not apply.
- For a non-specific reference, the latest version applies. In the case of a reference to a 3GPP document (including a GSM document), a non-specific reference implicitly refers to the latest version of that document *in the same Release as the present document*.

- [1] 3GPP TR 21.905: "Vocabulary for 3GPP Specifications".
- [2] 3GPP TS 38.300: "NG Radio Access Network; Overall description".
- [3] 3GPP TS 38.331: "NR Radio Resource Control (RRC); Protocol Specification".
- [4] 3GPP TS 38.321: "NR Medium Access Control (MAC) protocol specification".
- [5] 3GPP TS 38.322: "NR Radio Link Control (RLC) protocol specification".
- [6] 3GPP TS 33.501: "Security Architecture and Procedures for 5G System".
- [7] IETF RFC 5795: "The RObust Header Compression (ROHC) Framework".
- [8] IETF RFC 3095: "RObust Header Compression (ROHC): Framework and four profiles: RTP, UDP, ESP and uncompressed".
- [9] IETF RFC 4815: "RObust Header Compression (ROHC): Corrections and Clarifications to RFC 3095".
- [10] IETF RFC 6846: "RObust Header Compression (ROHC): A Profile for TCP/IP (ROHC-TCP)".
- [11] IETF RFC 5225: "RObust Header Compression (ROHC) Version 2: Profiles for RTP, UDP, IP, ESP and UDP Lite".
- [12] 3GPP TS 36.321: "Evolved Universal Terrestrial Radio Access (E-UTRA) Medium Access Control (MAC) protocol specification".
- [13] 3GPP TS 23.287: "Architecture enhancements for 5G System (5GS) to support Vehicle-to-Everything (V2X) services".
- [14] 3GPP TS 33.536: "Security Aspect of 3GPP Support for Advanced V2X Services".
- [15] IEEE Standard 802.3™-2018: "Ethernet".
- [16] 3GPP TS 24.587: "Vehicle-to-Everything (V2X) services in 5G System (5GS), Stage 3".

3 Definitions and abbreviations

3.1 Definitions

For the purposes of the present document, the terms and definitions given in TR 21.905 [1] and the following apply. A term defined in the present document takes precedence over the definition of the same term, if any, in TR 21.905 [1].

AM DRB: a data radio bearer which utilizes RLC AM.

DAPS bearer: a bearer whose radio protocols are located in both the source gNB and the target gNB during DAPS handover to use both source gNB and target gNB resources.

Non-split bearer: a bearer whose radio protocols are located in either the MgNB or the SgNB to use MgNB or SgNB resource, respectively.

NR sidelink communication: AS functionality enabling at least V2X communication as defined in TS 23.287 [13], between two or more nearby UEs, using NR technology but not traversing any network node.

PDCP data volume: the amount of data available for transmission in a PDCP entity.

Split bearer: in dual connectivity, a bearer whose radio protocols are located in both the MgNB and the SgNB to use both MgNB and SgNB resources.

Split secondary RLC entity: in dual connectivity, the RLC entity other than the primary RLC entity which is responsible for split bearer operation. If the PDCP entity is associated with two RLC entities, the split secondary RLC entity is the RLC entity other than the primary RLC entity. If the PDCP entity is associated with more than two RLC entities, the split secondary RLC entity is configured by upper layers.

UM DRB: a data radio bearer which utilizes RLC UM.

3.2 Abbreviations

For the purposes of the present document, the abbreviations given in TR 21.905 [1] and the following apply. An abbreviation defined in the present document takes precedence over the definition of the same abbreviation, if any, in TR 21.905 [1].

| | |
|-------|--|
| AM | Acknowledged Mode |
| CID | Context Identifier |
| DAPS | Dual Active Protocol Stack |
| DRB | Data Radio Bearer carrying user plane data |
| EHC | Ethernet Header Compression |
| gNB | NR Node B |
| HFN | Hyper Frame Number |
| IETF | Internet Engineering Task Force |
| IP | Internet Protocol |
| MAC | Medium Access Control |
| MAC-I | Message Authentication Code for Integrity |
| PDCP | Packet Data Convergence Protocol |
| PDU | Protocol Data Unit |
| RB | Radio Bearer |
| RFC | Request For Comments |
| RLC | Radio Link Control |
| ROHC | RObust Header Compression |
| RRC | Radio Resource Control |
| RTP | Real Time Protocol |
| SAP | Service Access Point |
| SCCH | Sidelink Control Channel |
| SDU | Service Data Unit |
| SLRB | Sidelink Radio Bearer carrying NR sidelink communication |
| SN | Sequence Number |

- For RBs configured with PDCP duplication, each PDCP entity is associated with N UM RLC entities (for same direction), $2 \times N$ UM RLC entities (N for each direction), or N AM RLC entities, where $2 \leq N \leq 4$;
- For DAPS bearers, each PDCP entity is associated with two UM RLC entities (for same direction, one for source and one for target cell), four UM RLC entities (two for each direction on source cell and target cell), or two AM RLC entities (one for source cell and one for target cell);
- Otherwise, each PDCP entity is associated with one UM RLC entity, two UM RLC entities (one for each direction), or one AM RLC entity.

4.2.2 PDCP entities

The PDCP entities are located in the PDCP sublayer. Several PDCP entities may be defined for a UE. Each PDCP entity is carrying the data of one radio bearer. A PDCP entity is associated either to the control plane or the user plane depending on which radio bearer it is carrying data for.

Figure 4.2.2.1 represents the functional view of the PDCP entity for the PDCP sublayer; it should not restrict implementation. The figure is based on the radio interface protocol architecture defined in TS 38.300 [2].

For split bearers and DAPS bearers, routing is performed in the transmitting PDCP entity.

A PDCP entity associated with DRB can be configured by upper layers TS 38.331 [3] to use header compression. In this version of the specification, the robust header compression protocol (ROHC) and the Ethernet header compression protocol (EHC) are supported. Each header compression protocol is independently configured for a DRB.




Figure 4.2.2-1: PDCP layer, functional view

Figure 4.2.2-2 represents the functional view of the PDCP entity associated with the DAPS bearer for the PDCP sublayer; it should not restrict implementation. The figure is based on the radio interface protocol architecture defined in TS 38.300 [2].

For DAPS bearers, the PDCP entity is configured with two sets of security functions and keys and two sets of header compression protocols.




Figure 4.2.2-2: PDCP layer associated with DAPS bearer, functional view

4.3 Services

4.3.1 Services provided to upper layers

The PDCP layer provides its services to the RRC or SDAP layers. The following services are provided by PDCP to upper layers:

- transfer of user plane data;
- transfer of control plane data;
- header compression;
- ciphering;
- integrity protection.

The maximum supported size of a PDCP SDU is 9000 bytes. The maximum supported size of a PDCP Control PDU is 9000 bytes.

4.3.2 Services expected from lower layers

A PDCP entity expects the following services from lower layers per RLC entity (for a detailed description see TS 38.322 [5]):

- acknowledged data transfer service, including indication of successful delivery of PDCP PDUs;
- unacknowledged data transfer service.

4.4 Functions

The PDCP layer supports the following functions:

- transfer of data (user plane or control plane);
- maintenance of PDCP SNs;
- header compression and decompression using the ROHC protocol;
- header compression and decompression using the EHC protocol;
- ciphering and deciphering;
- integrity protection and integrity verification;
- timer based SDU discard;
- for split bearers and DAPS bearer, routing;
- duplication;
- reordering and in-order delivery;
- out-of-order delivery;
- duplicate discarding.

5 Procedures

5.1 PDCP entity handling

5.1.1 PDCP entity establishment

When upper layers request a PDCP entity establishment for a radio bearer for Uu or PC5 interface; or for NR sidelink communication for groupcast and broadcast, when receiving the first PDCP PDU, and there is not yet a corresponding PDCP entity, the UE shall:

- establish a PDCP entity for the radio bearer;
- set the state variables of the PDCP entity to initial values;
- follow the procedures in clause 5.2.

NOTE: The receiving PDCP entity of sidelink SRB0 and sidelink SRB1 is established same as NR sidelink groupcast and broadcast.

5.1.2 PDCP entity re-establishment

When upper layers request a PDCP entity re-establishment, the UE shall additionally perform once the procedures described in this clause for Uu or PC5 interface. After performing the procedures in this clause, the UE shall follow the procedures in clause 5.2.

When upper layers request a PDCP entity re-establishment, the transmitting PDCP entity shall:

- for UM DRBs and AM DRBs, reset the ROHC protocol for uplink and start with an IR state in U-mode (as defined in RFC 3095 [8] and RFC 4815 [9]) if *drb-ContinueROHC* is not configured in TS 38.331 [3];
- for UM DRBs and AM DRBs, reset the EHC protocol for uplink if *drb-ContinueEHC-UL* is not configured in TS 38.331 [3];

- for UM DRBs and SRBs, set TX_NEXT to the initial value;
- for SRBs, discard all stored PDCP SDUs and PDCP PDUs;
- apply the ciphering algorithm and key provided by upper layers during the PDCP entity re-establishment procedure;
- apply the integrity protection algorithm and key provided by upper layers during the PDCP entity re-establishment procedure;
- for UM DRBs, for each PDCP SDU already associated with a PDCP SN but for which a corresponding PDU has not previously been submitted to lower layers, and;
- for AM DRBs for Uu interface whose PDCP entities were suspended, from the first PDCP SDU for which the successful delivery of the corresponding PDCP Data PDU has not been confirmed by lower layers, for each PDCP SDU already associated with a PDCP SN:
 - consider the PDCP SDUs as received from upper layer;
 - perform transmission of the PDCP SDUs in ascending order of the COUNT value associated to the PDCP SDU prior to the PDCP re-establishment without restarting the *discardTimer*, as specified in clause 5.2.1;
- for AM DRBs whose PDCP entities were not suspended, from the first PDCP SDU for which the successful delivery of the corresponding PDCP Data PDU has not been confirmed by lower layers, perform retransmission or transmission of all the PDCP SDUs already associated with PDCP SNs in ascending order of the COUNT values associated to the PDCP SDU prior to the PDCP entity re-establishment as specified below:
 - perform header compression of the PDCP SDU using ROHC as specified in the clause 5.7.4 and/or using EHC as specified in the clause 5.12.4;
 - perform integrity protection and ciphering of the PDCP SDU using the COUNT value associated with this PDCP SDU as specified in the clause 5.9 and 5.8;
 - submit the resulting PDCP Data PDU to lower layer, as specified in clause 5.2.1.

When upper layers request a PDCP entity re-establishment, the receiving PDCP entity shall:

- process the PDCP Data PDUs that are received from lower layers due to the re-establishment of the lower layers, as specified in the clause 5.2.2.1;
- for SRBs, discard all stored PDCP SDUs and PDCP PDUs;
- for SRBs and UM DRBs, if *t-Reordering* is running:
 - stop and reset *t-Reordering*;
 - for UM DRBs, deliver all stored PDCP SDUs to the upper layers in ascending order of associated COUNT values after performing header decompression;
- for AM DRBs for Uu interface, perform header decompression using ROHC for all stored PDCP SDUs if *drb-ContinueROHC* is not configured in TS 38.331 [3];
- for AM DRBs for PC5 interface, perform header decompression using ROHC for all stored PDCP IP SDUs;
- for AM DRBs for Uu interface, perform header decompression using EHC for all stored PDCP SDUs if *drb-ContinueEHC-DL* is not configured in TS 38.331 [3];
- for UM DRBs and AM DRBs, reset the ROHC protocol for downlink and start with NC state in U-mode (as defined in RFC 3095 [8] and RFC 4815 [9]) if *drb-ContinueROHC* is not configured in TS 38.331 [3];
- for UM DRBs and AM DRBs, reset the EHC protocol for downlink if *drb-ContinueEHC-DL* is not configured in TS 38.331 [3];
- for UM DRBs and SRBs, set RX_NEXT and RX_DELIV to the initial value;
- apply the ciphering algorithm and key provided by upper layers during the PDCP entity re-establishment procedure;