

# ETSI TS 138 463 V15.13.0 (2023-10)



**5G;  
NG-RAN;  
E1 Application Protocol (E1AP)  
(3GPP TS 38.463 version 15.13.0 Release 15)**

[ETSI TS 138 463 V15.13.0 \(2023-10\)](https://standards.iteh.ai/catalog/standards/sist/3ee7d9fe-a754-42b1-93ab-23b8172757a2/etsi-ts-138-463-v15-13-0-2023-10)

<https://standards.iteh.ai/catalog/standards/sist/3ee7d9fe-a754-42b1-93ab-23b8172757a2/etsi-ts-138-463-v15-13-0-2023-10>



---

**Reference**

RTS/TSGR-0338463vfd0

---

**Keywords**

5G

**ETSI**

---

650 Route des Lucioles  
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - APE 7112B  
Association à but non lucratif enregistrée à la  
Sous-Préfecture de Grasse (06) N° w061004871

---

**Important notice**

The present document can be downloaded from:

<https://www.etsi.org/standards-search>

The present document may be made available in electronic versions and/or in print. The content of any electronic and/or print versions of the present document shall not be modified without the prior written authorization of ETSI. In case of any existing or perceived difference in contents between such versions and/or in print, the prevailing version of an ETSI deliverable is the one made publicly available in PDF format at [www.etsi.org/deliver](http://www.etsi.org/deliver).

Users of the present document should be aware that the document may be subject to revision or change of status.

Information on the current status of this and other ETSI documents is available at

<https://portal.etsi.org/TB/ETSIDeliverableStatus.aspx>

If you find errors in the present document, please send your comment to one of the following services:

<https://portal.etsi.org/People/CommitteeSupportStaff.aspx>

If you find a security vulnerability in the present document, please report it through our

Coordinated Vulnerability Disclosure Program:

<https://www.etsi.org/standards/coordinated-vulnerability-disclosure>

---

**Notice of disclaimer & limitation of liability**

The information provided in the present deliverable is directed solely to professionals who have the appropriate degree of experience to understand and interpret its content in accordance with generally accepted engineering or other professional standard and applicable regulations.

No recommendation as to products and services or vendors is made or should be implied.

No representation or warranty is made that this deliverable is technically accurate or sufficient or conforms to any law and/or governmental rule and/or regulation and further, no representation or warranty is made of merchantability or fitness for any particular purpose or against infringement of intellectual property rights.

In no event shall ETSI be held liable for loss of profits or any other incidental or consequential damages.

Any software contained in this deliverable is provided "AS IS" with no warranties, express or implied, including but not limited to, the warranties of merchantability, fitness for a particular purpose and non-infringement of intellectual property rights and ETSI shall not be held liable in any event for any damages whatsoever (including, without limitation, damages for loss of profits, business interruption, loss of information, or any other pecuniary loss) arising out of or related to the use of or inability to use the software.

---

**Copyright Notification**

No part may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm except as authorized by written permission of ETSI.

The content of the PDF version shall not be modified without the written authorization of ETSI.

The copyright and the foregoing restriction extend to reproduction in all media.

© ETSI 2023.  
All rights reserved.

---

# Intellectual Property Rights

## Essential patents

IPRs essential or potentially essential to normative deliverables may have been declared to ETSI. The declarations pertaining to these essential IPRs, if any, are publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: "*Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards*", which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (<https://ipr.etsi.org/>).

Pursuant to the ETSI Directives including the ETSI IPR Policy, no investigation regarding the essentiality of IPRs, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

## Trademarks

The present document may include trademarks and/or tradenames which are asserted and/or registered by their owners. ETSI claims no ownership of these except for any which are indicated as being the property of ETSI, and conveys no right to use or reproduce any trademark and/or tradename. Mention of those trademarks in the present document does not constitute an endorsement by ETSI of products, services or organizations associated with those trademarks.

**DECT™**, **PLUGTESTS™**, **UMTS™** and the ETSI logo are trademarks of ETSI registered for the benefit of its Members. **3GPP™** and **LTE™** are trademarks of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners. **oneM2M™** logo is a trademark of ETSI registered for the benefit of its Members and of the oneM2M Partners. **GSM®** and the GSM logo are trademarks registered and owned by the GSM Association.

---

## Legal Notice

This Technical Specification (TS) has been produced by ETSI 3rd Generation Partnership Project (3GPP).

The present document may refer to technical specifications or reports using their 3GPP identities. These shall be interpreted as being references to the corresponding ETSI deliverables. (2023-10)

The cross reference between 3GPP and ETSI identities can be found under <https://webapp.etsi.org/key/queryform.asp>.

---

## Modal verbs terminology

In the present document "**shall**", "**shall not**", "**should**", "**should not**", "**may**", "**need not**", "**will**", "**will not**", "**can**" and "**cannot**" are to be interpreted as described in clause 3.2 of the [ETSI Drafting Rules](#) (Verbal forms for the expression of provisions).

"**must**" and "**must not**" are **NOT** allowed in ETSI deliverables except when used in direct citation.

# Contents

Intellectual Property Rights .....	2
Legal Notice .....	2
Modal verbs terminology.....	2
Foreword.....	8
1 Scope .....	9
2 References .....	9
3 Definitions and abbreviations.....	10
3.1 Definitions .....	10
3.2 Abbreviations .....	11
4 General .....	11
4.1 Procedure specification principles.....	11
4.2 Forwards and backwards compatibility.....	12
4.3 Specification notations .....	12
5 E1AP services .....	12
6 Services expected from signalling transport.....	12
7 Functions of E1AP .....	12
8 E1AP procedures.....	13
8.1 List of E1AP Elementary Procedures.....	13
8.2 Interface Management procedures .....	14
8.2.1 Reset .....	14
8.2.1.1 General .....	14
8.2.1.2 Successful Operation.....	14
8.2.1.2.1 Reset Procedure Initiated from the gNB-CU-CP.....	14
8.2.1.2.2 Reset Procedure Initiated from the gNB-CU-UP .....	15
8.2.1.3 Abnormal Conditions .....	16
8.2.2 Error Indication.....	16
8.2.2.1 General .....	16
8.2.2.2 Successful Operation.....	16
8.2.2.3 Abnormal Conditions .....	16
8.2.3 gNB-CU-UP E1 Setup.....	17
8.2.3.1 General .....	17
8.2.3.2 Successful Operation.....	17
8.2.3.3 Unsuccessful Operation .....	18
8.2.3.4 Abnormal Conditions .....	18
8.2.4 gNB-CU-CP E1 Setup .....	18
8.2.4.1 General .....	18
8.2.4.2 Successful Operation.....	19
8.2.4.3 Unsuccessful Operation .....	19
8.2.4.4 Abnormal Conditions .....	19
8.2.5 gNB-CU-UP Configuration Update.....	20
8.2.5.1 General .....	20
8.2.5.2 Successful Operation.....	20
8.2.5.3 Unsuccessful Operation .....	21
8.2.5.4 Abnormal Conditions .....	21
8.2.6 gNB-CU-CP Configuration Update.....	21
8.2.6.1 General .....	21
8.2.6.2 Successful Operation.....	22
8.2.6.3 Unsuccessful Operation .....	23
8.2.6.4 Abnormal Conditions .....	23
8.2.7 E1 Release .....	23
8.2.7.1 General .....	23

8.2.7.2	Successful Operation.....	23
8.2.7.2.1	E1 Release Procedure Initiated from the gNB-CU-CP.....	23
8.2.7.2.2	E1 Release Procedure Initiated from the gNB-CU-UP.....	24
8.2.7.3	Abnormal Conditions.....	24
8.2.8	gNB-CU-UP Status Indication.....	24
8.2.8.1	General.....	24
8.2.8.2	Successful Operation.....	24
8.2.8.3	Abnormal Conditions.....	25
8.3	Bearer Context Management procedures.....	25
8.3.1	Bearer Context Setup.....	25
8.3.1.1	General.....	25
8.3.1.2	Successful Operation.....	25
8.3.1.3	Unsuccessful Operation.....	28
8.3.1.4	Abnormal Conditions.....	28
8.3.2	Bearer Context Modification (gNB-CU-CP initiated).....	28
8.3.2.1	General.....	28
8.3.2.2	Successful Operation.....	29
8.3.2.3	Unsuccessful Operation.....	33
8.3.2.4	Abnormal Conditions.....	33
8.3.3	Bearer Context Modification Required (gNB-CU-UP initiated).....	33
8.3.3.1	General.....	33
8.3.3.2	Successful Operation.....	34
8.3.3.3	Abnormal Conditions.....	34
8.3.4	Bearer Context Release (gNB-CU-CP initiated).....	34
8.3.4.1	General.....	34
8.3.4.2	Successful Operation.....	35
8.3.4.3	Abnormal Conditions.....	35
8.3.5	Bearer Context Release Request (gNB-CU-UP initiated).....	35
8.3.5.1	General.....	35
8.3.5.2	Successful Operation.....	35
8.3.5.3	Abnormal Conditions.....	36
8.3.6	Bearer Context Inactivity Notification.....	36
8.3.6.1	General.....	36
8.3.6.2	Successful Operation.....	36
8.3.6.3	Abnormal Conditions.....	36
8.3.7	DL Data Notification.....	37
8.3.7.1	General.....	37
8.3.7.2	Successful Operation.....	37
8.3.7.3	Abnormal Conditions.....	37
8.3.8	Data Usage Report.....	37
8.3.8.1	General.....	37
8.3.8.2	Successful Operation.....	37
8.3.8.3	Abnormal Conditions.....	38
8.3.9	gNB-CU-UP Counter Check.....	38
8.3.9.1	General.....	38
8.3.9.2	Successful Operation.....	38
8.3.9.3	Unsuccessful Operation.....	38
8.3.9.4	Abnormal Conditions.....	38
8.3.10	UL Data Notification.....	38
8.3.10.1	General.....	38
8.3.10.2	Successful Operation.....	39
8.3.10.3	Abnormal Conditions.....	39
8.3.11	MR-DC Data Usage Report.....	39
8.3.11.1	General.....	39
8.3.11.2	Successful Operation.....	39
8.3.11.3	Abnormal Conditions.....	39
9	Elements for E1AP communication.....	40
9.1	General.....	40
9.2	Message Functional Definition and Content.....	40
9.2.1	Interface Management messages.....	40
9.2.1.1	RESET.....	40

9.2.1.2	RESET ACKNOWLEDGE .....	41
9.2.1.3	ERROR INDICATION .....	41
9.2.1.4	GNB-CU-UP E1 SETUP REQUEST .....	41
9.2.1.5	GNB-CU-UP E1 SETUP RESPONSE .....	42
9.2.1.6	GNB-CU-UP E1 SETUP FAILURE .....	42
9.2.1.7	GNB-CU-CP E1 SETUP REQUEST .....	42
9.2.1.8	GNB-CU-CP E1 SETUP RESPONSE .....	43
9.2.1.9	GNB-CU-CP E1 SETUP FAILURE .....	43
9.2.1.10	GNB-CU-UP CONFIGURATION UPDATE .....	44
9.2.1.11	GNB-CU-UP CONFIGURATION UPDATE ACKNOWLEDGE .....	44
9.2.1.12	GNB-CU-UP CONFIGURATION UPDATE FAILURE .....	44
9.2.1.13	GNB-CU-CP CONFIGURATION UPDATE .....	45
9.2.1.14	GNB-CU-CP CONFIGURATION UPDATE ACKNOWLEDGE .....	46
9.2.1.15	GNB-CU-CP CONFIGURATION UPDATE FAILURE .....	46
9.2.1.16	E1 RELEASE REQUEST .....	47
9.2.1.17	E1 RELEASE RESPONSE .....	47
9.2.1.18	GNB-CU-UP STATUS INDICATION .....	47
9.2.2	Bearer Context Management messages .....	47
9.2.2.1	BEARER CONTEXT SETUP REQUEST .....	47
9.2.2.2	BEARER CONTEXT SETUP RESPONSE .....	48
9.2.2.3	BEARER CONTEXT SETUP FAILURE .....	49
9.2.2.4	BEARER CONTEXT MODIFICATION REQUEST .....	49
9.2.2.5	BEARER CONTEXT MODIFICATION RESPONSE .....	50
9.2.2.6	BEARER CONTEXT MODIFICATION FAILURE .....	51
9.2.2.7	BEARER CONTEXT MODIFICATION REQUIRED .....	51
9.2.2.8	BEARER CONTEXT MODIFICATION CONFIRM .....	52
9.2.2.9	BEARER CONTEXT RELEASE COMMAND .....	53
9.2.2.10	BEARER CONTEXT RELEASE COMPLETE .....	53
9.2.2.11	BEARER CONTEXT RELEASE REQUEST .....	53
9.2.2.12	BEARER CONTEXT INACTIVITY NOTIFICATION .....	54
9.2.2.13	DL DATA NOTIFICATION .....	54
9.2.2.14	DATA USAGE REPORT .....	55
9.2.2.15	GNB-CU-UP COUNTER CHECK REQUEST .....	55
9.2.2.16	UL DATA NOTIFICATION .....	56
9.2.2.17	MR-DC DATA USAGE REPORT .....	56
9.3	Information Element Definitions .....	57
9.3.1	Radio Network Layer Related IEs .....	57
9.3.1.1	Message Type .....	57
9.3.1.2	Cause .....	57
9.3.1.3	Criticality Diagnostics .....	60
9.3.1.4	gNB-CU-CP UE E1AP ID .....	61
9.3.1.5	gNB-CU-UP UE E1AP ID .....	61
9.3.1.6	Time To wait .....	61
9.3.1.7	PLMN Identity .....	61
9.3.1.8	Slice Support List .....	62
9.3.1.9	S-NSSAI .....	62
9.3.1.10	Security Information .....	62
9.3.1.11	Cell Group Information .....	62
9.3.1.12	QoS Flow List .....	63
9.3.1.13	UP Parameters .....	63
9.3.1.14	NR CGI .....	64
9.3.1.15	gNB-CU-UP ID .....	64
9.3.1.16	DRB ID .....	64
9.3.1.17	E-UTRAN QoS .....	64
9.3.1.18	E-UTRAN Allocation and Retention Priority .....	64
9.3.1.19	GBR QoS Information .....	65
9.3.1.20	Bit Rate .....	66
9.3.1.21	PDU Session ID .....	66
9.3.1.22	PDU Session Type .....	66
9.3.1.23	Security Indication .....	66
9.3.1.24	QoS Flow Identifier .....	67
9.3.1.25	QoS Flow QoS Parameters List .....	67

9.3.1.26	QoS Flow Level QoS Parameters.....	67
9.3.1.27	Non Dynamic 5QI Descriptor .....	68
9.3.1.28	Dynamic 5QI Descriptor .....	68
9.3.1.29	NG-RAN Allocation and Retention Priority .....	69
9.3.1.30	GBR QoS Flow Information .....	69
9.3.1.31	Security Algorithm.....	70
9.3.1.32	User Plane Security Keys.....	70
9.3.1.33	UL Configuration.....	70
9.3.1.34	gNB-CU-UP Cell Group Related Configuration.....	70
9.3.1.35	PDCP Count.....	71
9.3.1.36	NR CGI Support List .....	71
9.3.1.37	QoS Parameters Support List .....	71
9.3.1.38	PDCP Configuration .....	72
9.3.1.39	SDAP Configuration .....	73
9.3.1.40	ROHC Parameters.....	74
9.3.1.41	T-Reordering Timer .....	74
9.3.1.42	Discard Timer .....	75
9.3.1.43	UL Data Split Threshold .....	75
9.3.1.44	Data Usage Report List .....	75
9.3.1.45	Flow Failed List .....	76
9.3.1.46	Packet Loss Rate .....	76
9.3.1.47	Packet Delay Budget.....	77
9.3.1.48	Packet Error Rate .....	77
9.3.1.49	Averaging Window .....	77
9.3.1.50	Maximum Data Burst Volume .....	77
9.3.1.51	Priority Level .....	77
9.3.1.52	Security Result .....	77
9.3.1.53	Transaction ID.....	78
9.3.1.54	Inactivity timer.....	78
9.3.1.55	Paging Priority Indicator (PPI).....	78
9.3.1.56	gNB-CU-UP Capacity.....	78
9.3.1.58	PDCP SN Status Information.....	79
9.3.1.59	QoS Flow Mapping List.....	79
9.3.1.60	QoS Flow Mapping Indication.....	80
9.3.1.61	PDCP SN Size.....	80
9.3.1.62	Network Instance .....	80
9.3.1.63	MR-DC Usage Information.....	80
9.3.1.64	MR-DC Data Usage Report List .....	81
9.3.1.65	gNB-DU ID.....	82
9.3.1.66	Common Network Instance.....	82
9.3.1.67	Activity Notification Level .....	82
9.3.2	Transport Network Layer Related IEs .....	82
9.3.2.1	UP Transport Layer Information.....	82
9.3.2.2	CP Transport Layer Information .....	82
9.3.2.3	GTP-TEID.....	83
9.3.2.4	Transport Layer Address.....	83
9.3.2.5	Data Forwarding Information Request.....	83
9.3.2.6	Data Forwarding Information.....	83
9.3.3	Container and List IE definitions .....	84
9.3.3.1	DRB To Setup List E-UTRAN .....	84
9.3.3.2	PDU Session Resource To Setup List .....	84
9.3.3.3	DRB Setup List E-UTRAN.....	86
9.3.3.4	DRB Failed List E-UTRAN.....	86
9.3.3.5	PDU Session Resource Setup List .....	86
9.3.3.6	PDU Session Resource Failed List.....	87
9.3.3.7	DRB To Setup Modification List E-UTRAN.....	87
9.3.3.8	DRB To Modify List E-UTRAN .....	88
9.3.3.9	DRB To Remove List E-UTRAN .....	88
9.3.3.10	PDU Session Resource To Setup Modification List .....	88
9.3.3.11	PDU Session Resource To Modify List .....	90
9.3.3.12	PDU Session Resource To Remove List.....	92
9.3.3.13	DRB Setup Modification List E-UTRAN .....	92

9.3.3.14 DRB Failed Modification List E-UTRAN .....92

9.3.3.15 DRB Modified List E-UTRAN .....93

9.3.3.16 DRB Failed To Modify List E-UTRAN.....93

9.3.3.17 PDU Session Resource Setup Modification List.....93

9.3.3.18 PDU Session Resource Failed Modification List.....94

9.3.3.19 PDU Session Resource Modified List.....94

9.3.3.20 PDU Session Resource Failed To Modify List .....95

9.3.3.21 DRB Required To Modify List E-UTRAN .....96

9.3.3.22 DRB Required To Remove List E-UTRAN.....96

9.3.3.23 PDU Session Resource Required To Modify List.....96

9.3.3.24 DRB Confirm Modified List E-UTRAN.....97

9.3.3.25 PDU Session Resource Confirm Modified List .....97

9.4 Message and Information Element Abstract Syntax (with ASN.1).....98

9.4.1 General.....98

9.4.2 Usage of private message mechanism for non-standard use.....98

9.4.3 Elementary Procedure Definitions .....99

9.4.4 PDU Definitions .....105

9.4.5 Information Element Definitions .....127

9.4.6 Common Definitions.....164

9.4.7 Constant Definitions .....165

9.4.8 Container Definitions.....168

9.5 Message Transfer Syntax .....172

9.6 Timers .....172

10 Handling of unknown, unforeseen and erroneous protocol data .....172

**Annex A (informative): Change History .....173**

History .....175

  
<https://standards.iteh.ai>  
 Document Preview

ETSI TS 138 463 V15.13.0 (2023-10)

<https://standards.iteh.ai/catalog/standards/sist/3ee7d9fe-a754-42b1-93ab-23b8172757a2/etsi-ts-138-463-v15-13-0-2023-10>

---

# Foreword

This Technical Specification has been produced by the 3rd Generation Partnership Project (3GPP).

The contents of the present document are subject to continuing work within the TSG and may change following formal TSG approval. Should the TSG modify the contents of the present document, it will be re-released by the TSG with an identifying change of release date and an increase in version number as follows:

Version x.y.z

where:

- x the first digit:
  - 1 presented to TSG for information;
  - 2 presented to TSG for approval;
  - 3 or greater indicates TSG approved document under change control.
- y the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- z the third digit is incremented when editorial only changes have been incorporated in the document.

**iTeh Standards**  
**(<https://standards.iteh.ai>)**  
**Document Preview**

[ETSI TS 138 463 V15.13.0 \(2023-10\)](https://standards.iteh.ai/catalog/standards/sist/3ee7d9fe-a754-42b1-93ab-23b8172757a2/etsi-ts-138-463-v15-13-0-2023-10)

<https://standards.iteh.ai/catalog/standards/sist/3ee7d9fe-a754-42b1-93ab-23b8172757a2/etsi-ts-138-463-v15-13-0-2023-10>

---

# 1 Scope

The present document specifies the 5G radio network layer signalling protocol for the E1 interface. The E1 interface provides means for interconnecting a gNB-CU-CP and a gNB-CU-UP of a gNB within an NG-RAN, or for interconnecting a gNB-CU-CP and a gNB-CU-UP of an en-gNB within an E-UTRAN. The E1 Application Protocol (E1AP) supports the functions of E1 interface by signalling procedures defined in the present document. E1AP is developed in accordance to the general principles stated in TS 38.401 [2] and TS 38.460 [3].

---

# 2 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- References are either specific (identified by date of publication, edition number, version number, etc.) or non-specific.
- For a specific reference, subsequent revisions do not apply.
- For a non-specific reference, the latest version applies. In the case of a reference to a 3GPP document (including a GSM document), a non-specific reference implicitly refers to the latest version of that document *in the same Release as the present document*.

- [1] 3GPP TR 21.905: "Vocabulary for 3GPP Specifications".
- [2] 3GPP TS 38.401: "NG-RAN; Architecture Description".
- [3] 3GPP TS 38.460: "NG-RAN; E1 general aspects and principles".
- [4] 3GPP TS 38.300: "NR; Overall description; Stage-2".
- [5] 3GPP TR 25.921 (version.7.0.0): "Guidelines and principles for protocol description and error".
- [6] 3GPP TS 38.413: "NG-RAN; NG Application Protocol (NGAP)".
- [7] ITU-T Recommendation X.691 (2002-07): "Information technology - ASN.1 encoding rules - Specification of Packed Encoding Rules (PER)".
- [8] ITU-T Recommendation X.680 (07/2002): "Information technology – Abstract Syntax Notation One (ASN.1): Specification of basic notation".
- [9] ITU-T Recommendation X.681 (07/2002): "Information technology – Abstract Syntax Notation One (ASN.1): Information object specification".
- [10] 3GPP TS 38.331: "NR; Radio Resource Control (RRC); Protocol Specification".
- [11] 3GPP TS 23.401: "General Packet Radio Service (GPRS) Enhancements for Evolved Universal Terrestrial Radio Access Network (E-UTRAN) access".
- [12] 3GPP TS 23.203: "Policy and Charging Control Architecture".
- [13] 3GPP TS 33.501: "Security Architecture and Procedures for 5G System".
- [14] IETF RFC 5905: "Network Time Protocol Version 4: Protocol and Algorithms Specification".
- [15] 3GPP TS 29.281: "General Packet Radio System (GPRS) Tunnelling Protocol User Plane (GTPv1-U)".
- [16] 3GPP TS 38.414: "NG-RAN; NG Data Transport".
- [17] 3GPP TS 38.323: "NR; Packet Data Convergence Protocol (PDCP) specification".
- [18] 3GPP TS 38.462: "NG-RAN; E1 Signalling Transport".
- [19] 3GPP TS 37.340: "NR; Multi-connectivity; Overall description; Stage-2".

- [20] 3GPP TS 23.501: "System Architecture for the 5G System".
- [21] 3GPP TS 36.331: "Evolved Universal Terrestrial Radio Access (E-UTRA); Radio Resource Control (RRC) protocol specification".
- [22] 3GPP TS 28.552: "Management and orchestration; 5G performance measurements".
- [23] 3GPP TS 23.003: "Numbering, addressing and identification".

---

## 3 Definitions and abbreviations

### 3.1 Definitions

For the purposes of the present document, the terms and definitions given in 3GPP TR 21.905 [1] and the following apply. A term defined in the present document takes precedence over the definition of the same term, if any, in 3GPP TR 21.905 [1].

**Elementary Procedure:** E1AP consists of Elementary Procedures (EPs). An Elementary Procedure is a unit of interaction between gNB-CU-CP and gNB-CU-UP. These Elementary Procedures are defined separately and are intended to be used to build up complete sequences in a flexible manner. If the independence between some EPs is restricted, it is described under the relevant EP description. Unless otherwise stated by the restrictions, the EPs may be invoked independently of each other as standalone procedures, which can be active in parallel. The usage of several E1AP EPs together is specified in stage 2 specifications (e.g., TS 38.460 [3]).

An EP consists of an initiating message and possibly a response message. Two kinds of EPs are used:

- **Class 1:** Elementary Procedures with response (success and/or failure).
- **Class 2:** Elementary Procedures without response.

For Class 1 EPs, the types of responses can be as follows:

Successful:

- A signalling message explicitly indicates that the elementary procedure successfully completed with the receipt of the response.

Unsuccessful:

- A signalling message explicitly indicates that the EP failed.
- On time supervision expiry (i.e., absence of expected response).

Successful and Unsuccessful:

- One signalling message reports both successful and unsuccessful outcome for the different included requests. The response message used is the one defined for successful outcome.

Class 2 EPs are considered always successful.

gNB: as defined in TS 38.300 [4].

gNB-CU: as defined in TS 38.401 [2].

gNB-DU: as defined in TS 38.401 [2].

gNB-CU-CP: as defined in TS 38.401 [2].

gNB-CU-UP: as defined in TS 38.401 [2].

PDU Session Resource: as defined in TS 38.401 [2].

UE-associated signalling: When E1AP messages associated to one UE uses the UE-associated logical E1-connection for association of the message to the UE in gNB-CU-UP and gNB-CU-CP.

UE-associated logical E1-connection: The UE-associated logical E1-connection uses the identities *GNB-CU-CP UE E1AP ID* and *GNB-CU-UP UE E1AP ID* according to the definition in TS 38.401 [2]. For a received UE associated E1AP message the gNB-CU-CP identifies the associated UE based on the *GNB-CU-CP UE E1AP ID IE* and the gNB-CU-UP identifies the associated UE based on the *GNB-CU-UP UE E1AP ID IE*.

## 3.2 Abbreviations

For the purposes of the present document, the abbreviations given in TR 21.905 [1] and the following apply. An abbreviation defined in the present document takes precedence over the definition of the same abbreviation, if any, in TR 21.905 [1].

5GC	5G Core Network
5QI	5G QoS Identifier
CGI	Cell Global Identifier
CN	Core Network
CP	Control Plane
DL	Downlink
EN-DC	E-UTRA-NR Dual Connectivity
EPC	Evolved Packet Core
MCG	Master Cell Group
NSSAI	Network Slice Selection Assistance Information
RANAC	RAN Area Code
SCG	Secondary Cell Group
SDAP	Service Data Adaptation Protocol
S-NSSAI	Single Network Slice Selection Assistance Information
TNLA	Transport Network Layer Association

## 4 General

### 4.1 Procedure specification principles

The principle for specifying the procedure logic is to specify the functional behaviour of the terminating node exactly and completely. Any rule that specifies the behaviour of the originating node shall be possible to be verified with information that is visible within the system.

The following specification principles have been applied for the procedure text in clause 8:

- The procedure text discriminates between:

- 1) Functionality which "shall" be executed.

The procedure text indicates that the receiving node "shall" perform a certain function Y under a certain condition. If the receiving node supports procedure X but cannot perform functionality Y requested in the REQUEST message of a Class 1 EP, the receiving node shall respond with the message used to report unsuccessful outcome for this procedure, containing an appropriate cause value.

- 2) Functionality which "shall, if supported" be executed.

The procedure text indicates that the receiving node "shall, if supported," perform a certain function Y under a certain condition. If the receiving node supports procedure X, but does not support functionality Y, the receiving node shall proceed with the execution of the EP, possibly informing the requesting node about the not supported functionality.

- Any required inclusion of an optional IE in a response message is explicitly indicated in the procedure text. If the procedure text does not explicitly indicate that an optional IE shall be included in a response message, the optional IE shall not be included. For requirements on including *Criticality Diagnostics IE*, see clause 10.

## 4.2 Forwards and backwards compatibility

The forwards and backwards compatibility of the protocol is assured by mechanism where all current and future messages, and IEs or groups of related IEs, include ID and criticality fields that are coded in a standard format that will not be changed in the future. These parts can always be decoded regardless of the standard version.

## 4.3 Specification notations

For the purposes of the present document, the following notations apply:

Procedure	When referring to an elementary procedure in the specification the Procedure Name is written with the first letters in each word in upper case characters followed by the word "procedure", e.g. Handover Preparation procedure.
Message	When referring to a message in the specification the MESSAGE NAME is written with all letters in upper case characters followed by the word "message", e.g. HANDOVER REQUEST message.
IE	When referring to an information element (IE) in the specification the <i>Information Element Name</i> is written with the first letters in each word in upper case characters and all letters in Italic font followed by the abbreviation "IE", e.g. <i>E-RAB ID</i> IE.
Value of an IE	When referring to the value of an information element (IE) in the specification the "Value" is written as it is specified in the specification enclosed by quotation marks, e.g. "Value".

---

## 5 E1AP services

E1AP provides the signalling service between the gNB-CU-CP and the gNB-CU-UP that is required to fulfil the E1AP functions described in clause 7. E1AP services are divided into two groups:

Non UE-associated services:	They are related to the whole E1 interface instance between the gNB-CU-CP and gNB-CU-UP utilising a non UE-associated signalling connection.
UE-associated services:	They are related to one UE. E1AP functions that provide these services are associated with a UE-associated signalling connection that is maintained for the UE in question.

Unless explicitly indicated in the procedure specification, at any instance in time one protocol endpoint shall have a maximum of one ongoing E1AP procedure related to a certain UE.

---

## 6 Services expected from signalling transport

The signalling connection shall provide in sequence delivery of E1AP messages. E1AP shall be notified if the signalling connection breaks.

---

## 7 Functions of E1AP

The functions of E1AP are described in TS 38.460 [3].

## 8 E1AP procedures

### 8.1 List of E1AP Elementary Procedures

In the following tables, all EPs are divided into Class 1 and Class 2 EPs (see subclause 3.1 for explanation of the different classes):

**Table 1: Class 1 procedures**

Elementary Procedure	Initiating Message	Successful Outcome	Unsuccessful Outcome
		Response message	Response message
Reset	RESET	RESET ACKNOWLEDGE	
gNB-CU-UP E1 Setup	GNB-CU-UP E1 SETUP REQUEST	GNB-CU-UP E1 SETUP RESPONSE	GNB-CU-UP E1 SETUP FAILURE
gNB-CU-CP E1 Setup	GNB-CU-CP E1 SETUP REQUEST	GNB-CU-CP E1 SETUP RESPONSE	GNB-CU-CP E1 SETUP FAILURE
gNB-CU-UP Configuration Update	GNB-CU-UP CONFIGURATION UPDATE	GNB-CU-UP CONFIGURATION UPDATE ACKNOWLEDGE	GNB-CU-UP CONFIGURATION UPDATE FAILURE
gNB-CU-CP Configuration Update	GNB-CU-CP CONFIGURATION UPDATE	GNB-CU-CP CONFIGURATION UPDATE ACKNOWLEDGE	GNB-CU-CP CONFIGURATION UPDATE FAILURE
E1 Release	E1 RELEASE REQUEST	E1 RELEASE RESPONSE	
Bearer Context Setup	BEARER CONTEXT SETUP REQUEST	BEARER CONTEXT SETUP RESPONSE	BEARER CONTEXT SETUP FAILURE
Bearer Context Modification (gNB-CU-CP initiated)	BEARER CONTEXT MODIFICATION REQUEST	BEARER CONTEXT MODIFICATION RESPONSE	BEARER CONTEXT MODIFICATION FAILURE
Bearer Context Modification Required (gNB-CU-UP initiated)	BEARER CONTEXT MODIFICATION REQUIRED	BEARER CONTEXT MODIFICATION CONFIRM	
Bearer Context Release (gNB-CU-CP initiated)	BEARER CONTEXT RELEASE COMMAND	BEARER CONTEXT RELEASE COMPLETE	

**Table 2: Class 2 procedures**

Elementary Procedure	Message
Error Indication	ERROR INDICATION
Bearer Context Release Request (gNB-CU-UP initiated)	BEARER CONTEXT RELEASE REQUEST
Bearer Context Inactivity Notification	BEARER CONTEXT INACTIVITY NOTIFICATION
DL Data Notification	DL DATA NOTIFICATION
UL Data Notification	UL DATA NOTIFICATION
Data Usage Report	DATA USAGE REPORT
gNB-CU-UP Counter Check	GNB-CU-UP COUNTER CHECK
gNB-CU-UP Status Indication	GNB-CU-UP STATUS INDICATION
MR-DC Data Usage Report	MR-DC DATA USAGE REPORT