

Draft **ETSI EN 300 395-2** V1.3.2 (2024-10)



**TETRA and Critical Communications Evolution (TCCE);
Speech codec for full-rate traffic channel;
Part 2: TETRA codec**

(http://standards.itech.ai)
Document Preview

[ETSI EN 300 395-2 V1.3.2 \(2024-10\)](https://standards.itech.ai/catalog/standards/etsi/c51f1c7e-1b98-4c50-bbf3-817b121d1735/etsi-en-300-395-2-v1-3-2-2024-10)

<https://standards.itech.ai/catalog/standards/etsi/c51f1c7e-1b98-4c50-bbf3-817b121d1735/etsi-en-300-395-2-v1-3-2-2024-10>



Reference

REN/TCCE-00266

Keywords

codec, radio, TETRA

ETSI

650 Route des Lucioles
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - APE 7112B
Association à but non lucratif enregistrée à la
Sous-Préfecture de Grasse (06) N° w061004871

Important notice

The present document can be downloaded from the
ETSI [Search & Browse Standards](#) application.

The present document may be made available in electronic versions and/or in print. The content of any electronic and/or print versions of the present document shall not be modified without the prior written authorization of ETSI. In case of any existing or perceived difference in contents between such versions and/or in print, the prevailing version of an ETSI deliverable is the one made publicly available in PDF format on [ETSI deliver](#).

Users should be aware that the present document may be revised or have its status changed,
this information is available in the [Milestones listing](#).

If you find errors in the present document, please send your comments to
the relevant service listed under [Committee Support Staff](#).

If you find a security vulnerability in the present document, please report it through our
[Coordinated Vulnerability Disclosure \(CVD\)](#) program.

Notice of disclaimer & limitation of liability

The information provided in the present deliverable is directed solely to professionals who have the appropriate degree of experience to understand and interpret its content in accordance with generally accepted engineering or other professional standard and applicable regulations.

No recommendation as to products and services or vendors is made or should be implied.
In no event shall ETSI be held liable for loss of profits or any other incidental or consequential damages.

Any software contained in this deliverable is provided "AS IS" with no warranties, express or implied, including but not limited to, the warranties of merchantability, fitness for a particular purpose and non-infringement of intellectual property rights and ETSI shall not be held liable in any event for any damages whatsoever (including, without limitation, damages for loss of profits, business interruption, loss of information, or any other pecuniary loss) arising out of or related to the use of or inability to use the software.

Copyright Notification

No part may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm except as authorized by written permission of ETSI.

The content of the PDF version shall not be modified without the written authorization of ETSI.

The copyright and the foregoing restriction extend to reproduction in all media.

© ETSI 2024.
All rights reserved.

Contents

Intellectual Property Rights	7
Foreword.....	7
Modal verbs terminology.....	8
1 Scope	9
2 References	9
2.1 Normative references	9
2.2 Informative references.....	9
3 Definition of terms, symbols and abbreviations.....	10
3.1 Terms.....	10
3.2 Symbols.....	10
3.3 Abbreviations	10
4 Full rate codec	11
4.1 Structure of the codec.....	11
4.2 Functional description of the codec.....	13
4.2.1 Pre- and post-processing	13
4.2.2 Encoder.....	13
4.2.2.0 General	13
4.2.2.1 Short-term prediction	14
4.2.2.2 LP to LSP and LSP to LP conversion	15
4.2.2.3 Quantization and interpolation of LP parameters.....	17
4.2.2.4 Long-term prediction analysis.....	18
4.2.2.5 Algebraic codebook: structure and search.....	20
4.2.2.6 Quantization of the gains	23
4.2.2.7 Detailed bit allocation	24
4.2.3 Decoder.....	25
4.2.3.0 General	25
4.2.3.1 Decoding process	25
4.2.3.1.0 General	25
4.2.3.1.1 Decoding of LP filter parameters	25
4.2.3.1.2 Decoding of the adaptive codebook vector.....	26
4.2.3.1.3 Decoding of the innovation vector	26
4.2.3.1.4 Decoding of the adaptive and innovative codebook gains.....	26
4.2.3.1.5 Computation of the reconstructed speech.....	26
4.2.3.2 Error concealment	26
5 Channel coding for speech	27
5.1 General	27
5.2 Interfaces in the error control structure	27
5.3 Notations	29
5.4 Definition of sensitivity classes and error control codes	29
5.4.1 Sensitivity classes	29
5.4.2 CRC codes	29
5.4.3 16-state RCPC codes	31
5.4.3.0 General	31
5.4.3.1 Encoding by the 16-state mother code of rate 1/3.....	31
5.4.3.2 Puncturing of the mother code	31
5.5 Error control scheme for normal speech traffic channel.....	32
5.5.0 General.....	32
5.5.1 CRC code.....	32
5.5.2 RCPC codes.....	32
5.5.2.0 General	32
5.5.2.1 Puncturing scheme of the RCPC code of rate 8/12 (equal to 2/3).....	33
5.5.2.2 Puncturing scheme of the RCPC code of rate 8/18	33
5.5.3 Matrix Interleaving	33
5.6 Error control scheme for speech traffic channel with frame stealing activated.....	34

5.6.0	General.....	34
5.6.1	CRC code.....	34
5.6.2	RCPC codes.....	35
5.6.2.0	General.....	35
5.6.2.1	Puncturing scheme of the RCPC code of rate 8/17.....	36
5.6.3	Interleaving.....	36
6	Channel decoding for speech.....	36
6.1	General.....	36
6.2	Error control structure.....	36
7	Codec performance.....	37
8	Bit exact description of the TETRA codec.....	37
9	AMR speech codec.....	39
10	Channel coding for AMR speech.....	39
10.1	General.....	39
10.2	Interfaces in the error control structure.....	39
10.3	Notations.....	39
10.4	Definition of sensitivity classes and error control codes.....	39
10.4.1	Sensitivity classes.....	39
10.4.2	CRC codes.....	39
10.4.3	16-state RCPC codes.....	41
10.4.3.0	General.....	41
10.4.3.1	Encoding by the 16-state mother code of rate 1/3.....	41
10.4.3.2	Puncturing of the mother code.....	41
10.5	Error control scheme for normal AMR speech traffic channel.....	42
10.5.0	General.....	42
10.5.1	CRC code.....	42
10.5.2	RCPC codes.....	42
10.5.2.0	General.....	42
10.5.2.1	Puncturing scheme of the RCPC code of rate 8/12 (equal to 2/3).....	43
10.5.2.2	Puncturing scheme of the RCPC code of rate 8/18.....	43
10.5.3	Matrix Interleaving.....	43
10.6	Error control scheme for AMR speech traffic channel with frame stealing activated.....	44
10.6.0	General.....	44
10.6.1	Speech frames in stealing mode.....	44
10.6.2	CRC code.....	44
10.6.3	RCPC codes.....	45
10.6.3.0	General.....	45
10.6.3.1	Puncturing scheme of the RCPC code of rate 14/8.....	46
10.6.4	Interleaving.....	46
11	Channel decoding for AMR speech.....	46
11.1	General.....	46
11.2	Error control structure.....	46
12	Bit exact description of the AMR codec FEC.....	47
Annex A (informative): Implementation of speech channel decoding.....		48
A.0	General.....	48
A.1	Algorithmic description of speech channel decoding.....	48
A.1.1	Definition of error control codes.....	48
A.1.1.1	16-state RCPC codes.....	48
A.1.1.1.0	General.....	48
A.1.1.1.1	Obtaining the mother code from punctured code.....	48
A.1.1.1.2	Viterbi decoding of the 16-state mother code of the rate 1/3.....	48
A.1.1.2	CRC codes.....	49
A.1.1.3	Type-4 bits.....	49
A.1.2	Error control scheme for normal speech traffic channel.....	49
A.1.2.0	General.....	49

A.1.2.1	Matrix Interleaving	49
A.1.2.2	RCPC codes	49
A.1.2.2.0	General	49
A.1.2.2.1	Puncturing scheme of the RCPC code of rate 8/12 (equal to 2/3).....	50
A.1.2.2.2	Puncturing scheme of the RCPC code of rate 8/18	50
A.1.2.3	CRC code.....	50
A.1.2.4	Speech parameters	50
A.1.3	Error control scheme for speech traffic channel with frame stealing activated.....	50
A.1.3.0	General.....	50
A.1.3.1	Interleaving	50
A.1.3.2	RCPC codes	51
A.1.3.2.0	General	51
A.1.3.2.1	Puncturing scheme of the RCPC code of rate 8/17	51
A.1.3.3	CRC code.....	51
A.1.3.4	Speech parameters	51
A.2	C Code for speech channel decoding	51
Annex B (informative): Indexes		52
B.1	Index of C code routines	52
B.2	Index of files.....	55
Annex C (informative): Codec performance.....		56
C.1	General	56
C.2	Quality	56
C.2.1	Subjective speech quality	56
C.2.1.1	Description of characterization tests	56
C.2.1.2	Absolute speech quality	56
C.2.1.3	Effect of input level	56
C.2.1.4	Effect of input frequency characteristic	56
C.2.1.5	Effect of transmission errors.....	57
C.2.1.6	Effect of tandeming	57
C.2.1.7	Effect of acoustic background noise.....	57
C.2.1.8	Effect of vocal effort.....	57
C.2.1.9	Effect of frame stealing.....	57
C.2.1.10	Speaker and language dependency	57
C.2.2	Comparison with analogue FM	57
C.2.2.0	General.....	57
C.2.2.1	Analogue and digital systems results	57
C.2.2.2	All conditions.....	58
C.2.2.3	Input level	58
C.2.2.4	Error patterns	59
C.2.2.5	Background noise	59
C.2.3	Additional tests.....	59
C.2.3.0	General.....	59
C.2.3.1	Types of signals	59
C.2.3.2	Codec behaviour	59
C.3	Performance of the channel coding/decoding for speech.....	60
C.3.0	General	60
C.3.1	Classes of simulation environment conditions	60
C.3.2	Classes of equipment.....	60
C.3.3	Classes of bits.....	61
C.3.4	Channel conditions	61
C.3.5	Results for normal case	61
C.4	Complexity	62
C.4.0	General	62
C.4.1	Complexity analysis	62
C.4.1.1	Measurement methodology.....	62
C.4.1.2	TETRA basic operators	62

C.4.1.3	Worst case path for speech encoder.....	64
C.4.1.4	Worst case path for speech decoder.....	65
C.4.1.5	Condensed complexity values for encoder and decoder.....	66
C.4.2	DSP independence.....	67
C.4.2.0	General.....	67
C.4.2.1	Program control structure.....	67
C.4.2.2	Basic operator implementation.....	67
C.4.2.3	Additional operator implementation.....	67
C.5	Delay.....	67
Annex D (informative): Results of the TETRA codec characterization listening and complexity tests.....		68
D.1	Characterization listening test.....	68
D.1.1	Experimental conditions.....	68
D.1.2	Tables of results.....	69
D.2	TETRA codec complexity study.....	77
D.2.1	Computational analysis results.....	77
D.2.1.1	TETRA speech encoder.....	77
D.2.1.2	TETRA speech decoder.....	85
D.2.1.3	TETRA channel encoder and decoder.....	88
D.2.2	Memory requirements analysis results.....	90
D.2.2.1	TETRA speech encoder.....	90
D.2.2.2	TETRA speech decoder.....	91
D.2.2.3	TETRA speech channel encoder.....	91
D.2.2.4	TETRA speech channel decoder.....	91
Annex E (informative): Description of attached computer files.....		92
E.0	General.....	92
E.1	Directory C-WORD.....	92
E.2	Directory C-CODE.....	92
E.3	Directory AMR-Code.....	92
Annex F (informative): Bibliography.....		93
History.....		94

Intellectual Property Rights

Essential patents

IPRs essential or potentially essential to normative deliverables may have been declared to ETSI. The declarations pertaining to these essential IPRs, if any, are publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: "*Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards*", which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (<https://ipr.etsi.org/>).

Pursuant to the ETSI Directives including the ETSI IPR Policy, no investigation regarding the essentiality of IPRs, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

Trademarks

The present document may include trademarks and/or tradenames which are asserted and/or registered by their owners. ETSI claims no ownership of these except for any which are indicated as being the property of ETSI, and conveys no right to use or reproduce any trademark and/or tradename. Mention of those trademarks in the present document does not constitute an endorsement by ETSI of products, services or organizations associated with those trademarks.

DECT™, **PLUGTESTS™**, **UMTS™** and the ETSI logo are trademarks of ETSI registered for the benefit of its Members. **3GPP™** and **LTE™** are trademarks of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners. **oneM2M™** logo is a trademark of ETSI registered for the benefit of its Members and of the oneM2M Partners. **GSM®** and the GSM logo are trademarks registered and owned by the GSM Association.

Foreword

This draft European Standard (EN) has been produced by ETSI Technical Committee TETRA and Critical Communications Evolution (TCCE), and is now submitted for the combined Public Enquiry and Vote phase of the ETSI EN Approval Procedure.

The present document is part 2 of a multi-part deliverable covering speech codec for full-rate traffic channel, as identified below:

- Part 1: "General description of speech functions";
- Part 2: "TETRA codec";**
- Part 3: "Specific operating features";
- Part 4: "Codec conformance testing".

Clause 4 provides a complete description of the full rate speech source encoder and decoder, whilst clause 5 describes the speech channel encoder and clause 6 the speech channel decoder.

Clause 7 describes the codec performance.

Clause 8 introduces the bit exact description of the codec. This description is given as an ANSI C code, fixed point, bit exact. The whole C code corresponding to the TETRA codec is given in computer files attached to the present document, and are an integral part of this multi-part deliverable.

Clause 9 describes the optional AMR codec.

Clause 10 describes the AMR speech channel encoder.

Clause 11 describes the AMR speech channel decoder.

Clause 12 introduces the AMR speech channel encoder and decoder. This description is given as an ANSI C code.

In addition to these clauses, five informative annexes are provided.

Annex A describes a possible implementation of the speech channel decoding function.

Annex B provides comprehensive indexes of all the routines and files included in the C code associated with the present document.

Annex C describes the actual quality, performance and complexity aspects of the codec.

Annex D reports detailed results from codec characterization listening and complexity tests.

Annex E contains instructions for the use of the attached electronic files.

Annex F lists informative references relevant to the speech codec.

Proposed national transposition dates

Date of latest announcement of this EN (doa):	3 months after ETSI publication
Date of latest publication of new National Standard or endorsement of this EN (dop/e):	6 months after doa
Date of withdrawal of any conflicting National Standard (dow):	6 months after doa

Modal verbs terminology

In the present document "**shall**", "**shall not**", "**should**", "**should not**", "**may**", "**need not**", "**will**", "**will not**", "**can**" and "**cannot**" are to be interpreted as described in clause 3.2 of the [ETSI Drafting Rules](#) (Verbal forms for the expression of provisions).

"**must**" and "**must not**" are **NOT** allowed in ETSI deliverables except when used in direct citation.

ETSI EN 300 395-2 V1.3.2 (2024-10)

<https://standards.iteh.ai/catalog/standards/etsi/c51f1c7e-1b98-4c50-bbf3-817b121d1735/etsi-en-300-395-2-v1-3-2-2024-10>

1 Scope

The present document contains the full specification of the speech codecs for use in the Terrestrial Trunked Radio (TETRA) system.

The TETRA codec specified in clauses 4 to 8 is mandatory for all TETRA mobiles and networks. The AMR codec specified in clauses 9 to 12 is optional. If the AMR codec is implemented, all clauses from 9 to 12 applies.

2 References

2.1 Normative references

References are either specific (identified by date of publication and/or edition number or version number) or non-specific. For specific references, only the cited version applies. For non-specific references, the latest version of the referenced document (including any amendments) applies.

Referenced documents which are not found to be publicly available in the expected location might be found at <https://docbox.etsi.org/Reference/>.

NOTE: While any hyperlinks included in this clause were valid at the time of publication, ETSI cannot guarantee their long term validity.

The following referenced documents are necessary for the application of the present document.

- [1] [ETSI EN 300 392-2](#): "Terrestrial Trunked Radio (TETRA); Voice plus Data (V+D); Part 2: Air Interface (AI)".
- [2] [ETSI TS 126 073](#): "Universal Mobile Telecommunications System (UMTS); ANSI-C code for the Adaptive Multi Rate speech codec (3GPP TS 26.073 Release 4)".
- [3] [ETSI TS 126 074](#): "Universal Mobile Telecommunications System (UMTS); Mandatory speech codec speech processing functions; AMR speech codec test sequences (3GPP TS 26.074 Release 4)".
- [4] [ETSI TS 126 090](#): "Universal Mobile Telecommunications System (UMTS); Mandatory Speech Codec speech processing functions AMR Speech Codec - Transcoding functions (3GPP TS 26.090 Release 4)".

2.2 Informative references

References are either specific (identified by date of publication and/or edition number or version number) or non-specific. For specific references, only the cited version applies. For non-specific references, the latest version of the referenced document (including any amendments) applies.

NOTE: While any hyperlinks included in this clause were valid at the time of publication, ETSI cannot guarantee their long term validity.

The following referenced documents are not necessary for the application of the present document but they assist the user with regard to a particular subject area.

- [i.1] Recommendation ITU-T P.48 (1988): "Specification for an intermediate reference system".
- [i.2] ETSI ETR 300-1: "Terrestrial Trunked Radio (TETRA); Voice plus Data (V+D); Designers' guide; Part 1: Overview, technical description and radio aspects".

3 Definition of terms, symbols and abbreviations

3.1 Terms

Void.

3.2 Symbols

Void.

3.3 Abbreviations

For the purposes of the present document, the following abbreviations apply:

ACELP	Algebraic CELP
AMR	Adaptive Multi-Rate
ANSI	American National Standards Institute
BER	Bit Error Ratio
BFI	Bad Frame Indicator
BS	Base Station
CELP	Code-Excited Linear Predictive
CRC	Cyclic Redundancy Code
DSP	Digital Signal Processor
DTMF	Dual Tone Multiple Frequency
EP	Error Pattern
EQ	Equalizer test
FEC	Forward Error Correction
FIR	Finite Impulse Response
FM	Frequency Modulation
GSM	Global System for Mobile communications
HT	Hilly Terrain
IRS	Intermediate Reference System
LP	Linear Prediction
LPC	Linear Predictive Coding
LSB	Least Significant Bit
LSF	Line Spectral Frequency
LSP	Line Spectral Pair
MER	Message Error Rate
MNRU	Multiplicative Noise Reference Unit
MOPS	Million of Operations per Second
MOS	Mean Opinion Score
MS	Mobile Station
MSB	Most Significant Bit
MSE	Mean Square Error
PCM	Pulse Code Modulation
PDF	Probability Density Function
PUEM	Probability of Undetected Erroneous Message
RAM	Random Access Memory
RCPC	Rate-Compatible Punctured Convolutional
RF	Radio Frequency
ROM	Read-Only Memory
SCR	Source Controlled Rate
SNR	Signal to Noise Ratio
STCH	Stealing CHannel
TCH/S	Speech Traffic Channel
TDM	Time Division Multiplex
TU	Typical Urban
UPCM	Uniform PCM

V+D Voice + Data
VQ Vector Quantization

4 Full rate codec

4.1 Structure of the codec

The TETRA speech codec is based on the Code-Excited Linear Predictive (CELP) coding model. In this model, a block of N speech samples is synthesized by filtering an appropriate innovation sequence from a codebook, scaled by a gain factor g_c , through two time varying filters. A simplified high level block diagram of this synthesis process, as implemented in the TETRA codec, is shown in figure 1.




Figure 1: High level block diagram of the TETRA speech synthesizer

The first filter is a long-term prediction filter (pitch filter) aiming at modelling the pseudo-periodicity in the speech signal and the second is a short-term prediction filter modelling the speech spectral envelope.

The long-term or pitch, synthesis filter is given by:

$$\frac{1}{B(z)} = \frac{1}{1 - g_p z^{-T}} \quad (1)$$

where T is the pitch delay and g_p is the pitch gain. The pitch synthesis filter is implemented as an adaptive codebook, where for delays less than the sub-frame length the past excitation is repeated.

The short-term synthesis filter is given by:

$$H(z) = \frac{1}{A(z)} = \frac{1}{1 + \sum_{i=1}^p a_i z^{-i}} \quad (2)$$

where $a_i, i = 1, \dots, p$, are the Linear Prediction (LP) parameters and p is the predictor order. In the TETRA codec p shall be 10.

The TETRA encoder uses an analysis-by-synthesis technique to determine the pitch and excitation codebook parameters. The simplified block diagram of the TETRA encoder is shown in figure 2.




Figure 2: High level block diagram of the TETRA speech encoder

In this analysis-by-synthesis technique, the synthetic speech is computed for all candidate innovation sequences retaining the particular sequence that produces the output closer to the original signal according to a perceptually weighted distortion measure. The perceptual weighting filter de-emphasizes the error at the formant regions of the speech spectrum and is given by:

$$W(z) = \frac{A(z)}{A(z/\gamma)} \quad (3)$$

where $A(z)$ is the LP inverse filter (as in Equation (2)) and $0 < \gamma \leq 1$. The value $\gamma_1 = 0,85$ shall be used.

Both the weighting filter, $W(z)$, and formant synthesis filter, $H(z)$, shall use the quantized LP parameters.

In the Algebraic CELP (ACELP) technique, special innovation codebooks having an algebraic structure are used. This algebraic structure has several advantages in terms of storage, search complexity, and robustness. The TETRA codec shall use a specific dynamic algebraic excitation codebook whereby the fixed excitation vectors are shaped by a dynamic shaping matrix (see annex F). The shaping matrix is a function of the LP model $A(z)$, and its main role is to shape the excitation vectors in the frequency domain so that their energies are concentrated in the important frequency bands. The shaping matrix used is a Toeplitz lower triangular matrix constructed from the impulse response of the filter:

$$F(z) = \frac{A(z/\gamma_1)}{A(z/\gamma_2)} \quad (4)$$

where $A(z)$ is the LP inverse filter. The values $\gamma_1 = 0,75$ and $\gamma_2 = 0,85$ shall be used.

In the TETRA codec, 30 ms speech frames shall be used. It is required that the short-term prediction parameters (or LP parameters) are computed and transmitted every speech frame. The speech frame shall be divided into 4 sub-frames of 7,5 ms (60 samples). The pitch and algebraic codebook parameters have also to be transmitted every sub-frame.

Table 1 gives the bit allocation for the TETRA codec. 137 bits shall be produced for each frame of 30 ms resulting in a bit rate of 4 567 bit/s.

Table 1: Bit allocation for the TETRA codec

Parameter	1 st subframe	2 nd subframe	3 rd subframe	4 th subframe	Total per frame
LP filter					26
Pitch delay	8	5	5	5	23
Algebraic code	16	16	16	16	64
VQ of 2 gains	6	6	6	6	24
Total					137

More details about the sequence of bits within the speech frame of 137 bits per 30 ms, with reference to the speech parameters, can be found in clause 4.2.2.7, table 3.

4.2 Functional description of the codec

4.2.1 Pre- and post-processing

Before starting the encoding process, the speech signal shall be pre-processed using the offset compensation filter:

$$H_p(z) = \frac{1}{2} \left(\frac{1 - z^{-1}}{1 - \alpha z^{-1}} \right) \quad (5)$$

where $\alpha = 32\,735/32\,768$. In the time domain, this filter corresponds to:

$$s'(n) = s(n)/2 - s(n-1)/2 + \alpha s'(n-1) \quad (6)$$

where $s(n)$ is the input signal and $s'(n)$ is the pre-processed signal. The purpose of this pre-processing is firstly to remove the dc from the signal (offset compensation), and secondly, to scale down the input signal in order to avoid saturation of the synthesis filtering.

At the decoder, the post-processing consists of scaling up the reconstructed signal (multiplication by 2 with saturation control).

4.2.2 Encoder

4.2.2.0 General

Figure 3 presents a detailed block diagram of the TETRA encoder illustrating the major parts of the codec as well as signal flow. On this figure, names appearing at the bottom of the various building blocks correspond to the C code routines associated with the present document.

