

Draft **ETSI EN 302 307-2** V1.4.1 (2024-05)



**Digital Video Broadcasting (DVB);
Second generation framing structure, channel coding and
modulation systems for Broadcasting,
Interactive Services, News Gathering and
other broadband satellite applications;
Part 2: DVB-S2 Extensions (DVB-S2X)**

ETSI EN 302 307-2 V1.4.1 (2024-05)

<https://standards.iteh.ai/catalog/standards/etsi/587cb462-7d5c-40ff-93e3-f2188c1723de/etsi-en-302-307-2-v1-4-1-2024-05>

EBU DVB[®]

Reference

REN/JTC-DVB-410-2

Keywords

BSS, digital, DVB, modulation, satellite, TV

ETSI

650 Route des Lucioles
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - APE 7112B
Association à but non lucratif enregistrée à la
Sous-Préfecture de Grasse (06) N° w061004871

Important notice

The present document can be downloaded from:
<https://www.etsi.org/standards-search>

The present document may be made available in electronic versions and/or in print. The content of any electronic and/or print versions of the present document shall not be modified without the prior written authorization of ETSI. In case of any existing or perceived difference in contents between such versions and/or in print, the prevailing version of an ETSI deliverable is the one made publicly available in PDF format at www.etsi.org/deliver.

Users of the present document should be aware that the document may be subject to revision or change of status.

Information on the current status of this and other ETSI documents is available at

<https://portal.etsi.org/TB/ETSIDeliverableStatus.aspx>

If you find errors in the present document, please send your comment to one of the following services:

<https://portal.etsi.org/People/CommitteeSupportStaff.aspx>

If you find a security vulnerability in the present document, please report it through our

Coordinated Vulnerability Disclosure Program:

<https://www.etsi.org/standards/coordinated-vulnerability-disclosure>

Notice of disclaimer & limitation of liability

The information provided in the present deliverable is directed solely to professionals who have the appropriate degree of experience to understand and interpret its content in accordance with generally accepted engineering or other professional standard and applicable regulations.

No recommendation as to products and services or vendors is made or should be implied.

In no event shall ETSI be held liable for loss of profits or any other incidental or consequential damages.

Any software contained in this deliverable is provided "AS IS" with no warranties, express or implied, including but not limited to, the warranties of merchantability, fitness for a particular purpose and non-infringement of intellectual property rights and ETSI shall not be held liable in any event for any damages whatsoever (including, without limitation, damages for loss of profits, business interruption, loss of information, or any other pecuniary loss) arising out of or related to the use of or inability to use the software.

Copyright Notification

No part may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm except as authorized by written permission of ETSI.

The content of the PDF version shall not be modified without the written authorization of ETSI.

The copyright and the foregoing restriction extend to reproduction in all media.

© ETSI 2024.

© European Broadcasting Union 2024.

All rights reserved.

Contents

Intellectual Property Rights	8
Foreword.....	8
Modal verbs terminology.....	9
Introduction	9
1 Scope	10
2 References	10
2.1 Normative references	10
2.2 Informative references.....	11
3 Definition of terms, symbols and abbreviations.....	11
3.1 Terms.....	11
3.2 Symbols.....	11
3.3 Abbreviations	11
4 Transmission system description.....	12
4.0 General aspects.....	12
4.1 System definition.....	12
4.2 System architecture	12
4.3 System configurations	12
5 Subsystems specifications	16
5.1 Mode adaptation.....	16
5.1.0 General aspects	16
5.1.1 Input Interfaces	16
5.1.2 Input stream synchronizer (optional, not relevant for single TS - BS)	16
5.1.3 Null-Packet Deletion (ACM and Transport Stream only)	16
5.1.4 CRC-8 encoder (for packetized streams only).....	16
5.1.5 Merger/Slicer	16
5.1.6 Base-Band Header insertion	16
5.1.7 GSE High Efficiency Mode (GSE-HEM).....	17
5.1.8 Channel bonding for multi-tuner (L) receivers	18
5.1.8.1 Introduction to channel bonding	18
5.1.8.2 Channel bonding for TS transmission.....	19
5.1.8.3 Channel bonding for GSE transmission.....	20
5.1.8.3.0 General aspects.....	20
5.1.8.3.1 Channel bonding for Generic Packetized streams	22
5.1.8.3.2 Channel bonding for Generic Continuous streams	22
5.2 Stream Adaptation.....	22
5.2.0 General aspects	22
5.2.1 Padding	22
5.2.2 BB scrambling	22
5.3 FEC Encoding	22
5.3.0 General aspects	22
5.3.1 Outer encoding (BCH).....	24
5.3.2 Inner encoding (LDPC)	24
5.3.2.0 General aspects	24
5.3.2.1 Inner coding for normal FECFRAME.....	24
5.3.2.2 Inner coding for short and medium FECFRAME	25
5.3.3 Bit interleaver	25
5.4 Constellations and Bit mapping.....	26
5.4.0 General aspects	26
5.4.0a Bit mapping into $\pi/2$ BPSK constellation (VL-SNR modes and VL-SNR Header).....	27
5.4.1 Bit mapping into QPSK constellation.....	27
5.4.2 Bit mapping into 8PSK and 8APSK constellations	27
5.4.3 Bit mapping into 16APSK constellation.....	28
5.4.4 Bit mapping into 32APSK constellations	30

5.4.5	Bit mapping into 64APSK constellations	32
5.4.6	Bit mapping into 128APSK constellations	35
5.4.7	Bit mapping into 256APSK constellations	37
5.5	Physical Layer (PL) framing	43
5.5.0	General aspects	43
5.5.1	Dummy PLFRAME insertion	43
5.5.2	PL signalling	44
5.5.2.0	General aspects	44
5.5.2.1	SOF field	46
5.5.2.2	MODCOD field.....	46
5.5.2.3	TYPE field	48
5.5.2.4	PLS code, no time slicing.....	48
5.5.2.5	VL-SNR Header.....	49
5.5.2.6	Shortening and Puncturing of VL-SNR MODCODs	50
5.5.3	Pilot Insertion.....	51
5.5.4	Physical layer scrambling	51
5.5.4.0	General aspects	51
5.5.4.1	PL scrambling for VL-SNR frames	52
5.5.4.1.0	General aspects.....	52
5.5.4.1.1	$\pi/2$ -BPSK modulated frames.....	52
5.6	Baseband shaping and quadrature modulation	53
6	Error performance	53
Annex A (normative):	Signal spectrum at the modulator output.....	55
Annex B (normative):	Addresses of parity bit accumulators for $n_{ldpc} = 64\ 800$.....	57
Annex C (normative):	Addresses of parity bit accumulators for $n_{ldpc} = 16\ 200$ and $n_{ldpc} = 32\ 400$.....	103
Annex D (normative):	Additional tools	108
D.0	General aspects.....	108
D.1	Implementation of TS based channel bonding	108
D.1.1	Transmitting side.....	108
D.1.2	Receiving side (informative)	108
D.2	Void.....	108
D.3	Void.....	108
D.4	Void.....	109
D.5	Signalling of reception quality via return channel (normative for ACM).....	109
Annex E (normative):	Super-Framing Structure (optional).....	111
E.1	Purpose of Super-Framing Structure	111
E.2	Specification of Super-Frame as a Container	111
E.2.1	Super-Frame Structure	111
E.2.2	Start of Super-Frame (SOSF) Field.....	112
E.2.3	Super-Frame Format Indicator (SFFI) Field.....	112
E.2.4	Two-Way Scrambling	113
E.2.4.0	General aspects	113
E.2.4.1	Scrambling Sequence Generation	113
E.2.4.2	Two-Way Scrambling Method	114
E.3	Format Specifications as Super-Frame Content.....	115
E.3.0	General aspects.....	115
E.3.1	Super-Frame-aligned Pilots (SF-Pilots).....	116
E.3.1.0	General aspects	116
E.3.1.1	Specification of SF-Pilots Type A	117
E.3.2	Format Specification 0: DVB-S2X.....	117

E.3.2.0	General aspects	117
E.3.2.1	Pilot structure.....	118
E.3.2.2	Modified VL-SNR-frame	118
E.3.3	Format Specification 1: DVB-S2 legacy	119
E.3.4	Format Specification 2: Bundled PLFRAME (64 800 payload Size) with SF-Pilots.....	119
E.3.4.0	General aspects	119
E.3.4.1	Bundled PLFRAME (64 800 payload) Definition	120
E.3.4.2	PLHEADER Specification for Bundled PLFRAMEs (64 800 payload)	121
E.3.4.3	SF-Pilot Structure	123
E.3.5	Format Specification 3: Bundled PLFRAME (16 200 Payload Size) with SF-Pilots.....	124
E.3.5.0	General aspects	124
E.3.5.1	Bundled PLFRAME Definition	125
E.3.5.2	PLHEADER Specification for Short Bundled PLFRAME.....	126
E.3.5.3	SF-Pilot Structure	127
E.3.6	Format Specification 4: Flexible Format with VL-SNR PLH tracking.....	129
E.3.6.0	General aspects	129
E.3.6.1	Super-Frame Header (SFH)	130
E.3.6.2	SFH-Trailer (ST)	131
E.3.6.3	Physical Layer Header (PLH).....	131
E.3.6.3.0	General aspects	131
E.3.6.3.1	PLSCODE Definition.....	131
E.3.6.3.2	PLH Protection Levels	132
E.3.6.3.3	Signalling of MOD/COD/SPREAD/SIZE	133
E.3.6.3.4	Field for TSN	134
E.3.6.3.5	SOF Sequence	134
E.3.6.4	PLFRAME structure	134
E.3.6.5	Pilot structure.....	136
E.3.6.5.1	SF-Pilots.....	136
E.3.6.5.2	Special VL-SNR Pilots	136
E.3.6.6	Spreading and Signalling Rules.....	136
E.3.6.7	Dummy PL Frame Definition	137
E.3.6.7.0	General aspects	137
E.3.6.7.1	Dummy PL frames with deterministic content.....	137
E.3.6.7.2	Dummy PL frames with arbitrary content.....	138
E.3.7	Format Specification 5: Periodic Beam Hopping Format with VL-SNR and fragmentation Support..	138
E.3.7.0	General aspects	138
E.3.7.1	Super-Frame Header (SFH)	140
E.3.7.2	SFH-Trailer (ST)	141
E.3.7.3	Physical Layer Header (PLH).....	141
E.3.7.3.0	General aspects	141
E.3.7.3.1	PLSCODE Definition.....	141
E.3.7.3.2	PLH Protection Levels	141
E.3.7.3.3	Signalling of MOD/COD/SPREAD/SIZE and TYPE.....	141
E.3.7.3.4	Field for TSN	142
E.3.7.3.5	SOF Sequence	142
E.3.7.4	PLFRAME structure	142
E.3.7.5	Pilot structure.....	143
E.3.7.5.1	SF-Pilots.....	143
E.3.7.5.2	Special VL-SNR Pilots	143
E.3.7.6	Spreading and Signalling Rules	143
E.3.7.7	Dummy PL Frame Definition	143
E.3.7.8	Postamble Definition	143
E.3.8	Format Specification 6: Traffic Driven Beam Hopping Format with VL-SNR Support.....	144
E.3.8.0	General aspects	144
E.3.8.1	Super-Frame Header (SFH)	146
E.3.8.2	Physical Layer Trailer (ST)	146
E.3.8.3	Physical Layer Header (PLH).....	146
E.3.8.4	PLFRAME structure	146
E.3.8.5	Pilot structure.....	146
E.3.8.5.1	SF-Pilots.....	146
E.3.8.5.2	Special VL-SNR Pilots	146
E.3.8.6	Spreading and Signalling Rules	147

E.3.8.7	Dummy PL Frame Definition	147
E.3.8.8	Postamble Definition	147
E.3.9	Format Specification 7: Simplified Traffic Driven Beam Hopping Format without VL-SNR Support	147
E.3.9.0	General aspects	147
E.3.9.1	Superframe Header (SFH)	148
E.3.9.2	SFH-Trailer (ST)	148
E.3.9.3	Physical Layer Header (PLH)	148
E.3.9.3.0	General aspects	148
E.3.9.3.1	PLSCODE Definition	148
E.3.9.3.2	PLH Protection Levels	149
E.3.9.3.3	Signalling of MOD/COD/SPREAD/SIZE and TYPE	149
E.3.9.3.4	Field for TSN	149
E.3.9.3.5	SOF Sequence	149
E.3.9.4	PLFRAME structure	149
E.3.9.5	SF-Pilot structure	149
E.3.9.5.1	SF-Pilots	149
E.3.9.5.2	Special VL-SNR Pilots	149
E.3.9.6	Spreading and Signalling Rules	149
E.3.9.7	Dummy PL Frame Definition	149
E.3.9.8	Postamble Definition	149
E.3.10	Format Specifications 8 - 15: Reserved	149
E.4	Signalling of additional reception quality parameters via return channel (normative for Interference Management at the Gateway)	150
Annex F:	Void	152
Annex G:	Void	153
Annex H (informative):	Examples of possible use of the System	154
H.0	General aspects	154
H.1	Void	154
H.2	Void	154
H.3	Void	154
H.4	Void	154
H.5	Void	154
H.6	Void	154
H.7	Satellite transponder models for simulations	154
H.8	Phase noise masks for simulations	156
Annex I (normative):	ACM	158
I.1	ACM Command	158
I.2	Dummy Synchronization Scheme (optional)	159
I.2.0	General aspects	159
I.2.1	Dummy Synchronization Frame structure	159
I.2.1.0	General aspects	159
I.2.1.1	PLH* description	160
I.2.1.2	Known Symbols	160
I.2.1.3	Known correlation structure	160
I.2.2	Scrambling	161
Annex J:	Void	162
Annex K:	For future use	163
Annex L:	For future use	164

Annex M (normative):	Transmission format for wideband satellite transponders using time-slicing (optional).....	165
History		166

iTeh Standards
(<https://standards.iteh.ai>)
Document Preview

[ETSI EN 302 307-2 V1.4.1 \(2024-05\)](https://standards.iteh.ai/catalog/standards/etsi/587cb462-7d5c-40ff-93e3-f2188c1723de/etsi-en-302-307-2-v1-4-1-2024-05)

<https://standards.iteh.ai/catalog/standards/etsi/587cb462-7d5c-40ff-93e3-f2188c1723de/etsi-en-302-307-2-v1-4-1-2024-05>

Intellectual Property Rights

Essential patents

IPRs essential or potentially essential to normative deliverables may have been declared to ETSI. The declarations pertaining to these essential IPRs, if any, are publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: "*Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards*", which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (<https://ipr.etsi.org/>).

Pursuant to the ETSI Directives including the ETSI IPR Policy, no investigation regarding the essentiality of IPRs, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

Trademarks

The present document may include trademarks and/or tradenames which are asserted and/or registered by their owners. ETSI claims no ownership of these except for any which are indicated as being the property of ETSI, and conveys no right to use or reproduce any trademark and/or tradename. Mention of those trademarks in the present document does not constitute an endorsement by ETSI of products, services or organizations associated with those trademarks.

DECT™, **PLUGTESTS™**, **UMTS™** and the ETSI logo are trademarks of ETSI registered for the benefit of its Members. **3GPP™** and **LTE™** are trademarks of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners. **oneM2M™** logo is a trademark of ETSI registered for the benefit of its Members and of the oneM2M Partners. **GSM®** and the GSM logo are trademarks registered and owned by the GSM Association.

Foreword

This draft European Standard (EN) has been produced by Joint Technical Committee (JTC) Broadcast of the European Broadcasting Union (EBU), Comité Européen de Normalisation ELECTrotechnique (CENELEC) and the European Telecommunications Standards Institute (ETSI), and is now submitted for the combined Public Enquiry and Vote phase of the ETSI EN Approval Procedure.

NOTE: The EBU/ETSI JTC Broadcast was established in 1990 to co-ordinate the drafting of standards in the specific field of broadcasting and related fields. Since 1995 the JTC Broadcast became a tripartite body by including in the Memorandum of Understanding also CENELEC, which is responsible for the standardization of radio and television receivers. The EBU is a professional association of broadcasting organizations whose work includes the co-ordination of its members' activities in the technical, legal, programme-making and programme-exchange domains. The EBU has active members in about 60 countries in the European broadcasting area; its headquarters is in Geneva.

European Broadcasting Union
CH-1218 GRAND SACONNEX (Geneva)
Switzerland
Tel: +41 22 717 21 11
Fax: +41 22 717 24 81

The Digital Video Broadcasting Project (DVB) is an industry-led consortium of broadcasters, manufacturers, network operators, software developers, regulatory bodies, content owners and others committed to designing global standards for the delivery of digital television and data services. DVB fosters market driven solutions that meet the needs and economic circumstances of broadcast industry stakeholders and consumers. DVB standards cover all aspects of digital television from transmission through interfacing, conditional access and interactivity for digital video, audio and data. The consortium came together in 1993 to provide global standardisation, interoperability and future proof specifications.

The present document is part 2 of a multi-part deliverable covering the optional extensions of the DVB-S2 system, denoted "DVB-S2X", as identified below:

Part 1: "DVB-S2";

Part 2: "DVB-S2 Extensions (DVB-S2X)".

Proposed national transposition dates	
Date of latest announcement of this EN (doa):	3 months after ETSI publication
Date of latest publication of new National Standard or endorsement of this EN (dop/e):	6 months after doa
Date of withdrawal of any conflicting National Standard (dow):	6 months after doa

Modal verbs terminology

In the present document "shall", "shall not", "should", "should not", "may", "need not", "will", "will not", "can" and "cannot" are to be interpreted as described in clause 3.2 of the [ETSI Drafting Rules](#) (Verbal forms for the expression of provisions).

"must" and "must not" are **NOT** allowed in ETSI deliverables except when used in direct citation.

Introduction

The optional extensions of the S2 system have been approved in 2014 and are identified by the S2X denomination. Such extensions are non-backwards-compatible with ETSI EN 302 307 [4], are optional for the implementation of new receivers under ETSI EN 302 307-1 [3], but are normative for the implementation of receivers under the present document: mapping of specific S2X building blocks to application areas is specified in Table 1. For every S2X application area, as defined in Table 1, the configurations for the corresponding S2 application area, as defined in ETSI EN 302 307-1 [3], Table 1, will be implemented. In case of conflicts the definition of the S2X application area applies.

The present document targets the core application areas of S2 (Digital Video Broadcasting, forward link for interactive services using ACM, Digital Satellite News Gathering and professional digital links such as video point-to-point or Internet trunking links), and new application areas requiring very-low carrier-to-noise and carrier-to-interference operation (VL-SNR).

In particular for DTH, a possible use case is the launch of UHD TV-1 (e.g. 4k) television services in Ku-/Ka-band that will adopt HEVC encoding. In this context it may be desirable to eventually use fragments of smaller blocks of capacity on two or three DTH transponders and bond them into one logical stream. This permits to maximize capacity exploitation by avoiding the presence of spare capacity in individual transponders and/or to take maximum advantage of statistical multiplexing.

The S2X system offers the ability to operate with very-low carrier-to-noise and carrier-to-interference ratios (SNR down to -10 dB), to serve markets such as airborne (business jets), maritime, civil aviation internet access, VSAT terminals at higher frequency ranges or in tropical zones, small portable terminals for journalists and other professionals. Furthermore, the S2X system provides transmission modes offering significantly higher capacity and efficiency to serve professional links characterized by very-high carrier-to-noise and carrier-to-interference ratios conditions.

The present document reuses the S2 system architecture, while adding finer MODCOD steps, sharper roll-off filtering, technical means for bonding of multiple transponders and additional signalling capacity by means of an optional periodic super-frame structure, extended PLHEADER signalling schemes and the support of GSE-Lite signals.

The present document maintains the same clause numbering as ETSI EN 302 307-1 [3], in order to facilitate cross-reference.

1 Scope

The present document specifies the optional extensions of the S2 system, identified by the S2X denomination. The present document also includes amendments to the standard to enable beam hopping operation.

2 References

2.1 Normative references

References are either specific (identified by date of publication and/or edition number or version number) or non-specific. For specific references, only the cited version applies. For non-specific references, the latest version of the referenced document (including any amendments) applies.

Referenced documents which are not found to be publicly available in the expected location might be found at <https://docbox.etsi.org/Reference/>.

NOTE: While any hyperlinks included in this clause were valid at the time of publication, ETSI cannot guarantee their long term validity.

The following referenced documents are necessary for the application of the present document.

- [1] [ETSI TS 101 545-1 \(V1.1.1\)](#): "Digital Video Broadcasting (DVB); Second Generation DVB Interactive Satellite System (DVB-RCS2); Part 1: Overview and System Level specification".
- [2] [ETSI TS 102 606-1 \(V1.2.1\)](#): "Digital Video Broadcasting (DVB); Generic Stream Encapsulation (GSE); Part 1: Protocol".
- [3] [ETSI EN 302 307-1](#): "Digital Video Broadcasting (DVB); Second generation framing structure, channel coding and modulation systems for Broadcasting, Interactive Services, News Gathering and other broadband satellite applications; Part 1: DVB-S2".
- [4] [ETSI EN 302 307 \(V1.1.1\)](#): "Digital Video Broadcasting (DVB); Second generation framing structure, channel coding and modulation systems for Broadcasting, Interactive Services, News Gathering and other broadband satellite applications".
- [5] [ETSI EN 300 468](#): "Digital Video Broadcasting (DVB); Specification for Service Information (SI) in DVB systems".
- [6] [ETSI TS 102 606-2](#): "Digital Video Broadcasting (DVB); Generic Stream Encapsulation (GSE); Part 2: Logical Link Control (LLC)".
- [7] [ETSI ETS 300 801](#): "Digital Video Broadcasting (DVB); Interaction channel through Public Switched Telecommunications Network (PSTN)/Integrated Services Digital Networks (ISDN)".
- [8] [ETSI EN 301 195](#): "Digital Video Broadcasting (DVB); Interaction channel through the Global System for Mobile communications (GSM)".
- [9] [ETSI ES 200 800](#): "Digital Video Broadcasting (DVB); DVB interaction channel for Cable TV distribution systems (CATV)".
- [10] [ETSI ETS 300 802](#): "Digital Video Broadcasting (DVB); Network-independent protocols for DVB interactive services".
- [11] [ETSI EN 301 790](#): "Digital Video Broadcasting (DVB); Interaction channel for satellite distribution systems".

2.2 Informative references

References are either specific (identified by date of publication and/or edition number or version number) or non-specific. For specific references, only the cited version applies. For non-specific references, the latest version of the referenced document (including any amendments) applies.

NOTE: While any hyperlinks included in this clause were valid at the time of publication, ETSI cannot guarantee their long term validity.

The following referenced documents are not necessary for the application of the present document but they assist the user with regard to a particular subject area.

Not applicable.

3 Definition of terms, symbols and abbreviations

3.1 Terms

Void.

3.2 Symbols

For the purposes of the present document, the symbols given in ETSI EN 302 307-1 [3] and the following apply:

d_{SF}	SF-pilot distances
P_{SF}	SF-pilot field length
H_{ST}	SFH-Trailer (ST) Matrix
H_{SOSF}	Start Of SuperFrame Matrix
R_S	Symbol rate corresponding to the bilateral Nyquist bandwidth of the modulated signal

3.3 Abbreviations

For the purposes of the present document, the abbreviations given in ETSI EN 302 307-1 [3] and the following apply:

128APSK	128-ary Amplitude and Phase Shift Keying
256APSK	256-ary Amplitude and Phase Shift Keying
64APSK	64-ary Amplitude and Phase Shift Keying
BBF	Base Band Frame
BH	Beam Hopping
BHTC	Beam Hopping Transmission Channel
BHTP	Beam Hopping Time Plan
BPSK	Binary Phase Shift Keying
CNTR	Counter
CU	Capacity Unit
DT	Dwell Time
EHF	Extended Header Field
EXOR	Exclusive-OR (logical operator/function)
FER	Frame Error Rate
GSE	Generic Stream Encapsulation
GSE-HEM	Generic Stream Encapsulation - High Efficiency Mode
GSE-LLC	Generic Stream Encapsulation - Logical Link Control
HEVC	High Efficiency Video Coding
PLH	Physical Layer Header
PLI	Protection Level Indication
RFU	Reserved for Future Use
SF	Super-Frame

SFFI	Super-Frame Format Indicator
SFH	Super-Frame Header
SFL	Super Frame Length
SOSF	Start Of Super-Frame
ST	Super-Frame Header Trailer
UHDTV	Ultra High Definition TeleVision
VL-SNR	Very Low - Signal to Noise Ratio
VSAT	Very Small Aperture Terminal
WH	Walsh-Hadamard

4 Transmission system description

4.0 General aspects

See ETSI EN 302 307-1 [3], clause 4.

4.1 System definition

See ETSI EN 302 307-1 [3], clause 4.1.

4.2 System architecture

See ETSI EN 302 307-1 [3], clause 4.2.

The present document reuses the S2 system architecture as described in ETSI EN 302 307-1 [3], Figure 1, while adding finer MODCOD steps, sharper roll-off filtering, technical means allowing time-slicing of wide-band signals (for a reduced processing speed in the receiver), technical means for bonding of multiple transponders, among other technologies.

Additional signalling capacity is provided:

- an optional periodic super-frame structure with signalling of the format of the super-frame content and further benefits like simplifying synch recovery at VL-SNR and allowing periodic pilot structures and PL-Scramblers;
- an extended PLHEADER signalling scheme to support the additional MODCODs;
- an extended PLHEADER signalling scheme to support Mobile Frames (VL-SNR);
- a high-efficiency BBFRAME mode (GSE-HEM), similar to the T2 and C2 systems, to transport GSE/GSE-Lite packets;
- signalling of streams which are GSE-Lite compliant.

Annex E includes optional additional formats to enable operation of beam -hopping. The specified waveforms provide additional signalling and framing options that support both periodic, pre-scheduled beam hopping operation, as well as random, traffic driven illumination policy, at signal to noise ratios ranging from -10 dB and above.

4.3 System configurations

See ETSI EN 302 307-1 [3], clause 4.3.

Table 1 associates the S2X system elements to the applications areas. All elements in Table 1 are optional in transmitting and receiving equipment complying with the S2 specification. At least "Normative" subsystems and functionalities shall be implemented in the transmitting and receiving equipment to comply with the present document for a specific application area.

Table 1: S2X System configurations and application areas

System configurations		Broadcast services	Interactive services	DSNG	Professional services	VL-SNR
FECFRAME (normal) (see MODCODs below)	64 800 (bits)					
QPSK	1/4, 1/3, 2/5 (S2-MODCODs)	N	N	N	N	N
	1/2, 3/5, 2/3, 3/4, 4/5, 5/6, 8/9, 9/10 (S2-MODCODs)	N	N	N	N	N
	13/45	N	N	N	N	N
	9/20; 11/20	N	N	N	N	N
8PSK	3/5, 2/3, 3/4, 5/6, 8/9, 9/10 (S2-MODCODs)	N	N	N	N	N
	23/36; 25/36; 13/18	N	N	N	N	N
8APSK-L (note 7)	5/9; 26/45	N	N	N	N	N
16APSK	2/3, 3/4, 4/5, 5/6, 8/9, 9/10 (S2-MODCODs)	N	N	N	N	N
	26/45; 3/5; 28/45; 23/36; 25/36; 13/18; 7/9; 77/90	N	N	N	N	N
16APSK-L (note 7)	5/9; 8/15; 1/2; 3/5; 2/3	N	N	N	N	N
32APSK	3/4, 4/5, 5/6, 8/9, 9/10 (S2-MODCODs)	N	N	N	N	N
	32/45; 11/15; 7/9	N	N	N	N	N
32APSK-L (note 7)	2/3	N	N	N	N	N
64APSK	11/15; 7/9; 4/5; 5/6	O	N	N	N	O
64APSK-L (note 7)	32/45	O	N	N	N	O
128APSK	3/4; 7/9	NA	O	O	N	NA
256APSK	32/45; 3/4	NA	O	O	N	NA
256APSK-L (note 7)	29/45; 2/3; 31/45; 11/15	NA	O	O	N	NA
FECFRAME (short) (see MODCODs below)	16 200 (bits)					
QPSK	1/4, 1/3, 2/5 (S2-MODCODs)	NA	N	O	N	N
	1/2, 3/5, 2/3, 3/4, 4/5, 5/6, 8/9 (S2-MODCODs)	NA	N	O	N	N
	11/45; 4/15; 14/45; 7/15 8/15; 32/45	NA	N	O	N	N
8PSK	3/5, 2/3, 3/4, 5/6, 8/9 (S2-MODCODs)	NA	N	O	N	N
	7/15; 8/15; 26/45; 32/45	NA	N	O	N	N
16APSK	2/3, 3/4, 4/5, 5/6, 8/9 (S2-MODCODs)	NA	N	O	N	N
	7/15; 8/15; 26/45; 3/5; 32/45	NA	N	O	N	N

System configurations		Broadcast services	Interactive services	DSNG	Professional services	VL-SNR
32APSK	3/4, 4/5, 5/6, 8/9 (S2-MODCODs)	NA	N	O	N	N
	2/3; 32/45	NA	N	O	N	N
VL-SNR Header (see MODCODs below) (note 1)		O	O	O	NA	N
QPSK	2/9 (normal)	NA	O	O	NA	N
BPSK	1/5; 4/15; 1/3 (short) 1/5; 11/45; 1/3 (medium)	NA	O	O	NA	N
BPSK-S Spreading Factor 2	1/5; 11/45 (short)	NA	O	O	NA	N
Fixed Size Super-frame (notes 8 and 11)		NA	O	O	O	O/NA (note 9)
Part 2 PLHEADER (note 5)	8-bits	N	N	N	N	N
Extended PLHEADER For Wide-band mode (note 5)	8+8 bits (time slicing)	O	O	NA	O	O
GSE-High Efficiency Mode	For GSE/GSE-Lite (note 6)	N	N	N	N	N
Roll-off 0,15; 0,10 and 0,05		N	N	N	N	N
Channel bonding (note 2)		N (note 3)	NA	NA	O	NA
VCM (note 4)		N	N	N	N	N
ACM		NA	N	O	O	N
Beam Hopping Periodic BH, VLSNR (note 8) (Superframe Format 5) (note 10)		O	O	O	O	O
Traffic driven BH VLSNR (note 8) (Superframe Format 6)		O	O	O	O	O