
**Optics and photonics — Lasers
and laser-related equipment —
Vocabulary and symbols**

*Optique et photonique — Lasers et équipements associés aux lasers
— Vocabulaire et symboles*

iTeh Standards
(<https://standards.iteh.ai>)
Document Preview

[ISO 11145:2018](#)

<https://standards.iteh.ai/catalog/standards/iso/1994e714-8a34-4449-b4bb-dcfd7c3ce292/iso-11145-2018>



iTeh Standards
(<https://standards.iteh.ai>)
Document Preview

[ISO 11145:2018](https://standards.iteh.ai/catalog/standards/iso/1994e714-8a34-4449-b4bb-dcfd7c3ce292/iso-11145-2018)

<https://standards.iteh.ai/catalog/standards/iso/1994e714-8a34-4449-b4bb-dcfd7c3ce292/iso-11145-2018>



COPYRIGHT PROTECTED DOCUMENT

© ISO 2018

All rights reserved. Unless otherwise specified, or required in the context of its implementation, no part of this publication may be reproduced or utilized otherwise in any form or by any means, electronic or mechanical, including photocopying, or posting on the internet or an intranet, without prior written permission. Permission can be requested from either ISO at the address below or ISO's member body in the country of the requester.

ISO copyright office
CP 401 • Ch. de Blandonnet 8
CH-1214 Vernier, Geneva
Phone: +41 22 749 01 11
Fax: +41 22 749 09 47
Email: copyright@iso.org
Website: www.iso.org

Published in Switzerland

Contents

Page

Foreword	iv
1 Scope	1
2 Normative references	1
3 Terms and definitions	1
3.1 Beam position.....	2
3.2 Beam axis.....	2
3.3 Beam diameter.....	3
3.4 Beam radius.....	3
3.5 Beam width.....	4
3.6 Beam cross-sectional area.....	4
3.7 Beam waist.....	5
3.8 Divergence.....	7
3.9 Rayleigh length.....	7
3.10 Beam parameter product.....	8
3.11 Coherence.....	8
3.12 Polarization.....	9
3.13 Power and Energy.....	10
3.14 Pulse duration and repetition rate.....	11
3.15 Optical resonator.....	12
3.16 Mode.....	12
3.17 Spectral bandwidth.....	12
3.18 Relative intensity noise.....	13
3.19 Laser.....	13
3.20 Efficiency.....	14
4 Symbols and units of measurement	15
Annex A (informative) Explanation of the difference in terminology between IEC 60825-1 and ISO 11145	17
Annex B (informative) List of symbols	18
Bibliography	19
Alphabetical index	20

Foreword

ISO (the International Organization for Standardization) is a worldwide federation of national standards bodies (ISO member bodies). The work of preparing International Standards is normally carried out through ISO technical committees. Each member body interested in a subject for which a technical committee has been established has the right to be represented on that committee. International organizations, governmental and non-governmental, in liaison with ISO, also take part in the work. ISO collaborates closely with the International Electrotechnical Commission (IEC) on all matters of electrotechnical standardization.

The procedures used to develop this document and those intended for its further maintenance are described in the ISO/IEC Directives, Part 1. In particular, the different approval criteria needed for the different types of ISO documents should be noted. This document was drafted in accordance with the editorial rules of the ISO/IEC Directives, Part 2 (see www.iso.org/directives).

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. ISO shall not be held responsible for identifying any or all such patent rights. Details of any patent rights identified during the development of the document will be in the Introduction and/or on the ISO list of patent declarations received (see www.iso.org/patents).

Any trade name used in this document is information given for the convenience of users and does not constitute an endorsement.

For an explanation of the voluntary nature of standards, the meaning of ISO specific terms and expressions related to conformity assessment, as well as information about ISO's adherence to the World Trade Organization (WTO) principles in the Technical Barriers to Trade (TBT) see www.iso.org/iso/foreword.html.

This document was prepared by Technical Committee ISO/TC 172, *Optics and photonics*, Subcommittee SC 9, *Laser and electro-optical systems*.

This fifth edition cancels and replaces the fourth edition ISO 11145:2016, which has been technically revised. The main changes compared to the previous edition are as follows:

- a) the term beam position has been renamed “beam centroid” and defined formally as a first-order moment;
- b) the term beam ellipticity has been clarified;
- c) the term beam waist location has been included;
- d) the term optical resonator has been included;
- e) the term 10 % pulse duration has been generalized to a selected percentage pulse duration;
- f) the formula in the term beam diameter has been adjusted;
- g) the order of the terms has been adjusted.

Any feedback or questions on this document should be directed to the user's national standards body. A complete listing of these bodies can be found at www.iso.org/members.html.

Optics and photonics — Lasers and laser-related equipment — Vocabulary and symbols

1 Scope

This document defines basic terms, symbols, and units of measurement for the field of laser technology in order to unify the terminology and to arrive at clear definitions and reproducible tests of beam parameters and laser-oriented product properties.

NOTE The laser hierarchical vocabulary laid down in this document differs from that given in IEC 60825-1. ISO and IEC have discussed this difference and agree that it reflects the different purposes for which the two standards serve. For more details, see informative [Annex A](#).

2 Normative references

There are no normative references in this document.

3 Terms and definitions

For the purposes of this document, the following terms and definitions apply.

ISO and IEC maintain terminological databases for use in standardization at the following addresses:

- ISO Online browsing platform: available at <http://www.iso.org/obp>
- IEC Electropedia: available at <http://www.electropedia.org/>

NOTE 1 The spatial distribution of the power (energy) density in a cross section of a laser beam does not always have circular symmetry. In this document, all terms related to these spatial distributions are split into those for beam cross sections with circular distributions and those for beam cross sections with non-circular distributions. A circular beam is characterized by its radius, w , or diameter, d . For a non-circular beam, the beam widths, d_x and d_y , for two orthogonal directions are given.

NOTE 2 The spatial distributions of laser beams do not have sharp edges. Therefore, the power (energy) values to which the spatial terms refer are defined. Depending on the application, different cut-off values can be chosen (for example $1/e$, $1/e^2$, $1/10$ of the peak value).

NOTE 3 This document uses the subscript u to denote a percentage. For example, the percentage of the total beam power (energy) included in the value of a given parameter. When stating quantities marked by an index “ u ”, “ u ” is replaced by the specific number, e.g. A_{90} for $u = 90\%$.

NOTE 4 The beam width $d_{x,u}$ (see [3.5.1](#)) and the beam diameter d_u (see [3.3.1](#)) can differ for the same value of u ($d_{x,u} \neq d_u$).

NOTE 5 In contrast to quantities defined by setting a cut-off value [“encircled power (energy)”], the beam widths and derived beam properties can also be defined based on the second moments of the power (energy) density distribution function (see [3.5.2](#)). Only beam propagation ratios (see [3.10.2](#)) that are calculated from beam widths and divergence angles derived from the second moments of the power (energy) density distribution function allow calculation of beam propagation. In this document, quantities based on the second moment are marked by a subscript “ σ ”.

NOTE 6 A list of symbols is given in [Annex B](#).

3.1 Beam position

3.1.1

beam centroid

$$\bar{x}(z), \bar{y}(z)$$

coordinates of the first-order moments of a power (energy) distribution of a beam at location z

$$\bar{x}(z) = \frac{\iint x \cdot E(x, y, z) \cdot dx dy}{\iint E(x, y, z) \cdot dx dy}$$

$$\bar{y}(z) = \frac{\iint y \cdot E(x, y, z) \cdot dx dy}{\iint E(x, y, z) \cdot dx dy}$$

where the integration shall be performed over an area such that at least 99 % of the beam power (energy) is captured

Note 1 to entry: The power density E is replaced by the energy density H for pulsed lasers.

Note 2 to entry: The terms beam centroid, centre of gravity and beam position are equivalent, formerly the term beam position was used.

Note 3 to entry: These quantities are defined in the beam axis system x, y, z , in which z is the direction of propagation of the beam.

3.1.2

beam positional stability

$$\Delta_x(z'), \Delta_y(z')$$

four times the standard deviation of the measured beam positional movement at plane z'

$$\Delta_x(z') = 4 \sqrt{\frac{\sum_{i=1}^N [\bar{x}(z')_i - \overline{\bar{x}(z')}]^2}{N-1}}$$

$$\Delta_y(z') = 4 \sqrt{\frac{\sum_{i=1}^N [\bar{y}(z')_i - \overline{\bar{y}(z')}]^2}{N-1}}$$

where $\bar{x}(z')$ and $\bar{y}(z')$ are the beam centroids in the z' plane, $\overline{\bar{x}(z')}$ and $\overline{\bar{y}(z')}$ are the mean beam centroids in the z' plane, and N is the number of measurements

Note 1 to entry: The term "beam angular stability", sometimes referred to as "beam pointing stability", is defined in ISO 11670:2003.

[SOURCE: ISO 11670:2003, 3.6, modified — The NOTE has been deleted, the text after "at plane z' " has been added and Note 1 to entry has been added.]

3.2 Beam axis

3.2.1

beam axis

straight line connecting the centroids defined by the first spatial moments of the cross-sectional power (energy) density distribution function at successive locations in the direction of propagation (z) of the beam in a homogeneous medium

3.2.2**misalignment angle** $\Delta\theta$

deviation angle of the beam axis from the mechanical axis defined by the manufacturer

3.3 Beam diameter**3.3.1****beam diameter** $d_u(z)$

<encircled power (energy)> diameter of a circular aperture in a plane perpendicular to the beam axis that contains u % of the total beam power (energy)

Note 1 to entry: For clarity, the term “beam diameter” is always used in combination with the symbol and its appropriate subscript: d_u or d_σ .

3.3.2**beam diameter** $d_\sigma(z)$

<second moment of power (energy) density distribution function> diameter defined by using the second moment of the power (energy) density distribution function

$$d_\sigma(z) = 2\sqrt{2}\sigma(z)$$

where the second moment of the power density distribution function $E(x, y, z)$ of the beam z is given by

$$\sigma^2(z) = \frac{\iint \left((x - \bar{x}(z))^2 + (y - \bar{y}(z))^2 \right) \cdot E(x, y, z) \cdot dx dy}{\iint E(x, y, z) \cdot dx dy}$$

where the first moments give the coordinates of the beam centroid $[\bar{x}(z), \bar{y}(z)]$

Note 1 to entry: For clarity, the term “beam diameter” is always used in combination with the symbol and its appropriate subscript: d_u or d_σ .

3.4 Beam radius**3.4.1****beam radius** $w_u(z)$

<encircled power (energy)> radius of a circular aperture in a plane perpendicular to the beam axis which contains u % of the total beam power (energy)

Note 1 to entry: For clarity, the term “beam radius” is always used in combination with the symbol and its appropriate subscript: w_u or w_σ .

Note 2 to entry: The beam radius is half the beam diameter $d_u(z)$.

3.4.2**beam radius** $w_\sigma(z)$

<second moment of power (energy) density distribution function> radius defined by using the second moment of the power (energy) density distribution function

$$w_\sigma(z) = \sqrt{2}\sigma(z)$$

Note 1 to entry: For a definition of the second moment $\sigma^2(z)$, see [3.3.2](#).

Note 2 to entry: For clarity, the term “beam radius” is always used in combination with the symbol and its appropriate subscript: w_u or w_σ .

Note 3 to entry: The beam radius is half the beam diameter $d_\sigma(z)$.

3.5 Beam width

3.5.1

beam width

$d_{x,u}(z), d_{y,u}(z)$

<slit transmitted power (energy)> width of the smallest slit aligned with the x or y transverse axes of the power (energy) density distribution function, transmitting u % of the total beam power (energy) along x or y

Note 1 to entry: For circular Gaussian beams, $d_{x,95,4}$ and $d_{y,95,4}$ both equal $d_{86,5}$.

Note 2 to entry: For clarity, the term “beam width” is always used in combination with the symbol and its appropriate subscripts: $d_{\sigma x}, d_{\sigma y}$ or $d_{x,u}, d_{y,u}$.

3.5.2

beam width

$d_{\sigma x}(z), d_{\sigma y}(z)$

<second moment of power (energy) density distribution function> width defined by using the second moment of the power (energy) density distribution function along x or y

$$d_{\sigma x}(z) = 4\sigma_x(z)$$

$$d_{\sigma y}(z) = 4\sigma_y(z)$$

where the second moments of the power density distribution function $E(x, y, z)$ of the beam at z are given by:

$$\sigma_x^2(z) = \frac{\iint (x - \bar{x}(z))^2 \cdot E(x, y, z) \cdot dx dy}{\iint E(x, y, z) \cdot dx dy}$$

$$\sigma_y^2(z) = \frac{\iint (y - \bar{y}(z))^2 \cdot E(x, y, z) \cdot dx dy}{\iint E(x, y, z) \cdot dx dy}$$

where $(x - \bar{x}(z))$ and $(y - \bar{y}(z))$ are the distances from the current point's coordinates to the beam centroid $(\bar{x}(z), \bar{y}(z))$

Note 1 to entry: For clarity, the term “beam width” is always used in combination with the symbol and its appropriate subscripts: $d_{\sigma x}, d_{\sigma y}$ or $d_{x,u}, d_{y,u}$.

3.6 Beam cross-sectional area

3.6.1

beam cross-sectional area

$A_u(z)$

<encircled power (energy)> smallest completely filled area containing u % of the total beam power (energy)

Note 1 to entry: For clarity, the term “beam cross-sectional area” is always used in combination with the symbol and its appropriate subscript: A_u or A_σ .

3.6.2**beam cross-sectional area** $A_{\sigma}(z)$

<second moment of power (energy) density distribution function> area of a beam with circular cross-section

$$A_{\sigma} = \left(\frac{\pi}{4} \right) \cdot d_{\sigma}(z)^2$$

or elliptical cross-section

$$A_{\sigma} = \left(\frac{\pi}{4} \right) \cdot d_{\sigma x}(z) \cdot d_{\sigma y}(z)$$

Note 1 to entry: For clarity, the term “beam cross-sectional area” is always used in combination with the symbol and its appropriate subscript: A_u or A_{σ} .

3.6.3**beam ellipticity** $\varepsilon(z)$

parameter for quantifying the circularity or squareness of a power (energy) density distribution at z

$$\varepsilon(z) = \frac{d_{\sigma y}(z)}{d_{\sigma x}(z)}$$

where the direction of x is chosen to be along the major axis of the distribution, such that $d_{\sigma x} \geq d_{\sigma y}$

Note 1 to entry: If $\varepsilon \geq 0,87$, elliptical distributions can be regarded as circular.

Note 2 to entry: In case of a rectangular distribution, ellipticity is often referred to as “aspect ratio”.

Note 3 to entry: In contrast to the definition given here, in literature the term “ellipticity” is sometimes related to $1 - \frac{d_{\sigma y}(z)}{d_{\sigma x}(z)}$. The definition given here has been chosen to be in concordance with the same definition of ellipticity in ISO 11146-1 and ISO 13694.

3.6.4**circular power density distribution**

power density distribution having an ellipticity greater than or equal to 0,87

3.7 Beam waist**3.7.1****beam waist**

portion of a beam where the beam diameter or beam width has a local minimum

3.7.2**beam waist location** z_{0x}, z_{0y}, z_0

location where the beam widths or the beam diameters reach their minimum values along the beam axis

Note 1 to entry: A particular beam can have multiple beam waist locations.

3.7.3

astigmatic beam waist separation

Δz_a

axial distance between the beam waist locations in the orthogonal principal planes of a beam possessing simple astigmatism

Note 1 to entry: Astigmatic beam waist separation is also known as “astigmatic difference”.

[SOURCE: ISO 15367-1:2003, 3.3.4, modified — In the term, “beam” has been added.]

3.7.4

beam waist diameter

$d_{0,u}$

<encircled power (energy)> diameter d_u of the beam at the location of the beam waist

Note 1 to entry: For clarity, the term “beam waist diameter” is always used in combination with the symbol and its appropriate subscripts: $d_{0,u}$ or $d_{\sigma 0}$.

3.7.5

beam waist diameter

$d_{\sigma 0}$

<second moment of power (energy) density distribution function> diameter d_{σ} of the beam at the location of the beam waist

Note 1 to entry: For clarity, the term “beam waist diameter” is always used in combination with the symbol and its appropriate subscripts: $d_{0,u}$ or $d_{\sigma 0}$.

3.7.6

beam waist radius

$w_{0,u}$

<encircled power (energy)> radius w_u of the beam at the location of the beam waist, which is half the beam waist diameter $d_{0,u}$

Note 1 to entry: For clarity, the term “beam waist radius” is always used in combination with the symbol and its appropriate subscripts: $w_{0,u}$ or $w_{\sigma 0}$.

3.7.7

beam waist radius

$w_{\sigma,0}$

<second moment of power (energy) density distribution function> radius w_{σ} of the beam at the location of the beam waist, which is half the beam waist diameter $d_{\sigma 0}$

Note 1 to entry: For clarity, the term “beam waist radius” is always used in combination with the symbol and its appropriate subscripts: $w_{0,u}$ or $w_{\sigma 0}$.

3.7.8

beam waist width

$d_{x0,u}, d_{y0,u}$

<slit transmitted power (energy)> beam width $d_{x,u}$ or $d_{y,u}$ at the location of the beam waist in the x or y direction, respectively

Note 1 to entry: For clarity, the term “beam waist width” is always used in combination with the symbol and its appropriate subscripts: $d_{x0,u}, d_{y0,u}$ or $d_{\sigma x0}, d_{\sigma y0}$.

3.7.9

beam waist width

$d_{\sigma x0}, d_{\sigma y0}$

<second moment of power (energy) density distribution function> beam width $d_{\sigma x}$ or $d_{\sigma y}$ at the location of the beam waist in the x or y direction, respectively

Note 1 to entry: For clarity, the term “beam waist width” is always used in combination with the symbol and its appropriate subscripts: $d_{x0,u}, d_{y0,u}$ or $d_{\sigma x0}, d_{\sigma y0}$.