



SLOVENSKI STANDARD
SIST I-ETS 300 230 E1:2003
01-december-2003

**Radijska oprema in sistemi (RES) – Storitve kopenskih mobilnih komunikacij –
Izmenjava binarnih podatkov in signalizacija (BIIS) s hitrostjo 1200 bit/s (BIIS 1
200)**

Radio Equipment and Systems (RES); Land mobile service; Binary Interchange of
Information and Signalling (BIIS) at 1 200 bit/s (BIIS 1 200)

iTeh STANDARD PREVIEW
(standards.iteh.ai)

[SIST I-ETS 300 230 E1:2003](https://standards.iteh.ai/catalog/standards/sist/402af814-b9eb-4888-8b46-258c51b2c63a/sist-i-ets-300-230-e1-2003)

Ta slovenski standard je istoveten z: [I-ETS 300 230 Edition 1](https://standards.iteh.ai/catalog/standards/sist/402af814-b9eb-4888-8b46-258c51b2c63a/sist-i-ets-300-230-e1-2003)

ICS:

33.060.20	Sprejemna in oddajna oprema	Receiving and transmitting equipment
33.070.01	Mobilni servisi na splošno	Mobile services in general

SIST I-ETS 300 230 E1:2003

en

iTeh STANDARD PREVIEW
(standards.iteh.ai)

[SIST I-ETS 300 230 E1:2003](https://standards.iteh.ai/catalog/standards/sist/402af814-b9eb-4888-8b46-238c51b2c83a/sist-i-ets-300-230-e1-2003)

<https://standards.iteh.ai/catalog/standards/sist/402af814-b9eb-4888-8b46-238c51b2c83a/sist-i-ets-300-230-e1-2003>



I
E
T
S

**INTERIM
EUROPEAN
TELECOMMUNICATION
STANDARD**

I-ETS 300 230

October 1993

Source: ETSI TC-RES

Reference: DI/RES-2-08

ICS: 33.060.20, 33.060.30

Key words: Land mobile service, BISS

Radio Equipment and Systems (RES);
Land mobile service
Binary Interchange of Information and Signalling (BIIS)
at 1 200 bit/s
(BIIS 1 200)

SIST I-ETS 300 230 E1:2003
<https://standards.iteh.ai/catalog/standards/sist/402af814-b9eb-4888-8b46-238c51b2c83a/etsi-i-ets-300-230-e1-2003>

ETSI

European Telecommunications Standards Institute

ETSI Secretariat

Postal address: F-06921 Sophia Antipolis CEDEX - FRANCE

Office address: 650 Route des Lucioles - Sophia Antipolis - Valbonne - FRANCE

X.400: c=fr, a=atlas, p=etsi, s=secretariat - **Internet:** secretariat@etsi.fr

Tel.: +33 92 94 42 00 - Fax: +33 93 65 47 16

Copyright Notification: No part may be reproduced except as authorized by written permission. The copyright and the foregoing restriction extend to reproduction in all media.

© European Telecommunications Standards Institute 1993. All rights reserved.

iTeh STANDARD PREVIEW (standards.iteh.ai)

SIST I-ETS 300 230 E1:2003

<https://standards.iteh.ai/catalog/standards/sist/402af814-b9eb-4888-8b46-238c51b2c83a/sist-i-ets-300-230-e1-2003>

Contents

Foreword	9
1 Scope	11
2 Normative references	11
3 Definitions, symbols and abbreviations	12
3.1 Definitions	12
3.2 Symbols	13
3.3 Abbreviations	14
4 System architecture	15
4.1 General network configuration	15
4.2 Addressing	15
4.3 Usage of repeaters	16
5 Basic system definitions	16
5.1 Modulation method	16
5.1.1 Subcarrier modulation	16
5.1.2 Frequency deviation	16
5.2 Transmission format	17
5.3 Link establishment time	17
5.4 Bit synchronisation	17
5.5 Block synchronisation	17
5.5.1 Normal block synchronisation	17
5.5.2 Optional bit and block synchronisation	18
5.6 Codewords	18
5.6.1 Redundancy	18
5.6.2 Optional data protection for error correction	19
5.7 Hang-over bit	20
5.8 Signalling cycle	20
6 Services and facilities	21
6.1 Selective calls	21
6.1.1 Individual call	21
6.1.2 Group call	21
6.1.3 Broadcast call	22
6.2 Call priority levels	22
6.2.1 Normal call	22
6.2.2 Priority call	22
6.2.3 Emergency call	22
6.3 Call management	22
6.3.1 Acknowledgements	22
6.3.1.1 Automatic acknowledgement	22
6.3.1.2 Emergency acknowledgement	22
6.3.1.3 Informative acknowledgements	22
6.3.1.4 Invalid call acknowledgement	22
6.3.2 Manual response	23
6.3.3 Call cancellation	23
6.3.4 Emergency reset	23
6.3.5 Repeater access	23
6.4 Telephone access	23
6.4.1 PABX access	23
6.4.2 PSTN access	23

6.5	Special functions	23
6.5.1	Request to call back	23
6.5.2	Channel control	23
6.5.3	Mobile enable/disable	23
6.5.4	Status transmission	24
6.5.5	Data transmission.....	24
6.5.6	System control	24
6.6	Identification	24
7	Codeword and block definition	24
7.1	Address block.....	24
7.1.1	General	24
7.1.2	Concatenated codewords	25
7.1.3	Normal address mode.....	25
7.1.4	External address mode	25
7.2	Operating mode characteristic.....	26
7.2.1	Category definitions.....	26
7.2.2	System functions	26
7.2.2.1	Emergency reset	27
7.2.2.2	Cancel	27
7.2.2.3	Clear down.....	27
7.2.2.4	Maintenance Identification	27
7.2.2.5	Transmitter key on.....	27
7.2.2.6	Transmitter key off.....	27
7.2.2.7	Repeater on.....	27
7.2.2.8	Repeater off.....	27
7.2.3	Call messages	27
7.2.3.1	Emergency radio call.....	28
7.2.3.2	Priority radio call.....	28
7.2.3.3	Normal radio call.....	28
7.2.3.4	Telephone call	28
7.2.3.5	Broadcast radio call.....	29
7.2.3.6	Request to call back	29
7.2.3.7	Manual response	29
7.2.3.8	External addressing	29
7.2.4	Acknowledgements.....	29
7.2.4.1	Emergency acknowledgement	30
7.2.4.2	Repeat acknowledgement	30
7.2.4.3	General acknowledgement	30
7.2.4.4	Absent/unavailable acknowledgement.....	30
7.2.4.5	Busy acknowledgement.....	30
7.2.4.6	Call back acknowledgement	30
7.2.4.7	Intermediate acknowledgement.....	30
7.2.4.8	Reject acknowledgement.....	30
7.2.5	Special functions	30
7.2.5.1	System control	31
7.2.5.2	Short data transfer.....	31
7.2.5.3	Dialogue data transfer.....	32
7.2.5.4	Change channel	32
7.2.5.5	Vote now	32
7.2.5.6	Status request.....	32
7.2.5.7	Mobile enable.....	32
7.2.5.8	Mobile disable	32
7.2.6	Status transfer	32
7.2.7	Reserved category	32
7.2.8	Custom functions.....	32
8	Message procedures.....	33
8.1	Normal or priority radio call procedure	33
8.2	Broadcast call procedure	34

8.3	Emergency call procedure	34
8.4	Manual response procedure.....	35
8.5	Call cancellation procedure	35
8.6	Repeater access procedure.....	36
8.7	Telephone call procedure.....	36
8.8	Call back request procedure	37
8.9	Change channel procedure.....	37
8.10	Mobile enable and mobile disable procedure	37
8.11	Status transfer procedure	38
8.12	Short data transfer procedure	38
9	Channel access protocol and occupation rules.....	39
9.1	Channel access.....	39
9.2	Retry procedure.....	40
9.3	Reversion time	40
10	Data protocol.....	40
10.1	Dialogue protocol services and facilities	41
10.1.1	Acknowledged point-to-point information transfer.....	41
10.1.2	Acknowledged broadcast information transfer	41
10.1.3	Unacknowledged information transfer.....	41
10.2	Data transmission structure.....	41
10.3	Elements of the control block	42
10.3.1	Data terminal sub-address, ADR	42
10.3.2	Command/Response bit, C/R	43
10.3.3	Control field, CONT	43
10.3.3.1	Sequence numbers, N(R), and N(S)	43
10.3.3.2	Poll and final bit, P/F	44
10.3.3.3	Supervisory and modifier function bits, S and M	44
10.3.4	PARAMETER field	44
10.4	I-frames	44
10.5	S-frames	45
10.5.1	Receive Ready (RR) command/response	45
10.5.2	Receive Not Ready (RNR) command/response.....	46
10.5.3	Reject (REJ) command/response	46
10.5.4	Selective reject (SREJ) command/response	46
10.6	U-frames	47
10.6.1	Set Asynchronous Balanced Mode (SABM) command.....	47
10.6.2	Disconnect (DISC) command	47
10.6.3	Un-numbered Acknowledgement (UA) response	48
10.6.4	Frame reject (FRMR) response.....	48
10.6.5	Disconnected Mode (DM) response.....	49
10.6.6	Un-numbered Information (UI) command	49
10.6.7	Set Group Mode (SGM) command	49
10.7	Data compression	50
11	Definition of the data transfer protocol	51
11.1	Data link set-up phase.....	51
11.1.1	Point-to-point link set-up	51
11.1.2	Group link set-up.....	51
11.2	Data transfer phase	52
11.2.1	Transmission of I-frames	52
11.2.1.1	Transmission of I-frames on a point-to-point connection.....	52
11.2.1.2	Transmission of I-frames on a group connection.....	52
11.2.2	Reception confirmation	52
11.2.2.1	Point-to-point reception confirmation	52
11.2.2.2	Group reception confirmation.....	53
11.2.3	Checkpointing	53
11.2.4	Recovery by time control	53
11.2.4.1	Point-to-point time control.....	53

	11.2.4.2	Group time control	53
	11.2.5	Reception of I-frames	54
	11.2.5.1	Ready-to-receive state.....	54
	11.2.5.2	Not-ready-to-receive state.....	54
11.3		Resetting phase	54
11.4		Transfer termination phase.....	54
	11.4.1	Point-to-point link termination.....	54
	11.4.2	Group link termination	55
12		Channel access protocol and occupation rules for data transmission	55
	12.1	Channel access for data transmission	55
	12.2	Retry procedure.....	55
Annex A (informative): Examples of channel access and occupation rules			57
A.1		Message duration.....	57
A.2		Successful transmission of a message	57
A.3		Unsuccessful transmission of a message and repetition	57
A.4		Channel access with time intervals.....	58
A.5		Channel access for data transmission with time intervals	58
Annex B (normative): Values of system parameters.....			59
Annex C (normative): The Radix 40 data compression method			60
Annex D (informative): System-terminal interface			63
D.1		Interface for data terminal equipment.....	63
D.2		Procedure for the system-terminal interface	63
	D.2.1	Asynchronous procedure 1 (CR/LF)	64
	D.2.2	Asynchronous procedure 2 (STX/ETX).....	64
	D.2.3	Synchronous procedure 1 (STX/ETX)	64
	D.2.4	Synchronous procedure 2 (HDLC)	64
Annex E (normative): Hexadecimal digit coding.....			65
Annex F (normative): Country code			66
Annex G (normative): OMC coding			67
Annex H (informative): Examples for the data dialogue procedure			68
H.1		Test algorithm for the validity of N(R)	68
H.2		State transition table of the data dialogue procedure.....	68
	H.2.1	State table for miscellaneous inputs.....	69
	H.2.2	State table for commands received.....	70
	H.2.3	State table for responses received	71
Annex J (informative): Verification of the integrity of the I-frames.....			73
Annex K (informative): Using forward error correction.....			74
Annex L (informative): Examples of using the COM field.....			76

Annex M (informative): Bibliography..... 77

History 78

iTeh STANDARD PREVIEW
(standards.iteh.ai)

SIST I-ETS 300 230 E1:2003

<https://standards.iteh.ai/catalog/standards/sist/402af814-b9eb-4888-8b46-238c51b2c83a/sist-i-ets-300-230-e1-2003>

Blank page

iTeh STANDARD PREVIEW
(standards.iteh.ai)

[SIST I-ETS 300 230 E1:2003](https://standards.iteh.ai/catalog/standards/sist/402af814-b9eb-4888-8b46-238c51b2c83a/sist-i-ets-300-230-e1-2003)

<https://standards.iteh.ai/catalog/standards/sist/402af814-b9eb-4888-8b46-238c51b2c83a/sist-i-ets-300-230-e1-2003>

Foreword

This Interim European Telecommunication Standard (I-ETS) has been prepared by the Radio Equipment and Systems (RES) Technical Committee of the European Telecommunications Standards Institute (ETSI), and having passed through the Voting phase of the ETSI standards approval procedure is now published.

The binary signalling procedure described in this I-ETS is an alternative to existing calling systems such as single-tone, multitone, subaudio and double-tone.

Every I-ETS and ETS prepared by ETSI is a voluntary standard. This I-ETS contains text concerning conformance testing of the equipment to which it relates. This text should be considered as guidance only and does not make this I-ETS mandatory.

Table F.1 in Annex F (normative) may be subject to the ETSI amendment procedure after consideration of a Vote comment submitted during the ETSI standards approval procedure.

iTeh STANDARD PREVIEW (standards.iteh.ai)

SIST I-ETS 300 230 E1:2003

<https://standards.iteh.ai/catalog/standards/sist/402af814-b9eb-4888-8b46-238c51b2c83a/sist-i-ets-300-230-e1-2003>

Blank page

iTeh STANDARD PREVIEW
(standards.iteh.ai)

SIST I-ETS 300 230 E1:2003

<https://standards.iteh.ai/catalog/standards/sist/402af814-b9eb-4888-8b46-238c51b2c83a/sist-i-ets-300-230-e1-2003>

1 Scope

This Interim European Telecommunication Standard (I-ETS) describes a binary signalling and data transmission system for private radio equipment operating at 1 200 bit/s using indirect modulation.

This I-ETS applies to systems operating on either shared, or exclusive, channels.

According to national regulations of various countries, Public Switched Telephone Network (PSTN) access and data transmission may be subject to licensing. The channel access protocol and occupation rules can also be a matter for licensing, depending on the different national regulations.

This I-ETS may be implemented only in parts. Where parts, or options, of this I-ETS are implemented, the requirements of this I-ETS shall be met. Conversely the bits specified in this I-ETS for options which are not implemented, shall not be used for any other purposes.

Fields that have been reserved to provide for future extensions to this I-ETS shall not be used. Finally, fields have been defined as free for custom specific applications and are not further defined in this I-ETS.

This I-ETS permits the addition, if necessary, of supplementary signalling, either sub-audio, multitone, or binary, as appropriate, to permit primary and secondary paging to be used. This I-ETS does not attempt to define the protocols necessary for such supplementary signalling.

Where parameters relating to the radio environment are specified, reference should be made to the appropriate Clauses of I-ETS 300 113 [3]. However, selective calls according to this I-ETS can be implemented in equipment fulfilling I-ETS 300 219 [2] (that is messages of categories 0, 2, 4, 5 and messages of category 1 and functions 0, 1 and 2 as defined in subclause 7.2 of this I-ETS).

2 Normative references

This I-ETS incorporates by dated or undated reference, provisions from other publications. These normative references are quoted at the appropriate places in the text and the publications are listed hereafter. For dated references, subsequent amendments to or revisions of any of these publications apply to this I-ETS only when incorporated in it by amendment or revision. For undated references the latest edition of the publication referred to applies.

- [1] ISO 4335 (Third edition: 1987): "Information processing systems - Data communication - High-level data link control elements of procedures".
- [2] pri-ETS 300 219: "Radio Equipment and Systems (RES); Land Mobile Service; Technical characteristics and test conditions for radio equipment, transmitting signals to initiate a specific response in the receiver".
- [3] I-ETS 300 113: "Radio Equipment and Systems (RES) Land mobile service; Technical characteristics and test conditions for non-speech and combined analogue speech/non-speech equipment with an internal and external antenna connector, intended for the transmission of data".
- [4] CCITT Recommendation T.50: "International Alphabet No. 5".
- [5] ISO 3309 (1991): "Information technology - Telecommunications and information exchange between systems - High-level data link control (HDLC) procedures - Frame structure".

3 Definitions, symbols and abbreviations

3.1 Definitions

For the purposes of this I-ETS, the following definitions apply:

Address: information which consists of a country code, a common address part, and an individual number or a group number.

Address block: a block containing addresses. The first block of a transmission is always an address block. It can be followed by other address blocks.

Address codeword: a 64-bit codeword. The first 48 bits contain the information, the remaining 16 bits contain the redundancy for the data protection. The first codeword of a transmission is always an address codeword that can be followed by others. The transmitter address, the receiver address and the function of the message are transmitted in the address codeword.

Block: the smallest quantity of information that will be exchanged over the radio channels according to this I-ETS. It can correspond to the transmission of either a "codeword" or an "encoded codeword".

Call or connection set-up: a complete information exchange between two or more stations, including the transmission of one or more messages.

Codeword: a word correctly coded according to this I-ETS. It contains 48 bits of information. These bits are protected by 16 bits of redundancy, producing a total of 64 bits.

Common address: a common part for an individual transmitter and individual receiver address.

Data block: a block intended for the transmission of information. The data blocks can only follow address blocks in a transmission.

Data codeword: a 64-bit codeword. The first 48 bits contain the information, the remaining 16 bits contain the redundancy for the data protection. The data codewords follow the address codewords. Data codewords are assigned to the transmission of any information.

Encoded codeword: the 64 bits of a codeword can optionally be encoded with the convolutional code, producing a total of 128 bits.

External addressing: the individual transmitter and receiver address are binary coded within 12 bits using the normal addressing mode. The complete transmitter address with its individual and common part is located in the first address codeword. The complete receiver address with its individual and common part is located in the second address codeword.

Group address: an address shared by several stations. The group number can be any number within the normal addressing capacity of 12 bits. The group numbers are user specific.

I-frame: see subclause 10.4.

Individual address: the address of a station, which is unique within the network. Each station has an individual address.

Message: the contiguous transmission of a codeword sequence consisting of an address codeword which may be followed by other address codewords and by one or several data codewords.

Normal addressing: the individual transmitter and receiver address are binary coded within 12 bits and completely located in the address codeword not being followed by other address codewords.

Reserved: fields within codewords which are intended for a future designation. Reserved fields are intended for the values specified in the protocol.

Selective address: see individual address.

S-frame: see subclause 10.5.

Signalling cycle: a sequence of several messages having the same function which are separated by bit and block synchronisation.

Sub-address: the individual address of a terminal equipment if a station has connections to more than one terminal. This is defined for data transmission only.

Telephone call: the entire telephone number is transmitted within concatenated codewords.

Transmission: the information transmitted in between the "power on" and "power off" period of a particular transmitter, which may include blocks and/or speech.

U-frame: see subclause 10.6.

3.2 Symbols

For the purposes of this I-ETS, the following symbols apply:

dTT	The maximum time during which an acknowledgement or reply may be sent after expiry of TT.
H	Hexadecimal notation, e.g. 2A _H is equal to 42 decimal.
K	The maximum number of unacknowledged sequentially numbered I-frames at a specific time.
N1	The highest number of data blocks which may be transmitted within an I-frame.
N2	The maximum number of retransmissions of an I-frame after the expiry of the time control T1.
NA	The number of acknowledgement repetitions within a signalling cycle.
ND	The maximum number of data blocks used for short data transfer.
NM	The number of message repetitions within a signalling cycle.
NR	The maximum number of retries of a message if an acknowledgement is not received.
T1F	The fixed part of the retry waiting time T1 after whose expiry a repetition of a frame is initiated.
T1I	The increment part of the retry waiting time T1 after whose expiry a repetition of a frame is initiated.
T3	The time after which a receiving station automatically exits the group mode.
TAC	The time waiting for an acknowledgement after whose expiry a repetition of the message is initiated.
TAD	The time waiting for a response after whose expiry a repetition of a frame is initiated.
TC	The maximum waiting time to access a channel.
TF	The time after which a call is cleared if an Radio Frequency (RF) carrier is lost.