



INTERNATIONAL STANDARD ISO/IEC 23090-10:2022
TECHNICAL CORRIGENDUM 1

Published 2023-05

INTERNATIONAL ORGANIZATION FOR STANDARDIZATION • МЕЖДУНАРОДНАЯ ОРГАНИЗАЦИЯ ПО СТАНДАРТИЗАЦИИ • ORGANISATION INTERNATIONALE DE NORMALISATION
INTERNATIONAL ELECTROTECHNICAL COMMISSION • МЕЖДУНАРОДНАЯ ЭЛЕКТРОТЕХНИЧЕСКАЯ КОМИССИЯ • COMMISSION ÉLECTROTECHNIQUE INTERNATIONALE

Information technology — Coded representation of immersive media — Part 10: Carriage of visual volumetric video-based coding data

TECHNICAL CORRIGENDUM 1

Technologies de l'information — Représentation codée de média immersifs — Partie 10: Transport de données de codage basé sur la vidéo volumétrique

RECTIFICATIF TECHNIQUE 1

Technical Corrigendum 1 to ISO/IEC 23090-10:2022 was prepared by Joint Technical Committee ISO/IEC JTC 1, *Information technology*, Subcommittee SC 29, *Coding of audio, picture, multimedia and hypermedia information*.

iTeh STANDARD PREVIEW
(standards.iteh.ai)

ISO/IEC 23090-10:2022/Cor 1:2023

<https://standards.iteh.ai/catalog/standards/sist/1e595b42-fc3f-41bc-a9a1-8d566556375a/iso-iec-23090-10-2022-cor-1-2023>

1 v3c_unit and nal_unit types

In the syntax of V3CDecoderConfigurationRecord the v3c_parameter_set is using the v3c_unit type which is defined in ISO/IEC 23090-5 but not in ISO/IEC 23090-10.

```
v3c_unit v3c_parameter_set(v3c_parameter_set_length);
```

Even worse is the fact that while the syntax defines the parameter set to be a v3c_unit, the semantics section only refers to a V3C Unit payload:

v3c_parameter_set is a V3C unit payload for V3C unit of type V3C_VPS, as defined in ISO/IEC 23090-5.

This is clearly a mismatch between semantics and the syntax, because ISO/IEC 23090-5 defines the v3c_unit, as a v3c_unit_header + v3c_unit_payload.

Similarly, nal_unit is also defined in ISO/IEC 23090-5 and should be replaced by generic bit(8) type. It is also proposed to remove unnecessary inline comments.

1.1 Proposed corrigendum

In 7.2.1.2, replace:

```
aligned(8) class V3CDecoderConfigurationRecord {
    // version 0

    unsigned int(3) unit_size_precision_bytes_minus1;

    unsigned int(5) num_of_v3c_parameter_sets;
    for (int i=0; i < num_of_v3c_parameter_sets; i++) {

        unsigned int(16) v3c_parameter_set_length;

        // v3c_unit() as defined in ISO/IEC 23090-5

        v3c_unit v3c_parameter_set(v3c_parameter_set_length);

    }

    unsigned int(8) num_of_setup_unit_arrays;
    for (int j=0; j < num_of_setup_unit_arrays; j++) {

        unsigned int(1) array_completeness;

        bit(1) reserved = 0;

        unsigned int(6) nal_unit_type;

        unsigned int(8) num_nal_units;

        for (int i=0; i < num_nal_units; i++) {

            unsigned int(16) setup_unit_length;

            // nal_unit(size) as defined in ISO/IEC 23090-5
```

```

        nal_unit setup_unit(setup_unit_length);
    }
}

// additional fields
}

with:
aligned(8) class V3CDecoderConfigurationRecord(int version) {
    if(version == 0){
        unsigned int(3) unit_size_precision_bytes_minus1;
        unsigned int(5) num_of_v3c_parameter_sets;
        for (int i=0; i < num_of_v3c_parameter_sets; i++) {
            unsigned int(16) v3c_parameter_set_length;
            bit(8) v3c_parameter_set[v3c_parameter_set_length];
        }
        unsigned int(8) num_of_setup_unit_arrays;
        for (int j=0; j < num_of_setup_unit_arrays; j++) {
            unsigned int(1) array_completeness;
            bit(1) reserved = 0;
            unsigned int(6) nal_unit_type;
            unsigned int(8) num_nal_units;
            for (int i=0; i < num_nal_units; i++) {
                unsigned int(16) setup_unit_length;
                bit(8) setup_unit[setup_unit_length];
            }
        }
    }
}

```

ISO/IEC 23090-10:2022/Cor 1:2023

<https://standards.iteh.ai/catalog/standards/sist/1e595b42-fc3f-41bc-a9a1-8d566556375a/iso-iec-23090-10-2022-cor-1-2023>

In 7.2.1.3, replace:

v3c_parameter_set_length indicates the size, in bytes, of the v3c_parameter_set field.
v3c_parameter_set is a V3C unit payload for V3C unit of type V3C_VPS, as defined in ISO/IEC 23090-5.

...

setup_unit_length indicates the size, in bytes, of the setup_unit field. The length field includes the size of both the NAL unit header and the NAL unit payload but does not include the length field itself.

setup_unit contains a NAL unit according to related nal_unit_type. When present in setup_unit, NAL_PREFIX_ESEI, NAL_PREFIX_NSEI, NAL_SUFFIX_ESEI, or NAL_SUFFIX_NSEI contain SEI messages of a 'declarative' nature, that is, those that provide information about the stream as a whole. An example of such an SEI could be a user-data SEI.

with:

v3c_parameter_set_length indicates the size, in bytes, of the v3c_parameter_set array. The signalled value shall not be equal to 0.

v3c_parameter_set is an array of data containing the entire v3c_unit of the type V3C_VPS, as defined in ISO/IEC 23090-5.

...

setup_unit_length indicates the size, in bytes, of the setup_unit array. The signalled value shall not be equal to 0.

setup_unit is an array of data containing the entire nal_unit as defined in ISO/IEC 23090-5. The contained NAL unit shall be of the same type as specified by nal_unit_type. When present in setup_unit, NAL_PREFIX_ESEI, NAL_PREFIX_NSEI, NAL_SUFFIX_ESEI, or NAL_SUFFIX_NSEI contain SEI messages of a 'declarative' nature, that is, those that provide information about the stream as a whole. An example of such an SEI could be a user-data SEI.

In 7.2.2.2, replace:

```
class V3CConfigurationBox extends FullBox('v3cC', version = 0, 0) {
    V3CDecoderConfigurationRecord();
}
```

with:

```
class V3CConfigurationBox extends FullBox('v3cC', version = 0, 0) {
    V3CDecoderConfigurationRecord v3c_config(version);
}
```

In 7.2.2.3, replace:

V3CDecoderConfigurationRecord is defined in subclause 7.2.1

with:

v3c_config is an instance of V3CDecoderConfigurationRecord as defined in subclause 7.2.1.

2 sample_stream_nal_unit type definition

In the context of ISO/IEC 23090-10 the sample_stream_nal_unit type is undefined. The following syntax of V3CAtlasSample addresses the problem.

2.1 Proposed corrigendum

<https://standards.iteh.ai/catalog/standards/sist/1e595b42-fc3f-41bc-a9a1-8d566556375a/iso-iec-23090-10-2022-cor-1-2023>

In 7.4.4.2, replace:

```
aligned(8) class V3CAtlasSample {
    // sample_size value is the size of the sample from the SampleSizeBox
    for (int i=0; i < sample_size; ) {
        sample_stream_nal_unit ss_nal_unit; // as defined in ISO/IEC 23090-5
        i += ss_nal_unit.ssnu_nal_unit_size +
            V3CDecoderConfigurationRecord.unit_size_precision_bytes_minus1 + 1;
    }
}
```

with:

```
aligned(8) class V3CAtlasSample {
    // sample_size value is the size of the sample from the SampleSizeBox
    for (int i=0; i < sample_size; ) {
        unsigned int((v3c_config.unit_size_precision_bytes_minus1 + 1)*8) nal_size;
        bit(8) ss_nal_unit[nal_size];
        i += nal_size + v3c_config.unit_size_precision_bytes_minus1 + 1;
    }
}
```

In 7.4.4.3, replace:

`ss_nal_unit` contains a single NAL unit in NAL unit sample stream format as defined in ISO/IEC 23090-5 :2021, Annex D.

`ssnu_nal_unit_size` specifies the size, in bytes, of the sample stream NAL unit. The number of bits used to represent `ssnu_nal_unit_size` is equal to $(V3CDecoderConfigurationRecord.unit_size_precision_bytes_minus1 + 1) * 8$.

with:

`nal_size` specifies the size, in bytes, of the `ss_nal_unit` array. This size is equivalent to the sample stream NAL unit size `ssnu_nal_unit_size` as defined in ISO/IEC 23090-5 :2021, Annex D.

`ss_nal_unit` is an array of data containing a single NAL unit as defined in ISO/IEC 23090-5.

NOTE Both, `nal_size` and `ss_nal_unit` replicate the sample stream NAL unit format `sample_stream_nal_unit` as defined in ISO/IEC 23090-5.

3 v3c_unit_header

In the context of ISO/IEC 23090-10 the `v3c_unit_header` type is undefined. The following change addresses the problem and removes unnecessary comment.

3.1 Proposed corrigendum

In 8.5.3.2, replace:

```
aligned(8) class V3CUnitHeaderProperty() extends ItemFullProperty('vutp',  
version=0, 0) {
```

```
    v3c_unit_header header(); // 4 bytes
```

```
}
```

with:

```
aligned(8) class V3CUnitHeaderProperty() extends ItemFullProperty('vutp',  
version=0, 0) {  
    bit(8) header[4];  
}
```

4 v3c_parameter_set type

Remove undefined syntax elements from `V3CConfigurationProperty` by updating the specification as defined in the subclasses.

4.1 Proposed corrigendum

In 8.5.2.2, replace:

```
aligned(8) class V3CConfigurationProperty
```

```
    extends ItemProperty('v3cp', version=0, flags) {
```

```
        unsigned int(16) v3c_parameter_set_length;
```

```
        // v3c_parameter_set() as defined in ISO/IEC 23090-5
```

```
        v3c_parameter_set v3c_parameter_set(v3c_parameter_set_length);
```