



Designation: F2939 – 13

# Standard Specification for High Voltage Phasing Testers<sup>1</sup>

This standard is issued under the fixed designation F2939; the number immediately following the designation indicates the year of original adoption or, in the case of revision, the year of last revision. A number in parentheses indicates the year of last reappraisal. A superscript epsilon ( $\epsilon$ ) indicates an editorial change since the last revision or reappraisal.

## 1. Scope

1.1 This specification covers portable, live-line tool-supported two-pole phasing testers to be used on AC electrical systems.

1.2 Two types of phasing testers are provided and are designated as Type I Resistive and Type II Capacitive.

1.3 Two styles of phasing testers are provided and are designated as Style A Numerical and Style B Audible/Visual.

1.4 The use and maintenance of these high voltage phasing testers and any necessary insulated tool handles are beyond the scope of this specification.

1.5 The values stated in inch-pound units are to be regarded as standard. The values given in parentheses are mathematical conversions to SI units that are provided for information only and are not considered standard.

1.6 *This standard does not purport to address all of the safety concerns, if any, associated with its use. It is the responsibility of the user of this standard to establish appropriate safety and health practices and determine the applicability of regulatory limitations prior to use.*

NOTE 1—Except where specified, all voltage defined in this specification refers to phase-to-phase voltage in a three-phase system. Phasing Testers covered by this specification may be used in other than three-phase systems, but the applicable phase-to-phase or phase-to-ground (earth) voltages shall be used to determine the operating voltage.

## 2. Referenced Documents

### 2.1 ASTM Standards:<sup>2</sup>

**F1796 Specification for High Voltage Detectors—Part 1 Capacitive Type to be Used for Voltages Exceeding 600 Volts AC**

<sup>1</sup> This test method is under the jurisdiction of ASTM Committee F18 on Electrical Protective Equipment for Workers and is the direct responsibility of Subcommittee F18.35 on Tools & Equipment.

Current edition approved Sept. 1, 2013. Published October 2013. DOI: 10.1520/F2939-13

<sup>2</sup> For referenced ASTM standards, visit the ASTM website, [www.astm.org](http://www.astm.org), or contact ASTM Customer Service at [service@astm.org](mailto:service@astm.org). For *Annual Book of ASTM Standards* volume information, refer to the standard's Document Summary page on the ASTM website.

### 2.2 Other Standards:<sup>3</sup>

**ANSI C84.1 Electric Power Systems and Equipment—Voltage Ranges**

## 3. Terminology

### 3.1 Definitions:

3.1.1 *clear indication, n*—a specific condition that detects and indicates the presence or absence of the correct voltage, or phase relationship, or both, between two energized parts.

3.1.2 *contact electrode, n*—the bare conductive part of the conductive element that establishes the electrical connection to the component to be tested.

3.1.3 *indicator, n*—part of the phasing tester that indicates the presence or absence of the correct voltage, or phase relationship, or both, between two energized parts.

3.1.4 *indication, n*—visible, audible, or numeric indication of which clearly indicates the presence of nominal operating voltage within the specified voltage range.

3.1.4.1 *Discussion*—Noise and light indications shall be clearly detectable under the conditions outlined as follows: (See Specification F1796, sections 10.3.13 and 10.3.14). Acceptable Audible Indication – The audible test should be performed in an environment where background noise does not exceed 60 dBA. Acceptable Visual Indication – The Style B visual tests should be conducted in an environment with ambient light conditions ranging from 0 to 18 000 fc.

3.1.5 *insertion limit, n*—distinctive location to indicate to the user the physical limit to which the phasing device may be inserted between energized/grounded parts, as specified by the manufacturer.

3.1.6 *interference field, n*—electrical field capable of affecting the indication. It may result from the part to be tested or other adjacent parts.

3.1.7 *interference ground, n*—ground potential capable of affecting the indication. It may result from the part to be tested or other adjacent parts.

3.1.8 *phasing tester, n*—portable device used to detect and indicate the presence or absence of the correct voltage, or

<sup>3</sup> Available from American National Standards Institute (ANSI), 25 W. 43rd St., 4th Floor, New York, NY 10036, <http://www.ansi.org>.

phase relationship, or both, between two energized parts at the same nominal voltage and frequency.

3.1.9 *response time, n*—time delay between sudden change of the voltage state on the contact electrode and the associated clear indication.

3.1.10 *status indication, n*—the ability by the user to determine that the phasing tester is in its operating position.

3.1.11 *test:*

3.1.11.1 *acceptance test, n*—a test made at the option of the purchaser to verify that a product meets design criteria.

3.1.11.2 *design test, n*—a test made on a sample treated as representative of an industrial product. These tests will not generally be repeated in quantity production.

3.1.11.3 *routine test, n*—a test made regularly on production material.

3.1.12 *testing element, n*—built-in or external device, by means of which the functioning of the phasing tester can be checked by the user.

3.1.13 *threshold angle, n*—minimum phase angle between the two parts to be compared which gives a change of signal indicating the incorrect presence or absence of the correct voltage, or phase relationship, or both.

3.1.14 *threshold voltage, n*—minimum voltage between the two parts to be compared to give a change of signal indicating the presence or absence of the correct voltage, or phase relationship, or both (not applicable for capacitive phasing testers).

3.1.15 *voltage, nominal design, n*—a nominal value consistent with the latest revision of ANSI C84.1, 2001, assigned to the circuit or system for the purpose of conveniently designating its voltage class.

3.1.16 *voltage range, n*—values stated by the manufacturer indicating the minimum and maximum operating voltage in which the phasing tester will operate.

#### 4. Significance and Use

4.1 This specification establishes requirements for the design and testing of high voltage phasing set, used in the electrical power industry, to determine the presence or absence of the correct voltage or phase relationships, or both, and approximate voltage line to line or line to ground.

#### 5. Classification

5.1 *Type I Resistive*—Two-pole phasing device with interconnect cable(s) used to detect and indicate the correct phase relationship of conductors by measuring voltage difference whose operation is based on the current passing through a resistor or other impedance device.

5.2 *Type II Capacitive*—Two-pole phasing device without interconnect cable(s) used to detect and indicate the correct phase relationship of conductors by measuring phase angle whose operation is based on the current passing through the stray capacitance to earth (ground).

5.3 *Style A, Numerical*—The presence of voltage or phase relationship is displayed numerically.

5.4 *Style B, Audible/Visual*—The presence of voltage or phase relationship is indicated by an audible sound and light, capable of being heard and seen as defined in Section 10.

#### 6. Ordering Information

6.1 Orders for high voltage phasing testers under this specification shall include this ASTM designation and the following information:

6.1.1 Type,

6.1.2 Style,

6.1.3 Voltage range(s), and

6.1.4 Catalog number.

#### 7. Marking and Instructions

7.1 Labeling:

7.1.1 Each phasing tester shall be marked clearly with the name of the manufacturer or supplier, operating voltage range, catalog number, and date code or serial number.

7.1.2 Instructions for operating the phasing tester shall be included with each unit.

#### 8. Specifications

8.1 The manufacturer shall clearly specify the limits of performance of phasing tester within the instructions as follows:

8.1.1 Operating voltage range(s),

8.1.2 Operating temperature range,

8.1.3 Operating humidity range,

8.1.4 Storage temperature range,

8.1.5 Storage humidity range, and

8.1.6 Precautions or limitations in use.

#### 9. Workmanship, Finish, and Appearance

9.1 Workmanship and finish shall be of such quality as to ensure safe operation of the unit. Appearance shall be the prerogative of the manufacturer.

#### 10. Testing

10.1 *General*—Tests shall be performed using a minimum of two phasing testers that have been completely assembled. Tests shall be carried out under the following test conditions:

10.1.1 Ambient temperature 59 to 95°F (15 to 35°C).

10.1.2 Relative humidity 45 to 75 %.

10.1.3 Unless otherwise specified, tests shall be carried out using a 60 Hz AC power source.

10.1.4 An acceptable tolerance of  $\pm 10$  % is allowed for all required values.

10.2 *Test Methods (Environmental):*

10.2.1 *Temperature Dependence of the Indication*—The phasing tester shall operate correctly in the temperature range of the climatic category according to 8.1.2. The numeric or threshold voltage shall not vary by more than  $\pm 10$  %, with respect to the numeric or threshold voltage measured when tested at the minimum and maximum temperature. The phasing tester shall be subjected to the minimum and maximum temperature extremes for 24 h and immediately subjected to a numeric or threshold voltage test. The numeric or threshold voltage is not to deviate more than  $\pm 10$  % from the previously