



Designation: **D6431–99 (Reapproved 2010) D6431 – 18**

Standard Guide for Using the Direct Current Resistivity Method for Subsurface Investigation Site Characterization¹

This standard is issued under the fixed designation D6431; the number immediately following the designation indicates the year of original adoption or, in the case of revision, the year of last revision. A number in parentheses indicates the year of last reapproval. A superscript epsilon (ϵ) indicates an editorial change since the last revision or reapproval.

1. Scope—Scope*

1.1 Purpose and Application:

1.1.1 This guide summarizes the equipment, field procedures, and interpretation methods for the assessment of the electrical properties of subsurface materials and their pore fluids, using the direct current (DC) resistivity method. Measurements of the electrical properties of subsurface materials are made from the land surface and yield an apparent resistivity. These data can then be interpreted to yield an estimate of the depth, thickness, voids, and resistivity of subsurface layer(s).

1.1.2 Resistivity measurements as described in this guide are applied in geological, geotechnical, environmental, and hydrologic investigations. The resistivity method is used to map geologic features such as lithology, structure, fractures, and stratigraphy; hydrologic features such as depth to water table, depth to aquitard, and groundwater salinity; and to delineate groundwater contaminants. General references are, Keller and Frischknecht (1),² Zohdy et al (2), Koefoed (3), EPA(4), Ward (5), Griffiths and King (6), and Telford et al (7).

1.1.3 This guide does not address the use tomographic interpretation methods, commonly referred to as electrical resistivity tomography (ERT) or electrical resistivity imaging (ERI). While many of the principles apply the data acquisition and interpretation differ from those set forth in this guide.

1.2 Limitations:

1.2.1 This guide provides an overview of the Direct Current Resistivity Method. It does not address in detail the theory, field procedures, or interpretation of the data. Numerous references are included for that purpose and are considered an essential part of this guide. It is recommended that the user of the resistivity method be familiar with the references cited in the text and with the Guide D420, Practice D5088, Practice D5608, Guide D5730, Test Method G57, D6429, and D6235.

1.2.2 This guide is limited to the commonly used approach for resistivity measurements using sounding and profiling techniques with the Schlumberger, Wenner, or dipole-dipole arrays and modifications to those arrays. It does not cover the use of a wide range of specialized arrays. It also does not include the use of spontaneous potential (SP) measurements, induced polarization (IP) measurements, or complex resistivity methods.

1.2.3 The resistivity method has been adapted for a number of special uses, on land, within a borehole, or on water. Discussions of these adaptations of resistivity measurements are not included in this guide.

1.2.4 The approaches suggested in this guide for the resistivity method are the most commonly used, widely accepted and proven; however, other approaches or modifications to the resistivity method that are technically sound may be substituted if technically justified and documented.

1.2.5 This guide offers an organized collection of information or a series of options and does not recommend a specific course of action. This document cannot replace education or experience and should be used in conjunction with professional judgements. Not all aspects of this guide may be applicable in all circumstances. This ASTM standard is not intended to represent or replace the standard of care by which the adequacy of a given professional service must be judged, nor should this document be applied without consideration of a project's many unique aspects. The word "Standard" in the title of this document means only that the document has been approved through the ASTM consensus process.

¹ This guide is under the jurisdiction of ASTM Committee D18 on Soil and Rock and is the direct responsibility of Subcommittee D18.01 on Surface and Subsurface Characterization.

Current edition approved May 1, 2010 Feb. 1, 2018. Published September 2010 March 2018. Originally approved in 1999. Last previous edition approved in 2005 2010 as D6431–99(2005); D6431–99(2010). DOI: 10.1520/D6431-99R10.10.1520/D6431-18.

² The boldface numbers in parentheses refer to the list of references at the end of this standard.

*A Summary of Changes section appears at the end of this standard

1.3 Units—The values stated in SI units are to be regarded as standard. No other units of measurement are included in this standard. Reporting of test results in units other than SI shall not be regarded as nonconformance with this test method.

1.4 Precautions:

1.4.1 *It is the responsibility of the user of this guide to follow any precautions in the equipment manufacturer's recommendations and to consider the safety implications when high voltages and currents are used.*

1.4.2 *If this guide is used at sites with hazardous materials, operations, or equipment, it is the responsibility of the user of this guide to establish appropriate safety and health practices and to determine the applicability of regulations prior to use.*

1.5 *This standard does not purport to address all of the safety concerns, if any, associated with its use. It is the responsibility of the user of this standard to establish appropriate ~~safety~~ safety, health, and health~~environmental~~ environmental practices and determine the applicability of regulatory limitations prior to use.*

1.6 *This international standard was developed in accordance with internationally recognized principles on standardization established in the Decision on Principles for the Development of International Standards, Guides and Recommendations issued by the World Trade Organization Technical Barriers to Trade (TBT) Committee.*

2. Referenced Documents

2.1 *ASTM Standards:*³

[D420 Guide to Site Characterization for Engineering Design and Construction Purposes](#) (Withdrawn 2011)

[D653 Terminology Relating to Soil, Rock, and Contained Fluids](#)

[D5088 Practice for Decontamination of Field Equipment Used at Waste Sites](#)

[D5608 Practices for Decontamination of Sampling and Non Sample Contacting Equipment Used at Low Level Radioactive Waste Sites](#)

[D5730 Guide for Site Characterization for Environmental Purposes With Emphasis on Soil, Rock, the Vadose Zone and Groundwater](#) (Withdrawn 2013)⁴

[D5753 Guide for Planning and Conducting Geotechnical Borehole Geophysical Logging](#)

[D6235 Practice for Expedited Site Characterization of Vadose Zone and Groundwater Contamination at Hazardous Waste Contaminated Sites](#)

[D6429 Guide for Selecting Surface Geophysical Methods](#)

[G57 Test Method for Field Measurement of Soil Resistivity Using the Wenner Four-Electrode Method](#)

3. Terminology

3.1 Definitions:

3.1.1 For common definitions of terms used in this standard, see Terminology [D653](#).

3.1.2 The majority of the technical terms used in this document are defined in Sheriff (1991).

3.2 Additional Definitions:

3.1.1 Definitions shall be in accordance with the terms and symbols given in Terminology [D653](#).

3.2.1 *apparent resistivity, n*—the resistivity of homogeneous, isotropic ground that would give the same voltage-current relationship as measured.

3.2.1.1 Discussion—

Apparent resistivity is expressed in ohm-meter (Ωm).

3.1.2 The majority of the technical terms used in this document are defined in Sheriff (1991).

3.2.2 *conductivity, n*—the ability of a material to conduct an electrical current. In isotropic material, it is the reciprocal of resistivity.

3.2.2.1 Discussion—

Conductivity is measured in Siemens per meter (S/m).

3.1.3 Additional Definitions:

3.1.3.1 *apparent resistivity*—the resistivity of homogeneous, isotropic ground that would give the same voltage-current relationship as measured.

3.1.3.2 *conductivity*—The ability of a material to conduct an electrical current. In isotropic material, it is the reciprocal of resistivity. The units of conductivity are siemens per metre.

³ For referenced ASTM standards, visit the ASTM website, www.astm.org, or contact ASTM Customer Service at service@astm.org. For *Annual Book of ASTM Standards* volume information, refer to the standard's Document Summary page on the ASTM website.

⁴ The last approved version of this historical standard is referenced on www.astm.org.

3.1.3.3 *resistance*—opposition to the flow of direct current. The unit of resistance is ohms.

3.1.3.4 *resistivity*—the property of a material that resists the flow of electrical current. The units of resistivity are ohm-metres or ohm-feet ($1 \Omega\text{m} = 3.28 \Omega\text{-ft}$).

3.2.3 *resistance, n*—opposition to the flow of direct current.

3.2.3.1 *Discussion*—

Resistance is measured in ohm (Ω).

3.2.4 *resistivity, n*—the property of a material that resists the flow of electrical current.

3.2.4.1 *Discussion*—

Resistivity is measured in ohm-meter (Ωm).

4. Summary of Guide

4.1 *Summary*—The measurement of electrical resistivity requires that four electrodes be placed in contact with the surface materials (Fig. 1). The geometry and separation of the electrode array are selected on the basis of the application and required depth of investigation: the site characterization.

4.1.1 In an electrical resistivity survey, a direct current or a very low frequency alternating current is passed into the ground through a pair of current electrodes, and electrodes (C1 and C2), and the resulting potential drop is measured across a pair of potential electrodes (P1 and P2) as shown in Fig. 1). The resistance is then derived as the ratio of the voltage measured across the potential electrodes and the current electrodes. The apparent resistivity of subsurface materials is derived as the resistance multiplied by a geometric factor that is determined by the geometry and spacing of the electrode array.

4.1.2 The calculated apparent resistivity measurement represents a bulk average resistivity of the volume of earth determined by the geometry of the array and the resistivity of the subsurface material. This apparent resistivity is different from true resistivity unless the subsurface materials are electrically uniform. Representative resistivity values of layers are interpreted from apparent resistivity values obtained from a series of measurements made with variable electrode spacing. Increasing electrode spacing may permit distinction among layers that vary in electrical properties with depth.




FIG. 1 Diagram Showing Basic Concept of Resistivity Measurement (from Benson et al, (8))

4.1.3 Most resistivity surveys for geologic, engineering, hydrologic, and environmental applications are carried out to determine depths of specific layers or lateral changes in geologic conditions at depths of less than a hundred metres. However, with sufficient power and instrument sensitivity, resistivity measurements are made to depths of several hundred metres.

4.2 *Complementary Data*—Other complementary surface geophysical methods (D6429) or borehole geophysical methods (Guide D5753) and non-geophysical methods may be necessary to properly interpret subsurface conditions.

5. Significance and Use

5.1 *Concepts*—The resistivity technique is used to measure the resistivity of subsurface materials. Although the resistivity of materials can be a good indicator of the type of subsurface material present, it is not a unique indicator. While the resistivity method is used to measure the resistivity of earth materials, it is the interpreter who, based on knowledge of local geologic conditions and other data, must interpret resistivity data and arrive at a reasonable geologic and hydrologic interpretation.

5.2 *Parameter Being Measured and Representative Values:*

5.2.1 Table 1 shows some general trends for resistivity values. Fig. 2 shows ranges in resistivity values for subsurface materials.

5.2.2 Materials with either a low effective porosity or that lack conductive pore fluids have a relatively high resistivity (>1000 Ωm – Ωm). These materials include massive limestones, most unfractured igneous rocks, unsaturated unconsolidated materials, and ice.

5.2.3 Materials that have high porosity with conductive pore fluids or that consist of or contain clays usually have low resistivity. These include clay soil and weathered rock.

5.2.4 Materials whose pore water has low salinity have moderately high resistivity.

5.2.5 The dependence of resistivity on water saturation is not linear. Resistivity increases relatively little as saturation decreases from 100 % to 40–60 % and somewhere between 40 and 60 % and then increases much more as saturation continues to decrease. An empirical relationship known as Archie’s Law describes the relationship between pore fluid resistivity, porosity, and bulk resistivity (McNeill (10)).

5.3 *Equipment*—Geophysical apparatus used for surface resistivity measurement includes a source of power, a means to measure the current, a high impedance voltmeter, electrodes to make contact with the ground, and the necessary cables to connect the electrodes to the power sources and the volt meter (Fig. 1).

5.3.1 While resistivity measurements can be made using common electronic instruments, it is recommended that commercial resistivity instruments specifically designed for the purpose be used for resistivity measurements in the field.

5.3.2 Commonly used equipment includes the following elements:

5.3.2.1 A source of current consisting of batteries or a generator,

5.3.2.2 A high-impedance voltmeter or resistivity unit,

5.3.2.3 Metal stakes for the current and potential electrodes, and

5.3.2.4 Insulated wire to connect together all of the preceding components.

5.3.2 Care must be taken to ensure good electrical contact of the electrodes with the ground. Electrodes should be driven into the ground until they are in firm contact. If connections between electrodes and the insulated wire are not waterproof, care must be taken to ensure that they will not be shorted out by moisture. Special waterproof cables and connectors are required for wet areas.

TABLE 1 Representative Resistivity Values for Soil, Water, and Rock (Mooney (4))

Regional Soil Resistivity		Ωm
Regional Soil Resistivity		m
- wet regions	50–200	
- wet regions	50 to 200	
- dry regions	400–500	
- dry regions	100 to 500	
- arid regions	200–1000 (sometimes as low as 50 if the soil is saline)	
- arid regions	200 to 1000 (sometimes as low as 50 if the soil is saline)	
Waters		Ωm
Water Type		m
- soil water	1 to 100	
- rain water	30 to 1000	
- sea water	order of 0.2	
- ice	105 to 108	
Rock Types		Ωm
Earth Material Types		m
- igneous and metamorphic	100 to 10,000	
- consolidated sediments	10 to 100	
- unconsolidated sediments	1 to 100	




FIG. 2 Typical Ranges of Resistivities of Earth Materials (from Sheriff, (9))

5.3.3 A large variety of resistivity systems are available from different manufacturers. Relatively inexpensive battery-powered units are available for shallow surveys. The current source (transmitter) and the potential measurement instrument (receiver) are often assembled into a single, portable unit. In some cases, the transmitter and receiver units are separate. High power units capable of deep survey work are powered by generators. The current used in dc resistivity surveys varies from a few milliamps to several amps, depending on the depth of the investigation-site characterization.

5.3.4 *Signal Enhancement*—Signal enhancement capability is available in many resistivity systems. It is a significant aid when working in noisy areas or with low power sources. Enhancement is accomplished by adding the results from a number of measurements at the same station. This process increases the signal-to-noise ratio.

5.4 *Limitations and Interferences*—*Interferences:*

5.4.1 *Limitations Inherent to Geophysical Methods:*

5.4.1.1 A fundamental limitation of all geophysical methods lies in the fact that a given set of data cannot be associated with a unique set of subsurface conditions. In most situations, surface geophysical measurements alone cannot resolve all ambiguities, and some additional information, such as borehole data, is required. Because of this inherent limitation in geophysical methods, a resistivity survey alone is never considered a complete assessment of subsurface conditions. Properly integrated with other information, resistivity surveying is an effective method of obtaining subsurface information.

5.4.1.2 All surface geophysical methods are inherently limited by decreasing resolution with depth.

5.4.2 *Limitations Specific to the Resistivity Method:*

5.4.2.1 Interpretation methods assume horizontal (or parallel) layered conditions where each layer has a uniform electrical resistivity. If subsurface conditions cannot be reasonably approximated by this assumption, then results will be in error.

5.4.2.2 Thin layers or multiple layers with similar resistivities may not be detected.

5.4.2.3 Ambiguities in interpretation arising from equivalence (where two resistive layers carry nearly the same electric current if the products of their resistivity and thickness equal).

5.4.2.4 Ambiguities in interpretation arising from suppression (where resistant layers are sandwiched between more conductive layers).

5.4.2.5 Extremely resistive materials will prevent current injection into the ground.

5.4.3 *Interferences Caused by Ambient and Geologic Conditions:*

5.4.3.1 The resistivity method is sensitive to electrical interference from a variety of sources. ~~It is inherently sensitive to electrical interference.~~ Spatial variables caused by geologic factors and cultural factors may also produce noise.

5.4.3.2 *Ambient Sources of Noise*—Natural (ambient) sources of noise include lightning or natural earth currents, which may induce a voltage in resistivity cables.

5.4.3.3 *Geologic Sources of Noise*—Geologic sources of noise include local inhomogeneities near electrodes that may result in measurement error and variations in the subsurface that are not the object of the survey.

5.4.3.4 *Cultural Sources of Noise*—Resistivity measurements may be influenced by nearby cultural features (such as power lines, radio stations, cathodic pipeline protection, and other geophysical equipment) that generate electrical or electromagnetic fields. Pipelines, fences, and metal buildings may also affect them.

5.4.3.5 *Leakage*—A resistivity measurement may also be affected by leakage from the insulated wire used to connect the instrument to the electrodes. Tests for leakage can be made at the time of the measurement.

5.4.4 *Summary—Cultural Interference*—During the course of designing survey locations, potential cultural interferences should be considered. ~~During the survey, the occurrence of electrical interferences should be noted.~~ Cultural interference may emanate from pipes, fences, buried utilities and other grounded linear electric conductors in the vicinity of the survey. These objects may “short circuit” the measured currents assumed to be passing through the ground.

5.5 *Alternate Methods*—The limitations previously discussed may prohibit the effective use of the resistivity method, and other methods may be required to resolve the problem. An alternative to the resistivity method is the EM method, which is preferred in high-resistivity (low-conductivity) materials, and may require less space to conduct the survey.

5.6 *Electrode Array Geometry*—Usually the electrodes are arranged in a collinear array in one of several fixed geometries. Several standard electrode geometries have been developed for various applications (Fig. 3). For engineering, environmental, and groundwater studies, the Wenner, Schlumberger, and dipole-dipole arrays are the most commonly used.

5.6.1 *Wenner Array*—The Wenner array consists of equally spaced, in-line electrodes (Fig. 3). The formula for calculating apparent resistivity from a Wenner measurement is:

$$R = 2\pi\alpha(V/I) \tag{1}$$

$$R = 2\pi A(V/I) \tag{1}$$

where:

- α = electrode spacing,
- A \equiv electrode spacing,
- V = measured voltage, and






FIG. 3 Standard Electrode Geometries