



AMENDMENT

TBR 22

A1

March 1998

Source: DECT

Reference: RTBR/DECT-000092

ICS: 33.020

Key words: Access, DECT, generic, radio, testing, type approval

**This amendment A1 modifies
the Technical Basis for Regulation TBR 22 (1997)**

**Radio Equipment and Systems (RES);
Attachment requirements for terminal equipment for
Digital Enhanced Cordless Telecommunications (DECT)
Generic Access Profile (GAP) applications**

ETSI

European Telecommunications Standards Institute

ETSI Secretariat

Postal address: F-06921 Sophia Antipolis CEDEX - FRANCE

Office address: 650 Route des Lucioles - Sophia Antipolis - Valbonne - FRANCE

X.400: c=fr, a=atlas, p=etsi, s=secretariat - **Internet:** secretariat@etsi.fr

Tel.: +33 4 92 94 42 00 - **Fax:** +33 4 93 65 47 16

Copyright Notification: No part may be reproduced except as authorized by written permission. The copyright and the foregoing restriction extend to reproduction in all media.

© European Telecommunications Standards Institute 1998. All rights reserved.

Sample Document

get full document from standards.iteh.ai

Foreword

This amendment to TBR 22 (1997) has been produced by the Digital Enhanced Cordless Telecommunications (DECT) Project of the European Telecommunications Standards Institute (ETSI).

NOTE: The amendments are shown with change bars and revision marks to facilitate identification of the changes introduced.

Sample Document

get full document from standards.iteh.ai

Amendments

Clause 2

Replace reference [10] of clause 2 as follows:

[10]	ETS 300 444 (1995): "Radio Equipment and Systems (RES); Digital European Cordless Telecommunications (DECT); Generic Access Profile (GAP)".
[10]	EN 300 444: "Digital Enhanced Cordless Telecommunications (DECT); Generic Access Profile (GAP)".

Subclause 6.1.1.2

Replace table 7 with the following table 7:

Table 7

TBR 22: Test Case Index		
Test Group Reference	Test Case Id	Description
PT/CC/BV/OC/	TC_PT_CC_BV_OC_01	Outgoing call; T-00, T-01, T-02, T-03, T-04, T-10; piece wise dialling in T-02
	TC_PT_CC_BV_OC_02	Outgoing call; states T-00, T-01, T-10; piece wise dialling in T-10
	TC_PT_CC_BV_OC_03	Outgoing call; states T-00, T-01, T-02, T-10; piece wise dialling in T-02 and T-10
	TC_PT_CC_BV_OC_04	Outgoing call; U-plane connection upon <<Progress ind.>> in {CC-SETUP-ACK}
PT/CC/BV/IC/	TC_PT_CC_BV_IC_01	Incoming call; T-01, T-06, T-07, T-08, T-10; <<SIGNAL>> in T-07
	TC_PT_CC_BV_IC_02	Incoming call; T-01, T-06, T-07, T-08, T-10; <<SIGNAL>> in {CC-SETUP}
PT/CC/BV/CI/	TC_PT_CC_BV_CI_01	Alerting the user; Incoming call; <<SIGNAL>> in {CC-SETUP}
	TC_PT_CC_BV_CI_02	Go to pulse invocation in T-02; Outgoing call
	TC_PT_CC_BV_CI_03	Go to pulse invocation in T-10; Outgoing call
	TC_PT_CC_BV_CI_04	Dialling pause indication in T-02; Outgoing call
	TC_PT_CC_BV_CI_05	Dialling pause indication in T-10; Outgoing call
	TC_PT_CC_BV_CI_06	Go to DTMF invocation in T-02; defined tone length; Outgoing call
	TC_PT_CC_BV_CI_07	Go to DTMF invocation in T-10; defined tone length; Outgoing call
	TC_PT_CC_BV_CI_08	Go to DTMF invocation in T-02; infinite tone length; Outgoing call
	TC_PT_CC_BV_CI_09	Go to DTMF invocation in T-10; infinite tone length; Outgoing call
	TC_PT_CC_BV_CI_10	Outgoing normal call; T-02; {CC-INFO}, sending <<Multi keypad>>, "0-9, star, hash mark"
	TC_PT_CC_BV_CI_11	Internal call
	TC_PT_CC_BV_CI_12	T-10; {CC-INFO}, <<Multi display>> standard characters handling
	TC_PT_CC_BV_CI_13	T-10; {CC-INFO}, <<Multi display>> control characters handling
	TC_PT_CC_BV_CI_14	T-10; invocation of "Register recall"; {CC-INFO}, <<Multi keypad>>
		(continued)

Table 7 (continued)

TBR 22: Test Case Index		
PT/CC/BV/CR/	TC_PT_CC_BV_CR_01	Outgoing normal call; T-02; FT initiated normal release
	TC_PT_CC_BV_CR_02	Outgoing normal call; T-03; FT initiated normal release
	TC_PT_CC_BV_CR_03	Outgoing normal call; T-04; FT initiated normal release
	TC_PT_CC_BV_CR_04	Incoming call; T-08; FT initiated normal release
	TC_PT_CC_BV_CR_05	T-10; FT initiated normal release
	TC_PT_CC_BV_CR_06	T-10; IUT initiated normal release
	TC_PT_CC_BV_CR_07	T-01; FT initiated abnormal release
	TC_PT_CC_BV_CR_08	T-02; FT initiated abnormal release
	TC_PT_CC_BV_CR_09	T-10; FT initiated abnormal release
	TC_PT_CC_BV_CR_10	T-10; FT initiated partial release
	TC_PT_CC_BV_CR_11	T-10; IUT initiated partial release
PT/CC/BV/RS/	TC_PT_CC_BV_RS_01	T-00; Incoming call; {CC-SETUP} with <<Calling party number>>; CLIP handling
PT/CC/BO/	TC_PT_CC_BO_01	T-03; 8; unexpected message {CC-CALL-PROC}; ignore
	TC_PT_CC_BO_02	T-19; receipt of {CC-RELEASE}; release collision; clear the call
PT/CC/BI/	TC_PT_CC_BI_01	T-00; {CC-SETUP} mandatory I.E. missing; answer upon with {CC-RELEASE-COM}
	TC_PT_CC_BI_02	T-00; {CC-SETUP} wrong mandatory I.E.; answer upon with {CC-RELEASE-COM}
	TC_PT_CC_BI_03	T-00; {CC-SETUP}-like message, non {CC-SETUP} unrecognized message type; ignore
	TC_PT_CC_BI_04	T-00; to short message to contain the complete <<Message type>>; ignore
PT/CC/TI/	TC_PT_CC_TI_01	T-19; timer P-<CC.02> expiry (-10% margin)(± 5% margin); IUT sends {CC-RELEASE-COM}
	TC_PT_CC_TI_02	Outgoing call; T-01; timer P-<CC.03> expiry (-10% margin)(± 5% margin); IUT sends {CC-RELEASE-COM}
	TC_PT_CC_TI_03	T-01; restarts P-<CC.03> upon {CC-NOTIFY}
	TC_PT_CC_TI_04	Outgoing call; T-08; timer P-<CC.05> expiry (-10% margin)(± 5% margin); IUT sends {CC-RELEASE}
PT/MM/BV/ID/	TC_PT_MM_BV_ID_01	Identity request; IPUI type requested; active IPUI returned
	TC_PT_MM_BV_ID_02	Identity request; unavailable id. type requested; no identity in the reply
	TC_PT_MM_BV_ID_08	Identity request; PARK requested; active PARK returned
PT/MM/BV/AU/	TC_PT_MM_BV_AU_01	Authentication of PT; IUT(PT) has no stored ZAP value and service class info
	TC_PT_MM_BV_AU_02	Authentication of PT; unacceptable algorithm requested; reject
	TC_PT_MM_BV_AU_03	Authentication of PT; IUT(PT) has stored ZAP value; IUT includes ZAP value in the replay
	TC_PT_MM_BV_AU_04	Authentication of PT; ZAP increment handling
	TC_PT_MM_BV_AU_05	Authentication of PT; ZAP increment handling; unsuccessful authentication of FT; ZAP is not incremented
	TC_PT_MM_BV_AU_06	Authentication of PT; storage of DCK handling
	TC_PT_MM_BV_AU_07	Authentication of user
	TC_PT_MM_BV_AU_08	Authentication of FT; IUT initiated
	TC_PT_MM_BV_AU_09	Authentication of PT; IUT(PT) has stored service class info; IUT includes service class info in the replay

(continued)

Table 7 (continued)

TBR 22: Test Case Index		
PT/MM/BV/LO/	TC_PT_MM_BV_LO_01	Location registration after obtain access rights; a44 and a38=1 at locking; no TPUI assignment
	TC_PT_MM_BV_LO_02	Location registration after obtain access rights; a44 and a38=1 at locking; TPUI assignment
	TC_PT_MM_BV_LO_03	Location registration after obtain access rights; a44=1 and a38=0 at locking; IUT does not perform location registration
	TC_PT_MM_BV_LO_04	Location registration; no CC activities; location area changes; a38=1 at locking and at the beginning of the procedure; no TPUI assignment
	TC_PT_MM_BV_LO_05	No CC activities; power off; power on; Location registration request
	TC_PT_MM_BV_LO_06	Location registration; unacceptable TPUI assignment; reject
	TC_PT_MM_BV_LO_07	Location registration; entering new location area; IUT deletes old TPUI; - no TPUI in identity reply sent from IUT
	TC_PT_MM_BV_LO_08	Location update suggested by FT; Location registration initiated by IUT; a38=1 at locking and at the beginning of the procedure
	TC_PT_MM_BV_LO_09	Location update suggested by FT; Location registration initiated by IUT; a38=1 at locking, a38=0 at the beginning of the procedure
PT/MM/BV/AR/	TC_PT_MM_BV_AR_01	Obtain access rights; a44=1; both sides use AC
	TC_PT_MM_BV_AR_03	Obtain access rights; a44=0; IUT does not initiate obtain access rights procedure
	TC_PT_MM_BV_AR_05	Terminate access rights; FT initiated; IUT(PT) may authenticate FT
	TC_PT_MM_BV_AR_06	Terminate access rights; FT initiated; IUT(PT) authenticates FT; authentication fails; termination rejected
	TC_PT_MM_BV_AR_09	Obtain access rights; FT assigns ZAP field; IUT stores it
	TC_PT_MM_BV_AR_10	Obtain access rights; FT assigns service class; IUT stores it
PT/MM/BV/KA/	TC_PT_MM_BV_KA_01	Key allocation
	TC_PT_MM_BV_KA_02	Key allocation; <<Auth type>> unacceptable; reject
	TC_PT_MM_BV_KA_03	Key allocation; implicit authentication of FT fails; key is not allocated
PT/MM/BV/CH/	TC_PT_MM_BV_CH_01	Cipher switching; IUT(PT) initiated; "cipher-off" to "cipher-on"
	TC_PT_MM_BV_CH_02	Cipher switching; IUT(PT) initiated; "cipher-on" to "cipher-off"
	TC_PT_MM_BV_CH_03	Cipher switching; FT initiated; "cipher-off" to "cipher-on"
	TC_PT_MM_BV_CH_04	Cipher switching; FT initiated; "cipher-on" to "cipher-off"
	TC_PT_MM_BV_CH_05	Cipher switching; FT initiated; "cipher-off" to "cipher-on"; unacceptable algorithm or key; reject
	TC_PT_MM_BV_CH_08	Cipher switching; IUT (PT) initiated; "cipher-off" to "cipher-on" fails; release of link
	TC_PT_MM_BV_CH_09	Cipher switching; IUT (PT) initiated; "cipher-off" to "cipher-on"; successful inter-cell bearer handover
	TC_PT_MM_BV_CH_10	Cipher switching; IUT (PT) initiated; "cipher-off" to "cipher-on"; successful intra-cell bearer handover

(continued)

Table 7 (continued)

TBR 22: Test Case Index		
	TC_PT_MM_BV_CH_11	Cipher switching; IUT (PT) initiated; "cipher-off" to "cipher-on"; "cipher-on" to "cipher-off" fails; release of link
	TC_PT_MM_BV_CH_12	Cipher switching; FT initiated; "cipher-off" to "cipher-on" fails; release of link
	TC_PT_MM_BV_CH_13	Cipher switching; FT initiated; "cipher-off" to "cipher-on"; successful inter-cell bearer handover
	TC_PT_MM_BV_CH_14	Cipher switching; FT initiated; "cipher-off" to "cipher-on"; successful intra-cell bearer handover
	TC_PT_MM_BV_CH_15	Cipher switching; FT initiated; "cipher-off" to "cipher-on"; "cipher-on" to "cipher-off" fails; release of link
PT/MM/BO/	TC_PT_MM_BO_01	Location registration request; receipt of {ACCESS-RIGHTS-ACCEPT}; unexpected, ignore
PT/MM/BI/	TC_PT_MM_BI_01	Unrecognized message type; ignore
	TC_PT_MM_BI_02	"Cipher off"; {CIPHER-REQUEST}, with invalid <<Cipher info>>; reject
	TC_PT_MM_BI_03	Authentication of PT; {AUTH-REQUEST} missing <<RAND>>; reject
	TC_PT_MM_BI_04	Obtain access rights; {ACCESS-RIGHTS-ACCEPT}, wrong <<Portable id>>; ignore
PT/MM/TI/	TC_PT_MM_TI_01	Key allocation; timer P-<MM_auth.1> expiry ($\pm 5\%$ margin) (+ 5% margin)
	TC_PT_MM_TI_02	Authentication of FT; timer P-<MM_auth.1> expiry ($\pm 5\%$ margin)
	TC_PT_MM_TI_03	Location registration; just before timer P-<MM_locate.1> expiry ($\pm 5\%$ margin) (- 10% margin)
	TC_PT_MM_TI_04	Obtain access rights; just before timer P-<MM_access.1> expiry ($\pm 5\%$ margin) (- 10% margin)
	TC_PT_MM_TI_05	Cipher switching; IUT(PT) initiated; timer P-<MM_cipher.2> expiry ($\pm 5\%$ margin) (- 10% margin)
PT/ME/BV/	TC_PT_ME_BV_01	Outgoing call; T-01; Authentication of IUT(PT) performed before answering the setup request
	TC_PT_ME_BV_02	Cipher switching IUT(PT) initiated; Locate update; location registration initiation after "cipher off"
	TC_PT_ME_BV_03	Obtain access rights; Interrupted by Authentication of user
	TC_PT_ME_BV_04	Obtain access rights; Interrupted by Authentication of IUT(PT)
	TC_PT_ME_BV_05	Outgoing call and authentication of IUT(PT) in parallel
Test Case Index		
	TC_PT_ME_BV_06	Outgoing call and cipher switching FT initiated in parallel
	TC_PT_ME_BV_07	Outgoing call; T-01; Cipher switching FT initiated performed before answering the setup request
	TC_PT_ME_BV_08	Outgoing call; T-01; Authentication of user performed before answering the setup request; {CC-NOTIFY} restart timer handling
	TC_PT_ME_BV_09	Cipher on; Store DCK; new DCK not used in the current ciphering
	TC_PT_ME_BV_10	T-10; a38=1; location area changes; location registration request during the call or in T-00
	TC_PT_ME_BV_11	Outgoing call; T-01; Terminate access rights FT initiated performed before answering the setup request
	TC_PT_ME_BV_12	T-10; link fails; IUT clears the call
	TC_PT_ME_BV_13	Obtain access rights interrupted by key allocation

(continued)