

# ETSI TS 136 104 V16.17.0 (2026-02)



TECHNICAL SPECIFICATION

**LTE;  
Evolved Universal Terrestrial Radio Access (E-UTRA);  
Base Station (BS) radio transmission and reception  
(3GPP TS 36.104 version 16.17.0 Release 16)**

get full document from [standards.iteh.ai](https://standards.iteh.ai)



---

**Reference**

RTS/TSGR-0436104vgh0

---

**Keywords**

LTE

**ETSI**

---

650 Route des Lucioles  
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - APE 7112B  
Association à but non lucratif enregistrée à la  
Sous-Préfecture de Grasse (06) N° w061004871

---

**Important notice**

The present document can be downloaded from the  
[ETSI Search & Browse Standards](#) application.

The present document may be made available in electronic versions and/or in print. The content of any electronic and/or print versions of the present document shall not be modified without the prior written authorization of ETSI. In case of any existing or perceived difference in contents between such versions and/or in print, the prevailing version of an ETSI deliverable is the one made publicly available in PDF format on [ETSI deliver](#) repository.

Users should be aware that the present document may be revised or have its status changed, this information is available in the [Milestones listing](#).

If you find errors in the present document, please send your comments to the relevant service listed under [Committee Support Staff](#).

If you find a security vulnerability in the present document, please report it through our [Coordinated Vulnerability Disclosure \(CVD\)](#) program.

---

**Notice of disclaimer & limitation of liability**

The information provided in the present deliverable is directed solely to professionals who have the appropriate degree of experience to understand and interpret its content in accordance with generally accepted engineering or other professional standard and applicable regulations.

No recommendation as to products and services or vendors is made or should be implied.

No representation or warranty is made that this deliverable is technically accurate or sufficient or conforms to any law and/or governmental rule and/or regulation and further, no representation or warranty is made of merchantability or fitness for any particular purpose or against infringement of intellectual property rights.

In no event shall ETSI be held liable for loss of profits or any other incidental or consequential damages.

Any software contained in this deliverable is provided "AS IS" with no warranties, express or implied, including but not limited to, the warranties of merchantability, fitness for a particular purpose and non-infringement of intellectual property rights and ETSI shall not be held liable in any event for any damages whatsoever (including, without limitation, damages for loss of profits, business interruption, loss of information, or any other pecuniary loss) arising out of or related to the use of or inability to use the software.

---

**Copyright Notification**

No part may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm except as authorized by written permission of ETSI.

The content of the PDF version shall not be modified without the written authorization of ETSI.

The copyright and the foregoing restriction extend to reproduction in all media.

© ETSI 2026.  
All rights reserved.

---

# Intellectual Property Rights

## Essential patents

IPRs essential or potentially essential to normative deliverables may have been declared to ETSI. The declarations pertaining to these essential IPRs, if any, are publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: "*Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards*", which is available from the ETSI Secretariat. Latest updates are available on the [ETSI IPR online database](#).

Pursuant to the ETSI Directives including the ETSI IPR Policy, no investigation regarding the essentiality of IPRs, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

## Trademarks

The present document may include trademarks and/or tradenames which are asserted and/or registered by their owners. ETSI claims no ownership of these except for any which are indicated as being the property of ETSI, and conveys no right to use or reproduce any trademark and/or tradename. Mention of those trademarks in the present document does not constitute an endorsement by ETSI of products, services or organizations associated with those trademarks.

**DECT™**, **PLUGTESTS™**, **UMTS™** and the ETSI logo are trademarks of ETSI registered for the benefit of its Members. **3GPP™**, **LTE™** and **5G™** logo are trademarks of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners. **oneM2M™** logo is a trademark of ETSI registered for the benefit of its Members and of the oneM2M Partners. **GSM®** and the GSM logo are trademarks registered and owned by the GSM Association.

---

# Legal Notice

This Technical Specification (TS) has been produced by ETSI 3rd Generation Partnership Project (3GPP).

The present document may refer to technical specifications or reports using their 3GPP identities. These shall be interpreted as being references to the corresponding ETSI deliverables.

The cross reference between 3GPP and ETSI identities can be found at [3GPP to ETSI numbering cross-referencing](#).

---

# Modal verbs terminology

In the present document "**shall**", "**shall not**", "**should**", "**should not**", "**may**", "**need not**", "**will**", "**will not**", "**can**" and "**cannot**" are to be interpreted as described in clause 3.2 of the [ETSI Drafting Rules](#) (Verbal forms for the expression of provisions).

"**must**" and "**must not**" are **NOT** allowed in ETSI deliverables except when used in direct citation.

# Contents

Intellectual Property Rights .....	2
Legal Notice .....	2
Modal verbs terminology.....	2
Foreword.....	8
1 Scope .....	10
2 References .....	10
3 Definitions, symbols and abbreviations .....	11
3.1 Definitions .....	11
3.2 Symbols.....	14
3.3 Abbreviations .....	15
4 General .....	17
4.1 Relationship between minimum requirements and test requirements .....	17
4.2 Base station classes .....	17
4.3 Regional requirements.....	17
4.4 Applicability of requirements.....	18
4.5 Requirements for BS capable of multi-band operation .....	19
5 Operating bands and channel arrangement.....	20
5.1 General .....	20
5.2 Void.....	20
5.3 Void.....	20
5.4 Void.....	20
5.5 Operating bands.....	20
5.6 Channel bandwidth.....	24
5.7 Channel arrangement.....	28
5.7.1 Channel spacing.....	28
5.7.1A CA Channel spacing .....	28
5.7.2 Channel raster .....	29
5.7.3 Carrier frequency and EARFCN.....	29
5.7.4 EARFCN sets for Type B multi-carrier downlink transmissions and conversion to Type 2 channel access for multi-carrier uplink transmissions on multiple Scells configured in Band 46 .....	32
5.8 Requirements for contiguous and non-contiguous spectrum.....	33
6 Transmitter characteristics .....	33
6.1 General .....	33
6.2 Base station output power .....	34
6.2.1 Minimum requirement .....	35
6.2.2 Additional requirement (regional) .....	35
6.2.3 Home BS output power for adjacent UTRA channel protection.....	35
6.2.4 Home BS output power for adjacent E-UTRA channel protection.....	36
6.2.5 Home BS Output Power for co-channel E-UTRA protection.....	37
6.3 Output power dynamics.....	38
6.3.1 RE Power control dynamic range .....	38
6.3.1.1 Minimum requirements .....	38
6.3.2 Total power dynamic range .....	39
6.3.2.1 Minimum requirements .....	39
6.3.3 NB-IoT RB power dynamic range for in-band or guard band operation .....	39
6.3.3.1 Minimum Requirement .....	40
6.4 Transmit ON/OFF power .....	40
6.4.1 Transmitter OFF power .....	40
6.4.1.1 Minimum Requirement .....	40
6.4.2 Transmitter transient period.....	40
6.4.2.1 Minimum requirements.....	41
6.5 Transmitted signal quality .....	41

6.5.1	Frequency error.....	41
6.5.1.1	Minimum requirement .....	41
6.5.2	Error Vector Magnitude.....	42
6.5.3	Time alignment error .....	42
6.5.3.1	Minimum Requirement .....	42
6.5.4	DL RS power .....	43
6.5.4.1	Minimum requirements .....	43
6.6	Unwanted emissions.....	43
6.6.1	Occupied bandwidth .....	43
6.6.1.1	Minimum requirement .....	44
6.6.2	Adjacent Channel Leakage power Ratio (ACLR) .....	44
6.6.2.1	Minimum requirement .....	44
6.6.2.2	Cumulative ACLR requirement in non-contiguous spectrum.....	47
6.6.3	Operating band unwanted emissions .....	48
6.6.3.1	Minimum requirements for Wide Area BS (Category A).....	50
6.6.3.2	Minimum requirements for Wide Area BS (Category B).....	53
6.6.3.2.1	Category B requirements (Option 1) .....	53
6.6.3.2.2	Category B (Option 2).....	57
6.6.3.2A	Minimum requirements for Local Area BS (Category A and B) .....	59
6.6.3.2B	Minimum requirements for Home BS (Category A and B) .....	60
6.6.3.2C	Minimum requirements for Medium Range BS (Category A and B) .....	61
6.6.3.2D	Minimum requirements for Local Area and Medium Range BS in Band 46 (Category A and B).....	64
6.6.3.2E	Minimum requirements for standalone NB-IoT Wide Area BS.....	65
6.6.3.2F	Minimum requirements for standalone NB-IoT Local Area BS .....	65
6.6.3.2G	Minimum requirements for standalone NB-IoT Home BS (Category A and B).....	66
6.6.3.2H	Minimum requirements for standalone NB-IoT Medium Range BS .....	68
6.6.3.3	Additional requirements.....	69
6.6.4	Transmitter spurious emissions.....	74
6.6.4.1	Mandatory Requirements.....	75
6.6.4.1.1	Spurious emissions (Category A).....	75
6.6.4.1.2	Spurious emissions (Category B) .....	75
6.6.4.2	Protection of the BS receiver of own or different BS .....	75
6.6.4.2.1	Minimum Requirement .....	76
6.6.4.3	Additional spurious emissions requirements.....	76
6.6.4.3.1	Minimum Requirement .....	76
6.6.4.4	Co-location with other base stations .....	91
6.6.4.4.1	Minimum Requirement .....	91
6.7	Transmitter intermodulation.....	104
6.7.1	Minimum requirement .....	104
6.7.2	Additional requirement for Band 41 .....	105
7	Receiver characteristics .....	106
7.1	General .....	106
7.2	Reference sensitivity level.....	106
7.2.1	Minimum requirement .....	106
7.3	Dynamic range .....	111
7.3.1	Minimum requirement .....	112
7.4	In-channel selectivity .....	118
7.4.1	Minimum requirement .....	118
7.5	Adjacent Channel Selectivity (ACS) and narrow-band blocking.....	125
7.5.1	Minimum requirement .....	125
7.6	Blocking .....	136
7.6.1	General blocking requirement.....	136
7.6.1.1	Minimum requirement .....	136
7.6.2	Co-location with other base stations .....	152
7.6.2.1	Minimum requirement .....	152
7.6.3	Additional requirement (regional) .....	164
7.7	Receiver spurious emissions.....	164
7.7.1	Minimum requirement .....	164
7.8	Receiver intermodulation .....	165
7.8.1	Minimum requirement .....	165

8	Performance requirement .....	180
8.1	General .....	180
8.2	Performance requirements for PUSCH .....	180
8.2.1	Requirements in multipath fading propagation conditions .....	180
8.2.1.1	Minimum requirements .....	181
8.2.2	Requirements for UL timing adjustment .....	200
8.2.2.1	Minimum requirements .....	201
8.2.3	Requirements for high speed train .....	201
8.2.3.1	Minimum requirements .....	202
8.2.4	Requirements for HARQ-ACK multiplexed on PUSCH .....	205
8.2.4.1	Minimum requirement .....	205
8.2.5	Requirements for PUSCH with TTI bundling and enhanced HARQ pattern .....	206
8.2.5.1	Minimum requirements .....	207
8.2.6	Enhanced performance requirement type A in multipath fading propagation conditions with synchronous interference .....	207
8.2.6.1	Minimum requirements .....	208
8.2.6A	Enhanced performance requirement type A in multipath fading propagation conditions with asynchronous interference .....	209
8.2.6A.1	Minimum requirements .....	210
8.2.7	Requirements for PUSCH supporting coverage enhancement .....	212
8.2.8	Requirements for PUSCH of Frame structure type 3 .....	213
8.2.9	Enhanced performance requirement type B in multipath fading propagation conditions .....	214
8.2.9.1	Minimum requirements .....	216
8.2.10	Requirements for PUSCH supporting subPRB transmission .....	218
8.3	Performance requirements for PUCCH .....	220
8.3.1	DTX to ACK performance .....	220
8.3.1.1	Minimum requirement .....	220
8.3.2	ACK missed detection requirements for single user PUCCH format 1a .....	220
8.3.2.1	Minimum requirements .....	221
8.3.3	CQI performance requirements for PUCCH format 2 .....	221
8.3.3.1	Minimum requirements .....	221
8.3.4	ACK missed detection requirements for multi user PUCCH format 1a .....	222
8.3.4.1	Minimum requirement .....	222
8.3.5	ACK missed detection requirements for PUCCH format 1b with Channel Selection .....	222
8.3.5.1	Minimum requirements .....	223
8.3.6	ACK missed detection requirements for PUCCH format 3 .....	223
8.3.6.1	Minimum requirements .....	223
8.3.7	NACK to ACK requirements for PUCCH format 3 .....	224
8.3.7.1	Minimum requirement .....	224
8.3.8	CQI performance requirements for PUCCH format 2 with DTX detection .....	224
8.3.8.1	Minimum requirements .....	225
8.3.9	PUCCH performance requirements for coverage enhancement .....	225
8.3.9.1	DTX to ACK performance .....	225
8.3.9.1.1	Minimum requirement .....	225
8.3.9.2	ACK missed detection requirements for single user PUCCH format 1a .....	225
8.3.9.2.1	Minimum requirements .....	226
8.3.9.3	CQI performance requirements for PUCCH format 2 .....	226
8.3.9.3.1	Minimum requirements .....	226
8.3.10	ACK missed detection requirements for PUCCH format 4 .....	226
8.3.10.1	Minimum requirements .....	227
8.3.11	ACK missed detection requirements for PUCCH format 5 .....	227
8.3.11.1	Minimum requirements .....	227
8.4	Performance requirements for PRACH .....	228
8.4.1	PRACH False alarm probability .....	228
8.4.1.1	Minimum requirement .....	228
8.4.2	PRACH detection requirements .....	228
8.4.2.1	Minimum requirements .....	228
8.5	Performance requirements for Narrowband IoT .....	230
8.5.1	Requirements for NPUSCH format 1 .....	230
8.5.1.1	Requirements .....	230
8.5.1.1.1	Minimum requirements .....	231
8.5.2	Performance requirements for NPUSCH format 2 .....	232

8.5.2.1	DTX to ACK performance .....	232
8.5.2.1.1	Minimum requirement .....	232
8.5.2.2	ACK missed detection requirements .....	232
8.5.2.2.1	Minimum requirements .....	232
8.5.3	Performance requirements for NPRACH .....	233
8.5.3.1	NPRACH False alarm probability .....	233
8.5.3.1.1	Minimum requirement .....	233
8.5.3.2	NPRACH detection requirements .....	233
8.5.3.2.1	Minimum requirements .....	234
8.6	Performance requirements for subslot-PUSCH .....	234
8.6.1	Requirements .....	234
8.6.1.1	Minimum requirements .....	234
8.7	Performance requirements for SPUCCH .....	235
8.7.1	ACK missed detection requirements for single user SPUCCH format 1a .....	235
8.7.1.1	Minimum requirements .....	235
8.7.2	ACK missed detection requirements for SPUCCH format 4 .....	236
8.7.2.1	Minimum requirements .....	236
9	Void .....	237
<b>Annex A (normative): Reference measurement channels .....</b>		<b>238</b>
A.1	Fixed Reference Channels for reference sensitivity and in-channel selectivity (QPSK, R=1/3) .....	239
A.2	Fixed Reference Channels for dynamic range (16QAM, R=2/3) .....	240
A.3	Fixed Reference Channels for performance requirements (QPSK 1/3) .....	240
A.4	Fixed Reference Channels for performance requirements (16QAM 3/4) .....	241
A.5	Fixed Reference Channels for performance requirements (64QAM 5/6) .....	241
A.6	PRACH Test preambles .....	241
A.7	Fixed Reference Channels for UL timing adjustment (Scenario 1) .....	242
A.8	Fixed Reference Channels for UL timing adjustment (Scenario 2) .....	243
A.9	Multi user PUCCH test .....	243
A.10	PUCCH transmission on two antenna ports test .....	243
A.11	Fixed Reference Channel for PUSCH with TTI bundling and enhanced HARQ pattern .....	244
A.12	Fixed Reference Channels for performance requirements (QPSK 0.36) .....	244
A.13	Fixed Reference Channels for performance requirements (16QAM 1/2) .....	245
A.14	Fixed Reference Channels for NB-IOT reference sensitivity ( $\pi/2$ BPSK, R=1/3) .....	245
A.15	Fixed Reference Channels for NB-IoT dynamic range ( $\pi/4$ QPSK, R=2/3) .....	245
A.16	Fixed Reference Channels for NB-IoT NPUSCH format 1 .....	246
A.16.1	One PRB .....	246
A.17	Fixed Reference Channels for performance requirements (256QAM 5/6) .....	247
A.18	Fixed Reference Channels for PUSCH transmission in UpPTS (16QAM 0.65) .....	247
A.19	Fixed Reference Channels for PUSCH transmission in UpPTS (256QAM 0.69) .....	248
A.20	Fixed Reference Channels for PUSCH of Frame structure type 3 .....	248
A.21	Fixed Reference Channels for performance requirements (QPSK 3/5) .....	249
A.22	Fixed Reference Channels for performance requirements (64QAM 1/2) .....	250
A.23	Fixed Reference Channels for SubPRB allocation reference sensitivity ( $\pi/2$ BPSK, R=1/3) .....	250
A.24	Fixed Reference Channel for subslot-PUSCH .....	251
A.25	Fixed Reference Channels for PUSCH with SubPRB transmission .....	251

<b>Annex B (normative):</b>	<b>Propagation conditions.....</b>	<b>252</b>
B.1	Static propagation condition.....	252
B.2	Multi-path fading propagation conditions.....	252
B.3	High speed train condition .....	253
B.4	Moving propagation conditions.....	257
B.5	Multi-Antenna channel models .....	258
B.5.1	Definition of MIMO Correlation Matrices.....	258
B.5.2	MIMO Correlation Matrices at High, Medium and Low Level .....	259
B.5A	Multi-Antenna channel models using cross polarized antennas.....	261
B.5A.1	Definition of MIMO Correlation Matrices using cross polarized antennas.....	262
B.5A.2	Spatial Correlation Matrices at UE and eNB sides.....	262
B.5A.2.1	Spatial Correlation Matrices at UE side.....	262
B.5A.2.2	Spatial Correlation Matrices at eNB side.....	263
B.5A.3	MIMO Correlation Matrices using cross polarized antennas .....	263
B.6	Interference model for enhanced performance requirements type A and type B .....	263
B.6.1	Dominant interferer proportion .....	263
B.6.2	Interference model for synchronous scenario.....	264
B.6.3	Interference model for asynchronous scenario .....	264
<b>Annex C (normative):</b>	<b>Characteristics of the interfering signals.....</b>	<b>265</b>
<b>Annex D (normative):</b>	<b>Environmental requirements for the BS equipment .....</b>	<b>266</b>
<b>Annex E (normative):</b>	<b>Error Vector Magnitude .....</b>	<b>267</b>
E.1	Reference point for measurement.....	267
E.2	Basic unit of measurement .....	267
E.3	Modified signal under test.....	268
E.4	Estimation of frequency offset .....	268
E.5	Estimation of time offset .....	268
E.5.1	Window length .....	269
E.6	Estimation of TX chain amplitude and frequency response parameters .....	271
E.7	Averaged EVM .....	272
<b>Annex F (Informative):</b>	<b>Unwanted emission requirements for multi-carrier BS.....</b>	<b>274</b>
F.1	General .....	274
F.2	Multi-carrier BS of different E-UTRA channel bandwidths.....	274
F.3	Multi-carrier BS of E-UTRA and UTRA.....	274
<b>Annex G (Informative):</b>	<b>Regional requirement for protection of DTT .....</b>	<b>275</b>
G.1	Regional requirement for protection of DTT .....	275
G.2	Regional requirement for Public Safety LTE BS in Korea .....	275
<b>Annex H (Informative):</b>	<b>Calculation of EIRP based on manufacturer declarations and site specific conditions .....</b>	<b>278</b>
H.1	Calculation of EIRP based on manufacturer declarations and site specific conditions.....	278
<b>Annex I (Informative):</b>	<b>Change history .....</b>	<b>279</b>
History .....		294

---

# Foreword

This Technical Specification has been produced by the 3rd Generation Partnership Project (3GPP).

The contents of the present document are subject to continuing work within the TSG and may change following formal TSG approval. Should the TSG modify the contents of the present document, it will be re-released by the TSG with an identifying change of release date and an increase in version number as follows:

Version x.y.z

where:

- x the first digit:
  - 1 presented to TSG for information;
  - 2 presented to TSG for approval;
  - 3 or greater indicates TSG approved document under change control.
- y the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- z the third digit is incremented when editorial only changes have been incorporated in the document.

In the present document, modal verbs have the following meanings:

**shall** indicates a mandatory requirement to do something

**shall not** indicates an interdiction (prohibition) to do something

The constructions "shall" and "shall not" are confined to the context of normative provisions, and do not appear in Technical Reports.

The constructions "must" and "must not" are not used as substitutes for "shall" and "shall not". Their use is avoided insofar as possible, and they are not used in a normative context except in a direct citation from an external, referenced, non-3GPP document, or so as to maintain continuity of style when extending or modifying the provisions of such a referenced document.

**should** indicates a recommendation to do something

**should not** indicates a recommendation not to do something

**may** indicates permission to do something

**need not** indicates permission not to do something

The construction "may not" is ambiguous and is not used in normative elements. The unambiguous constructions "might not" or "shall not" are used instead, depending upon the meaning intended.

**can** indicates that something is possible

**cannot** indicates that something is impossible

The constructions "can" and "cannot" are not substitutes for "may" and "need not".

**will** indicates that something is certain or expected to happen as a result of action taken by an agency the behaviour of which is outside the scope of the present document

**will not** indicates that something is certain or expected not to happen as a result of action taken by an agency the behaviour of which is outside the scope of the present document

**might** indicates a likelihood that something will happen as a result of action taken by some agency the behaviour of which is outside the scope of the present document

**might not** indicates a likelihood that something will not happen as a result of action taken by some agency the behaviour of which is outside the scope of the present document

In addition:

**is** (or any other verb in the indicative mood) indicates a statement of fact

**is not** (or any other negative verb in the indicative mood) indicates a statement of fact

The constructions "is" and "is not" do not indicate requirements.

# Sample Document

get full document from [standards.iteh.ai](https://standards.iteh.ai)

---

# 1 Scope

The present document establishes the minimum RF characteristics and minimum performance requirements of E-UTRA, E-UTRA with NB-IoT or NB-IoT Base Station (BS).

---

# 2 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- References are either specific (identified by date of publication, edition number, version number, etc.) or non-specific.
- For a specific reference, subsequent revisions do not apply.
- For a non-specific reference, the latest version applies. In the case of a reference to a 3GPP document (including a GSM document), a non-specific reference implicitly refers to the latest version of that document *in the same Release as the present document*.

- [1] 3GPP TR 21.905: "Vocabulary for 3GPP Specifications".
- [2] ITU-R Recommendation SM.329: "Unwanted emissions in the spurious domain".
- [3] ITU-R Recommendation M.1545: "Measurement uncertainty as it applies to test limits for the terrestrial component of International Mobile Telecommunications-2000".
- [4] 3GPP TS 36.141: "Evolved Universal Terrestrial Radio Access (E-UTRA); Base Station (BS) conformance testing".
- [5] ITU-R recommendation SM.328: "Spectra and bandwidth of emissions".
- [6] 3GPP TS 25.104: "Base Station (BS) radio transmission and reception (FDD)".
- [7] 3GPP TS 25.105: "Base Station (BS) radio transmission and reception (TDD)".
- [8] 3GPP TR 25.942: "RF system scenarios".
- [9] 3GPP TR 36.942: "E-UTRA RF system scenarios".
- [10] 3GPP TS 36.211: "Evolved Universal Terrestrial Radio Access (E-UTRA); Physical Channels and Modulation".
- [11] 3GPP TS 36.213: "Evolved Universal Terrestrial Radio Access (E-UTRA); Physical layer procedures".
- [12] ECC/DEC/(09)03 "Harmonised conditions for MFCN in the band 790-862 MHz", 30 Oct. 2009
- [13] IEC 60721-3-3 (2002): "Classification of environmental conditions - Part 3: Classification of groups of environmental parameters and their severities - Section 3: Stationary use at weather protected locations".
- [14] IEC 60721-3-4 (1995): "Classification of environmental conditions - Part 3: Classification of groups of environmental parameters and their severities - Section 4: Stationary use at non-weather protected locations".
- [15] 3GPP TS 37.104: "E-UTRA, UTRA and GSM/EDGE; Multi-Standard Radio (MSR) Base Station (BS) radio transmission and reception".
- [16] CEPT ECC Decision (13)03, "The harmonised use of the frequency band 1452-1492 MHz for Mobile/Fixed Communications Networks Supplemental Downlink (MFCN SDL)".
- [17] 3GPP TS 36.211: "Evolved Universal Terrestrial Radio Access (E-UTRA); Physical channels and modulation".

- [18] 3GPP TS 36.213: "Evolved Universal Terrestrial Radio Access (E-UTRA); Physical layer procedures".
- [19] CEPT ECC Decision (17)06, "The harmonised use of the frequency bands 1427-1452 MHz and 1492-1518 MHz for Mobile/Fixed Communications Networks Supplemental Downlink (MFCN SDL)".
- [20] 3GPP TS 37.213: "Physical layer procedures for shared spectrum channel access".

---

## 3 Definitions, symbols and abbreviations

### 3.1 Definitions

For the purposes of the present document, the terms and definitions given in TR 21.905 [1] and the following apply. A term defined in the present document takes precedence over the definition of the same term, if any, in TR 21.905 [1].

**Aggregated Channel Bandwidth:** RF bandwidth in which a base station transmits and/or receives multiple contiguously aggregated carriers.

NOTE: The Aggregated Channel Bandwidth is measured in MHz.

**Base station receive period:** time during which the base station is receiving data subframes or UpPTS.

**Base Station RF Bandwidth:** RF bandwidth in which a base station transmits and/or receives single or multiple carrier(s) within a supported operating band.

NOTE: In single E-UTRA carrier operation, the Base Station RF Bandwidth is equal to the channel bandwidth.

**Base Station RF Bandwidth edge:** frequency of one of the edges of the Base Station RF Bandwidth.

**Carrier:** modulated waveform conveying the E-UTRA or UTRA physical channels

**Carrier aggregation:** aggregation of two or more component carriers in order to support wider transmission bandwidths

**Carrier aggregation band:** a set of one or more operating bands across which multiple carriers are aggregated with a specific set of technical requirements.

NOTE: Carrier aggregation band(s) for an E-UTRA BS is declared by the manufacturer according to the designations in Tables 5.5-2 to 5.5-4.

**Channel bandwidth:** RF bandwidth supporting a single E-UTRA RF carrier with the transmission bandwidth configured in the uplink or downlink of a cell.

NOTE: The channel bandwidth is measured in MHz and is used as a reference for transmitter and receiver RF requirements.

**Channel edge:** lowest or highest frequency of the E-UTRA carrier, separated by the channel bandwidth.

**Contiguous carriers:** set of two or more carriers configured in a spectrum block where there are no RF requirements based on co-existence for un-coordinated operation within the spectrum block.

**Contiguous spectrum:** spectrum consisting of a contiguous block of spectrum with no sub-block gap(s).

**DL RS power:** resource element power of Downlink Reference Symbol.

**DL NRS power:** resource element power of Downlink Narrowband Reference Signal.

**Downlink operating band:** part of the operating band designated for downlink.

**Enhanced performance requirements type A:** This defines performance requirements assuming baseline receiver as demodulation reference signal based linear minimum mean square error interference rejection combining.

**Enhanced performance requirements type B:** This defines performance requirements assuming baseline receiver as code word level interference cancellation for intra-cell inter-user interference plus demodulation reference signal based linear minimum mean square error interference rejection combining for inter-cell interference.

**Highest carrier:** carrier with the highest carrier centre frequency transmitted/received in a specified operating band.

**Inter RF Bandwidth gap:** frequency gap between two consecutive Base Station RF Bandwidths that are placed within two supported operating bands.

**Inter-band carrier aggregation:** carrier aggregation of component carriers in different operating bands.

NOTE: Carriers aggregated in each band can be contiguous or non-contiguous.

**Inter-band gap:** The frequency gap between two supported consecutive operating bands.

**Intra-band contiguous carrier aggregation:** contiguous carriers aggregated in the same operating band.

**Intra-band non-contiguous carrier aggregation:** non-contiguous carriers aggregated in the same operating band.

**Lower sub-block edge:** frequency at the lower edge of one sub-block.

NOTE: It is used as a frequency reference point for both transmitter and receiver requirements.

**Lowest carrier:** carrier with the lowest carrier centre frequency transmitted/received in a specified operating band.

**Maximum output power:** mean power level per carrier of the base station measured at the antenna connector in a specified reference condition.

**Maximum throughput:** maximum achievable throughput for a reference measurement channel.

**Mean power:** power measured in the channel bandwidth of the carrier.

NOTE: The period of measurement shall be at least one subframe (1ms), unless otherwise stated.

**Measurement bandwidth:** RF bandwidth in which an emission level is specified.

**Multi-band base station:** base station characterized by the ability of its transmitter and/or receiver to process two or more carriers in common active RF components simultaneously, where at least one carrier is configured at a different operating band (which is not a sub-band or superseding-band of another supported operating band) than the other carrier(s).

**Multi-band transmitter:** transmitter characterized by the ability to process two or more carriers in common active RF components simultaneously, where at least one carrier is configured at a different operating band (which is not a sub-band or superseding-band of another supported operating band) than the other carrier(s).

**Multi-band receiver:** receiver characterized by the ability to process two or more carriers in common active RF components simultaneously, where at least one carrier is configured at a different operating band (which is not a sub-band or superseding-band of another supported operating band) than the other carrier(s).

**Multi-carrier transmission configuration:** set of one or more contiguous or non-contiguous carriers that a BS is able to transmit simultaneously according to the manufacturer's specification.

**NB-IoT In-band operation:** NB-IoT is operating in-band when it utilizes the resource block(s) within a normal E-UTRA carrier

**NB-IoT guard band operation:** NB-IoT is operating in guard band when it utilizes the unused resource block(s) within a E-UTRA carrier's guard-band.

**NB-IoT standalone operation:** NB-IoT is operating standalone when it utilizes its own spectrum, for example the spectrum currently being used by GERAN systems as a replacement of one or more GSM carriers, as well as scattered spectrum for potential IoT deployment.

**Non-contiguous spectrum:** spectrum consisting of two or more sub-blocks separated by sub-block gap(s).

**Occupied bandwidth:** width of a frequency band such that, below the lower and above the upper frequency limits, the mean powers emitted are each equal to a specified percentage  $\beta/2$  of the total mean power of a given emission.

**Operating band:** frequency range in which E-UTRA operates (paired or unpaired), that is defined with a specific set of technical requirements.

NOTE: The operating band(s) for an E-UTRA BS is declared by the manufacturer according to the designations in table 5.5-1.

**Output power:** mean power of one carrier of the base station, delivered to a load with resistance equal to the nominal load impedance of the transmitter.

**Radio Bandwidth:** frequency difference between the upper edge of the highest used carrier and the lower edge of the lowest used carrier.

**Rated output power:** mean power level per carrier that the manufacturer has declared to be available at the antenna connector during the transmitter ON period.

**RE power control dynamic range:** difference between the power of a RE and the average RE power for a BS at maximum output power for a specified reference condition.

**RRC filtered mean power:** mean power of an UTRA carrier as measured through a root raised cosine filter with roll-off factor  $\alpha$  and a bandwidth equal to the chip rate of the radio access mode.

NOTE 1: The RRC filtered mean power of a perfectly modulated UTRA signal is 0.246 dB lower than the mean power of the same signal.

**sTTI:** A transmission time interval (TTI) of either one slot or one subslot as defined in [10] on either uplink or downlink.

**Sub-band:** A sub-band of an operating band contains a part of the uplink and downlink frequency range of the operating band.

**Sub-block:** one contiguous allocated block of spectrum for transmission and reception by the same base station.

NOTE: There may be multiple instances of sub-blocks within a Base Station RF Bandwidth.

**Sub-block bandwidth:** bandwidth of one sub-block.

**Sub-block gap:** frequency gap between two consecutive sub-blocks within a Base Station RF Bandwidth, where the RF requirements in the gap are based on co-existence for un-coordinated operation.

**Superseding-band:** A superseding-band of an operating band includes the whole of the uplink and downlink frequency range of the operating band.

**Synchronized operation:** operation of TDD in two different systems, where no simultaneous uplink and downlink occur.

**Throughput:** number of payload bits successfully received per second for a reference measurement channel in a specified reference condition.

**Total power dynamic range:** difference between the maximum and the minimum transmit power of an OFDM symbol for a specified reference condition.

**Transmission bandwidth:** RF Bandwidth of an instantaneous transmission from a UE or BS, measured in resource block units.

**Transmission bandwidth configuration:** highest transmission bandwidth allowed for uplink or downlink in a given channel bandwidth, measured in resource block units.

**Transmitter ON period:** time period during which the BS transmitter is transmitting data and/or reference symbols, i.e. data subframes or DwPTS.

**Transmitter OFF period:** time period during which the BS transmitter is not allowed to transmit.

**Transmitter transient period:** time period during which the transmitter is changing from the OFF period to the ON period or vice versa.

**Unsynchronized operation:** operation of TDD in two different systems, where the conditions for synchronized operation are not met.

**Uplink operating band:** part of the operating band designated for uplink.

**Upper sub-block edge:** frequency at the upper edge of one sub-block.

NOTE: It is used as a frequency reference point for both transmitter and receiver requirements.

## 3.2 Symbols

For the purposes of the present document, the following symbols apply:

$\alpha$	Roll-off factor
$\beta$	Percentage of the mean transmitted power emitted outside the occupied bandwidth on the assigned channel
BW	Bandwidth
$BW_{\text{Channel}}$	Channel bandwidth
$BW_{\text{Channel,CA}}$	Aggregated Channel Bandwidth, expressed in MHz. $BW_{\text{Channel,CA}} = F_{\text{edge,high}} - F_{\text{edge,low}}$ .
$BW_{\text{Channel,block}}$	Sub-block bandwidth, expressed in MHz. $BW_{\text{Channel,block}} = F_{\text{edge,block,high}} - F_{\text{edge,block,low}}$ .
$BW_{\text{Config}}$	Transmission bandwidth configuration, expressed in MHz, where $BW_{\text{Config}} = N_{\text{RB}} \times 180$ kHz in the uplink and $BW_{\text{Config}} = 15$ kHz + $N_{\text{RB}} \times 180$ kHz in the downlink.
CA_X	Intra-band contiguous CA of component carriers in one sub-block within band X where X is the applicable E-UTRA operating band
CA_X-X	Intra-band non-contiguous CA of component carriers in two sub-blocks within band X where X is the applicable E-UTRA operating band
CA_X-Y	Inter-band CA of component carrier(s) in one sub-block within band X and component carrier(s) in one sub-block within Band Y where X and Y are the applicable E-UTRA operating bands
CA_X-X-Y	CA of component carriers in two sub-blocks within Band X and component carrier(s) in one sub-block within Band Y where X and Y are the applicable E-UTRA operating bands
f	Frequency
$\Delta f$	Separation between the channel edge frequency and the nominal -3dB point of the measuring filter closest to the carrier frequency
$\Delta f_{\text{max}}$	The largest value of $\Delta f$ used for defining the requirement
$F_{\text{C}}$	Carrier centre frequency
$F_{\text{C,block,high}}$	Centre frequency of the highest transmitted/received carrier in a sub-block.
$F_{\text{C,block,low}}$	Centre frequency of the lowest transmitted/received carrier in a sub-block.
$F_{\text{C,low}}$	The carrier centre frequency of the lowest carrier, expressed in MHz.
$F_{\text{C,high}}$	The carrier centre frequency of the highest carrier, expressed in MHz.
$F_{\text{edge,low}}$	The lower edge of Aggregated Channel Bandwidth, expressed in MHz. $F_{\text{edge,low}} = F_{\text{C,low}} - F_{\text{offset}}$ .
$F_{\text{edge,high}}$	The upper edge of Aggregated Channel Bandwidth, expressed in MHz. $F_{\text{edge,high}} = F_{\text{C,high}} + F_{\text{offset}}$ .
$F_{\text{edge,block,low}}$	The lower sub-block edge, where $F_{\text{edge,block,low}} = F_{\text{C,block,low}} - F_{\text{offset}}$ .
$F_{\text{edge,block,high}}$	The upper sub-block edge, where $F_{\text{edge,block,high}} = F_{\text{C,block,high}} + F_{\text{offset}}$ .
$F_{\text{offset}}$	Frequency offset from $F_{\text{C,high}}$ to the upper Base Station RF Bandwidth edge, or from $F_{\text{C,block,high}}$ to the upper sub-block edge, or $F_{\text{C,low}}$ to the lower Base Station RF Bandwidth edge, or from $F_{\text{C,block,low}}$ to the lower sub-block edge.
$F_{\text{filter}}$	Filter centre frequency
$f_{\text{offset}}$	Separation between the channel edge frequency and the centre of the measuring filter
$f_{\text{offset,max}}$	The maximum value of $f_{\text{offset}}$ used for defining the requirement
$F_{\text{DL,low}}$	The lowest frequency of the downlink operating band
$F_{\text{DL,high}}$	The highest frequency of the downlink operating band
$F_{\text{UL,low}}$	The lowest frequency of the uplink operating band
$F_{\text{UL,high}}$	The highest frequency of the uplink operating band
$G_{\text{ant}}$	Net antenna gain
$M_{\text{DL}}$	Offset of NB-IoT Downlink channel number to Downlink EARFCN
$M_{\text{UL}}$	Offset of NB-IoT Uplink channel number to Uplink EARFCN
$N_{\text{ant}}$	Number of transmitter antennas
$N_{\text{DL}}$	Downlink EARFCN
$N_{\text{Offs-DL}}$	Offset used for calculating downlink EARFCN