ETSI TS 138 215 V19.2.0 (2026-02)



TECHNICAL SPECIFICATION

5G;
NR;
Physical layer measurements
(3GPP TS 38.215 version 19.2.0 Release 19)

Sample Document
get full document from standards.iteh.ai

Reference
RTS/TSGR-0138215vj20

Keywords
5G

ETSI

650 Route des Lucioles
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - APE 7112B
Association à but non lucratif enregistrée à la
Sous-Préfecture de Grasse (06) N° w061004871

Important notice

The present document can be downloaded from the
ETSI Search & Browse Standards application.

The present document may be made available in electronic versions and/or in print. The content of any electronic and/or print versions of the present document shall not be modified without the prior written authorization of ETSI. In case of any existing or perceived difference in contents between such versions and/or in print, the prevailing version of an ETSI deliverable is the one made publicly available in PDF format on ETSI deliver repository.

Users should be aware that the present document may be revised or have its status changed, this information is available in the Milestones listing.

If you find errors in the present document, please send your comments to the relevant service listed under Committee Support Staff.

If you find a security vulnerability in the present document, please report it through our Coordinated Vulnerability Disclosure (CVD) program.

Notice of disclaimer & limitation of liability

The information provided in the present deliverable is directed solely to professionals who have the appropriate degree of experience to understand and interpret its content in accordance with generally accepted engineering or other professional standard and applicable regulations.
No recommendation as to products and services or vendors is made or should be implied.
No representation or warranty is made that this deliverable is technically accurate or sufficient or conforms to any law and/or governmental rule and/or regulation and further, no representation or warranty is made of merchantability or fitness for any particular purpose or against infringement of intellectual property rights.
In no event shall ETSI be held liable for loss of profits or any other incidental or consequential damages.

Any software contained in this deliverable is provided "AS IS" with no warranties, express or implied, including but not limited to, the warranties of merchantability, fitness for a particular purpose and non-infringement of intellectual property rights and ETSI shall not be held liable in any event for any damages whatsoever (including, without limitation, damages for loss of profits, business interruption, loss of information, or any other pecuniary loss) arising out of or related to the use of or inability to use the software.

Copyright Notification

No part may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm except as authorized by written permission of ETSI.
The content of the PDF version shall not be modified without the written authorization of ETSI.
The copyright and the foregoing restriction extend to reproduction in all media.

© ETSI 2026.
All rights reserved.

Sample Document
get full document from standards.iteh.ai

ETSI TS 138 215 V19.2.0 (2026-02) • https://standards.iteh.ai/catalog/standards/etsi/5459796b-617d-4dbb-92ab-59ea75816f06/etsi-ts-138-215-v19-2-0-2026-02

Intellectual Property Rights

Essential patents

IPRs essential or potentially essential to normative deliverables may have been declared to ETSI. The declarations pertaining to these essential IPRs, if any, are publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: *"Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards"*, which is available from the ETSI Secretariat. Latest updates are available on the ETSI IPR online database.

Pursuant to the ETSI Directives including the ETSI IPR Policy, no investigation regarding the essentiality of IPRs, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

Trademarks

The present document may include trademarks and/or tradenames which are asserted and/or registered by their owners. ETSI claims no ownership of these except for any which are indicated as being the property of ETSI, and conveys no right to use or reproduce any trademark and/or tradename. Mention of those trademarks in the present document does not constitute an endorsement by ETSI of products, services or organizations associated with those trademarks.

DECT™, **PLUGTESTS™**, **UMTS™** and the ETSI logo are trademarks of ETSI registered for the benefit of its Members. **3GPP™**, **LTE™** and **5G™** logo are trademarks of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners. **oneM2M™** logo is a trademark of ETSI registered for the benefit of its Members and of the oneM2M Partners. **GSM®** and the GSM logo are trademarks registered and owned by the GSM Association.

Sample Document

Legal Notice

This Technical Specification (TS) has been produced by ETSI 3rd Generation Partnership Project (3GPP).

get full document from standards.iteh.ai

The present document may refer to technical specifications or reports using their 3GPP identities. These shall be interpreted as being references to the corresponding ETSI deliverables.

The cross reference between 3GPP and ETSI identities can be found at 3GPP to ETSI numbering cross-referencing.

Modal verbs terminology

In the present document "**shall**", "**shall not**", "**should**", "**should not**", "**may**", "**need not**", "**will**", "**will not**", "**can**" and "**cannot**" are to be interpreted as described in clause 3.2 of the ETSI Drafting Rules (Verbal forms for the expression of provisions).

"**must**" and "**must not**" are **NOT** allowed in ETSI deliverables except when used in direct citation.

ETSI TS 138 215 V19.2.0 (2026-02) • https://standards.iteh.ai/catalog/standards/etsi/5459796b-617d-4dbb-92ab-59ea75816f06/etsi-ts-138-215-v19-2-0-2026-02

Contents

Intellectual Property Rights 2
Legal Notice 2
Modal verbs terminology 2
Foreword 5
1 Scope 6
2 References 6
3 Definitions of terms, symbols and abbreviations 6
3.1 Terms 6
3.2 Symbols 7
3.3 Abbreviations 7
4 Control of UE/NG-RAN measurements 7
5 Measurement capabilities for NR 8
5.1 UE measurement capabilities 8
5.1.1 SS reference signal received power (SS-RSRP) 9
5.1.2 CSI reference signal received power (CSI-RSRP) 10
5.1.3 SS reference signal received quality (SS-RSRQ) 11
5.1.4 CSI reference signal received quality (CSI-RSRQ) 12
5.1.5 SS signal-to-noise and interference ratio (SS-SINR) 13
5.1.6 CSI signal-to-noise and interference ratio (CSI-SINR) 14
5.1.7 Void 14
5.1.8 Void 14
5.1.9 UE GNSS Timing of Cell Frames for UE positioning for E-UTRA 14
5.1.10 UE GNSS code measurements 15
5.1.11 UE GNSS carrier phase measurements 15
5.1.12 IEEE 802.11 WLAN RSSI 15
5.1.13 Reference signal time difference (RSTD) for E-UTRA 15
5.1.14 SFN and frame timing difference (SFTD) 16
5.1.15 E-UTRA RSRP 16
5.1.16 E-UTRA RSRQ 17
5.1.17 E-UTRA RS-SINR 17
5.1.18 SS reference signal received power per branch (SS-RSRPB) 18
5.1.19 SRS reference signal received power (SRS-RSRP) 18
5.1.20 CLI Received signal strength indicator (CLI-RSSI) 19
5.1.21 Received Signal Strength Indicator (RSSI) 19
5.1.22 PSBCH reference signal received power (PSBCH-RSRP) 19
5.1.23 PSSCH reference signal received power (PSSCH-RSRP) 20
5.1.24 PSCCH reference signal received power (PSCCH-RSRP) 20
5.1.25 Sidelink received signal strength indicator (SL RSSI) 21
5.1.26 Sidelink channel occupancy ratio (SL CR) 21
5.1.27 Sidelink channel busy ratio (SL CBR) 22
5.1.28 DL PRS reference signal received power (DL PRS-RSRP) 22
5.1.29 DL reference signal time difference (DL RSTD) 22
5.1.30 UE Rx – Tx time difference 23
5.1.31 SS reference signal antenna relative phase (SS-RSARP) 23
5.1.32 UTRA FDD CPICH RSCP 24
5.1.33 UTRA FDD carrier RSSI 24
5.1.34 UTRA FDD CPICH Ec/No 24
5.1.35 DL PRS reference signal received path power (DL PRS-RSRPP) 24
5.1.36 Sidelink PRS reference signal received power (SL PRS-RSRP) 25
5.1.37 Sidelink PRS reference signal received path power (SL PRS-RSRPP) 25
5.1.38 Sidelink relative time of arrival ($T_{SL-RTOA}$) 25
5.1.39 Sidelink angle of arrival (SL AoA) 26
5.1.40 Sidelink Rx – Tx time difference 26

Sample Document
Sample Document from standards.iteh.ai

ETSI TS 138 215 V19.2.0 (2026-02) • https://standards.iteh.ai/catalog/standards/etsi/5459796b-617d-4dbb-92ab-59ea75816f06/etsi-ts-138-215-v19-2-0-2026-02

5.1.41 Sidelink reference signal time difference (SL RSTD) 26
5.1.42 DL reference signal carrier phase (DL RSCP) 27
5.1.43 DL reference signal carrier phase difference (DL RSCPD) 27
5.1.44 Sidelink PRS received signal strength indicator (SL PRS-RSSI) 27
5.1.45 Time domain channel property (TDCP) 28
5.1.46 UE Rx – Tx time difference subframe offset 28
5.1.47 DL timing drift 28
5.1.48 Sidelink PRS channel occupancy ratio (SL PRS-CR) 28
5.1.49 Sidelink PRS channel busy ratio (SL PRS-CBR) 29
5.1.50 Coherent joint transmission calibration delay offset 29
5.1.51 Coherent joint transmission calibration frequency offset 30
5.1.52 Coherent joint transmission calibration phase offset 30
5.1.53 Low power reference signal received power (LP-RSRP) 30
5.1.54 Low power reference signal received quality (LP-RSRQ) 31
5.1.55 Squared Generalized Cosine Similarity (SGCS) 31
5.2 NG-RAN measurement abilities 31
5.2.1 SSS transmit power 32
5.2.2 UL Relative Time of Arrival ($T_{UL-RTOA}$) 32
5.2.3 gNB Rx – Tx time difference 32
5.2.4 UL Angle of Arrival (UL AoA) 33
5.2.5 UL SRS reference signal received power (UL SRS-RSRP) 33
5.2.6 UL SRS reference signal received path power (UL SRS-RSRPP) 34
5.2.7 Timing advance (T_{ADV}) 34
5.2.8 UL reference signal carrier phase (UL RSCP) 35
5.2.9 UL SRS time domain channel timing (UL SRS-TDCT) 35
5.2.10 UL SRS time domain channel power (UL SRS-TDCP) 36

Annex A (informative): Change history 37

History 41

Sample Document
get full document from standards.iteh.ai

ETSI TS 138 215 V19.2.0 (2026-02) • https://standards.iteh.ai/catalog/standards/etsi/5459796b-617d-4dbb-92ab-59ea75816f06/etsi-ts-138-215-v19-2-0-2026-02

Foreword

This Technical Specification has been produced by the 3rd Generation Partnership Project (3GPP).

The contents of the present document are subject to continuing work within the TSG and may change following formal TSG approval. Should the TSG modify the contents of the present document, it will be re-released by the TSG with an identifying change of release date and an increase in version number as follows:

Version x.y.z

where:

- x the first digit:
  - 1 presented to TSG for information;
  - 2 presented to TSG for approval;
  - 3 or greater indicates TSG approved document under change control.
- y the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- z the third digit is incremented when editorial only changes have been incorporated in the document.

Sample Document

get full document from standards.iteh.ai

ETSI TS 138 215 V19.2.0 (2026-02) • https://standards.iteh.ai/catalog/standards/etsi/5459796b-617d-4dbb-92ab-59ea75816f06/etsi-ts-138-215-v19-2-0-2026-02

1 Scope

The present document describes the physical layer measurements for NR.

2 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

[1] 3GPP TR 21.905: "Vocabulary for 3GPP Specifications"

[2] 3GPP TS 38.201: "NR; Physical Layer – General Description"

[3] 3GPP TS 38.211: "NR; Physical channels and modulation"

[4] 3GPP TS 38.212: "NR; Multiplexing and channel coding"

[5] 3GPP TS 38.213: "NR; Physical layer procedures for control channels"

[6] 3GPP TS 38.214: "NR; Physical layer procedures for data channels"

[7] 3GPP TS 38.321: "NR; Medium Access Control (MAC) protocol specification"

[8] 3GPP TS 38.331: "NR; Radio Resource Control (RRC); Protocol specification"

[9] 3GPP TS 38.104: "NR; Base Station (BS) radio transmission and reception"

[10] 3GPP TS 36.331: "Evolved Universal Terrestrial Radio Access (E-UTRA); Radio Resource Control (RRC); Protocol specification"

[11] IEEE 802.11, Part 11: "Wireless LAN Medium Access Control (MAC) and Physical Layer (PHY) specifications, IEEE Std."

[12] 3GPP TS 38.133: "NR; Requirements for support of radio resource management"

[13] 3GPP TS 36.211: "Evolved Universal Terrestrial Radio Access (E-UTRA); Physical channels and modulation"

[14] 3GPP TS 38.509: "5GS; Special conformance testing functions for User Equipment (UE)"

[15] 3GPP TS 38.901: "Study on channel model for frequencies from 0.5 to 100 GHz"

[16] 3GPP TS 38.455: "NR Positioning Protocol A (NRPPa)"

[17] 3GPP TS 37.213: "Physical layer procedures for shared spectrum channel access"

[18] 3GPP TS 38.305: "NG Radio Access Network (NG-RAN); Stage 2 functional specification of User Equipment (UE) positioning in NG-RAN"

[19] 3GPP TS 38.108: "Satellite Access Node radio transmission and reception"

Sample Document
det full document from standards.iteh.ai

3 Definitions of terms, symbols and abbreviations

3.1 Terms

For the purposes of the present document, the terms and definitions given in TR 21.905 [1] and the following apply. A term defined in the present document takes precedence over the definition of the same term, if any, in TR 21.905 [1].

ETSI TS 138 215 V19.2.0 (2026-02) • https://standards.iteh.ai/catalog/standards/etsi/5459796b-617d-4dbb-92ab-59ea75816f06/etsi-ts-138-215-v19-2-0-2026-02

3.2 Symbols

For the purposes of the present document, the following symbols apply:

3.3 Abbreviations

For the purposes of the present document, the abbreviations given in TR 21.905 [1] and the following apply. An abbreviation defined in the present document takes precedence over the definition of the same abbreviation, if any, in TR 21.905 [1].

ARFCN	Absolute Radio-Frequency Channel Number
CLI	Cross Link Interference
CSI-RSRP	CSI Reference Signal Received Power
CSI-RSRQ	CSI Reference Signal Received Quality
E-UTRAN	Evolved UTRAN
GNSS	Global Navigation Satellite System
GSM	Global System for Mobile communication
LBT	Listen Before Talk
SRS	Sounding Reference Signal
SS-RSRP	Synchronization Signal Reference Signal Received Power
SS-RSRQ	Synchronization Signal Reference Signal Received Quality
UTRAN	Universal Terrestrial Radio Access Network

4 Control of UE/NG-RAN measurements

Sample Document
Content Segment from Standards.iteh.ai

In this clause the general measurement control concept of the higher layers is briefly described to provide an understanding on how L1 measurements are initiated and controlled by higher layers.

With the measurement specifications L1 provides measurement capabilities for the UE and NG-RAN. These measurements can be classified in different reported measurement types: intra-frequency, inter-frequency, inter-system, traffic volume, quality and UE internal measurements.

In the L1 measurement definitions, see clause 5, the measurements are categorised as measurements in the UE or measurements in the NG-RAN.

ETSI TS 138 215 V19.2.0 (2026-02) • https://standards.iteh.ai/catalog/standards/etsi/5459796b-617d-4dbb-92ab-59ea75816f06/etsi-ts-138-215-v19-2-0-2026-02

5 Measurement capabilities for NR

5.1 UE measurement capabilities

The structure of the table defining a UE measurement quantity is shown below.

Column field	Comment
Definition	Contains the definition of the measurement.
Applicable for	States in which state(s) it shall be possible to perform this measurement. The following terms are used in the tables: RRC_IDLE; RRC_INACTIVE; RRC_CONNECTED; Intra-frequency appended to the RRC state: Shall be possible to perform in the corresponding RRC state on an intra-frequency cell; Inter-frequency appended to the RRC state: Shall be possible to perform in the corresponding RRC state on an inter-frequency cell Inter-RAT appended to the RRC state: Shall be possible to perform in the corresponding RRC state on an inter-RAT cell. If sidelink: it shall be possible to perform this measurement on sidelink.

Sample Document
get full document from standards.iteh.ai

ETSI TS 138 215 V19.2.0 (2026-02) • https://standards.iteh.ai/catalog/standards/etsi/5459796b-617d-4dbb-92ab-59ea75816f06/etsi-ts-138-215-v19-2-0-2026-02

5.1.1 SS reference signal received power (SS-RSRP)

Definition	SS reference signal received power (SS-RSRP) is defined as the linear average over the power contributions (in [W]) of the resource elements that carry secondary synchronization signals. The measurement time resource(s) for SS-RSRP are confined within SS/PBCH Block Measurement Time Configuration (SMTC) window duration, except when measurement is being performed by wake-up receiver (WUR). If SS-RSRP is used for L1-RSRP as configured by reporting configurations as defined in TS 38.214 [6], the measurement time resources(s) restriction by SMTC window duration is not applicable. For SS-RSRP determination demodulation reference signals for physical broadcast channel (PBCH) and, if indicated by higher layers, CSI reference signals in addition to secondary synchronization signals may be used. SS-RSRP using demodulation reference signal for PBCH or CSI reference signal shall be measured by linear averaging over the power contributions of the resource elements that carry corresponding reference signals taking into account power scaling for the reference signals as defined in TS 38.213 [5]. If SS-RSRP is not used for L1-RSRP, the additional use of CSI reference signals for SS-RSRP determination is not applicable. SS-RSRP shall be measured only among the reference signals corresponding to SS/PBCH blocks with the same SS/PBCH block index and the same physical-layer cell identity. If SS-RSRP is not used for L1-RSRP and higher-layers indicate certain SS/PBCH blocks for performing SS-RSRP measurements, then SS-RSRP is measured only from the indicated set of SS/PBCH block(s). For frequency range 1, the reference point for the SS-RSRP shall be the antenna connector of the UE. For frequency range 2, SS-RSRP shall be measured based on the combined signal from antenna elements corresponding to a given receiver branch. For frequency range 1 and 2, if receiver diversity is in use by the UE, the reported SS-RSRP value shall not be lower than the corresponding SS-RSRP of any of the individual receiver branches.
Applicable for	If SS-RSRP is used for L1-RSRP or predicted RSRP, RRC_CONNECTED intra-frequency. If SS-RSRP is being performed by wake-up receiver (WUR), RRC_IDLE for serving cell, RRC_INACTIVE for serving cell. Otherwise, RRC_IDLE intra-frequency, RRC_IDLE inter-frequency, RRC_INACTIVE intra-frequency, RRC_INACTIVE inter-frequency, RRC_CONNECTED intra-frequency, RRC_CONNECTED inter-frequency

NOTE 1: The number of resource elements within the measurement period that are used by the UE to determine SS-RSRP is left up to the UE implementation with the limitation that corresponding measurement accuracy requirements have to be fulfilled.

NOTE 2: The power per resource element is determined from the energy received during the useful part of the symbol, excluding the CP.

Standards Document
getting document from standards.iteh.ai

ETSI TS 138 215 V19.2.0 (2026-02) • https://standards.iteh.ai/catalog/standards/etsi/5459796b-617d-4dbb-92ab-59ea75816f06/etsi-ts-138-215-v19-2-0-2026-02

5.1.2 CSI reference signal received power (CSI-RSRP)

Definition	CSI reference signal received power (CSI-RSRP), is defined as the linear average over the power contributions (in [W]) of the resource elements of the antenna port(s) that carry CSI reference signals configured for RSRP measurements within the considered measurement frequency bandwidth in the configured CSI-RS occasions. For CSI-RSRP determination CSI reference signals transmitted on antenna port 3000 according to TS 38.211 [3] shall be used. If CSI-RSRP is used for L1-RSRP, CSI reference signals transmitted on antenna ports 3000, 3001 can be used for CSI-RSRP determination. For intra-frequency CSI-RSRP measurements, if the measurement gap is not configured, UE is not expected to measure the CSI-RS resource(s) outside of the active downlink bandwidth part. For frequency range 1, the reference point for the CSI-RSRP shall be the antenna connector of the UE. For frequency range 2, CSI-RSRP shall be measured based on the combined signal from antenna elements corresponding to a given receiver branch. For frequency range 1 and 2, if receiver diversity is in use by the UE, the reported CSI-RSRP value shall not be lower than the corresponding CSI-RSRP of any of the individual receiver branches.
Applicable for	If CSI-RSRP is used for L1-RSRP or predicted RSRP, RRC_CONNECTED intra-frequency. Otherwise, RRC_CONNECTED intra-frequency, RRC_CONNECTED inter-frequency

NOTE 1: The number of resource elements within the considered measurement frequency bandwidth and within the measurement period that are used by the UE to determine CSI-RSRP is left up to the UE implementation with the limitation that corresponding measurement accuracy requirements have to be fulfilled.

NOTE 2: The power per resource element is determined from the energy received during the useful part of the symbol, excluding the CP.

Sample Document
get full document from standards.iteh.ai

ETSI TS 138 215 V19.2.0 (2026-02) • https://standards.iteh.ai/catalog/standards/etsi/5459796b-617d-4dbb-92ab-59ea75816f06/etsi-ts-138-215-v19-2-0-2026-02

5.1.3 SS reference signal received quality (SS-RSRQ)

Definition	Secondary synchronization signal reference signal received quality (SS-RSRQ) is defined as the ratio of N×SS-RSRP / NR carrier RSSI, where N is the number of resource blocks in the NR carrier RSSI measurement bandwidth. The measurements in the numerator and denominator shall be made over the same set of resource blocks. NR carrier Received Signal Strength Indicator (NR carrier RSSI), comprises the linear average of the total received power (in [W]) observed only in certain OFDM symbols of measurement time resource(s), in the measurement bandwidth, over N number of resource blocks from all sources, including co-channel serving and non-serving cells, adjacent channel interference, thermal noise etc. For cell selection, according to Clause 4.1 of TS 38.133 [12], the measurement time resources(s) for NR Carrier RSSI are not constrained. Otherwise, the measurement time resource(s) for NR Carrier RSSI are confined within SS/PBCH Block Measurement Time Configuration (SMTC) window duration, except when measurement is being performed by wake-up receiver (WUR). If indicated by higher-layers, if measurement gap is not used, the NR Carrier RSSI is measured in slots within the SMTC window duration that are indicated by the higher layer parameter *measurementSlots* and in OFDM symbols given by Table 5.1.3-1 and, if measurement gap is used, the NR Carrier RSSI is measured in slots within the SMTC window duration that are indicated by the higher layer parameter *measurementSlots* and in OFDM symbols given by Table 5.1.3-1 that are overlapped with the measurement gap, which is defined in TS38.133 [12]. - For intra-frequency measurements, NR Carrier RSSI is measured with timing reference corresponding to the serving cell in the frequency layer - For inter-frequency measurements, NR Carrier RSSI is measured with timing reference corresponding to any cell in the target frequency layer Otherwise not indicated by higher-layers, if measurement gap is not used, NR Carrier RSSI is measured from OFDM symbols within SMTC window duration and, if measurement gap is used, NR Carrier RSSI is measured from OFDM symbols corresponding to overlapped time span between SMTC window duration and the measurement gap. If higher-layers indicate certain SS/PBCH blocks for performing SS-RSRQ measurements, then SS-RSRP is measured only from the indicated set of SS/PBCH block(s). For frequency range 1, the reference point for the SS-RSRQ shall be the antenna connector of the UE. For frequency range 2, NR Carrier RSSI shall be measured based on the combined signal from antenna elements corresponding to a given receiver branch, where the combining for NR Carrier RSSI shall be the same as the one used for SS-RSRP measurements. For frequency range 1 and 2, if receiver diversity is in use by the UE, the reported SS-RSRQ value shall not be lower than the corresponding SS-RSRQ of any of the individual receiver branches.
Applicable for	If SS-RSRQ is being performed by wake-up receiver (WUR), RRC_IDLE for serving cell, RRC_INACTIVE for serving cell. Otherwise, RRC_IDLE intra-frequency, RRC_IDLE inter-frequency, RRC_INACTIVE intra-frequency, RRC_INACTIVE inter-frequency, RRC_CONNECTED intra-frequency, RRC_CONNECTED inter-frequency

Table 5.1.3-1: NR Carrier RSSI measurement symbols

OFDM signal indication *endSymbol*	Symbol indexes
0	{0,1}
1	For 480 kHz and 960 kHz {0,1,2,..,11,12}; otherwise {0,1,2,..,10,11}
2	{0,1,2,…, 5}
3	{0,1,2,…, 7}

ETSI TS 138 215 V19.2.0 (2026-02) • https://standards.iteh.ai/catalog/standards/etsi/5459796b-617d-4dbb-92ab-59ea75816f06/etsi-ts-138-215-v19-2-0-2026-02