

ETSI TS 138 304 V17.11.0 (2026-04)



TECHNICAL SPECIFICATION

**5G;
NR;
User Equipment (UE)
procedures in Idle mode and in RRC Inactive state
(3GPP TS 38.304 version 17.11.0 Release 17)**



Reference

RTS/TSGR-0238304vnb0

Keywords

5G

ETSI

650 Route des Lucioles
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - APE 7112B
Association à but non lucratif enregistrée à la
Sous-Préfecture de Grasse (06) N° w061004871

Important notice

The present document can be downloaded from the
[ETSI Search & Browse Standards](#) application.

The present document may be made available in electronic versions and/or in print. The content of any electronic and/or print versions of the present document shall not be modified without the prior written authorization of ETSI. In case of any existing or perceived difference in contents between such versions and/or in print, the prevailing version of an ETSI deliverable is the one made publicly available in PDF format on [ETSI deliver](#) repository.

Users should be aware that the present document may be revised or have its status changed, this information is available in the [Milestones listing](#).

If you find errors in the present document, please send your comments to the relevant service listed under [Committee Support Staff](#).

If you find a security vulnerability in the present document, please report it through our [Coordinated Vulnerability Disclosure \(CVD\)](#) program.

Notice of disclaimer & limitation of liability

The information provided in the present deliverable is directed solely to professionals who have the appropriate degree of experience to understand and interpret its content in accordance with generally accepted engineering or other professional standard and applicable regulations.

No recommendation as to products and services or vendors is made or should be implied.

No representation or warranty is made that this deliverable is technically accurate or sufficient or conforms to any law and/or governmental rule and/or regulation and further, no representation or warranty is made of merchantability or fitness for any particular purpose or against infringement of intellectual property rights.

In no event shall ETSI be held liable for loss of profits or any other incidental or consequential damages.

Any software contained in this deliverable is provided "AS IS" with no warranties, express or implied, including but not limited to, the warranties of merchantability, fitness for a particular purpose and non-infringement of intellectual property rights and ETSI shall not be held liable in any event for any damages whatsoever (including, without limitation, damages for loss of profits, business interruption, loss of information, or any other pecuniary loss) arising out of or related to the use of or inability to use the software.

Copyright Notification

No part may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm except as authorized by written permission of ETSI.

The content of the PDF version shall not be modified without the written authorization of ETSI.

The copyright and the foregoing restriction extend to reproduction in all media.

© ETSI 2026.
All rights reserved.

Intellectual Property Rights

Essential patents

IPRs essential or potentially essential to normative deliverables may have been declared to ETSI. The declarations pertaining to these essential IPRs, if any, are publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: "*Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards*", which is available from the ETSI Secretariat. Latest updates are available on the [ETSI IPR online database](#).

Pursuant to the ETSI Directives including the ETSI IPR Policy, no investigation regarding the essentiality of IPRs, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

Trademarks

The present document may include trademarks and/or tradenames which are asserted and/or registered by their owners. ETSI claims no ownership of these except for any which are indicated as being the property of ETSI, and conveys no right to use or reproduce any trademark and/or tradename. Mention of those trademarks in the present document does not constitute an endorsement by ETSI of products, services or organizations associated with those trademarks.

DECT™, **PLUGTESTS™**, **UMTS™** and the ETSI logo are trademarks of ETSI registered for the benefit of its Members. **3GPP™**, **LTE™** and **5G™** logo are trademarks of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners. **oneM2M™** logo is a trademark of ETSI registered for the benefit of its Members and of the oneM2M Partners. **GSM®** and the GSM logo are trademarks registered and owned by the GSM Association.

Legal Notice

This Technical Specification (TS) has been produced by ETSI 3rd Generation Partnership Project (3GPP).

The present document may refer to technical specifications or reports using their 3GPP identities. These shall be interpreted as being references to the corresponding ETSI deliverables.

The cross reference between 3GPP and ETSI identities can be found at [3GPP to ETSI numbering cross-referencing](#).

Modal verbs terminology

In the present document "**shall**", "**shall not**", "**should**", "**should not**", "**may**", "**need not**", "**will**", "**will not**", "**can**" and "**cannot**" are to be interpreted as described in clause 3.2 of the [ETSI Drafting Rules](#) (Verbal forms for the expression of provisions).

"**must**" and "**must not**" are **NOT** allowed in ETSI deliverables except when used in direct citation.

Contents

Intellectual Property Rights	2
Legal Notice	2
Modal verbs terminology.....	2
Foreword.....	5
1 Scope	6
2 References	6
3 Definitions, symbols and abbreviations	7
3.1 Definitions	7
3.2 Abbreviations	9
4 General description of RRC_IDLE state and RRC_INACTIVE state	10
4.1 Overview	10
4.2 Functional division between AS and NAS in RRC_IDLE state and RRC_INACTIVE state	12
4.3 Service types in RRC_IDLE state	15
4.4 Service types in RRC_INACTIVE state	15
4.5 Cell Categories	15
5 Process and procedure descriptions.....	16
5.1 PLMN selection and SNPN selection.....	16
5.1.1 Support for PLMN selection.....	17
5.1.1.1 General	17
5.1.1.2 NR case	17
5.1.1.3 E-UTRA case	17
5.1.2 Support for SNPN selection.....	17
5.1.2.1 General	17
5.1.2.2 NR case	17
5.2 Cell selection and reselection	18
5.2.1 Introduction.....	18
5.2.2 States and state transitions in RRC_IDLE state and RRC_INACTIVE state	19
5.2.3 Cell Selection process	20
5.2.3.1 Description	20
5.2.3.2 Cell Selection Criterion.....	21
5.2.3.3 E-UTRAN case in Cell Selection.....	22
5.2.4 Cell Reselection evaluation process.....	22
5.2.4.1 Reselection priorities handling.....	22
5.2.4.2 Measurement rules for cell re-selection	24
5.2.4.3 Mobility states of a UE	25
5.2.4.3.0 Introduction	25
5.2.4.3.1 Scaling rules	26
5.2.4.4 Cells with cell reservations, access restrictions or unsuitable for normal camping.....	27
5.2.4.5 NR Inter-frequency and inter-RAT Cell Reselection criteria.....	27
5.2.4.6 Intra-frequency and equal priority inter-frequency Cell Reselection criteria.....	28
5.2.4.7 Cell reselection parameters in system information broadcasts.....	29
5.2.4.7.0 General reselection parameters.....	29
5.2.4.7.1 Speed dependent reselection parameters	31
5.2.4.7.2 Slice-based cell reselection parameters	32
5.2.4.8 Inter-RAT Cell reselection in RRC_INACTIVE state	32
5.2.4.9 Relaxed measurement	32
5.2.4.9.0 Relaxed measurement rules	32
5.2.4.9.1 Relaxed measurement criterion for UE with low mobility	34
5.2.4.9.2 Relaxed measurement criterion for UE not at cell edge	34
5.2.4.9.3 Relaxed measurement criterion for a stationary RedCap UE	34
5.2.4.9.4 Relaxed measurement criterion for a stationary RedCap UE not at cell edge	35
5.2.4.10 Cell reselection with CAG cells.....	35
5.2.4.11 Reselection priorities for slice-based cell reselection.....	35

5.2.5	Camped Normally state	36
5.2.6	Selection of cell at transition to RRC_IDLE or RRC_INACTIVE state	36
5.2.7	Any Cell Selection state	37
5.2.8	Camped on Any Cell state	37
5.3	Cell Reservations and Access Restrictions	37
5.3.0	Introduction	37
5.3.1	Cell status and cell reservations	37
5.3.2	Unified access control	40
5.4	Tracking Area registration	40
5.5	RAN Area registration	41
6	Reception of broadcast information	41
6.1	Reception of system information	41
6.2	Reception of MBS	41
7	Paging	41
7.1	Discontinuous Reception for paging	41
7.2	Paging Early Indication	44
7.2.1	Paging Early Indication reception	44
7.3	Subgrouping	45
7.3.0	General	45
7.3.1	CN assigned subgrouping	45
7.3.2	UE_ID based subgrouping	45
7.4	Paging in extended DRX	46
8	Sidelink Operation	47
8.1	NR sidelink communication, and V2X sidelink communication, and NR sidelink discovery	47
8.2	Cell selection and reselection for Sidelink	47
8.2.1	Parameters used for cell selection and reselection triggered for sidelink	48
9	Tracking Reference Signal	48
Annex A (informative): Example of Hashed ID Calculation using 32-bit FCS		49
Annex B (informative): Change history		50
History		54

Foreword

This Technical Specification has been produced by the 3rd Generation Partnership Project (3GPP).

The contents of the present document are subject to continuing work within the TSG and may change following formal TSG approval. Should the TSG modify the contents of the present document, it will be re-released by the TSG with an identifying change of release date and an increase in version number as follows:

Version x.y.z

where:

- x the first digit:
 - 1 presented to TSG for information;
 - 2 presented to TSG for approval;
 - 3 or greater indicates TSG approved document under change control.
- y the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- z the third digit is incremented when editorial only changes have been incorporated in the document.

Sample Document

get full document from standards.iteh.ai

1 Scope

The present document specifies the Access Stratum (AS) part of the UE procedures in RRC_IDLE state (also called Idle mode) and RRC_INACTIVE state. The non-access stratum (NAS) part of Idle mode procedures and processes is specified in TS 23.122 [9].

The present document specifies the model for the functional division between the NAS and AS in a UE.

The present document applies to all UEs that support at least NR Radio Access, including multi-RAT UEs as described in 3GPP specifications, in the following cases:

- When the UE is camped on a NR cell;
- When the UE is searching for a cell to camp on;

NOTE: When the UE is camped on or searching for a cell to camp on belonging to other RATs, the UE behaviour is described in the specifications of the other RATs.

2 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- References are either specific (identified by date of publication, edition number, version number, etc.) or non-specific.
- For a specific reference, subsequent revisions do not apply.
- For a non-specific reference, the latest version applies. In the case of a reference to a 3GPP document (including a GSM document), a non-specific reference implicitly refers to the latest version of that document *in the same Release as the present document*.

- [1] 3GPP TR 21.905: "Vocabulary for 3GPP Specifications".
- [2] 3GPP TS 38.300: "NR Overall Description; Stage 2".
- [3] 3GPP TS 38.331: "NR; Radio Resource Control (RRC) - Protocol Specification".
- [4] 3GPP TS 38.213: "NR; Physical layer procedures for control".
- [5] Void
- [6] 3GPP TS 36.331: "E-UTRA; Radio Resource Control (RRC) - Protocol Specification".
- [7] 3GPP TS 36.304: "E-UTRA; User Equipment (UE) procedures in RRC_IDLE state".
- [8] 3GPP TS 38.133: "NR; Requirements for Support of Radio Resource Management".
- [9] 3GPP TS 23.122: "NAS functions related to Mobile Station (MS) in RRC_IDLE state".
- [10] 3GPP TS 23.501: "System Architecture for the 5G System; Stage 2".
- [11] 3GPP TS 38.215: "NR; Physical layer measurements".
- [12] 3GPP TS 22.261: "Service requirements for the 5G system".
- [13] 3GPP TS 24.890: "5G System – Phase 1; CT WG1 Aspects".
- [14] 3GPP TS 24.501: "Non-Access-Stratum (NAS) protocol for 5G System (5GS); Stage 3".
- [15] 3GPP TS 38.101-1: "NR; User Equipment (UE) radio transmission and reception; Part 1: Range 1 Standalone".

- [16] 3GPP TS 23.287: "Architecture enhancements for 5G System (5GS) to support Vehicle-to-Everything (V2X) services".
- [17] 3GPP TS 23.285: "Technical Specification Group Services and System Aspects; Architecture enhancements for V2X services".
- [18] 3GPP TS 22.011: "Service accessibility".
- [19] 3GPP TS 38.321: "NR; Medium Access Control (MAC); Protocol specification".
- [20] 3GPP TS 26.517: "5G Multicast-Broadcast User Services; Protocols and Formats".
- [21] 3GPP TS 23.247: "Architectural enhancements for 5G multicast-broadcast services; Stage 2".
- [22] 3GPP TS 23.304: "Proximity based Services (ProSe) in 5G Systems (5GS)".
- [23] 3GPP TS 23.003: "Numbering, addressing and identification".
- [24] 3GPP TS 38.306: "User Equipment (UE) radio access capabilities".

3 Definitions, symbols and abbreviations

3.1 Definitions

For the purposes of the present document, the following terms and definitions apply:

Acceptable Cell: A cell that satisfies certain conditions as specified in 4.5.

Allowed CAG list: A per-PLMN list of CAG Identifiers the UE is allowed to access (see TS 23.501 [10]).

Available PLMN(s): One or more PLMN(s) for which the UE has found at least one cell and read its PLMN identity(ies).

Available SNPN(s): One or more SNPN(s) for which the UE has found at least one cell and read its SNPN identity(ies).

Barred Cell: A cell a UE is not allowed to camp on.

CAG cell: A cell broadcasting at least one Closed Access Group Identifier.

Camped on a cell: UE has completed the cell selection/reselection process and has chosen a cell. The UE monitors system information and (in most cases) paging information.

Camped on any cell: UE is in idle mode and has completed the cell selection/reselection process and has chosen a cell irrespective of PLMN identity.

Closed Access Group Identifier: Identifier of a CAG within a PLMN.

Commercial Mobile Alert System: Public Warning System that delivers *Warning Notifications* provided by *Warning Notification Providers* to CMAS capable UEs.

eCall Only Mode: A UE configuration option that allows the UE to register at 5GC and register in IMS to perform only eCall Over IMS, and a non-emergency IMS call for test and/or terminal reconfiguration services.

EHPLMN: Any of the PLMN entries contained in the Equivalent HPLMN list TS 23.122 [9].

Equivalent PLMN list: List of PLMNs considered as equivalent by the UE for cell selection, cell reselection, and handover according to the information provided by the NAS.

Home PLMN: A PLMN where the Mobile Country Code (MCC) and Mobile Network Code (MNC) of the PLMN identity are the same as the MCC and MNC of the IMSI.

HSDN cell: A cell that has higher priority than other cells for cell reselection for HSDN capable UE in a High-mobility state.

Network Identifier: Identifier of an SNPN in combination with a PLMN ID (TS 23.501 [10]).

Non-Public Network: A network deployed for non-public use, as defined in TS 22.261 [12].

Non-terrestrial network: An NG-RAN consisting of gNBs, which provides non-terrestrial NR access to UEs by means of an NTN payload embarked on an airborne or space-borne NTN vehicle and an NTN Gateway.

NR sidelink communication: AS functionality enabling at least V2X Communication as defined in TS 23.287 [16], and ProSe communication (including ProSe non-Relay and UE-to-Network Relay communication) as defined in TS 23.304 [22], between two or more nearby UEs, using NR technology but not traversing any network node.

NR sidelink discovery: AS functionality enabling ProSe non-Relay Discovery and ProSe UE-to-Network Relay discovery for Proximity based Services as defined in TS 23.304 [22] between two or more nearby UEs, using NR technology but not traversing any network node.

Process: A local action in the UE invoked by an RRC procedure or an RRC_IDLE or RRC_INACTIVE state procedure.

Quasi-earth fixed cell: An NTN cell fixed with respect to a certain geographic area on the earth during a certain time duration. This can be provisioned by beam(s) covering one geographic area for a limited period and a different geographic area during another period (e.g., the case of NGSO satellites generating steerable beams).

Radio Access Technology: Type of technology used for radio access, for instance NR or E-UTRA.

RedCap UE: A UE with reduced capabilities as specified in clause 4.2.21 in TS 38.306 [24].

Registration Area: (NAS) registration area is an area in which the UE may roam without a need to perform location registration, which is a NAS procedure.

Registered PLMN: This is the PLMN on which certain Location Registration outcomes have occurred, as specified in TS 23.122 [9].

Registered SNPN: This is the SNPN on which certain Location Registration outcomes have occurred, as specified in TS 23.122 [9].

Reserved Cell: A cell on which camping is not allowed, except for particular UEs, if so indicated in the system information.

Selected PLMN: This is the PLMN that has been selected by the NAS, either manually or automatically.

Selected SNPN: This is the SNPN that has been selected by the NAS, either manually or automatically.

Serving cell: The cell on which the UE is camped.

Sidelink: UE to UE interface for V2X sidelink communication defined in TS 23.287[16].

SNPN Access Mode: Mode of operation wherein UE only selects SNPNS (as defined in TS 23.501 [10]).

SNPN identity: An identifier of an SNPN comprising of a PLMN ID and an NID combination.

Strongest cell: The cell on a particular frequency that is considered strongest according to the layer 1 cell search procedure (TS 38.213 [4], TS 38.215 [11]).

Suitable Cell: This is a cell on which a UE may camp. For NR cell, the criteria are defined in clause 4.5, for E-UTRA cell in TS 36.304 [7].

U2N Relay UE: a UE that provides functionality to support connectivity to the network for U2N Remote UE(s).

U2N Remote UE: a UE that communicates with the network via a U2N Relay UE.

V2X sidelink communication: AS functionality enabling V2X Communication as defined in TS 23.285 [17], between nearby UEs, using E-UTRA technology but not traversing any network node.

3.2 Abbreviations

For the purposes of the present document, the abbreviations given in TR 21.905 [1] and the following apply. An abbreviation defined in the present document takes precedence over the definition of the same abbreviation, if any, in TR 21.905 [1].

AS	Access Stratum
CAG	Closed Access Group
CAG-ID	Closed Access Group Identifier
CMAS	Commercial Mobile Alert System
CN	Core Network
DCI	Downlink Control Information
DRX	Discontinuous Reception
eDRX	Extended DRX
ETWS	Earthquake and Tsunami Warning System
E-UTRA	Evolved UMTS Terrestrial Radio Access
E-UTRAN	Evolved UMTS Terrestrial Radio Access Network
GIN	Group ID for Network selection
H-SFN	Hyper System Frame Number
HRNN	Human-Readable Network Name
HSDN	High Speed Dedicated Network
IAB	Integrated Access and Backhaul
IMSI	International Mobile Subscriber Identity
L2	Layer-2
MBS	Multicast/Broadcast Services
MBS FSAI	MBS Frequency Selection Area Identity
MCC	Mobile Country Code
MCCH	MBS Control Channel
MICO	Mobile Initiated Connection Only
MRB	MBS Radio Bearer
MTCH	MBS Traffic Channel
NAS	Non-Access Stratum
NID	Network Identifier
NPN	Non-Public Network
NR	NR Radio Access
NSAG	Network Slice AS Group
NTN	Non-Terrestrial Network
PEI	Paging Early Indication
PEI-O	Paging Early Indication-Occasion
PH	Paging Hyperframe
PLMN	Public Land Mobile Network
PTW	Paging Time Window
RAT	Radio Access Technology
RNA	RAN-based Notification Area
RNAU	RAN-based Notification Area Update
RRC	Radio Resource Control
SDT	Small Data Transmission
SL	Sidelink
SNPN	Stand-alone Non-Public Network
TRS	Tracking Reference Signal
U2N	UE-to-Network
UAC	Unified Access Control
UE	User Equipment
UMTS	Universal Mobile Telecommunications System
V2X	Vehicle to Everything

4 General description of RRC_IDLE state and RRC_INACTIVE state

4.1 Overview

The RRC_IDLE state and RRC_INACTIVE state tasks can be subdivided into three processes:

- PLMN selection (for UE not operating in SNPN access mode) or SNPN selection (for UE operating in SNPN access mode);
- Cell selection and reselection;
- Location registration and RNA update.

PLMN selection, SNPN selection, cell reselection procedures, and location registration are common for both RRC_IDLE state and RRC_INACTIVE state. RNA update is only applicable for RRC_INACTIVE state. When UE selects a new PLMN or SNPN, UE transitions from RRC_INACTIVE to RRC_IDLE, as specified in TS 24.501 [14].

When a UE is switched on, a public land mobile network (PLMN) or a SNPN is selected by NAS. For the selected PLMN/SNPN, associated RAT(s) may be set, as specified in TS 23.122 [9]. The NAS shall provide a list of equivalent PLMNs, if available, that the AS shall use for cell selection and cell reselection.

With cell selection, the UE searches for a suitable cell of the selected PLMN or selected SNPN, chooses that cell to provide available services, and monitors its control channel. This procedure is defined as "camping on the cell".

The UE shall, if necessary, then register its presence, by means of a NAS registration procedure, in the tracking area of the chosen cell. As an outcome of a successful Location Registration, the selected PLMN/SNPN then becomes the registered PLMN/SNPN, as specified in TS 23.122 [9].

If the UE finds a more suitable cell, according to the cell reselection criteria, it reselects onto that cell and camps on it. If the new cell does not belong to at least one tracking area to which the UE is registered, location registration is performed. In RRC_INACTIVE state, if the new cell does not belong to the configured RNA, an RNA update procedure is performed.

If necessary, the UE shall search for higher priority PLMNs at regular time intervals as described in TS 23.122 [9] and search for a suitable cell if another PLMN has been selected by NAS.

For UE not operating in SNPN access mode, search of available CAGs may be triggered by NAS to support manual CAG selection. The AS shall report available CAG-ID(s) together with their HRNN (if broadcast) and PLMN(s) to the NAS.

NAS may also provide the network slice(s) and Network Slice AS Group (NSAG) information, which contains NSAG(s), their applicable TA(s) if present and their priorities, to be considered by the UE during cell reselection (as specified in TS 23.501 [10], TS 24.501 [14]).

If the UE loses coverage of the registered PLMN/SNPN, either a new PLMN/SNPN is selected automatically (automatic mode), or an indication of available PLMNs/SNPNs is given to the user so that a manual selection can be performed (manual mode). As part of manual SNPN selection, the AS shall report available SNPN identifiers together with their HRNN (if broadcast) to the NAS.

Registration is not performed by UEs only capable of services that need no registration.

The UE may perform NR sidelink communication and/or V2X sidelink communication while in-coverage or out-of-coverage for sidelink, as specified in clause 8.

The U2N Remote UE, the U2N Relay UE, or both may perform sidelink discovery transmissions while in-coverage for the purpose of sidelink relay operations, as specified in clause 8. In addition, the U2N Remote UE can also perform sidelink discovery transmissions while out-of-coverage for the purpose of sidelink relay operations.

An L2 U2N Remote UE in RRC_IDLE or in RRC_INACTIVE may perform all the relevant procedures (e.g., acquiring system information and paging message) via the L2 U2N Relay UE. An L2 U2N Remote UE may choose not to perform any procedures related to cell selection and reselection.

The UE may perform NR sidelink discovery transmissions while in-coverage or out-of-coverage for the purpose of sidelink non-relay operations, as specified in clause 8.

The purpose of camping on a cell in RRC_IDLE state and RRC_INACTIVE state is as follows:

- a) It enables the UE to receive system information from the PLMN or the SNPN.
- b) When registered and if the UE wishes to establish an RRC connection or resume a suspended RRC connection, it can do this by initially accessing the network on the control channel of the cell on which it is camped.
- c) If the network needs to send a message or deliver data to the registered UE, it knows (in most cases) the set of tracking areas (in RRC_IDLE state) or RNA (in RRC_INACTIVE state) in which the UE is camped. It can then send a "paging" message for the UE on the control channels of all the cells in the corresponding set of areas. The UE will then receive the paging message and can respond.
- d) It enables the UE to receive ETWS and CMAS notifications.
- e) It enables the UE to receive MBS broadcast services.

When the UE is in RRC_IDLE state, upper layers may deactivate AS layer when MICO mode is activated as specified in TS 24.501 [14]. When MICO mode is activated, the AS configuration (e.g. priorities provided by dedicated signalling) is kept and all running timers continue to run but the UE need not perform any idle mode tasks. If a timer expires while MICO mode is activated it is up to the UE implementation whether it performs the corresponding action immediately or the latest when MICO mode is deactivated. When MICO mode is deactivated, the UE shall perform all idle mode tasks.

Sample Document

get full document from standards.iteh.ai

4.2 Functional division between AS and NAS in RRC_IDLE state and RRC_INACTIVE state

Table 4.2-1 presents the functional division between UE non-access stratum (NAS) and UE access stratum (AS) in RRC_IDLE state and RRC_INACTIVE states. The NAS part is specified in TS 23.122 [9] and the AS part in the present document.

Table 4.2-1: Functional division between AS and NAS in RRC_IDLE state and RRC_INACTIVE state

Sample Document

get full document from standards.iteh.ai

RRC_IDLE and RRC_INACTIVE state Process	UE Non-Access Stratum	UE Access Stratum
PLMN Selection and SNPN Selection	<p>For a UE not operating in SNPN access mode, perform the following: Maintain a list of PLMNs in priority order according to TS 23.122 [9]. Select a PLMN using automatic or manual mode as specified in TS 23.122 [9] and request AS to select a cell belonging to this PLMN. For each PLMN, associated RAT(s) may be set.</p> <p>Evaluate reports of available PLMNs and any associated CAG-IDs from AS for PLMN selection.</p> <p>Maintain a list of equivalent PLMN identities.</p> <p>Maintain a list of "PLMNs not allowed to operate at the present UE location".</p> <p>Maintain applicable disaster roaming information for available PLMNs including potential disaster PLMNs for available PLMNs.</p> <p>To support manual CAG selection, provide request to search for available CAGs and evaluate reports of available CAGs from AS for CAG selection.</p> <p>For a UE operating in SNPN access mode, perform the following: Maintain a list of SNPNS according to TS 23.122 [9]. Select a SNPN using automatic or manual mode as specified in TS 23.122 [9] and request AS to select a cell belonging to this SNPN.</p> <p>Evaluate reports of available SNPNS from AS for SNPN selection.</p>	<p>For a UE not operating in SNPN access mode, search for available PLMNs.</p> <p>If associated RAT(s) is (are) set for the PLMN, search in this (these) RAT(s) and other RAT(s) for that PLMN as specified in TS 23.122 [9].</p> <p>For a UE operating in SNPN access mode, search for available SNPNS only consider NR cells.</p> <p>Perform measurements to support PLMN/SNPN selection.</p> <p>Synchronise to a broadcast channel to identify found PLMNs/SNPNS.</p> <p>Report available PLMNs and any associated CAG-IDs with associated RAT(s) to NAS on request from NAS or autonomously.</p> <p>Report applicable disaster roaming information for available PLMNs autonomously including potential disaster PLMNs.</p> <p>For a UE operating in SNPN access mode, report available SNPNS to NAS autonomously; report information related to SNPN access with subscription of a different Credentials Holder, indicator whether onboarding is enabled, and the list of supported GINs to NAS autonomously, as specified in TS 38.331 [3].</p> <p>To support manual CAG selection, perform the following: Search for cells broadcasting a CAG-ID.</p> <p>Read the HRNN (if broadcast) for each CAG-ID if a cell broadcasting a CAG-ID is found.</p> <p>Report CAG-ID(s) of found cell(s) broadcasting a CAG-ID together with the associated manual CAG selection allowed indicator, HRNN and PLMN to NAS.</p> <p>On selection of a CAG by NAS, select any acceptable or suitable cell belonging to the selected CAG and give an indication to NAS that access is possible (for the registration procedure)</p> <p>To support manual SNPN selection, report available SNPNS together with associated HRNNs (if available) to NAS on request from NAS.</p>

RRC_IDLE and RRC_INACTIVE state Process	UE Non-Access Stratum	UE Access Stratum
Cell Selection	<p>Control cell selection for example by indicating RAT(s) associated with the selected PLMN to be used initially in the search of a cell in the cell selection.</p> <p>Maintain a list of "Forbidden Tracking Areas" and provide the list to AS.</p> <p>Maintain a list of "PLMNs not allowed to operate at the present UE location" and provide the list to AS.</p> <p>For a UE not operating in SNPN access mode: Maintain Allowed CAG list and optional CAG-only indication along with associated PLMN ID(s) on which the UE is allowed access and provide these lists to AS. To support manual CAG selection, select a CAG and request AS to select a cell belonging to this CAG.</p>	<p>Perform measurements needed to support cell selection.</p> <p>Detect and synchronise to a broadcast channel. Receive and handle broadcast information. Forward NAS system information to NAS.</p> <p>Search for a suitable cell. The cells broadcast one or more 'PLMN identity' or 'SNPN identity' (for a UE operating in SNPN access mode) in the system information. Respond to NAS whether such cell is found or not.</p> <p>If associated RATs is (are) set for the PLMN, perform the search in this (these) RAT(s) and other RATs for that PLMN as specified in TS 23.122 [9].</p> <p>If a cell is found which satisfies cell selection criteria, camp on that cell.</p>
Cell Reselection	<p>For a UE not operating in SNPN access mode, maintain a list of equivalent PLMN identities and provide the list to AS.</p> <p>Maintain a list of "Forbidden Tracking Areas" and provide the list to AS.</p> <p>Maintain a list of "PLMNs not allowed to operate at the present UE location" and provide the list to AS.</p> <p>For a UE not operating in SNPN access mode, maintain Allowed CAG list and optional CAG-only indication along with associated PLMN ID(s) on which the UE is allowed access and provide these lists to AS.</p> <p>Maintain the network slice(s) and NSAG information and provide network slice(s) and NSAG information to AS.</p>	<p>Perform measurements needed to support cell reselection.</p> <p>Detect and synchronise to a broadcast channel. Receive and handle broadcast information. Forward NAS system information to NAS.</p> <p>Change cell if a more suitable cell is found.</p> <p>Derive cell reselection priorities for slice-based cell reselection.</p>
Location registration	<p>Register the UE as active after power on.</p> <p>Register the UE's presence in a registration area, for instance regularly or when entering a new tracking area.</p> <p>Deregister UE when shutting down.</p> <p>Maintain a list of "Forbidden Tracking Areas".</p> <p>Maintain a list of "PLMNs not allowed to operate at the present UE location".</p> <p>Control and restrict location registration for a UE in eCall Only Mode.</p>	<p>Report registration area information to NAS.</p>