



INTERNATIONAL STANDARD

CONSOLIDATED VERSION

**Electric motor-operated hand-held tools, transportable tools and lawn and garden machinery - Safety -
Part 2-16: Particular requirements for hand-held fastener driving tools**

get full document from standards.iteh.ai



THIS PUBLICATION IS COPYRIGHT PROTECTED

Copyright © 2026 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester. If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

IEC Secretariat
3, rue de Varembe
CH-1211 Geneva 20
Switzerland

Tel.: +41 22 919 02 11
info@iec.ch
www.iec.ch

About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigendum or an amendment might have been published.

IEC publications search -

webstore.iec.ch/advsearchform

The advanced search enables to find IEC publications by a variety of criteria (reference number, text, technical committee, ...). It also gives information on projects, replaced and withdrawn publications.

IEC Just Published - webstore.iec.ch/justpublished

Stay up to date on all new IEC publications. Just Published details all new publications released. Available online and once a month by email.

IEC Customer Service Centre - webstore.iec.ch/csc

If you wish to give us your feedback on this publication or need further assistance, please contact the Customer Service Centre: sales@iec.ch.

IEC Products & Services Portal - products.iec.ch

Discover our powerful search engine and read freely all the publications previews, graphical symbols and the glossary. With a subscription you will always have access to up to date content tailored to your needs.

Electropedia - www.electropedia.org

The world's leading online dictionary on electrotechnology, containing more than 22 500 terminological entries in English and French, with equivalent terms in 25 additional languages. Also known as the International Electrotechnical Vocabulary (IEV) online.

Warning! Make sure that you obtained this publication from an authorized distributor.

CONTENTS

FOREWORD	3
1 Scope	5
2 Normative references	5
3 Terms and definitions	6
4 General requirements	9
5 General conditions for the tests	9
6 Radiation, toxicity and similar hazards	9
7 Classification	9
8 Marking and instructions	9
9 Protection against access to live parts	12
10 Starting	12
11 Input and current	12
12 Heating	12
13 Resistance to heat and fire	13
14 Moisture resistance	13
15 Resistance to rusting	13
16 Overload protection of transformers and associated circuits	13
17 Endurance	13
18 Abnormal operation	14
19 Mechanical hazards	15
20 Mechanical strength	18
21 Construction	18
22 Internal wiring	19
23 Components	19
24 Supply connection and external flexible cords	19
25 Terminals for external conductors	19
26 Provision for earthing	20
27 Screws and connections	20
28 Creepage distances, clearances and distances through insulation	20
Annexes	26
Annex I (informative) Measurement of noise and vibration emissions	26
Annex K (normative) Battery tools and battery packs	29
Annex L (normative) Battery tools and battery packs provided with mains connection or non-isolated sources	35
Annex AA (normative) Product safety labels	36
Bibliography	37
Figure AA.1 – Product safety label for tools capable of only contact actuation or contact actuation with automatic reversion actuation modes	36
Table 4 – Required performance levels	15

Table 101 – Permitted actuation modes and workpiece contact force for fastener driving tools that require a workpiece contact	16
Table 12 – Minimum creepage distances and clearances	22
Table I.101 – Detailed example of a concrete formulation	27
Table K.1 – Minimum creepage distances and clearances between parts of different potential.....	32
Table K.2 – Minimum total sum of creepage distances and clearances to accessible surfaces.....	33

Sample Document

get full document from standards.iteh.ai

INTERNATIONAL ELECTROTECHNICAL COMMISSION

**Electric motor-operated hand-held tools, transportable tools
and lawn and garden machinery - Safety -
Part 2-16: Particular requirements for hand-held fastener driving tools**

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) IEC draws attention to the possibility that the implementation of this document may involve the use of (a) patent(s). IEC takes no position concerning the evidence, validity or applicability of any claimed patent rights in respect thereof. As of the date of publication of this document, IEC had not received notice of (a) patent(s), which may be required to implement this document. However, implementers are cautioned that this may not represent the latest information, which may be obtained from the patent database available at <https://patents.iec.ch>. IEC shall not be held responsible for identifying any or all such patent rights.

This consolidated version of the official IEC Standard and its amendment has been prepared for user convenience.

IEC 62841-2-16 edition 1.1 contains the first edition (2024-06) [documents 116/757/FDIS and 116/800/RVD] and its amendment 1 (2026-02) [documents 116/936/FDIS and 116/939/RVD].

In this Redline version, a vertical line in the margin shows where the technical content is modified by amendment 1. Additions are in green text, deletions are in strikethrough red text. A separate Final version with all changes accepted is available in this publication.

IEC 62841-2-16 has been prepared by IEC technical committee 116: Safety of motor-operated electric tools. It is an International Standard.

The text of this International Standard is based on the following documents:

Draft	Report on voting
116/757/FDIS	116/800/RVD

Full information on the voting for its approval can be found in the report on voting indicated in the above table.

The language used for the development of this International Standard is English.

This document was drafted in accordance with ISO/IEC Directives, Part 2, and developed in accordance with ISO/IEC Directives, Part 1 and ISO/IEC Directives, IEC Supplement, available at www.iec.ch/members_experts/refdocs. The main document types developed by IEC are described in greater detail at www.iec.ch/publications.

This document is to be used in conjunction with IEC 62841-1:2014.

This document supplements or modifies the corresponding clauses in IEC 62841-1, so as to convert it into the IEC Standard: Particular requirements for hand-held fastener driving tools.

Where a particular subclause of IEC 62841-1 is not mentioned in this document, that subclause applies as far as reasonable. Where this document states "addition", "modification" or "replacement", the relevant text in IEC 62841-1 is to be adapted accordingly.

The following print types are used:

- requirements: in roman type;
- *test specifications: in italic type;*
- terms defined in Clause 3: in **bold** type;
- notes: in small roman type.

Subclauses, notes, tables and figures which are additional to those in IEC 62841-1 are numbered starting from 101.

Subclauses, notes, tables and figures in Annex K and Annex L which are additional to those in the main body of this document are numbered starting from 301.

A list of all parts in the IEC 62841 series, published under the general title *Electric motor-operated hand-held tools, transportable tools and lawn and garden machinery – Safety*, can be found on the IEC website.

The committee has decided that the contents of this document and its amendment will remain unchanged until the stability date indicated on the IEC website under webstore.iec.ch in the data related to the specific document. At this date, the document will be

- reconfirmed,
- withdrawn, or
- revised.

1 Scope

IEC 62841-1:2014, Clause 1 is applicable, except as follows:

Addition:

This document applies to hand-held **fastener driving tools**

- intended for driving **fasteners** into or through concrete, fabric, fiberboard, metal, plastic, wood, wood products, cartons, and other materials; and
- whose energy to drive the **fastener** is derived directly or indirectly from an electric motor or magnetic drive.

This document does not apply to pneumatically driven tools where the compressed gas comes from an external source, such as a compressor or a tank.

This document does not apply to tools powered by combustible gases, even if electrically ignited.

NOTE 101 Tools powered by compressed air or combustible gases are covered by ISO 11148-13:2017.

2 Normative references

IEC 62841-1:2014, Clause 2 is applicable, except as follows:

Addition:

IEC 60664-3, *Insulation coordination for equipment within low-voltage systems – Part 3: Use of coating, potting or moulding for protection against pollution*

IEC 60664-4:2005, *Insulation coordination for equipment within low-voltage systems – Part 4: Consideration of high-frequency voltage stress*

IEC 62841-1:2014, *Electric motor-operated hand-held tools, transportable tools and lawn and garden machinery – Safety – Part 1: General requirements*

ISO 630-2:2021, *Structural steels – Part 2: Technical delivery conditions for structural steels for general purposes*

ISO 28927-13:2022, *Hand-held portable power tools – Test methods for evaluation of vibration emission – Part 13: Fastener driving tools*

EN 12549:1999, *Acoustics – Noise test code for fastener driving tools – Engineering method*

~~EN 15895:2011, *Cartridge-operated hand-held tools – Safety requirements – Fixing and hard marking tools*~~

EN 15895:2025, *Powder actuated hand-held fixing and hard marking tools - Safety requirements*

3 Terms and definitions

IEC 62841-1:2014, Clause 3 is applicable, except as follows:

Addition:

3.101

activate

move or otherwise engage a **trigger** or **workpiece contact** so that it is in a state that allows the **fastener driving tool** to be **actuated** or that satisfies one requirement for the **fastener driving tool** to be **actuated**

3.102

actuate

cause movement of the tool component(s) intended to drive a **fastener**

3.103

actuation mode

sequence by which a fastening operation is performed

3.103.1

contact actuation

actuation mode which allows the tool to operate by **activating** the **workpiece contact** whilst the **trigger** is continually depressed and held

Note 101 to entry: **Contact actuation** is also known as bump mode.

3.103.2

contact actuation with automatic reversion

actuation mode that is capable of **contact actuation** and where the tool cannot **actuate** if the **trigger** is depressed without operation of the **workpiece contact** within the **trigger time-out period**

Note 101 to entry: Additional actuation is possible only after the **trigger** is released and re-**activated**.

3.103.3

dual activation

actuation mode where two devices, such as **triggers**, levers, or switches, work in conjunction with each other such that two sequential dissimilar actions are required to **actuate** the tool

3.103.4

full sequential actuation

actuation mode which allows single driving operations via the **trigger** after the **workpiece contact** has been **activated** and during which additional actuation can occur only when all operating controls are released and re-**activated** in the same sequence

3.103.5

single sequential actuation

actuation mode which allows single driving operations via the **trigger**, after the **workpiece contact** has been **activated**, and during which additional actuation can occur only when the **trigger** has been returned to the non-driving position whilst the **workpiece contact** remains in the **activated** position

3.104

actuation system

trigger or **workpiece contact activated** separately or in some combination or sequence to **actuate** the tool

3.105

coil nailer

fastener driving tool that drives **fasteners** from a collated coil of nails for **production applications**

Note 101 to entry: Roofing nailers are an example of a **coil nailer**.

Note 102 to entry: The primary purpose of this tool is **production applications**.

3.106

fastener

mechanical device used for securing fixings to surfaces or joining materials together, such as nails, staples and pins, for use in **fastener driving tools**

3.107

fastener driving tool

hand-held tool in which energy is transmitted in a linear motion to a **fastener** for the purpose of driving the **fastener** into defined materials

Note 101 to entry: **Fasteners** are typically driven by mechanical or pneumatic means.

3.108

heavy duty ~~brad~~ finish nailer

fastener driving tool capable of driving nails of 1,2 mm (18 gauge) or larger nominal diameter wire

Note 101 to entry: The **fasteners** described here are consistent, except for description, with those described for heavy duty bradders in ISO 11148-13:2017.

Note 102 to entry: These tools are primarily for **production applications**.

3.109

heavy duty stapler

fastener driving tool capable of driving staples with a **staple leg width** of 1,6 mm or larger and a nominal **staple leg thickness** of 1,4 mm or larger

Note 101 to entry: The **fasteners** described here are consistent, except for description, with those described for **heavy duty staplers** in ISO 11148-13:2017.

Note 102 to entry: These tools are primarily for **production applications**.

3.110

horizontal-down

tool orientation where the tool nose is normal to a horizontal work surface and pointed downwards

3.111

horizontal-up

tool orientation where the tool nose is normal to a horizontal work surface and pointed upwards

3.112

light duty tool

fastener driving tool that is only capable of driving **fasteners** with a diameter of 1,2 mm (18 gauge) or less and where

- the mass of the **fastener** is less than 0,5 g and the length of the **fastener** does not exceed 26 mm; or
- the mass of the **fastener** is less than 0,4 g and the length of the **fastener** does not exceed 36 mm

Note 101 to entry: **Heavy duty ~~brad~~ finish nailers, heavy duty staplers and pinners** are considered not to be **light duty tools**.

3.113

multi-blow tool

fastener driving tool that drives **fasteners** through multiple impacts on the head of the **fastener** and not through the forcible ejection of the **fastener**

Note 101 to entry: An example of a **multi-blow tool**, also known as a percussion nailer, is a palm nailer.

3.114

pinner

fastener driving tool capable of driving headless **fasteners** up to 51 mm in length and a maximum diameter of 0,64 mm (23 gauge)

3.115

staple leg thickness

maximum dimension of staple leg cross-section measured parallel to the staple crown axis

3.116

staple leg width

maximum dimension of staple leg cross-section measured perpendicular to the staple crown axis

3.117

trigger

control element **activated** manually by a tool operator

3.118

trigger time-out period

for tools with **contact actuation with automatic reversion actuation mode**, the duration of time a **trigger** can be depressed without operation of the **workpiece contact** before the tool becomes inoperable

3.119

workpiece contact

control element or assembly on the **fastener driving tool** intended to be **activated** by the workpiece

Note 101 to entry: This includes retractable **workpiece contacts** that are normally retracted and extend when the **trigger** is **activated**.

3.119.1

protected workpiece contact

workpiece contact that is recessed such that it cannot be **activated** by pressing against a flat surface

Note 101 to entry: **Protected workpiece contacts** are found on tools that are designed to affix cable, tubing and the like with staples where the **workpiece contact** presses against the material being affixed.

3.120

production application

high-volume professional application such as pallets, furniture, manufactured housing, upholstery, sheathing and roofing

Note 101 to entry: Tools that are designed for **production applications** include **heavy duty staplers**, **heavy duty finish nailers** and **coil nailers**

3.121

selective actuation

actuation system that allows discrete selection of two or more of the following **actuation modes**: **single sequential actuation**, **full sequential actuation**, **contact actuation** or **contact actuation with automatic reversion**

4 General requirements

IEC 62841-1:2014, Clause 4 is applicable.

5 General conditions for the tests

IEC 62841-1:2014, Clause 5 is applicable, except as follows:

5.17 Addition:

*The mass of the tool includes the heaviest **fastener** magazine in accordance with 8.14.2 b) 102), but excludes any **fasteners**.*

5.101 *For tests that are conducted without **fasteners**, the test may be conducted using a test fixture that simulates a **fastener** in order to avoid abnormal stresses that may occur in the tool.*

5.102 *For tools that employ a function that does not permit the tool to **actuate** without **fasteners**, tests that require the tool to **actuate** shall be conducted with **fasteners** or the function shall be disabled. If required, special hardware or software (or both) may be used in order to disable the function.*

6 Radiation, toxicity and similar hazards

IEC 62841-1:2014, Clause 6 is applicable.

7 Classification

IEC 62841-1:2014, Clause 7 is applicable.

8 Marking and instructions

IEC 62841-1:2014, Clause 8 is applicable, except as follows:

8.1 Replacement of the third dash:

- **rated input**, in watts or **rated current**, in amperes;

8.2 Addition:

Fastener driving tools shall be marked with safety information which shall be written in one of the official languages of the country in which the machine is to be sold or marked with the appropriate symbol:

- "Wear eye protection" or symbol M004 of ISO 7010;
- "Wear ear protection", or symbol M003 of ISO 7010. This marking may be omitted if the measured sound pressure level at the operator's ear in accordance with Annex I does not exceed 85 dB(A).

A combination of product safety labels, such as eye, ear, dust and head protection, is allowed.

8.2.101 Tools capable of only **contact actuation** or **contact actuation with automatic reversion actuation modes** in accordance with 19.102 and 19.104 shall be visibly marked with

the product safety label specified in Figure AA.1 of Annex AA. This subclause is not applicable to tools with **selective actuation**.

Compliance is checked by inspection.

8.11 Addition:

For tools with ~~the ability to select different actuation modes~~ **selective actuation**, markings indicating which **actuation mode** is enabled.

8.14.1 Addition:

The additional safety instructions as specified in 8.14.1.101 or 8.14.1.102 (as applicable) shall be given. The term "tool" in these warnings may be replaced by a specific tool designation, such as **fastener driving tool**, nailer, **pinner**, stapler, tacker, etc. The term "fastener(s)" in these warnings may be replaced by a specific **fastener** designation such as nail(s), pin(s), staple(s), tack(s), etc. This part may be printed separately from the "General Power Tool Safety Warnings".

8.14.1.101 Fastener driving tool safety warnings (except for multi-blow tools)

- a) **Always assume that the tool contains fasteners.** *Careless handling of the tool may result in unexpected firing of fasteners and personal injury.*
- b) **Disconnect the tool from the power source when loading and unloading fasteners, making adjustments or changing accessories.** *The tool may be accidentally activated if it is connected to the power source, which may result in personal injury.*
- c) **Be careful when handling fasteners, especially when loading and unloading.** *The fasteners have sharp points which may result in personal injury.*
- d) **Do not point the tool towards yourself or anyone nearby.** *Unexpected triggering will discharge a fastener, which may result in personal injury.*
- e) **Keep fingers away from the trigger when not operating the tool and when moving from one operating position to another.** *Unexpected triggering will discharge a fastener, which may result in personal injury.*
- f) **Hold the tool by insulated gripping surfaces, when performing an operation where the fastener may contact hidden wiring or its own cord.** *A fastener contacting a "live" wire may make exposed metal parts of the tool "live" and could give the operator an electric shock.*
- g) **Hold the tool with a firm grasp during operation.** *Uncontrolled recoil of the tool may result in unintended activation, which may result in personal injury.*
- h) **Keep all body parts such as hands and legs, etc. away from the firing direction of the tool.** *The fastener may penetrate the workpiece as well as any object behind it, which may result in personal injury.*
- i) **When using the tool, keep all body parts such as hands and legs, etc. away from the area where the fastener is driven into the workpiece.** *The fastener could deflect and exit the workpiece, which may result in personal injury.*
- j) **Do not actuate the tool unless the tool is placed firmly against the workpiece.** *If the tool is not in contact with the workpiece, the fastener may be deflected away from the workpiece, which may result in personal injury.*
- k) **When fastening electrical cables, make sure the cables are not energized. Hold the tool only by insulated gripping surfaces. Use only fasteners designed for electrical cable installations. Inspect that the fastener has not damaged the insulation of the electrical cables.** *A fastener that damages the insulation of electric cables can lead to electric shock and fire hazards.*

NOTE 101 The warning in item k) above is omitted for tools that are not intended to fasten electrical cables.

- l) **Do not use this tool for fastening electrical cables.** *It is not designed for electric cable installation and may damage the insulation of electric cables, thereby causing electric shock or fire hazards.*

NOTE 102 The warning in item l) above is omitted for tools intended to fasten electric cables in accordance with 8.14.2 b) 106).

- m) **Disconnect the tool from the power source if a fastener jams in the tool.** *While removing a jammed fastener, the tool may be accidentally activated if it is connected to the power source, which may result in personal injury.*
- n) **Use caution while removing a jammed fastener.** *The mechanism may be under compression and the fastener may be forcefully discharged, which may result in personal injury.*

NOTE 103 The warning in item n) above is omitted for tools that do not utilize a stored potential energy to drive the **fasteners**.

8.14.1.102 Multi-blow tool safety warnings

- a) **Hold the tool by insulated gripping surfaces, when performing an operation where the fastener may contact hidden wiring or its own cord.** *A fastener contacting a "live" wire may make exposed metal parts of the tool "live" and could give the operator an electric shock.*
- b) **Keep all body parts such as hands and legs, etc. away from the driving direction of the fastener.** *The fastener may penetrate the workpiece as well as any object behind it, which may result in personal injury.*
- c) **When fastening electrical cables, make sure the cables are not energized. Hold the tool only by insulated gripping surfaces. Use only fasteners designed for electrical cable installations. Inspect that the fastener has not damaged the insulation of the electrical cables.** *A fastener that damages the insulation of electric cables can lead to electric shock and fire hazards.*

NOTE 101 The warning in item c) above is omitted for tools that are not intended to fasten electrical cables.

- d) **Do not use this tool for fastening electrical cables.** *It is not designed for electric cable installation and may damage the insulation of electric cables, thereby causing electric shock or fire hazards.*

NOTE 102 The warning in item d) above is omitted for tools intended to fasten electric cables in accordance with 8.14.2 b) 106).

8.14.1.103 Additional warnings for tools capable of contact actuation

- a) **Contact actuation should only be used for non-precision fastening applications such as for roofing and sheathing or the production of pallets, furniture, manufactured housing or upholstery.** *For work requiring more precision, a sequential tool or sequential operating mode should be selected.*
- b) **Always check the actuation mode before operating tools with selective actuation.** *Operating the tool without verifying the actuation mode could lead to injury from inadvertent actuation of a fastener.*
- c) **Use this tool on controlled jobsites where safe work practices are implemented.** *Environments where safe work practices are not maintained increases the risk of personal injury.*

8.14.2 b) Addition:

- 101) Information on suitable **fasteners** to be used with the tool;
- 102) Information on suitable **accessories** to be used with the tool, such as **fastener** magazines or **workpiece contact** tip protectors;
- 103) Information on the correct operation of all control elements of the tool (e.g. **trigger**, **workpiece contact**, **actuation mode** selector);
- 104) Information stating what materials the tool is designed to drive **fasteners** into;

- 105) Information indicating if the tool is intended to be used on hard materials such as steel and concrete, including information regarding the additional downforce required to operate the tool;
- 106) Information that the tool is intended to fasten electrical cables, if applicable;
- 107) Information on the **fasteners** to be used for fixing electric cables, if applicable;
- 108) Instructions for removing a jammed **fastener** in the tool;
- 109) Information on **actuation modes** of the tool;
- 110) Information on the method to change the **fastener** magazine, if any.

9 Protection against access to live parts

IEC 62841-1:2014, Clause 9 is applicable.

10 Starting

IEC 62841-1:2014, Clause 10 is applicable.

11 Input and current

IEC 62841-1:2014, Clause 11 is applicable.

12 Heating

IEC 62841-1:2014, Clause 12 is applicable, except as follows:

12.2 Replacement:

*For tools with one or more **rated voltages**: The tool is operated at each **rated voltage**, under the load conditions specified in 12.2.1. The voltage is then adjusted to 0,94 times the **rated voltage** and 1,06 times the **rated voltage**.*

The temperatures are measured at the most unfavourable of the two voltage settings. The temperatures that are measured by means of thermocouples are taken while the tool is operating.

*For tools with a **rated voltage range**: The tool is operated*

- *at the lower limit of the **rated voltage range**, under the load conditions specified in 12.2.1. The voltage is then adjusted to 0,94 times the lower limit of the **rated voltage range**; and*
- *at the upper limit of the **rated voltage range**, under the load conditions specified in 12.2.1. The voltage is then adjusted to 1,06 times the upper limit of the **rated voltage range**.*

The temperatures are measured at the most unfavourable of the two voltage settings. The temperatures that are measured by means of thermocouples are taken while the tool is operating.

12.2.1 Replacement:

*The test is conducted with or without **fasteners** in the tool.*

NOTE 101 See 5.101 for tests that are conducted without **fasteners**.

For tools other than **multi-blow tools**, the tool is operated for 10 cycles or until thermal equilibrium is reached, whichever is achieved first. Each cycle consists of the tool operating at

- a rate of one actuation approximately every 1 s; or
- for tools with an **inherent operating cycle** greater than 1 s, operation with consecutive operating cycles

for 1 min and a rest period of 3 min with the tool switched off. The temperature rises are measured at the end of the "on" period. At the manufacturer's option, the tool may be operated without a rest period until thermal equilibrium is reached.

For **multi-blow tools**, the tool is operated continuously at a minimum load to activate the percussion mechanism for 10 min or until thermal equilibrium is reached, whichever is achieved first.

13 Resistance to heat and fire

IEC 62841-1:2014, Clause 13 is applicable.

14 Moisture resistance

IEC 62841-1:2014, Clause 14 is applicable.

15 Resistance to rusting

IEC 62841-1:2014, Clause 15 is applicable.

16 Overload protection of transformers and associated circuits

IEC 62841-1:2014, Clause 16 is applicable.

17 Endurance

IEC 62841-1:2014, Clause 17 is applicable, except as follows:

17.2 Replacement:

The test is conducted with or without **fasteners** in the tool.

NOTE See 5.101 for tests that are conducted without **fasteners**.

For tools other than **multi-blow tools**, the tool is operated at the cycle rate as specified in 12.2.1 for 20 000 actuations at a voltage equal to the highest **rated voltage** or equal to the upper limit of the **rated voltage range**. It is not necessary for the test to be continuous.

For **multi-blow tools**, the tool is cycled for 12 h at a voltage equal to the highest **rated voltage** or equal to the upper limit of the **rated voltage range**. It is not necessary for the 12 h of operation to be continuous. Each cycle of operation comprises an "on" period of 20 s and an "off" period of 20 s, the "off" periods being included in the specified 12 h operating time. If the cycle of operation limited by the construction is less than 20 s "on" and 20 s "off", then this cycle may be used.

The tool may be switched on and off by means of a switch other than that incorporated in the tool unless this disables a functionality of the tool switch.