

TECHNICAL REPORT

Residual current devices (RCDs) associated with additional function(s)
(standards.iteh.ai)

[IEC TR 62710:2015](https://standards.iteh.ai/catalog/standards/sist/5bffe95d-13a5-4342-9330-421053968575/iec-tr-62710-2015)

<https://standards.iteh.ai/catalog/standards/sist/5bffe95d-13a5-4342-9330-421053968575/iec-tr-62710-2015>



THIS PUBLICATION IS COPYRIGHT PROTECTED

Copyright © 2015 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester. If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

IEC Central Office
3, rue de Varembe
CH-1211 Geneva 20
Switzerland

Tel.: +41 22 919 02 11
Fax: +41 22 919 03 00
info@iec.ch
www.iec.ch

About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigenda or an amendment might have been published.

IEC Catalogue - webstore.iec.ch/catalogue

The stand-alone application for consulting the entire bibliographical information on IEC International Standards, Technical Specifications, Technical Reports and other documents. Available for PC, Mac OS, Android Tablets and iPad.

IEC publications search - www.iec.ch/searchpub

The advanced search enables to find IEC publications by a variety of criteria (reference number, text, technical committee,...). It also gives information on projects, replaced and withdrawn publications.

IEC Just Published - webstore.iec.ch/justpublished

Stay up to date on all new IEC publications. Just Published details all new publications released. Available online and also once a month by email.

Electropedia - www.electropedia.org

The world's leading online dictionary of electronic and electrical terms containing more than 30 000 terms and definitions in English and French, with equivalent terms in 15 additional languages. Also known as the International Electrotechnical Vocabulary (IEV) online.

IEC Glossary - std.iec.ch/glossary

More than 60 000 electrotechnical terminology entries in English and French extracted from the Terms and Definitions clause of IEC publications issued since 2002. Some entries have been collected from earlier publications of IEC TC 37, 77, 86 and CISPR.

IEC Customer Service Centre - webstore.iec.ch/csc

If you wish to give us your feedback on this publication or need further assistance, please contact the Customer Service Centre: csc@iec.ch.

INTERNATIONAL STANDARD PREVIEW
(standards.iteh.ai)
IEC TR 62710-2015
https://standards.iteh.ai/catalog/standards/iec/62710-2015
421053968575/iec-tr-62710-2015

TECHNICAL REPORT

Residual current devices (RCDs) associated with additional function(s)
(standards.iteh.ai)

IEC TR 62710:2015
<https://standards.iteh.ai/catalog/standards/sist/5b1e95d-13a5-4342-9330-421053968575/iec-tr-62710-2015>

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

ICS 29.200

ISBN 978-2-8322-2660-5

Warning! Make sure that you obtained this publication from an authorized distributor.

CONTENTS

FOREWORD.....	4
INTRODUCTION.....	6
1 Scope.....	7
2 Normative references	7
3 Terms and definitions	8
4 Classification according to the association of a RCD with additional function(s).....	9
4.1 General.....	9
4.2 According to the type of construction	9
4.3 According to the interface between a RCD and additional function(s).....	9
5 Characteristics	10
6 Marking and other product information.....	10
6.1 Instructions and operation for RCDs with integrated additional function(s) according to 4.2 a).....	10
6.2 Instructions and operation for a non integrated additional function according to 4.2 b)	10
7 Standard conditions for operation in service and for installation.....	10
8 Requirements for construction and operation.....	11
8.1 General.....	11
8.2 Mechanical requirements	12
8.3 Electrical compatibility	12
8.4 Protection against electric shock.....	12
8.5 Dielectric properties, isolating capability and insulation coordination.....	12
8.6 Clearances and creepage distances.....	13
8.7 Screws, current-carrying parts and connections	13
8.8 Terminals for external conductors	13
8.9 Temperature rise	13
8.10 Mechanical and electrical endurance	13
8.11 Performance at short-circuit currents	13
8.12 Resistance to mechanical shock and impact	14
8.13 Resistance to heat, to abnormal temperature and to fire	14
8.14 Test device	14
8.15 Behaviour of RCDs in the case of overcurrents in the main circuit.....	14
8.16 Behaviour of RCDs in the case of current surges caused by impulse voltages	14
8.17 Behaviour of RCDs in the case of sinusoidal residual currents and in case of residual currents comprising a d.c. component.....	14
8.18 Reliability.....	15
8.19 Electromagnetic compatibility (EMC).....	15
8.20 Operating characteristics	15
8.20.1 Operating characteristics of the RCD	15
8.20.2 Influence of the additional function(s) on the performance of the RCD with different conditions of supply voltage.....	15
9 Tests	16
9.1 General.....	16
9.2 The additional function is integrated within the RCD according to 4.2 a)	16
9.3 The additional function is not integrated within a declared RCD according to 4.2b) whose compliance to the relevant RCD standard is not yet tested.....	17

9.4	The additional function is not integrated within a declared RCD according to 4.3 whose compliance to the relevant RCD standard is already tested	17
9.5	Testing procedure	17
9.5.1	General	17
9.5.2	Impairment identification	20
9.5.3	Impairment assessment	21
9.5.4	Verification of the influence of the additional function(s) on the performance of the RCD at different states of supply voltage	23
9.6	Documentation	24
Annex A (informative) Additional requirements and tests for RCDs consisting of a RCD and a non integrated additional function unit designed for assembly on site		25
A.1	General	25
A.2	Scope	25
A.3	Terms and definitions	25
A.4	Marking and other product information	25
A.4.1	Manufacturer's name or trademark	25
A.4.2	Marking	25
A.4.3	Instructions for assembly and operation	26
A.5	Constructional requirements	26
A.5.1	General	26
A.5.2	Degree of protection	26
A.5.3	Mechanical requirements	26
A.5.4	Electrical compatibility	27
A.6	Type tests and verifications	27
A.6.1	Tests on RCDs	27
A.6.2	Tests on non integrated additional function unit to be assembled on site	27
A.6.3	Tests on assembled RCDs and non integrated additional function unit	27
A.6.4	Verification of marking and constructional requirements	27
Bibliography		28
Table 1 – List of basic tests to be considered, according to the interface between RCDs and additional function(s), during the assessment		18

INTERNATIONAL ELECTROTECHNICAL COMMISSION

**RESIDUAL CURRENT DEVICES (RCDs) ASSOCIATED
WITH ADDITIONAL FUNCTION(S)**

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

The main task of IEC technical committees is to prepare International Standards. However, a technical committee may propose the publication of a technical report when it has collected data of a different kind from that which is normally published as an International Standard, for example "state of the art".

IEC TR 62710, which is a Technical Report, has been prepared by subcommittee 23E: Circuit-breakers and similar equipment for household use, of IEC technical committee 23: Electrical accessories.

The text of this standard is based on the following documents:

Enquiry draft	Report on voting
23E/875/DTR	23E/900/RVC

Full information on the voting for the approval of this technical report can be found in the report on voting indicated in the above table.

This publication has been drafted in accordance with the ISO/IEC Directives, Part 2.

In this Technical Report, the following print types are used:

- compliance statements: *in italic type*

The committee has decided that the contents of this publication will remain unchanged until the stability date indicated on the IEC website under "<http://webstore.iec.ch>" in the data related to the specific publication. At this date, the publication will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

A bilingual version of this publication may be issued at a later date.

iTeh STANDARD PREVIEW (standards.iteh.ai)

[IEC TR 62710:2015](https://standards.iteh.ai/catalog/standards/sist/5bf1e95d-13a5-4342-9330-421053968575/iec-tr-62710-2015)

<https://standards.iteh.ai/catalog/standards/sist/5bf1e95d-13a5-4342-9330-421053968575/iec-tr-62710-2015>

INTRODUCTION

This Technical Report (TR) introduces information allowing manufacturers to introduce additional function(s) associated with Residual current devices (RCD). This TR is also relevant for technical committees in charge of drafting an International Standard for additional function(s); for this purpose, requirements and tests have been introduced. It would also be of benefit to laboratories having difficulties in testing RCDs associated with an additional function. This TR does not cover the additional function(s) itself (this is the purpose of an International Standard covering the additional function(s)), nor the RCD function and characteristics (this is the purpose of an RCD International Standard). It is limited to checking that the additional function(s) do not impair any function of the RCD in case there is no International Standard for the additional function(s) for household and similar uses. Where there is a relevant International Standard for household and similar uses for the additional function(s), then it is used. This means that the assembly of the RCD plus the additional function(s) behave correctly according to the referred standards.

This Technical Report is drafted according to the following basic principles:

- In order not to restrict innovation, it is drafted independently of the additional function(s) and is thus applicable whatever the additional function(s) are.

NOTE It is not possible to list all possible existing and future additional function(s); some examples are given within the definitions.

- The verification is only limited to the assembly and association of an RCD with one or several additional function(s), being integrated or not.
- The verification aims to show that the assembly of one or several additional function(s) declared suitable to a specific protective device is safe and does not impair the basic characteristics of the RCD.
- Responsibility for the assembly means that the additional function(s) and the RCD are intended to be from the same manufacturer or to be affixed with the same trademark. As a consequence, it is intended that the manufacturer or trademark owner declare with which protective devices the additional function(s) can be associated.

RESIDUAL CURRENT DEVICES (RCDs) ASSOCIATED WITH ADDITIONAL FUNCTION(S)

1 Scope

This Technical Report (TR) provides information concerning the possible use of:

- dedicated additional function(s) declared by a manufacturer as suitable for an assembly with declared RCDs complying with IEC standards for household and similar uses;
- specific RCDs complying with IEC standards for household and similar uses having integrated additional function(s).

NOTE 1 The term RCD is a generic term applied to a family of products which open automatically in response to a residual current at or exceeding the RCD's rated residual operating current $I_{\Delta n}$. This generic term is often applied to the following:

- RCCB: Residual current operated circuit-breaker without integral overcurrent protection;
- RCBO: Residual current operated circuit-breaker with integral overcurrent protection;
- SRCD: Residual current device with or without overcurrent protection for socket-outlets;
- PRCD: Portable residual current device without integral overcurrent protection.

This TR identifies the applicable testing procedure to determine the effect on the normal functioning of specific RCD(s) declared suitable with one or more additional function(s) integrated into or added to or assembled with this specific RCD.

This TR may also be used to draft additional requirements to standards for additional function(s) intended to be combined with RCDs for household and similar applications.

This TR provides a procedure based on an assessment in order to identify the necessary testing to demonstrate compliance with the appropriate requirements. If the assessment of the additional function integrated in the RCDs concludes that the additional function does not impair the RCD, no additional test is required by this TR.

Where more than one additional function(s) can be simultaneously associated with one or several RCD(s), the possible combinations is checked by considering the most severe ones.

This TR does not apply:

- to additional functions covered by a standard which explicitly addresses the combination with RCDs for household and similar applications;

NOTE 2 Example of an additional device with independent product standard is auxiliary contacts according to IEC 62019.

- to additional function(s) associated with RCDs for connection purposes;

NOTE 3 Examples of additional function(s) for connection purposes are connection devices between RCBOs and a circuit breakers.

- to locking devices.

2 Normative references

The following documents, in whole or in part, are normatively referenced in this document and are indispensable for its application. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC TR 60755, *General requirements for residual current operated protective devices*

IEC 60898 (all parts), *Electrical accessories – Circuit-breakers for overcurrent protection for household and similar installations*

IEC 61008 (all parts), *Residual current operated circuit-breakers without integral overcurrent protection for household and similar uses (RCCBs)*

IEC 61009 (all parts), *Residual current operated circuit-breakers with integral overcurrent protection for household and similar uses (RCBOs)*

IEC 62423, *Type F and type B residual current operated circuit-breakers with and without integral overcurrent protection for household and similar uses*

3 Terms and definitions

For the purposes of this document, the terms and definitions given in IEC 60755, IEC 60898, IEC 61008, IEC 61009 and IEC 62423, as well as the following apply.

3.1

additional function

feature, action, capability, or the like integrated or assembled with a declared RCD, and not required by the basic product standard

Note 1 to entry: The additional function(s) can have a mechanical and/or electrical interface with one or more parts of the RCD.

Note 2 to entry: Examples of additional function(s) are: automatic reclosing devices, protection against too high or too low voltage, remote-controlled mechanism, remote-controlled tripping, telemonitoring, undervoltage release, shunt release, residual current indicator, lifetime monitoring, installation monitoring, thermal monitoring, self monitoring and test, data communication, smoke detector as well as any combinations of these devices, etc.

3.1.1

integrated additional function

additional function completely built into the RCD

3.1.2

non integrated additional function

external additional function such as a module which can subsequently be built-in on site or can be added on by the manufacturer

Note 1 to entry: The additional function(s) may influence the RCD via interfaces.

Note 2 to entry: After assembly of the external additional function(s) with the RCD, the device becomes a constructional unit.

3.2

RCD

residual current device

mechanical switching device designed to make, carry and break currents under normal service conditions and to cause the opening of the contacts when the residual current attains a given value under specified conditions

Note 1 to entry: RCDs are covered by an applicable RCD product standard and are used as a protective device against electric shock.

[SOURCE: IEC 60050-442:1998, 442-05-02, modified – The note has been modified.]

3.3**impair**

impact on the operating characteristics of an RCD that results in the lack of compliance with the applicable RCD requirements

3.4**impairment**

any effect caused by an additional function that takes the operating characteristics outside the limits specified in the relevant RCD product standard

3.5**exploratory testing**

analysis and/or relevant testing performed on the assembly of

- an additional function and a RCD declared to be assembled with the additional function(s) according to the manufacturer instructions, or
- a RCD with integrated additional function(s),

with the objective of determining whether the additional function(s) impair the correct operation of the RCD.

3.6**residual current tripping circuit**

any electrical part of the RCD allowing the RCD to trip due to residual fault current

3.7**operating means**

part of a RCD which allows operation of the mechanism by manual means

EXAMPLE Rocker or rotary handle.

iTeh STANDARD PREVIEW
(standards.iteh.ai)
<https://standards.iteh.ai/catalog/standards/sist/5bf1e95d-13a5-4342-9330-421053968575/iec-tr-62710-2015>

4 Classification according to the association of a RCD with additional function(s)

4.1 General

Additional functions are classified in the following way.

4.2 According to the type of construction

Additional functions are classified according to the type of construction:

- a) RCDs with integrated additional function(s);
- b) RCDs with non integrated additional function(s);

4.3 According to the interface between a RCD and additional function(s)

Additional functions are classified according to the type of interface:

- a) interface via the operating means,
- b) interface via the mechanism of the RCD,
EXAMPLE Latching mechanism, operating shaft.
- c) interface via the circuit of the test device,
- d) interface via the residual current tripping circuit,

EXAMPLE Summation current transformer with additional winding, tripping relay, protective circuit of the tripping relay or of the secondary circuit of the summation current transformer.

- e) interface via the main circuit / main contacts / main terminals,

- f) interface via a combination of more than one interface.


5 Characteristics

The characteristics of the RCD are given in the relevant RCD standard.

The characteristics of the additional function(s) are given in the relevant standard, if any.

6 Marking and other product information

6.1 Instructions and operation for RCDs with integrated additional function(s) according to 4.2 a)

Where the manufacturer has integrated the additional function(s) within the RCD, the RCD shall be marked with the symbol  (IEC 60417-6291) and the manufacturer shall provide adequate instructions and information in a leaflet or data sheet.

These instructions shall cover at least the following:

- detailed description and explanation about the use and objective of the additional function(s);
- derating factor(s), if any;
- instructions for wiring and installation of the RCD integrating the additional function(s) in normal use;
- instructions for correct use of the additional function(s).

6.2 Instructions and operation for a non integrated additional function according to 4.2 b)

Where the additional function is not integrated within the RCD, the manufacturer shall provide adequate instructions and information in a leaflet or data sheet. These instructions shall cover at least the following:

- detailed description and explanation about the use and objective of the additional function(s);
- reference to the type(s) and catalogue number(s), covering current and voltage ratings, etc. of the declared RCD;
- derating factor(s), if any;
- method of assembly with the declared RCD(s);
- instruction for wiring and installation for normal use;
- method for checking operation after assembly to verify the mechanical operation of the RCD by mechanical means and using the test device;
- instructions for correct use of the additional function(s).

The non-integrated additional function(s) and the RCD shall be from the same manufacturer or be affixed with the same trademark.

7 Standard conditions for operation in service and for installation

The additional function(s) associated with a RCD shall be capable of operating under the standard conditions for operation in service and for installation of the RCD standard with which it is declared to be associated (IEC 61008-1 or IEC 61009-1 or IEC 61540 or IEC 62335 or IEC 62423 or IEC 62640 as applicable).