

# INTERNATIONAL STANDARD

**Electric motor-operated hand-held tools, transportable tools and lawn and garden machinery – Safety –  
Part 2-17: Particular requirements for hand-held routers**

Document Preview

[IEC 62841-2-17:2017](#)

<https://standards.iteh.ai/catalog/standards/iec/a6f860f4-2158-42df-890f-8eb1abe16cde/iec-62841-2-17-2017>





**THIS PUBLICATION IS COPYRIGHT PROTECTED**  
**Copyright © 2025 IEC, Geneva, Switzerland**

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester. If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

IEC Secretariat  
3, rue de Varembe  
CH-1211 Geneva 20  
Switzerland

Tel.: +41 22 919 02 11  
[info@iec.ch](mailto:info@iec.ch)  
[www.iec.ch](http://www.iec.ch)

**About the IEC**

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

**About IEC publications**

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigendum or an amendment might have been published.

**IEC publications search - [webstore.iec.ch/advsearchform](http://webstore.iec.ch/advsearchform)**

The advanced search enables to find IEC publications by a variety of criteria (reference number, text, technical committee, ...). It also gives information on projects, replaced and withdrawn publications.

**IEC Just Published - [webstore.iec.ch/justpublished](http://webstore.iec.ch/justpublished)**

Stay up to date on all new IEC publications. Just Published details all new publications released. Available online and once a month by email.

**IEC Customer Service Centre - [webstore.iec.ch/csc](http://webstore.iec.ch/csc)**

If you wish to give us your feedback on this publication or need further assistance, please contact the Customer Service Centre: [sales@iec.ch](mailto:sales@iec.ch).

**IEC Products & Services Portal - [products.iec.ch](http://products.iec.ch)**

Discover our powerful search engine and read freely all the publications previews, graphical symbols and the glossary. With a subscription you will always have access to up to date content tailored to your needs.

**Electropedia - [www.electropedia.org](http://www.electropedia.org)**

The world's leading online dictionary on electrotechnology, containing more than 22 500 terminological entries in English and French, with equivalent terms in 25 additional languages. Also known as the International Electrotechnical Vocabulary (IEV) online.

International  
Standards  
Document Preview  
iteh.standards.iteh.ai

[IEC 62841-2-17:2017](https://standards.iteh.ai/catalog/standards/iec/a6f860f4-2158-42df-890f-8eb1abe16cde/iec-62841-2-17-2017)

<https://standards.iteh.ai/catalog/standards/iec/a6f860f4-2158-42df-890f-8eb1abe16cde/iec-62841-2-17-2017>



IEC 62841-2-17

Edition 1.1 2025-02  
CONSOLIDATED VERSION

# INTERNATIONAL STANDARD

Electric motor-operated hand-held tools, transportable tools and lawn and garden machinery – Safety –  
Part 2-17: Particular requirements for hand-held routers

Document Preview

[IEC 62841-2-17:2017](https://standards.iteh.ai/catalog/standards/iec/a6f860f4-2158-42df-890f-8eb1abe16cde/iec-62841-2-17-2017)

<https://standards.iteh.ai/catalog/standards/iec/a6f860f4-2158-42df-890f-8eb1abe16cde/iec-62841-2-17-2017>

INTERNATIONAL  
ELECTROTECHNICAL  
COMMISSION

ICS 25.140.20

ISBN 978-2-8327-0290-1

**Warning! Make sure that you obtained this publication from an authorized distributor.**

## CONTENTS

FOREWORD .....	4
1 Scope .....	6
2 Normative references .....	6
3 Terms and definitions .....	6
4 General requirements .....	7
5 General conditions for the tests .....	7
6 Radiation, toxicity and similar hazards .....	7
7 Classification .....	7
8 Marking and instructions .....	7
9 Protection against access to live parts .....	8
10 Starting .....	8
11 Input and current .....	8
12 Heating .....	8
13 Resistance to heat and fire .....	8
14 Moisture resistance .....	8
15 Resistance to rusting .....	8
16 Overload protection of transformers and associated circuits .....	9
17 Endurance .....	9
18 Abnormal operation .....	9
19 Mechanical hazards .....	9
20 Mechanical strength .....	11
21 Construction .....	11
22 Internal wiring .....	12
23 Components .....	12
24 Supply connection and external flexible cords .....	12
25 Terminals for external conductors .....	12
26 Provision for earthing .....	12
27 Screws and connections .....	12
28 Creepage distances, clearances and distances through insulation .....	12
Annexes .....	16
Annex I (informative) Measurement of noise and vibration emissions .....	16
Annex K (normative) Battery tools and battery packs .....	19
Annex L (normative) Battery tools and battery packs provided with mains connection or non-isolated sources .....	20
Bibliography .....	21
Figure 101 – Measurement of distance between handle and rotary cutting bit .....	13
Figure 102 – Various designs with barrier .....	14
Figure 103 – Design with minimum distance from grasping surface .....	15
Figure I.101 – Positions of transducers for type 2 routers .....	17
Figure I.102 – Positions of transducers for type 1 routers .....	18

Table 4 – Required performance levels .....	9
Table I.101 – Test conditions for type 2 routers .....	16

**iTeh Standards**  
**(<https://standards.iteh.ai>)**  
**Document Preview**

[IEC 62841-2-17:2017](https://standards.iteh.ai/catalog/standards/iec/a6f860f4-2158-42df-890f-8eb1abe16cde/iec-62841-2-17-2017)

<https://standards.iteh.ai/catalog/standards/iec/a6f860f4-2158-42df-890f-8eb1abe16cde/iec-62841-2-17-2017>

## INTERNATIONAL ELECTROTECHNICAL COMMISSION

**ELECTRIC MOTOR-OPERATED HAND-HELD TOOLS, TRANSPORTABLE  
TOOLS AND LAWN AND GARDEN MACHINERY – SAFETY –****Part 2-17: Particular requirements for hand-held routers**

## FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) IEC draws attention to the possibility that the implementation of this document may involve the use of (a) patent(s). IEC takes no position concerning the evidence, validity or applicability of any claimed patent rights in respect thereof. As of the date of publication of this document, IEC had not received notice of (a) patent(s), which may be required to implement this document. However, implementers are cautioned that this may not represent the latest information, which may be obtained from the patent database available at <https://patents.iec.ch>. IEC shall not be held responsible for identifying any or all such patent rights.

**This consolidated version of the official IEC Standard and its amendment has been prepared for user convenience.**

**IEC 62841-2-17 edition 1.1 contains the first edition (2017-08) [documents 116/335/FDIS and 116/342/RVD] and its amendment 1 (2025-02) [documents 116/858/FDIS and 116/881/RVD].**

**In this Redline version, a vertical line in the margin shows where the technical content is modified by amendment 1. Additions are in green text, deletions are in strikethrough red text. A separate Final version with all changes accepted is available in this publication.**

International Standard IEC 62841-2-17 has been prepared by IEC technical committee 116: Safety of motor-operated electric tools.

This document has been drafted in accordance with the ISO/IEC Directives, Part 2.

This Part 2-17 is to be used in conjunction with the first edition of IEC 62841-1 (2014).

This Part 2-17 supplements or modifies the corresponding clauses in IEC 62841-1, so as to convert it into the IEC standard: Particular requirements for hand-held routers.

Where a particular subclause of Part 1 is not mentioned in this Part 2-17, that subclause applies as far as relevant. Where this standard states “addition”, “modification” or “replacement”, the relevant text in Part 1 is to be adapted accordingly.

The following print types are used:

- requirements: in roman type;
- *test specifications: in italic type;*
- notes: in small roman type.

The terms defined in Clause 3 are printed in **bold typeface**.

Subclauses, notes and figures which are additional to those in Part 1 are numbered starting from 101.

A list of all parts of the IEC 62841 series, under the general title: *Electric motor-operated hand-held tools, transportable tools and lawn and garden machinery – Safety*, can be found on the IEC website.

The committee has decided that the contents of this document and its amendment will remain unchanged until the stability date indicated on the IEC website under [webstore.iec.ch](http://webstore.iec.ch) in the data related to the specific document. At this date, the document will be

- reconfirmed,
- withdrawn, or
- revised.

The National Committees are requested to note that for this document the stability date is 2019.

THIS TEXT IS INCLUDED FOR THE INFORMATION OF THE NATIONAL COMMITTEES AND WILL BE DELETED AT THE PUBLICATION STAGE.

NOTE The attention of National Committees is drawn to the fact that equipment manufacturers and testing organizations may need a transitional period following publication of a new, amended or revised IEC publication in which to make products in accordance with the new requirements and to equip themselves for conducting new or revised tests.

It is the recommendation of the committee that the content of this publication be adopted for implementation nationally not earlier than 36 months from the date of publication.

# ELECTRIC MOTOR-OPERATED HAND-HELD TOOLS, TRANSPORTABLE TOOLS AND LAWN AND GARDEN MACHINERY – SAFETY –

## Part 2-17: Particular requirements for hand-held routers

### 1 Scope

This clause of Part 1 is applicable, except as follows:

*Addition:*

This part of IEC 62841 applies to hand-held **routers** intended for cutting slots into or shaping the edge of wood and analogous materials, plastics and non-ferrous metals except magnesium.

NOTE 101 **Routers** that are primarily used for trimming the edge of materials are also known as trimmers.

NOTE 102 **Routers** that are used to cut various materials through the rotary action are also known as rotary cutters.

This part of IEC 62841 does not apply to jointers.

NOTE 103 Jointers are covered by IEC 62841-2-19.

This part of IEC 62841 does not apply to small rotary tools.

NOTE 104 Small rotary tools are covered by IEC 62841-2-23.

### 2 Normative references

[IEC 62841-2-17:2017](https://standards.iteh.ai/catalog/standards/iec/a6f860f4-2158-42df-890f-8eb1abe16cde/iec-62841-2-17-2017)

<https://standards.iteh.ai/catalog/standards/iec/a6f860f4-2158-42df-890f-8eb1abe16cde/iec-62841-2-17-2017>

This clause of Part 1 is applicable.

### 3 Terms and definitions

This clause of Part 1 is applicable, except as follows:

*Additional definitions:*

#### 3.101

##### **base**

part ~~supporting~~ of the **router** that supports other parts of the tool on the workpiece

#### 3.102

##### **rotary cutting bit**

rotating cutting **accessory** with a shank for mounting it into a collet having its main feed direction perpendicular to its axis of rotation

Note 1 to entry: There are **rotary cutting bits** that allow an additional plunging operation parallel to its axis of rotation.

#### 3.103

##### **router**

tool ~~with a~~ which includes a motor housing, **base** and a collet, designed to be fitted with a **rotary cutting bit**



### 3.104 trimmer

**type 1 router** designed to be fitted with a rotary cutter and a base that allows for control of trimming the edge of laminate sheet or similar materials

### 3.105 type 1 router

**router** that has the following criteria:

- a) ~~a mass, excluding a detachable base, a separable battery pack or a detachable battery pack~~ a mass of the motor housing and collet, excluding the **base**, **supply cord**, any **separable battery pack** or any **detachable battery pack**, not exceeding 2 kg; and
- b) a collet capacity not exceeding 8 mm

### 3.106 type 2 router

**router** that has the following criteria:

- a) ~~a mass, excluding a detachable base, a separable battery pack or a detachable battery pack~~ a mass of the motor housing and collet, excluding the **base**, **supply cord**, any **separable battery pack** or any **detachable battery pack**, exceeding 2 kg; or
- b) a collet capacity exceeding 8 mm

## 4 General requirements

This clause of Part 1 is applicable.

## 5 General conditions for the tests

This clause of Part 1 is applicable, except as follows:

**5.17 Addition:** [IEC 62841-2-17:2017](https://standards.iteh.ai/catalog/standards/iec/a6f860f4-2158-42df-890f-8eb1abe16cde/iec-62841-2-17-2017)

*The mass of the tool includes all handles and the dust extraction adapter, if any.*

## 6 Radiation, toxicity and similar hazards

This clause of Part 1 is applicable.

## 7 Classification

This clause of Part 1 is applicable.

## 8 Marking and instructions

This clause of Part 1 is applicable, except as follows:

### 8.1 Addition:

- **rated no-load speed.**

### 8.14.1 Addition:

The additional safety instructions as specified in 8.14.1.101 shall be given. This part may be printed separately from the “General Power Tool Safety Warnings”.

#### 8.14.1.101 Safety instructions for routers

- a) **Hold the power tool by insulated gripping surfaces only, because the cutter may contact its own cord.** *Cutting a "live" wire may make exposed metal parts of the power tool "live" and could give the operator an electric shock.*
- b) **Use clamps or another practical way to secure and support the workpiece to a stable platform.** *Holding the work by your hand or against the body leaves it unstable and may lead to loss of control.*

#### 8.14.2 a) Additional items:

- 101) Information about the types of **rotary cutting bits** for which the tool is designed;
- 102) Information concerning the diameter of shank for which the collet(s) is intended;
- 103) Instruction to use only **rotary cutting bits** of the correct shank diameter for the collet mounted;
- 104) Instruction to use only **rotary cutting bits** suitable for the speed of the tool;
- 105) Instruction on how to change the collet or the collet cone (e.g. for setting up different shank diameters), if applicable.

#### 8.14.2 b) Additional items:

- 101) Instruction on the correct use of the dust collection system, if applicable.

### 9 Protection against access to live parts

This clause of Part 1 is applicable.

### 10 Starting

This clause of Part 1 is applicable.

### 11 Input and current

This clause of Part 1 is applicable.

### 12 Heating

This clause of Part 1 is applicable.

### 13 Resistance to heat and fire

This clause of Part 1 is applicable.

### 14 Moisture resistance

This clause of Part 1 is applicable.

### 15 Resistance to rusting

This clause of Part 1 is applicable.

## 16 Overload protection of transformers and associated circuits

This clause of Part 1 is applicable.

## 17 Endurance

This clause of Part 1 is applicable.

## 18 Abnormal operation

This clause of Part 1 is applicable, except as follows:

### 18.8 Replacement of Table 4 by the following:

**Table 4 – Required performance levels**

Type and purpose of SCF	Minimum performance level (PL)
Power switch – prevent unwanted switch-on for <b>type 1 routers</b>	b
Power switch – prevent unwanted switch-on for <b>type 2 routers</b>	c
Power switch – provide desired switch-off	b
Any electronic control to pass the test of 18.3	a
Overspeed prevention to prevent output speed above 130 % of <b>rated no-load speed</b>	b
Provide desired direction of rotation	a
Prevent exceeding thermal limits as in <b>Clause 18.4 and 18.5.3</b>	a
Prevent self-resetting as required in 23.3 for <b>type 1 routers</b>	a
Prevent self-resetting as required in 23.3 for <b>type 2 routers</b>	b
Prevent unwanted lock-on of the <b>power switch</b> function	b
Lock-off function as required by 21.18.1.2 for <b>type 1 routers</b>	a
Lock-off function as required by 21.18.1.2 for <b>type 2 routers</b>	b
NOTE In Europe (EN 62841-2-17), the following additional requirement applies: Restart prevention as required by 21.18.1.1	b

## 19 Mechanical hazards

This clause of Part 1 is applicable, except as follows:

### 19.1 Replacement of the first paragraph:

Moving and dangerous parts other than the **rotary cutting bit** and the collet shall be so positioned or enclosed to provide adequate protection against personal injury. The protection of the user against accidental contact with the **rotary cutting bit** and the collet is provided by the requirements of 19.4.101.

### 19.4 Replacement:

**Type 1 routers** shall have at least one handle or grasping surface. The motor housing and/or parts of the **base** that assist in guiding the **router** in use may be considered as a grasping surface, if identified as such in accordance with 8.14.2 b) 6).

**Type 2 routers** shall have at least one handle and an additional handle or grasping surface to allow the operation of the tool with two hands. The motor housing and/or parts of the **base** that assist in guiding the **router** in use may be considered as a grasping surface, if identified as such in accordance with 8.14.2 b) 6).

*Compliance is checked by inspection.*

#### 19.4.101 Prevention of inadvertent contact

The handles shall be so shaped or located as to minimise the risk of inadvertent contact of the user's hand with the **rotary cutting bit** and the collet.

For **type 1 routers**, a removable cover for the purpose of changing the **accessory** which is provided to meet the requirements of 19.4.101 may be removable without the aid of a tool.

For handle(s), inadvertent contact of the user's hand is considered to be prevented if there is sufficient distance between a defined measuring point on the handle surface and the **rotary cutting bit** and the collet.

*Compliance is checked as follows:*

*A test pin with a diameter of the largest collet size is mounted to the tool. A mark is applied around the test pin ( $10 \pm 1$ ) mm from the collet. The distance between the defined measuring point and the mark on the test pin shall be at least 120 mm. The measurement shall be carried out as a chain distance. See Figure 101.*

*With the **base** set to maximum depth of cut, to establish the measuring point on the handle(s), follow the outlined procedure below.*

- a) *Establish the closest (A) and the most distant (B) points from the plane of the **base** on the handle. Equidistant between points (A) and (B), draw the horizontal intersecting line on the plane parallel with the **base** and the surface of the handle.*
- b) *The point on the intersecting line of the handle surface with the largest radial distance from the centreline of the spindle is the defined measuring point.*

For a motor housing and/or parts of the **base** used as a grasping surface, inadvertent contact of the user's hand is considered to be prevented by a barrier located between the grasping surface and the **rotary cutting bit**, see Figure 102. The barrier shall have a height  $x$  of at least 6 mm. A dust collecting system may be part of this barrier.

Alternatively to a barrier, for a motor housing and/or parts of the **base** used as a grasping surface in a **type 1 router** with an open portion(s) above the **base**, inadvertent contact of the user's hand is also considered to be prevented if either

- the **rotary cutting bit** and the collet are not accessible above the **base** by means of the test probe B of IEC 61032:1997 with a force not exceeding 5 N;

or

- there is a minimum distance of 60 mm between
  - a point located 40 mm above the lower edge of the grasping surface area in accordance with 8.14.2 b) 6) along its centreline; and
  - any point on the edge of any open portion (see Figure 103).

*Compliance is checked by manual test using test probe B of IEC 61032:1997 and by measurement. No covers are removed for the manual test. The 60 mm measurement is carried out as a chain distance.*