
**Niskonapetostne električne inštalacije - 1. del: Temeljna načela, ocenjevanje
splošnih značilnosti, definicije**

Low-voltage electrical installations - Part 1: Fundamental principles, assessment of
general characteristics, definitions

INTERNATIONAL STANDARD

IEC
60364-1

Fifth edition
2005-11

Low-voltage electrical installations –

Part 1: Fundamental principles, assessment of general characteristics, definitions

© IEC 2005 Copyright - all rights reserved

No part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from the publisher.

International Electrotechnical Commission, 3, rue de Varembe, PO Box 131, CH-1211 Geneva 20, Switzerland
Telephone: +41 22 919 02 11 Telefax: +41 22 919 03 00 E-mail: inmail@iec.ch Web: www.iec.ch



Commission Electrotechnique Internationale
International Electrotechnical Commission
Международная Электротехническая Комиссия

PRICE CODE

X

For price, see current catalogue

CONTENTS

FOREWORD.....	9
11 Scope.....	13
12 Normative references	17
13 Fundamental principles	19
131 Protection for safety.....	19
131.1 General.....	19
131.2 Protection against electric shock	19
131.3 Protection against thermal effects	21
131.4 Protection against overcurrent.....	21
131.5 Protection against fault currents.....	21
131.6 Protection against voltage disturbances and measures against electromagnetic influences	21
131.7 Protection against power supply interruption	23
132 Design	23
132.1 General	23
132.2 Characteristics of available supply or supplies	23
132.3 Nature of demand.....	25
132.4 Electric supply systems for safety services or standby electric supply systems.....	25
132.5 Environmental conditions	25
132.6 Cross-sectional area of conductors	25
132.7 Type of wiring and methods of installation	27
132.8 Protective equipment.....	27
132.9 Emergency control	27
132.10 Disconnecting devices.....	27
132.11 Prevention of mutual detrimental influence	27
132.12 Accessibility of electrical equipment	27
132.13 Documentation for the electrical installation	29
133 Selection of electrical equipment	29
133.1 General	29
133.2 Characteristics	29
133.3 Conditions of installation	29
133.4 Prevention of harmful effects.....	31
134 Erection and verification of electrical installations	31
134.1 Erection	31
134.2 Initial verification.....	33
134.3 Periodic verification.....	33
20 Terms and definitions	33
30 Assessment of general characteristics.....	33
31 Purposes, supplies and structure.....	33
311 Maximum demand and diversity	33
312 Conductor arrangement and system earthing	33
312.1 Current-carrying conductors depending on kind of current.....	35
312.2 Types of system earthing	37

313	Supplies.....	71
313.1	General.....	71
313.2	Supplies for safety services and standby systems.....	71
314	Division of installation.....	71
32	Classification of external influences.....	73
33	Compatibility.....	73
33.1	Compatibility of characteristics.....	73
33.2	Electromagnetic compatibility.....	73
34	Maintainability.....	73
35	Safety services.....	75
35.1	General.....	75
35.2	Classification.....	75
36	Continuity of service.....	75
Annex A (informative) Numbering system and plan of IEC 60364 series.....		77
Annex B (informative) Definitions – Application guide and explanations to selected terms of IEC 60050-826 (IEV 826 – Electrical Installations).....		83
Annex C (informative) Comparison of the structure of IEC 60364-1 fourth edition 2001 and IEC 60364-1 fifth edition 2005.....		89
Bibliography.....		93
Figure 1 – Single-phase 2-wire.....		35
Figure 2 – Single-phase 3-wire.....		35
Figure 3 – Two-phase 3-wire.....		35
Figure 4 – Three-phase 3-wire.....		35
Figure 5 – Three-phase 4-wire.....		37
Figure 6 – 2-wire.....		37
Figure 7 – 3-wire.....		37
Figure 31A1 – TN-S system with separate neutral conductor and protective conductor throughout the system.....		39
Figure 31A2 – TN-S system with separate earthed line conductor and protective conductor throughout the system.....		41
Figure 31A3 – TN-S system with earthed protective conductor and no distributed neutral conductor throughout the system.....		41
Figure 31B1 – TN-C-S system 3-phase, 4-wire, where the PEN is separated into PE and N elsewhere in the installation.....		43
Figure 31B2 – TN-C-S system 3-phase, 4-wire where the PEN is separated into PE and N at the origin of the installation.....		45
Figure 31B3 – TN-C-S system – Single-phase, 2-wire where the PEN is separated into PE and N at the origin of the installation.....		45
Figure 31C – TN-C system with neutral and protective conductor functions combined in a single conductor throughout the system.....		47
Figure 31D – TN-C-S multiple source system with separate protective conductor and neutral conductor to current using equipment.....		49
Figure 31E – TN multiple source system with protective conductor and no neutral conductor throughout the system for 2- or 3-phase load.....		51

Figure 31F1 – TT system with separate neutral conductor and protective conductor throughout the installation.....	53
Figure 31F2 – TT system with earthed protective conductor and no distributed neutral conductor throughout the installation	55
Figure 31G1 – IT system with all exposed-conductive-parts interconnected by a protective conductor which is collectively earthed	57
Figure 31G2 – IT system with exposed-conductive-parts earthed in groups or individually.....	59
Figure 31H – TN-S d.c. system	61
Figure 31J – TN-C d.c. system.....	63
Figure 31K – TN-C-S d.c. system.....	65
Figure 31L – TT d.c. system	67
Figure 31M – IT d.c. system.....	69
Figure B.1 – Zone of arm's reach.....	85
Table A.1 – Numbering system of IEC 60364 series.....	77
Table A.2 – Plan of IEC 60364 series: Electrical installations of buildings	79

INTERNATIONAL ELECTROTECHNICAL COMMISSION

LOW-VOLTAGE ELECTRICAL INSTALLATIONS –

**Part 1: Fundamental principles, assessment of
general characteristics, definitions**

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC provides no marking procedure to indicate its approval and cannot be rendered responsible for any equipment declared to be in conformity with an IEC Publication.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

International Standard IEC 60364-1 has been prepared by IEC Technical Committee 64: Electrical installations and protection against electric shock.

This fifth edition cancels and replaces the fourth edition, published in 2001. It constitutes a technical revision.

The main changes with respect to the previous edition are:

- in order to complete the scope, the new items external lighting and similar installations, medical locations, mobile or transportable units, photovoltaic power supply units and low-voltage generating sets are added;
- in Clause 131, "Fundamental principles", the list of hazards which may arise in electrical installations is completed; furthermore, a new subclause dealing with protection against voltage disturbances and measures against electromagnetic influences and a new subclause dealing with protection against power supply interruption are added;

- in Clause 132, "Design", the new subclause "Documentation for the electrical installation" is added;
- in Clause 134, "Erection and verification of electrical installations", the new subclause "periodic verification" is added;
- the former Clause 312, "Types of distribution system" is renamed "Conductor arrangement and system earthing" and, in the relevant subclauses, several new figures are included for better understanding of the different kind of a.c. and d.c. circuits and types of systems and their earthing being applied nowadays in IEC member countries;
- in 33.1, "Compatibility of characteristics", a new item for excessive PE conductor currents is added;
- a new Clause 36, "Continuity of service", is included;
- Annex B is aligned with the second edition of IEC 60050-826:2004.

The text of this standard is based on the following documents:

FDIS	Report on voting
64/1488/FDIS	64/1499/RVD

Full information on the voting for the approval of this standard can be found in the report on voting indicated in the above table.

This publication has been drafted in accordance with the ISO/IEC Directives, Part 2.

IEC 60364 consists of the following parts, under the general title *Low-voltage electrical installations*:

Part 1: Fundamental principles, assessment of general characteristics, definitions

Part 4: Protection for safety

Part 5: Selection and erection of electrical equipment

Part 6: Verification

Part 7: Requirements for special installations or locations

The committee has decided that the contents of this publication will remain unchanged until the maintenance result date indicated on the IEC web site under "<http://webstore.iec.ch>" in the data related to the specific publication. At this date, the publication will be

- reconfirmed;
- withdrawn;
- replaced by a revised edition, or
- amended.

LOW-VOLTAGE ELECTRICAL INSTALLATIONS –

Part 1: Fundamental principles, assessment of general characteristics, definitions

11 Scope ¹

IEC 60364-1 gives the rules for the design, erection, and verification of electrical installations. The rules are intended to provide for the safety of persons, livestock and property against dangers and damage which may arise in the reasonable use of electrical installations and to provide for the proper functioning of those installations.

11.1 IEC 60364-1 applies to the design, erection and verification of electrical installations such as those of

- a) residential premises;
- b) commercial premises;
- c) public premises;
- d) industrial premises;
- e) agricultural and horticultural premises;
- f) prefabricated buildings;
- g) caravans, caravan sites and similar sites;
- h) construction sites, exhibitions, fairs and other installations for temporary purposes;
- i) marinas;
- j) external lighting and similar installations (see, however, 11.3e));
- k) medical locations;
- l) mobile or transportable units;
- m) photovoltaic systems;
- n) low-voltage generating sets.

NOTE "Premises" covers the land and all facilities including buildings belonging to it.

11.2 IEC 60364-1 covers

- a) circuits supplied at nominal voltages up to and including 1 000 V a.c. or 1 500 V d.c.;
For a.c., the preferred frequencies which are taken into account in this standard are 50 Hz, 60 Hz and 400 Hz. The use of other frequencies for special purposes is not excluded.
- b) circuits, other than the internal wiring of apparatus, operating at voltages exceeding 1 000 V and derived from an installation having a voltage not exceeding 1 000 V a.c., for example, discharge lighting, electrostatic precipitators;

¹ The numbering system is explained in Annex A.

- c) wiring systems and cables not specifically covered by the standards for appliances;
- d) all consumer installations external to buildings;
- e) fixed wiring for information and communication technology, signalling, control and the like (excluding internal wiring of apparatus);
- f) the extension or alteration of the installation and also parts of the existing installation affected by the extension or alteration.

NOTE The rules of IEC 60364-1 are intended to apply to electrical installations generally but, in certain cases, they may need to be supplemented by the requirements or recommendations of other IEC standards (for example, for installations in explosive gas atmospheres).

11.3 IEC 60364-1 does not apply to

- a) electric traction equipment, including rolling stock and signaling equipment;
- b) electrical equipment of motor vehicles, except those covered in Part 7;
- c) electrical installations on board ships and mobile and fixed offshore platforms;
- d) electrical installations in aircraft;
- e) public street-lighting installations which are part of the public power grid;
- f) installations in mines and quarries;
- g) radio interference suppression equipment, except where it affects the safety of the installation;
- h) electric fences;
- i) external lightning protection systems for buildings (LPS);

NOTE Atmospheric phenomena are covered in IEC 60364-1 but only insofar as effects on the electrical installations are concerned (for example, with respect to selection of surge protective devices).

- j) certain aspects of lift installations;
- k) electrical equipment of machines.

11.4 IEC 60364-1 is not intended to apply to

- systems for distribution of energy to the public, or
- power generation and transmission for such systems.

NOTE 1 Countries wishing to do so may, however, use this standard in whole or in part for that purpose.

NOTE 2 According to IEC 61936 which provides common rules for the design and the erection of electrical power installations in systems with nominal voltages above 1kV a.c. and nominal frequency up to and including 60 Hz, low-voltage a.c. and d.c. protection and monitoring systems should be in accordance with IEC 60364 series.

11.5 Electrical equipment is dealt with only so far as its selection and application in the installation are concerned.

This applies also to assemblies of electrical equipment complying with the relevant standards.

12 Normative references

The following referenced documents are indispensable for the application of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60038, *IEC standard voltages*

IEC 60050(691), *International Electrotechnical Vocabulary (IEV) – Chapter 691: Tariffs for electricity*

IEC 60050-826, *International Electrotechnical Vocabulary (IEV) – Part 826: Electrical installations*

IEC 60364-4-41, *Electrical installations of buildings – Part 4-41: Protection for safety – Protection against electric shock*

IEC 60364-4-42, *Electrical installations of buildings – Part 4-42: Protection for safety – Protection against thermal effects*

IEC 60364-4-43, *Electrical installations of buildings – Part 4-43: Protection for safety – Protection against overcurrent*

IEC 60364-4-44, *Electrical installations of buildings – Part 4-44: Protection for safety – Protection against voltage disturbances and electromagnetic disturbances*

IEC 60364-5-51, *Electrical installations of buildings – Part 5-51: Selection and erection of electrical equipment – Common rules*

IEC 60364-5-52, *Electrical installations of buildings – Part 5-52: Selection and erection of electrical equipment – Wiring systems*

IEC 60364-5-53:2001, *Electrical installations of buildings – Part 5-53: Selection and erection of electrical equipment – Isolation, switching and control*

IEC 60364-5-54, *Electrical installations of buildings – Part 5-54: Selection and erection of electrical equipment – Earthing arrangements, protective conductors and protective bonding conductors*

IEC 60364-5-55:2001, *Electrical installations of buildings – Part 5-55: Selection and erection of electrical equipment – Other equipment*

IEC 60445, *Basic and safety principles for man-machine interface, marking and identification - Identification of equipment terminals and of terminations of certain designated conductors, including general rules for an alphanumeric system*

IEC 60446, *Basic and safety principles for man-machine interface, marking and identification – Identification of conductors by colours or numerals*

IEC 60617-DB:20012, *Graphical symbols for diagrams*

IEC 60721 (all parts), *Classification of environmental conditions*

² "DB" refers to the IEC on-line database.

13 Fundamental principles

NOTE 1 Where countries not yet having national regulations for electrical installations deem it necessary to establish legal requirements for this purpose, it is recommended that such requirements be limited to fundamental principles which are not subject to frequent modification on account of technical development. The contents of Clause 13 may be used as a basis for such legislation.

NOTE 2 This clause contains basic requirements. In other parts of this standard (see Table A.2), more detailed requirements may be given.

131 Protection for safety

131.1 General

The requirements stated in 131.2 to 131.7 are intended to provide for the safety of persons, livestock and property against dangers and damage which may arise in the reasonable use of electrical installations. The requirements to provide for the safety of livestock are applicable in locations intended for them.

NOTE In electrical installations, the following hazards may arise:

- shock currents;
- excessive temperatures likely to cause burns, fires and other injurious effects;
- ignition of a potentially explosive atmosphere;
- undervoltages, overvoltages and electromagnetic influences likely to cause or result in injury or damage;
- power supply interruptions and/or interruption of safety services;
- arcing, likely to cause blinding effects, excessive pressure, and/or toxic gases;
- mechanical movement of electrically activated equipment.

131.2 Protection against electric shock

131.2.1 Basic protection (protection against direct contact)

NOTE For low-voltage installations, systems and equipment, basic protection generally corresponds to protection against direct contact.

Protection shall be provided against dangers that may arise from contact with live parts of the installation by persons or livestock.

This protection can be achieved by one of the following methods:

- preventing a current from passing through the body of any person or any livestock;
- limiting the current which can pass through a body to a non-hazardous value.

131.2.2 Fault protection (protection against indirect contact)

NOTE For low-voltage installations, systems and equipment, fault protection generally corresponds to protection against indirect contact, mainly with regard to failure of basic insulation.

Protection shall be provided against dangers that may arise from contact with exposed-conductive-parts of the installation by persons or livestock.

This protection can be achieved by one of the following methods:

- preventing a current resulting from a fault from passing through the body of any person or any livestock;
- limiting the magnitude of a current resulting from a fault, which can pass through a body, to a non-hazardous value;
- limiting the duration of a current resulting from a fault, which can pass through a body, to a non-hazardous time period.

131.3 Protection against thermal effects

The electrical installation shall be so arranged to minimize the risk of damage or ignition of flammable materials due to high temperature or electric arc. In addition, during normal operation of the electrical equipment, there shall be no risk of persons or livestock suffering burns.

131.4 Protection against overcurrent

Persons and livestock shall be protected against injury and property shall be protected against damage due to excessive temperatures or electromechanical stresses caused by any overcurrents likely to arise in conductors.

Protection can be achieved by limiting the overcurrent to a safe value or duration.

131.5 Protection against fault currents

Conductors, other than live conductors, and any other parts intended to carry a fault current shall be capable of carrying that current without attaining an excessive temperature. Electrical equipment, including conductors shall be provided with mechanical protection against electromechanical stresses of fault currents as necessary to prevent injury or damage to persons, livestock or property.

Live conductors shall be protected against overcurrents arising from faults by the methods in 131.4.

NOTE Particular attention should be given to PE conductor and earthing conductor currents.

131.6 Protection against voltage disturbances and measures against electromagnetic influences

131.6.1 Persons and livestock shall be protected against injury and property shall be protected against any harmful effects as a consequence of a fault between live parts of circuits supplied at different voltages.

131.6.2 Persons and livestock shall be protected against injury and property shall be protected against damage as a consequence of overvoltages such as those originating from atmospheric events or from switching.

NOTE For protection against direct lightning strikes, see IEC 62305 series.

131.6.3 Persons and livestock shall be protected against injury and property shall be protected against damage as a consequence of undervoltage and any subsequent voltage recovery.